

FieldMan

Measurement Device for Electromagnetic Fields

User manual



narda 
Safety Test Solutions

Narda Safety Test Solutions GmbH
Sandwiesenstraße 7
72793 Pfullingen, Deutschland

® Names and Logo are registered trademarks of Narda Safety Test Solutions GmbH -
Trade names are trademarks of the owners.

© 2022

Order no.: 2460/98.21

Issue: 01/10.2022, A ...

Previous issue: --/--, A ...

Subject to change.

Our normal terms of warranty and delivery
apply.

English

1	About this product	7
1.1	About the measurement of electromagnetic fields	8
1.2	About the Narda FieldMan	8
1.3	Supported probes	9
2	General safety instructions	11
2.1	Using these operating instructions	12
2.2	Intended use	12
2.3	Non-intended use	12
2.4	Dangers due to electromagnetic fields	12
2.5	Correct handling of rechargeable batteries	13
3	About this operating manual	15
3.1	Structure of the operating instructions	16
3.2	Language of the user interface	16
3.3	Characters and symbols used	17
4	Connection and commissioning	19
4.1	Unpacking	20
4.2	Equipping the case	21
4.3	Device overview	22
4.4	Power supply/rechargeable battery operation	24
4.5	Connect and test probe	25
4.6	Initial commissioning	27

5	Controls and display elements	29
5.1	Controls	30
5.2	LED display	32
5.3	Display overview	33
5.4	Display of probe info on the display	34
5.5	Status bar symbols	35
5.6	Symbols of function keys	36
6	General operation	37
6.1	The operating concept	38
6.2	Basic operating steps	39
6.3	The display in measuring mode	42
7	Device settings	43
7.1	Setting types	44
7.2	Personalizing device settings	45
7.3	General Settings	45
7.4	Legal Notices	47
7.5	Expert Settings	47
7.6	Position and Time	48
7.7	Connectivity	50
7.8	Information	51
7.9	Setups	53
7.10	Data Logger	56
8	Operating modes	57
8.1	Overview of operating modes and probe types	58
8.2	Field Strength	60
8.3	Spatial Average	67
8.4	Timer Logging	71
8.5	Spectrum	78
8.6	Shaped Time Domain	83

9	Data Logger	91
9.1	Structure of the Data Logger	92
9.2	Managing projects (Project)	93
9.3	Managing measurements (Measurements)	94
9.4	Managing screenshots (Screenshots)	96
9.5	Managing media (Media)	96
10	Cross-mode functions	97
10.1	Post-Processing	98
10.2	Selection of a standard	100
10.3	Offset correction – Zero	102
10.4	Commenting on measurement results	103
10.5	Alarm function	104
10.6	Acoustic intensity display (HF probes only)	105
10.7	Peak marker	106
10.8	Display of overdriven measured values	107
11	PC software and updates	109
11.1	Narda-TSX PC software	110
11.2	Firmware update	111
12	Care, maintenance and disposal	113
12.1	Cleaning the device	114
12.2	Replacing/removing rechargeable batteries	115
12.3	Disposal	116
13	Conformity	117
13.1	EU Declaration of Conformity	118
13.2	UKCA Declaration of Conformity	118
13.3	Regulatory Compliance Mark (RCM)	118
13.4	Radio approval	118

1

About this product

In this chapter you will find some useful information about measuring electromagnetic fields, about the Narda FieldMan and about the probes.

- 1.1 About the measurement of electromagnetic fields
(page 8)**
- 1.2 About the Narda FieldMan (page 8)**
- 1.3 Supported probes (page 9)**

1.1 About the measurement of electromagnetic fields

In the modern world, people live and work virtually permanently in the vicinity of technical equipment that generates electromagnetic fields. With increasing research into their effect on humans, there is an increasing awareness of the problem and availability of information on this topic. Limits have long since been defined by various bodies to protect users from exposure to emissions.

1.2 About the Narda FieldMan

The Narda FieldMan measures non-ionizing radiation and low frequency fields with the highest accuracy. With its digital measuring probes for electric and magnetic field strengths, the instrument covers the range from static and low-frequency fields in medical and industrial applications to mobile phone frequencies and millimeter waves. Both broadband HF probes with a flat frequency response and “shaped probes” are available, which evaluate the field strength according to a personal protection standard. Probes with integrated FFT analysis allow spectral measurements and analysis in the time domain up to frequencies of 400 kHz. All probes have a digital interface that transmits the measurement data to the base unit without interference. This eliminates the need for calibration of the base unit.

The newly developed, extremely powerful Narda-TSX PC software is available for evaluating and documenting the measurement results, media and other information. It is Narda's new software platform that will support other Narda products in the future in addition to FieldMan. The firmware update is also performed via the PC software (see *11 PC software and updates on page 109*).

Applications and standards

The FieldMan enables precision measurements to ensure the safety of people, especially in working environments where high electric or magnetic field strengths are expected. A key task is to demonstrate compliance with general safety regulations such as FCC, IEEE, ICNIRP or the EMF Directive 2013/35/EU. Examples of measurement environments are:

- Broadcast transmitters (e.g. IEC 62577)
- Radio base stations (e.g. IEC/EN 62232)
- Induction heating and melting (e.g. EN 50519)
- Household appliances (e.g. IEC/EN 62233)
- Electric welding equipment (e.g. IEC/EN 62822)
- Railroad environment (e.g. EN 50500)
- Vehicle environment (e.g. IEC 62764)
- Power supply systems (e.g. IEC/EN 62110)
- Medical electrical equipment (e.g. IEC/EN 60601)
- TEM cells and absorber chambers for the verification of electromagnetic compatibility (EMC)

1.3 Supported probes

A variety of isotropic field probes are available for the FieldMan. All of them transmit their information and measurement data as a digital signal to the FieldMan, either via an electrical USB interface or via an optical COM interface. In this way, interference is almost completely eliminated compared to high-impedance analog interfaces. The specially developed screw connectors and electrical contacts are extremely robust and resistant. The probes are automatically detected after connection to the FieldMan.

The characteristics of the probes are listed in the respective data sheet. The following probe types are supported:

- Broadband probes with digital interface for FieldMan (P/N 2462/xx)
- Selective probes with digital interface for FieldMan (P/N 2463/xx)
- EHP-50F and EHP-50G field analyzers with optical interface (P/N 2404/xxx)
- HP-01 magnetometer with optical interface (P/N 2405/xxx)

2

General safety instructions

This chapter contains important information on the safe use of the FieldMan. You should therefore read this chapter carefully and follow the instructions given.

- 2.1 Using these operating instructions (page 12)**
- 2.2 Intended use (page 12)**
- 2.3 Non-intended use (page 12)**
- 2.4 Dangers due to electromagnetic fields (page 12)**
- 2.5 Correct handling of rechargeable batteries (page 13)**

2.1 Using these operating instructions

- ⇒ Read these operating instructions carefully and completely before working with the device.
- ⇒ Keep these operating instructions at hand so that they are always available to all users when working with the device.
- ⇒ Only pass the device on to third parties together with these operating instructions.

2.2 Intended use

The Narda FieldMan is used to measure and evaluate electromagnetic fields.

- ⇒ Only operate the device under the conditions and for the purposes for which it was designed.
- ⇒ Pay particular attention to the technical specifications in the data sheet for the device.

Intended use also includes the following:

- ⇒ Observe the national accident prevention regulations at the deployment location.
- ⇒ The device may only be operated by appropriately qualified and trained personnel.

2.3 Non-intended use

The Narda FieldMan is not a warning device that actively warns of the existence of dangerous fields by means of visual or acoustic signals.

- ⇒ Always consider the device as a measuring device, never as a warning device.
- ⇒ Only approach unknown field sources while carefully observing the current measured value display.
- ⇒ In case of doubt, use an additional warning device such as **RadMan** or **Nardalert** from Narda Safety Test Solutions.

2.4 Dangers due to electromagnetic fields

2.4.1 Strong fields

Very strong electromagnetic fields occur near many radiation sources.

- ⇒ Observe safety barriers and markings.
- ⇒ In particular, persons with electronic implants must keep away from dangerous areas.

2.4.2 Undervaluation of the field strength

Metallic stickers in the sensor area of the probe can lead to measurement errors, especially to undervaluation of the electromagnetic field strength.

- ⇒ Attach all types of stickers to the black probe shaft only.
- ⇒ An automatic self-test function can detect any probe faults, alerts the user and does not allow further measurement in case of serious faults. The sensor system is also checked for open circuits and short circuits in the process. In case of doubt, a test generator (see accessories in the data sheet) can also be used for checking.
- ⇒ If a malfunction is suspected, take the unit out of operation and contact your Narda service center. Addresses can be found at the end of these operating instructions and on the Internet at www.narda-sts.com.

2.5 Correct handling of rechargeable batteries

Rechargeable batteries can overheat, explode or ignite if handled incorrectly.

- ⇒ Observe the following notes when handling rechargeable batteries:
 - Always handle the rechargeable battery with care.
 - Do not drop, damage or expose the rechargeable battery to excessively high temperatures.
 - Never store the rechargeable battery under very high temperatures (e.g. in the car) for more than one to two days.
 - Never leave the discharged rechargeable battery in the unused measuring instrument for a long time.
 - Never store the rechargeable battery for more than six months without charging it in between.
 - Close the rechargeable battery compartment again after replacing the rechargeable battery and never operate the FieldMan with the rechargeable battery compartment open.
 - Defective rechargeable batteries are special waste and must therefore not be disposed of with the usual household waste.
 - Observe the national regulations for the disposal of rechargeable batteries.

3

About this operating manual

This chapter contains information on the structure and layout of the operating instructions.

- 3.1 Structure of the operating instructions (page 16)**
- 3.2 Language of the user interface (page 16)**
- 3.3 Characters and symbols used (page 17)**

3.1 Structure of the operating instructions

These operating instructions are divided into the following main sections:

- **General operation:** Here you will find basic operations such as switching on and off.
- **Device settings (DEVICE SETTINGS):** Device settings describes all settings that relate to the device in general.
- **Operating modes:** The operating modes and the operating mode-specific settings (**MEASUREMENT SETTINGS**) are described here.
- **DATA LOGGER:** In this chapter you will find all of the information about retrieving stored measurements.
- **Cross-mode functions:** Some functions affect several or all operating modes. These functions are described here.

3.2 Language of the user interface

In these operating instructions, screen contents are presented in English. However, the user interface of the FieldMan can also be displayed in other languages (see “**Select the language**”).

⇒ Please note that in this case the displayed terms differ from those described.

3.3 Characters and symbols used

In these operating instructions, various elements are used to indicate special text meanings or especially important text passages.

3.3.1 Symbols and warning words in warning instructions

In accordance with American National Standard ANSI Z535.6-2006, the following warning instructions, symbols and warning words are used in this document:

	In combination with the warning words CAUTION , WARNING and DANGER , the general danger symbol warns of a risk of serious injuries. Observe all the following instructions to avoid injuries or death.
NOTICE	Indicates a danger that will result in damage to or destruction of the device.
CAUTION	Indicates a danger with low to moderate risk of injury.
WARNING	Indicates a danger that may result in death or serious injury.
DANGER	Indicates a danger that will result in immediate death or severe injury.

Structure of the warning instructions

All warnings are structured as follows:

 WARNING WORD
Type and source of the danger
Consequences resulting from non-observance
⇒ Action for danger avoidance

3.3.2 Symbols and text markings in the document

Symbol	Meaning
✓	Prerequisite Indicates a prerequisite that must be satisfied before one of the following actions is performed, e.g.: ✓ The device is switched off.
⇒	Action Indicates a single action, e.g.: ⇒ Switch on device.
1. 2. 3.	Sequence of actions Indicates a sequence of actions that must be performed in the specified order.
↳	Result Indicates the result of an action, e.g.: ↳ The device starts a self-test.
Bold text	Controls and display elements Identifies controls and display elements, e.g.: ⇒ Press ENTER key.

3.3.3 Terms and abbreviations

Term	Meaning
Rechargeable battery	Rechargeable battery
Battery	Non-rechargeable battery
SK1 – SK4	Softkey 1 – Softkey 4

4

Connection and commissioning

This chapter provides information about the connection options of the Narda FieldMan, gives instructions for commissioning and describes the connection options.

- 4.1 Unpacking (page 20)**
- 4.2 Equipping the case (page 21)**
- 4.3 Device overview (page 22)**
- 4.4 Power supply/rechargeable battery operation (page 24)**
- 4.5 Connect and test probe (page 25)**
- 4.6 Initial commissioning (page 27)**

4.1 Unpacking

ATTENTION

Device/accessories damaged during transport

Commissioning of damaged equipment/accessories may cause consequential damage.

- ⇒ After unpacking, check the device and all accessories for any damage that may have occurred during shipping.
- ⇒ In case of damage to the device or components, contact your Narda service center. The addresses of your Narda service center can be found at the end of these operating instructions manual and on the Internet at www.narda-sts.com.

4.1.1 Packaging

The packaging is designed so that it can be reused if not damaged during a prior transport.

- ⇒ Do not throw away the packaging and use the original packaging for all further transportation.

4.1.2 Package contents

- ⇒ Check the delivery for completeness.
- **Narda FieldMan**
- Rechargeable battery (already inserted)
- Case
- Probe (type and quantity according to order)
- Charging power supply
- Shoulder strap
- USB cable
- Bag with 5 colored marking rings for broadband probes
- PC software (free download from www.narda-sts.com)
- General safety instructions
- Operating instructions on USB stick
- Calibration certificate (for probes)

4.2 Equipping the case

In addition to the components included in the scope of delivery, numerous other optionally available accessories can be stored in the supplied case. The following diagrams show the distribution in the top and bottom of the case.




Fig. 1: Case with equipment

- 1 FieldMan
- 2 Small parts and bag with marking rings
- 3 Shoulder strap (2244/90.49)
- 4 EHP-50F
- 5 Suitable for all probes
- 6 HP-01
- 7 EHP/HP-01 charging power supply with country adapter (2259/92.08)
- 8 FieldMan charging power supply (2259/92.29)
- 9 Country adapter for FieldMan charging power supply
- 10 EHP-50 table-top tripod (2404/90.02)
- 11 Folding bag for USB cable, optical cables, safety instructions and USB stick
- 12 RadMan belt bag (2250/92.06)
- 13 O/E converter (2260/90.06)
- 14 Tripod extension (2244/90.45)
- 15 Test generator (2244/90.38)
- 16 Broadband probes

4.3 Device overview



Fig. 2: Device overview FieldMan

No.	Description
1	Connector plug for probes With USB-C socket
2	Display Display area with LEDs for the operating and charging status (top) and the softkey fields.
3	On/Off key
4	Keypad With the soft keys, cross key, Back and Save key
5	Tripod connection With thread ¹⁾ for vertical mounting on a tripod
6	USB-C socket For charging the rechargeable battery, remote control and data transmission
7	Optical port For connecting components (e.g. EHP-50F/G, HP-01)
8	Micro SD card For saving measurement data, setups, user standards and media files
9	Network connection Gigabit Ethernet LAN connection for remote control and data transmission
10	Auxiliary MMCX connector (for future applications)
11	Flap <ul style="list-style-type: none"> Closed: to store the device with small probes Opened: to store the device with large probes Ultrasonic range finder (flap open) For distance measurement in conjunction with the GNSS/Range Finder option
12	Tripod connection With thread ¹⁾ for horizontal mounting on a tripod
13	Battery compartment ⇒ To change the rechargeable battery (see <i>12.2 Replacing/removing rechargeable batteries on page 115</i>).

1) 1/4-inch 20-thread UNC female thread

4.4 Power supply/rechargeable battery operation

This device uses a rechargeable Li-ion battery pack, which is installed and pre-charged in the device. The included USB-C Power Delivery charger (12 V, 3 A) enables fast charging of the built-in rechargeable batteries. A full charge takes place within 4 hours, with 80% of capacity reached after just 2.5 hours.

4.4.1 Operation with charger connected

Measuring with the charger connected can influence the measurement properties. This means that compliance with the technical data is no longer guaranteed.

With the above restriction, the FieldMan can be powered from any USB interface that supplies a current of at least 1 A. Operation is then also possible without a built-in rechargeable battery.

- ⇒ Use a floating power supply for long-term operation, e.g. a suitable power bank (PD 12 V, 2.5 A, BC1.2 and QC3.0).
- ⇒ To ensure compliance with the permissible radio interference emissions, use only the supplied charging power supply or the car charger (optional accessory) from Narda.

4.4.2 Operation with rechargeable battery

- ⇒ Fully charge the rechargeable battery pack before commissioning.

Charging rechargeable batteries

If the device is not expected to be used for several months:

- ⇒ Charge the device before storage to avoid deep discharge.

Starting the charging process:

1. Plug the included USB-C charging power supply with the matching country adapter into a power outlet.
2. Connect the FieldMan with the supplied USB-C cable.
 - ↳ The charging process begins.

Not all USB-C cables support fast charging with Power Delivery.

Display of rechargeable battery and charge status

The charge status is indicated by the status LED:

- Rechargeable batteries are being charged: Status LED lights up **red**.
- Rechargeable batteries are charged: The device automatically switches to trickle charge, status LED lights up **green**.

In addition, the display shows the rechargeable battery capacity as well as the charging or rechargeable battery mode:

- **Device on:** Rechargeable battery capacity in percent and charge status are displayed in the upper right corner (see 5.5 *Status bar symbols on page 35*).
- **Device off:** When charging begins, the current charging process, the capacity and the charging mode are displayed for approx. 1 minute.
 - **Fast Charging:** Fast charging
 - **Charging:** Normal charging

⇒ Activate the display again by pressing any key.

4.5 Connect and test probe

Probes can be connected directly to the probe connector on the top of the FieldMan or to the optical input:

- **Connection at the probe connector:** All digital HF and LFFieldMan probes
- **Connection at the optical input:** HP-01 and EHP-50F/G field analyzers.

4.5.1 Connect the probe to the probe connector

1. Hold the probe so that the lug on the probe connector faces the groove in the socket on the top of the instrument.
NOTICE! Do not push in the connector by force. Check position of lug and groove.
2. Insert the probe connector straight into the probe socket all the way from the top.
3. Tighten the locking nut finger-tight. Do not use tools.

Removing the probe:

⇒ Loosen the locking nut and pull the probe upwards and out at the metal plug.

4.5.2 Connecting the probe to the optical input

The HP-01 and EHP-50F/GF field analyzers are connected to the optical input of the FieldMan. A suitable optical cable is included with the probes.

Connecting a probe:

1. Go to **GENERAL SETTINGS > CONNECTIVITY > OPTICAL INTERFACE** and select **Probe**.
2. Connect a suitable probe via the optical cable to the optical connector on the FieldMan (see *Fig. 2: 7*).

⇒ For more information on using a probe via the optical link, refer to the operating instructions for the probe.

4.5.3 Test probe

After connecting a probe to the probe connector, a self-test is automatically started. The digital part, the analog part and the measuring sensors of the probe are checked for correct function. If a fault is detected that could affect the measurement, a corresponding message is displayed and measurements are not possible.

WARNING

Probe is not working properly

Due to a defective probe, any high radiation levels that may be present cannot be detected.

⇒ Observe the information displayed during and after the self-test of a probe. If there is any doubt about the correct functioning of the probe, a test source (see accessories in the data sheet) can be helpful to check the probe.

⇒ In order to make the correct probe selection, you should always obtain knowledge of the expected frequency and field strength before starting a measurement.

4.5.4 Attaching marking rings

Broadband probes are provided with a groove for a marking ring in the area of the connector. Probes are generally supplied with a black ring. Users of different probes are offered the possibility to distinguish the probes more easily by attaching colored rings. The scope of delivery includes 5 colored rings for this purpose.

4.6 Initial commissioning

4.6.1 Switch on the device

NOTICE

Damage to a device covered in dew during commissioning

A device stored or transported at low temperatures may become covered in dew when brought into a warm room. If it is put into operation in this condition, it may be damaged.

- ⇒ To prevent damage, wait until all dew on the surface of the device has evaporated.
- ⇒ The device is not ready for operation until it has reached the operating range of -20 to $+50$ °C.

The device is switched on via the **Power** key on the left side of the housing.

- ⇒ Press **Power** key for > 1 s to switch on the device.
 - ↳ After the system start, the device is ready for operation.

During initial commissioning, then change the following settings if necessary:

- The language of the interface
- Local time
- Time zone (with GNSS option)
- Country of use (for WiFi/Bluetooth option)

4.6.2 Selecting the language of the interface

1. Press **SK4** to open the device settings.
2. Under **GENERAL SETTINGS > Language**, select the language (see 7.3.1 *DISPLAY* on page 45).

4.6.3 Setting the local time and time zone

1. Press **SK4** to open the device settings.
2. Under **POSITION AND TIME > DATE / TIME > Time**, set the time, under... > **Time Zone**, set the time zone (see 7.6.3 *DATE / TIME* on page 49).

4.6.4 Selecting the country of use (for WiFi/Bluetooth option)

If the WiFi/Bluetooth option is available, a selection list of countries for which a radio license exists appears during initial commissioning and after a factory reset. Then select the country in which the device will be operated. The country selection configures the radio module for this region and selects the corresponding radio standard.

The device may only be operated with the correct country setting! Operation of the radio module in countries not listed is not permitted.

Select the country of use:

- ✓ The device is being operated for the first time or a factory reset has been performed.
- ⇒ On the start screen, select the country of use from the drop-down menu and confirm with **OK**.

Changing the country setting at a later date:

A factory reset must be performed for this purpose.

1. Press **SK4** to open the device settings.
2. Perform the reset under **GENERAL SETTINGS > DEVICE > Factory Reset** (see [7.3.5 DEVICE on page 47](#)).
3. On the start screen, select the country of use from the drop-down menu and confirm with **OK**.

5

Controls and display elements

In this chapter you will find descriptions of the device with its connections and keys as well as the display.

- 5.1 Controls (page 30)**
- 5.2 LED display (page 32)**
- 5.3 Display overview (page 33)**
- 5.4 Display of probe info on the display (page 34)**
- 5.5 Status bar symbols (page 35)**
- 5.6 Symbols of function keys (page 36)**

5.1 Controls



No.	Description
1	Status LED Operating display and charge status (see 5.2 LED display on page 32).
2	Power key <ul style="list-style-type: none"> Switch device on/off: Press and hold key > 1 s Screen saver: With the device switched on, briefly press the key (see 6.2.2 Using the screen saver on page 39) Hardware reset: Press key for a very long time (> 10 s)
3	Softkeys SK1... SK4: (from left to right) Performs different functions depending on the associated screen display. The labeling mainly takes the form of symbols (see 5.6 Symbols of function keys on page 36).
4	Back key Change back to the next higher menu level. However, a paused measurement remains in HOLD mode (display is paused). A long key press resets the measured values (Reset Results).
5	Cross key ◀ Navigation in menus and input fields, move marker horizontally, change result type for large measurement display, peak marker to left. Cross key ▶ Navigation in menus and input fields, move marker horizontally, change result type for large measurement display, peak marker to right. Cross key ▲ Navigation in menus and selection lists, change values in selection fields, move peak marker to the next higher peak. Cross key ▼ Navigation in menus and selection lists, change values in selection fields, move peak marker to the next lower peak. Cross key ● Confirmation of a selection (OK key).
6	Save key A short key press saves the displayed measurement results, if desired also with a screen copy. A long key press saves a screen copy as a PNG file.

5.2 LED display

The device status is indicated via the 3-color status LED above the display.

When the device is switched on:

- ✓ The status LED immediately lights up red and signals the device response.
- ✓ The screen remains dark.
- ✓ Shortly after, the boot screen is displayed with the Narda logo and FieldMan lettering.
- ✓ After the operating system is loaded, the status LED lights up according to the following conditions:

USB connected

Device status	Display
Device off	Red: Device charging rechargeable battery Green: Rechargeable battery is full
Device on	Red: Device charging rechargeable battery Green: Rechargeable battery is full Red flashing fast: Fault, has priority over red


USB not connected

Device status	Display
Device off	LED off
Device on	Yellow: Power-On status Red flashing slowly: Rechargeable battery almost empty (operating time < 15 min), has priority over white Red flashing fast: Fault, has priority over red flashing slowly

Alarms or remote operation are indicated on the display and not via the status LED.

5.3 Display overview

The display is divided into different display areas:



No.	Area	Description
1	Status bar	Time, alarm, GPS, BT, WiFi, charge status, mute, date, air temperature, humidity, distance meter
2	Probe information	Probe model, charge status, correction frequency, frequency range/span, field type, filter setting, pulse detection (Pulse Detection = On , short integration time e.g. for radar signals)
3	Information about the measured values	Result type, detector
4	Main display of the measured values	Isotropic measured value (RSS) and measuring unit, measured values for spatial axes (if available)
5	Additional display of the measured values	Statistical measured values over the entire period of the measurement, depending on the operating mode
6	Measurement sequence or measurement graphic	Graphical display of measured values in the time or frequency range, bar display, or information on the measurement process
7	Function keys (softkeys)	SK1 – SK4

5.4 Display of probe info on the display

The most important probe information and its settings are shown on the display during the measurement. This means that the result of a measurement can also be clearly assessed on the basis of a screenshot. Some examples of the probe info field are explained below.

HF broadband probes

1	EFD-0691		
2	100 kHz - 6 GHz	E-Feld	3
	EFD-0691	CF: 2.45 GHz	4
	100 kHz - 6 GHz	E-Feld	
	EFD-0691	REF: 103 MHz	5
	100 kHz - 6 GHz	E-Feld	

- 1 Probe model
- 2 Probe frequency range
- 3 Field type, filter setting, **Pulse** when pulse detection is switched on (probe-dependent)
- 4 Correction frequency
- 5 Reference frequency

EHP-50F/G and HP-01

1	EHP-50F	100% 	3
2	6 Hz - 500 Hz	E-Feld 100 kV/m	4

- 1 Probe model
- 2 Configured span
- 3 Probe rechargeable battery charge
- 4 Field type and range

BFD-400

1	BFD-400-1		
2	1 Hz - 400 KHz	B-Feld 80 mT	3
	BFD-400-1	50 Hz BPF	4
	30 Hz - 4 kHz	B-Feld 80 mT	

- 1 Probe model
- 2 Configured span incl. low-pass filter setting
- 3 Field type and range
- 4 Pass or stop filter

5.5 Status bar symbols

Symbol	Function	Symbol	Function	Symbol	Function
	Rechargeable battery charge full		WiFi switched on		WiFi connected
	Rechargeable battery charge half full		Bluetooth switched on		Bluetooth connected
	Rechargeable battery charge low		GNSS switched on, no position yet		GNSS position found
	Rechargeable battery charge critical		Speaker muted		GNSS signal lost, position frozen
	Rechargeable battery is charging		Alarm switched on		Memory card missing
	Ambient temperature		Relative humidity		Distance measurement

5.6 Symbols of function keys

Symbol	Function	Symbol	Function	Symbol	Function
	Operating mode ¹⁾	—	Zoom out		Add text comment
	Measurement settings		Axis selection		Edit text comment
	Menu		Exit		Upper case
	Pause		Edit or rename		Lower case
	Start		Confirm		Backspace
	Stop		Delete		Move data to another project
	Marker on/off		Activate timer		Jump to next record
	Peak marker on/off		Apply current time		Jump to previous record
	Zoom on/off		Record voice comment		Restart audio/video
	Zoom in or add		Edit voice comment		Stand-by (only for TIMER LOGGING)

1) Initials indicate the active operating mode (e.g. FS = **FIELD STRENGTH**)

6

General operation

In this chapter you will find information on the general operation of the FieldMan. Operating mode-specific operating instructions can be found in the descriptions of the respective operating mode.

- 6.1 The operating concept (page 38)**
- 6.2 Basic operating steps (page 39)**
- 6.3 The display in measuring mode (page 42)**

6.1 The operating concept

The combination of the context-dependent softkeys (**SK1 - SK4**) and the permanently assigned keys (**cross key**, **Back**, **Save**) enables intuitive and fast operation of the Narda FieldMan.

6.1.1 Basic functions of the softkeys

The softkeys **SK1 - SK4** provide access to all instrument and measurement settings as well as to all measurement functions. At the top level, the softkeys **SK1**, **SK2** and **SK4** have identical functions in all operating modes. **SK3** has an operation-specific function (e.g. starting the measurement)


SK1	SK2	SK3	SK4
Operating mode selection	Measurement settings	Operating mode-specific function	Device settings

Display of the active function

The symbol above a softkey always shows the function that is activated when the softkey is pressed (i.e. not the one that is currently active), e.g.:

Key	Function
-  -	The symbol indicates that pressing the softkey will turn on the marker (i.e. not that it is already on).

6.1.2 Functions of the fixed keys

Key	Function
	Back: Return from all submenus to the next higher level.
	Save: Save measurements (short press) and screenshots (long press).
	Cross key: Navigate in menus, select entries, change values, change cursor position in a graphical display ● key: Confirm selection
	Power: Short press activates the screen saver

6.2 Basic operating steps

Even if some functions and displays differ in the various operating modes, the operation is basically identical. These identical functions and displays are described below. Differences and details can be found in the descriptions of the operating modes and the menus (e.g. **DATA LOGGER**).

6.2.1 Switching the device on/off

The device is switched on and off via the **Power** key on the left side of the housing.

Switch device on/off:

- ⇒ Press **Power** key and hold for > 1 s.

6.2.2 Using the screen saver

When the screen saver is activated, the screen is turned off, thus saving power. However, the device continues to measure normally. The screen saver can either be activated immediately by briefly pressing the **Power** key or configured via a timer in the device settings.

Activate/deactivate screen saver immediately:

- ✓ The device is switched on.
- ⇒ Press the **Power** key briefly (< 1 s).
 - ↳ The screen is switched off.
The operating indicator (yellow LED) remains lit.
- ⇒ Press any key briefly to turn the screen back on.

Configure screen saver:

1. Press **SK4** to open the device settings.
2. Select **GENERAL SETTINGS > DISPLAY > Screen Saver**.
3. Select the desired time after which the screen saver is to be activated without pressing any keys (see 7.3.1 *DISPLAY* on page 45).

⇒ If the screen saver was automatically turned off after the selected time, press any key briefly to turn the screen back on.

6.2.3 Selecting an operating mode

- ⇒ Press **SK1** , use the **▲▼** keys to highlight an entry, and use the **●** key to select it.
- ⇒ For information on the operating modes, see 8 *Operating modes* on page 57.

6.2.4 Changing the measurement settings in an operating mode

- ✓ The desired operating mode is active.
- ⇒ Press **SK2** , use the **▲** **▼** keys to highlight an entry, and use the **●** key to select it.
- ⇒ For information on the menus and functions, see the descriptions of the respective operating mode.

Simplified representation

In the following descriptions, this simplified representation is used for changes in the measurement settings:

- ⇒ **MEASUREMENT SETTINGS**: ... (corresponding action).

6.2.5 Starting and pausing/stopping a measurement

- ⇒ Press **SK3**.

6.2.6 Changing the device settings

- ⇒ Press **SK4** .
- ⇒ For information on device settings, see *7 Device settings on page 43*.

6.2.7 Exiting a submenu

- ⇒ Press  key.

6.2.8 Saving a measurement

- ⇒ Briefly press the  key.
 - ↳ A message confirms that the measurement has been saved.
- ⇒ To manage stored measurements, see *9 DATA LOGGER on page 91*.


6.2.9 Taking a screenshot

- ⇒ Press the  key for approx. 2 s.
 - ↳ A message confirms that the screenshot has been taken.
- ⇒ To manage saved screenshots see *9 DATA LOGGER on page 91*.

6.3 The display in measuring mode

The displays in the operating modes are always structured in the same way. The displayed measured values, evaluations and graphical representations then differ depending on the operating mode, the probe used and the selected settings.

⇒ Detailed information on the displays can be found in the descriptions of the operating modes.



No.	Area	Values
1	Selection field	<ul style="list-style-type: none"> Display type: ACTUAL, AVERAGE... Detector type: RMS, Peak
2	Main field	Measured value display X/Y/Z only for ACTUAL , the unit can be selected
3	Status bar	When the measurement is running, a bar indicates the progress of the averaging.
4	Supplementary field	Evaluations MAX, MIN, MAXAVG, AVG and the current averaging time until the set time is reached.
5	Graphic display	<ul style="list-style-type: none"> Temporal or spectral display of the measurement results Bar graph of the instantaneous value.

7

Device settings

The menu can be used to change the device settings and to display the information about the measuring instrument and a connected probe. In addition, the menu allows access to user-defined setups and stored measurement results in **DATA LOGGER**.

- 7.1 Setting types (page 44)**
- 7.2 Personalizing device settings (page 45)**
- 7.3 GENERAL SETTINGS (page 45)**
- 7.4 LEGAL NOTICES (page 47)**
- 7.5 EXPERT SETTINGS (page 47)**
- 7.6 POSITION AND TIME (page 48)**
- 7.7 CONNECTIVITY (page 50)**
- 7.8 INFORMATION (page 51)**
- 7.9 SETUPS (page 53)**
- 7.10 DATA LOGGER (page 56)**

7.1 Setting types

On this device, a distinction is made between **Device settings** and **Measurement settings**.

7.1.1 Device settings

Device settings include all parameters that affect the general device behavior or the form of the display, but do not affect the measurement itself. The device always remembers the last used device settings, stores them on the SD card and loads them the next time the device is started. Device settings, with the exception of **EXPERT SETTINGS**, are not saved in a setup.

Open device settings:

⇒ Press **SK4**.

For information on device settings, see the following sections:

- *GENERAL SETTINGS on page 45*
- *EXPERT SETTINGS on page 47*
- *POSITION AND TIME on page 48*
- *CONNECTIVITY on page 50*
- *INFORMATION on page 51*
- *SETUPS on page 53*
- *DATA LOGGER on page 91*

7.1.2 Measurement settings

These include all parameters that influence a measurement. They are grouped under the softkey **SK2** and are supplemented by the settings under **EXPERT SETTINGS** (see *7.5 EXPERT SETTINGS on page 47*). Only measurement settings are used for saving and loading a setup.

Open measurement settings:

⇒ Press **SK2** in the respective operating mode.

Information on the measurement settings can be found in the description of the respective operating modes.

7.1.3 Resetting settings

Via **Factory Reset** (see *7.3 GENERAL SETTINGS on page 45*), both setting types can be reset to the delivery state.

7.2 Personalizing device settings

Measuring instruments are often used by several people. The FieldMan offers a quick and easy way to personalize settings, setups and measurement results through its removable memory card. We therefore recommend every user to use their own personal memory card.

Using a new memory card is completely hassle-free:

- ⇒ Insert new memory card.
- ↳ The required directory structure is created automatically.

Narda recommends the use of high quality memory cards for industrial applications.

7.3 GENERAL SETTINGS

In this submenu, settings are made for the device behavior that affect the screen display, acoustic notifications, and the power-on and power-off behavior of the device.

7.3.1 DISPLAY

Parameter	Default	Description
Language	English	Language of the user interface
Color Scheme	Normal	Color scheme of display
Auto-Brightness Control	On	Automatic adjustment of screen brightness (via light sensor)
Brightness Level	40%	Setting of screen brightness
Screen Saver	10 min	Screen saver. Reactivation of screen by pressing any key.
Temperature Unit	°C	Temperature unit

7.3.2 SAVE OPTIONS

Parameter	Default	Description
Add Voice Comment	Off	Add a voice comment when saving.
Add Text Comment	Off	Add a text comment when saving.
Default Text	...	Default text when adding text comments.
Auto Save Screenshot	Off	When saving manually, a screen copy is automatically created.

7.3.3 SOUND

Parameter	Default	Description
Mute	Off	Muting of the speaker, symbol in the status bar
Sound Level	50%	Playback volume
Audible RF Indicator	Off	Acoustic intensity display with 3 sensitivity settings (parameter appears only with HF probes)

7.3.4 ALARM

Parameter	Default	Description
Alarm Function	Off	Alarm when limit exceeded ⇒ For description, see <i>10.5 Alarm function on page 104</i> .
E-Field Unit	V/m	Unit of E-field
E-Field Limit	61 V/m	Limit of E-field
B/H-Field Unit	A/m	Unit of B/H field
B/H-Field Limit	0.16 A/m	Limit of B/H field
Limit for Results in %	100%	For evaluating probes and SHAPED TIME DOMAIN

7.3.5 DEVICE

Parameter	Default	Description
Format Memory Card	FORMAT	Format SD card after confirmation
Automatic Shutdown	30 min	Power off during inactivity
Calibration Reminder	When due	Can be activated on expiry or in advance, or generally deactivated
Factory Reset	RESET	Sets all adjustable parameters to the as-delivered values

7.4 LEGAL NOTICES

In this submenu you will find information about the radio approvals, and the Electronic Label (E-Label).

The E-Label can be accessed with 3 Keystrokes: SK4, Cross key ▼ and OK.

⇒ For more information, see *13.5 Radio approval on page 119*.

7.5 EXPERT SETTINGS

This submenu is probe-dependent and can only be selected if an HF probe or BFD-400 is connected. There are no adjustment options for other probes.

7.5.1 POST-PROCESSING

In this submenu, settings can be made for HF probes that require precise knowledge of the prevailing field. If the frequency of a field source is known and is specified here as the reference frequency, a more accurate display result can be obtained by applying the correction factor stored in the probe, or the percentage of the limit that has been reached can be displayed in % relative to a safety standard (see *10.1 Post-Processing on page 98*).

HF probes are broadband probes and cannot measure selectively at the set frequency. In the case of incorrect frequency specification or multifrequency fields, these settings can therefore lead to incorrect results.

Parameter	Default	Description
Apply Correction Factor CF	Off	Apply correction factor on/off
Reference Frequency	Fmin (probe dependent)	Reference frequency for correction factor and for % of standard
% of Standard	Off	Conversion to display in % of standard for measured field strengths at a reference frequency
Standard	ICNIRP 1998 Occ	Applied standard

7.5.2 Band-Filter

In this submenu, settings for a bandpass or bandstop filter with variable center frequency can be made for suitable probes (currently only BFD-400). After switching on, the filter has an effect only in the broadband modes **FIELD STRENGTH**, **SPATIAL AVERAGE** and **TIMER LOGGING**.

Parameter	Default	Description
Band-Filter	Off	Switch band filter on/off
Filter Type	Band-pass	Filter type
Center Frequency	50 Hz	Center frequency of the filter

7.6 POSITION AND TIME

In this submenu, settings are made which affect the position determination by means of the satellite receiver and the integrated ultrasonic distance sensor. The system time of the device can also be set or synchronized with the very accurate satellite time. The results of the GNSS position determination are also displayed.

7.6.1 DISTANCE METER (optional)

Parameter	Default	Description
Distance Meter	Off	Distance meter on/off
Status at Power-on	Off	Activate function automatically after device start
Distance Unit	Meter (m)	Distance unit

7.6.2 LOCATION SERVICES (optional)

Parameter	Default	Description
GNSS Receiver	Off	GNSS receiver on/off
Status at Power-on	Off	Activate function automatically after device start
GNSS Format	DMS	GNSS format
Latitude	48°27'29.718"N	Current latitude
Longitude	9°13'49.425"E	Current longitude
Altitude (MSL)	440 m	Current altitude
Accuracy H/V	4.3/8.0 m	Approximate horizontal and vertical position accuracy
Systems	GPS/ Galileo/ GLONASS	GNSS systems to be used

7.6.3 DATE / TIME

Parameter	Default	Description
Date Format	YYYY-MM-DD	Date format
Date	2022-08-18	Current date
Time Format	24 h	Time format
Time	13:30:59	Current time
Time Zone	UTC+01:00	Time zone
Daylight Saving Time	Off	Daylight saving time on/off
Sync with GNSS	SYNC	Synchronization of time with GNSS

7.7 CONNECTIVITY

In this submenu, settings are made for remote operation via wireless and wired connections.

7.7.1 SERIAL INTERFACE

Parameter	Default	Description
USB	On	USB on/off
Optical Interface	Probe	Optical interface selection: <ul style="list-style-type: none">• Off• Remote: Remote control function• Probe: Probe connection

7.7.2 NETWORK

Parameter	Default	Description
TCP Remote Port	5025	Port for TCP Remote
Host Name	fieldman_<S/N>	Predefined host name

7.7.3 WIRELESS INTERFACE (optional)

This group only appears if the chargeable **WiFi/BT** option has been activated.

Parameter	Default	Description
WiFi	Off	WiFi on/off
Bluetooth	Off	Bluetooth on/off

7.7.4 ETHERNET

Parameter	Default	Description
Ethernet	Off	LAN on/off With LAN = Off the following lines are grayed out
DHCP	On	If DHCP is enabled, the following lines are grayed out
IPv4 Address	192.168.128.128	Settings menu, individually scrollable digit groups
Subnet Mask	255.255.255.0	Settings menu default masks 1...32, default 24
IPv6 Address	fc00::192:168:128:128	Settings menu, individually scrollable digit groups
Prefix	7	Prefix length of the IPv6 address
MAC	Device-dependent	Individual MAC address of the Field-Man

7.8 INFORMATION

This submenu displays device and probe-specific information. In addition, the user or a calibration laboratory can update the third-party calibration date and recommended calibration interval for all probes except the HP-01 and EHP-50F/G. For probes with self-test capability, the test can be performed here.

7.8.1 DEVICE INFORMATION

Parameter	Default	Description
Device Self-Test	START	Starts self-test to be performed in separate window (also performed at each restart)
Product Name	FieldMan	Product name
Part Number	2461-01	Article number
Serial Number	A-0051	Serial number
Firmware Version	V1.0.0	Firmware version

Parameter	Default	Description
Bootloader Version	V1.0.1	Bootloader version
Image Version	V1.0.2	The image contains all SW components
<option name>	P/N of the option	Display only if option is enabled

7.8.2 PROBE INFORMATION

Parameter	Default	Description
Probe Self-Test	START	Starts self-test to be performed in separate window (also performed each time the probe is connected)
Product Name	EFD-0691	Probe product name
Part Number	2462/14	Probe article number
Serial Number	A-0051	Probe serial number
Field Type	E	Field type
Shaping Standard	No shaping	Standard
Lower Frequency Limit	0.1 MHz	Lower cutoff frequency
Upper Frequency Limit	6000 MHz	Upper cutoff frequency
Firmware Version	V1.0.0	Firmware version of the probe
Bootloader Version	V1.0.0	Bootloader version of the probe
Temperature Sensor	15.7 °C	Probe temperature
Narda Calibration Date	2022-12-15	Last calibration by Narda
Third-Party Calibration Date	–	Calibration date of other suppliers can be entered here by the user.
Recalibration after (months)	24	Number can be edited here by the user.
<option name>	P/N of the option	Display only if option is enabled

The information under **Narda Calibration Date** or **Third-Party Calibration Date** (most recent date counts) and **Recalibration after (months)** are used as a reminder function for an upcoming calibration. The values are stored in the EEPROM of the connected probe. No values can be changed for the EHP-50F/G and HP-01 probes. There is therefore no Third-Party Calibration Date here and the recommended calibration interval is always 24 months.

7.9 SETUPS

A setup contains all changeable settings that can influence a measurement and its measurement result. This includes all settings under **MEASUREMENT SETTINGS** (see in the respective operating mode) and **EXPERT SETTINGS** (see *7.5 EXPERT SETTINGS on page 47*).

Using a setup can greatly simplify and speed up the preparation of recurring measurements. In addition, faulty measurements due to incorrectly selected settings can be ruled out.

Since the selection options offered and the saved setups depend on the type of probe connected in each case, the submenu can only be activated when the probe is plugged in. The device setups are stored separately according to the 4 defined probe groups on the SD card of the device.

7.9.1 SD card directory structure

The setups are stored in the directory structure specified below. A maximum of 99 setups can be created per subdirectory.

Directory	Setups
Setups / RF /	HF probes (high frequency broadband probes)
Setups / HP /	HP-01 (probes for static fields)
Setups / EHP /	EHP-50F, EHP-50G (FFT field analyzers)
Setups / LF /	BFD-400, 100 cm ² and 3 cm ² (and other low frequency probes)

In the delivery state, the directories are empty. Measurement settings are saved to one of the above directories whenever the instrument is turned off, a probe is disconnected or unplugged, or the user saves the current measurement settings as a setup with the probe connected.

The last general device settings used (see 7.3 *GENERAL SETTINGS* on page 45) are also saved on the SD card when the device is switched off. Since the settings are probe-independent, they are stored in the **Device Settings** directory. When the device is switched on, these settings are loaded or – if the file is missing – the factory settings are loaded.

7.9.2 Switching on the device without a probe connected

Without a probe connected, only the probe-independent Last Device Settings are loaded. The last measurement settings **Last Settings** are loaded only after a connected probe has been detected.

7.9.3 Switching on the device with a probe connected

After switching on the device, the last used device and measurement settings are restored by loading the two settings files. If one of the files is not available, the factory settings are loaded instead.

7.9.4 Probe change during operation

If a probe is unplugged while the device is running, the current measurement settings are saved as **Last Settings** for this probe type. When reconnecting the same probe type, the same **Last Settings** will be used. If another probe type is detected instead, the **Last Settings** for this probe type will be loaded.

7.9.5 Creating and managing setups

Open the setup menu:

- ✓ The desired probe is connected.
- ✓ To create a new setup, make the desired settings.
- ⇒ Open **MAIN MENU > SETUPS**.
 - ↳ Only the setups created for the currently connected probe type are displayed in alphabetical order.

Create a new setup:

- ⇒ Press **SK4**.
 - ↳ A new setup is created under the default name **Setup [n]** with the current settings. The digit [n] is incremented up automatically.

Rename a setup:

1. Highlight a setup with **▲▼**, then press **SK2**.
 - ↳ The editor opens.
2. Edit the setup title:
 - **Cross key**: Navigate to the character area and select with the central key.
 - **SK1**: Cancel editing
 - **SK2**: Switch upper/lower case letters
 - **SK3**: Delete character to the left of the cursor
 - **SK4**: Accept input and finish

Load a setup:

- ⇒ Use **▲▼** to highlight a setup and select it with the central key.
 - ↳ The parameters are loaded and the measurement screen is displayed.

Delete a setup:

1. Use **▲▼** to highlight a setup, then press **SK1**.
2. Confirm deletion with **SK4** or cancel with **SK1**.

Delete multiple setups:

Setups can only be deleted individually in the device.

- ⇒ To delete multiple setups, remove the SD card and edit the setup directories externally.
- ⇒ Alternatively, format the SD card.

ATTENTION! This will cause all stored data to be lost.

7.10 DATA LOGGER

⇒ For a description of the settings for the **DATA LOGGER**, see **9 DATA LOGGER** on *page 91*.

8

Operating modes

In this chapter, after an overview of the operating modes, you will find detailed information on each operating mode, with the specific settings and the measurement procedures.

- 8.1 Overview of operating modes and probe types (page 58)**
- 8.2 FIELD STRENGTH (page 60)**
- 8.3 SPATIAL AVERAGE (page 67)**
- 8.4 TIMER LOGGING (page 71)**
- 8.5 SPECTRUM (page 78)**
- 8.6 Shaped Time Domain (page 83)**

8.1 Overview of operating modes and probe types

Depending on the connected and recognized probe type, the following operating modes are available for selection in the FieldMan:

Operating mode (abbreviation ¹⁾)	HF probes	HP-01 (DC/LF)	EHP-50F/G (LF)	BFD-400-1 (LF)
FIELD STRENGTH (FS)	X	X	X	X
SPATIAL AVERAGE (SA)	X	X	X	X
TIMER LOGGING (TL)	X	X	X	X
SPECTRUM (SP)	–	X	X	X
SHAPED TIME DOMAIN (ST)	–	–	X	X

1) Name displayed on the soft key in connection with the mode symbol

The operating mode is selected and displayed on the device via **SK1**. **SK1** is only available for selection when a valid probe has been detected.

FIELD STRENGTH (FS)

Measurement of field strength or flux density and numerical representation of the measurement results for a defined frequency range, which may be broadband or band-limited. A time curve (**Time Curve**) can be optionally activated for the measurement results, which is implemented as a rolling memory.

⇒ See [8.2 FIELD STRENGTH on page 60](#).

SPATIAL AVERAGE (SA)

Allows spatial averaging of measured field strength values from multiple measurement positions and is mostly required for measuring thermal effects with HF probes. Averaging is done via the square of the field strength values (RMS averaging). In addition, a delay can be set for the measurement start. This allows the person performing the measurement to move away from the measuring location to avoid influencing the field.

⇒ See [8.3 SPATIAL AVERAGE on page 67](#).

TIMER LOGGING (TL)

Time-controlled broadband measurement of field strength values in a definable period of time. With the RMS detector type, all measured values (samples) acquired in a measurement interval are condensed into isotropic min/avg/max values that characterize the measurement interval. With the peak detector type (BFD-400 only), the acquired measured values (samples) are compressed to an isotropic max value.

⇒ See *8.4 TIMER LOGGING on page 71*.

SPECTRUM (SP)

FFT analysis of the measurement signal in the selected frequency range with display of the frequency spectrum, frequency marker evaluation and display of the broadband level. With the % unit selected, a normalized representation of the frequency response is shown, related to the limit values of a selected standard.

⇒ See *8.5 SPECTRUM on page 78*.

SHAPED TIME DOMAIN (ST)

Evaluation method in the time domain for the gapless recording of the weighted peak or RMS values with display of the exposure index in % related to a selectable personal protection standard. Whether the peak or RMS detector is used is defined in the measurement method standards IEC/EN 62233 for household appliances (Weighted RMS) or IEC/EN 62311 for other appliances (Weighted Peak).

⇒ See *8.6 Shaped Time Domain on page 83*.

8.2 FIELD STRENGTH

The **FIELD STRENGTH** operating mode is used to measure the field strength or flux density and enables the numerical display of the measurement results for a defined frequency range. This frequency range can be broadband or band-limited. A time curve (**Time Curve**) can be activated as a rolling memory for the measurement results.

This is the most commonly used mode for broadband or band-limited measurements.

8.2.1 Measurement settings

The **MEASUREMENT SETTINGS** menu provides quick access to the most important measurement settings for the selected operating mode.

Function ¹⁾	Description
Reset Results	Reset measurement results
Zero	Offset correction (HP-01 probe only) ⇒ See 10.3 Offset correction – Zero on page 102.
Frequency Span	Frequency range
Field	Electric or magnetic field
Range	Measuring range
Unit	Unit
Low Cut Filter	Filter for suppression of low frequencies (low cut filter)
Detector	Detector type
Time Curve	Show/hide time curve display
Time Span	Timeline for time curve display
Single Run	Automatic stop of the measuring sequence (only visible if Time Curve = On)
Pulse Detection	Short integration time for HF measurement, e.g. for more accurate measurement of short radar pulses (only visible with suitable HF probes)
Averaging Time	Time for moving averaging

1) The available parameters depend on the selected operating mode and the connected probe type.

8.2.2 Numerical display

Two fields are available for numerical display:

- **Main field:** Displays current or static measured values depending on the selected result type and detection type
- **Supplementary field:** Always displays static values

Detector

Select a detector:

⇒ **MEASUREMENT SETTINGS:** Select a detector under **Detector**.

↳ The selection option depends on the probe used:

Detector	Description	Availability
RMS	All measured values are recorded and displayed as RMS values.	All probes
Peak	All measured values are recorded and displayed as peak values.	BFD-400-1 probe only

Result type

The result types are always displayed in the supplementary field. To display them in the main field, the result type must be selected in the selection field using the cross key.

Select a result type:

⇒ Press the **◀ ▶** keys repeatedly until the desired result type is displayed.

↳ The selection option depends on the selected detector:

Detector	Result types	Display in supplementary field	Evaluation
RMS	ACTUAL	-	Current measured value
	MINIMUM	MIN	Smallest value
	MAXIMUM	MAX	Highest value
	AVERAGE	AVG	Averaged value
	MAX AVERAGE	MAXAVG	Highest averaged value
Peak	ACTUAL	-	Current measured value
	MINIMUM	MIN	Smallest peak value
	MAXIMUM	MAX	Highest peak value

The display in detail




Fig. 3: Numerical display in the **FIELD STRENGTH** operating mode

- 1 Result type selection field
- 2 Selected detector (selection in **MEASUREMENT SETTINGS**)
- 3 Main field:
 - Left: Result type **ACTUAL** (current isotropic value and three axes)
 - Right: Other result type (maximum value and current value)
- 4 Display status of measurement (e.g. **HOLD**) and averaging time until the set value was reached.
- 5 Supplementary field with statistical values

Result types **AVG** and **MAXAVG**

The time window defined by the **Averaging Time** (see 8.3 SPATIAL AVERAGE on page 67) for the formation of the moving average for the result types **AVG** and **MAXAVG** shifts continuously. As long as not all measured values are available to fill the time window, the averaging time is reduced to the actual acquisition time. The progress of the averaging is displayed in the **AVG TIME** field and in the progress bar between the main field and the supplementary field. After the set averaging time has been reached, the status display disappears. For **MAXAVG**, a valid value can only be displayed after the averaging time has elapsed.

Reset the measured values:

⇒ Press and hold key (> 2 s).

- oder –

1. Press **SK2**.
- ↳ **Reset Results** is already selected as the first entry.
2. Press key.
- ↳ The measured values are reset and the menu is closed.

8.2.3 Bar display

The bar represents the **ACTUAL** values with logarithmic scaling. The left and right limits are specified by the measuring range limits of the connected probe. **MIN** and **MAX** are displayed as marker lines.

Activate the bar display:

To display the bar graph, the time curve graph must be turned off.

⇒ **MEASUREMENT SETTINGS**: Deactivate **Time Curve**.

Start and stop the measurement:

⇒ Press **SK3**.

The display in detail




Fig. 4: Bar display in the **FIELD STRENGTH** operating mode

- 1 Current measured value
- 2 MIN value
- 3 MAX value
- 4 Overall bar scaled to measuring range

8.2.4 Time curve display

The time curve display shows the isotropic result of the field strength running from right to left with a rolling memory. The individual axes are not displayed graphically.

Activate the time curve display:

⇒ **MEASUREMENT SETTINGS**: Activate **Time Curve**.

- ↳ Since the curve memory is always active in the **FIELD STRENGTH** operating mode (even with **Time Curve = Off**), the complete curves of **ACTUAL** and, if applicable, **AVG** since the last operating mode change or reset appear immediately.

Start and stop the measurement:

⇒ Press **SK3**.

The display in detail




Fig. 5: Time curve display in the **FIELD STRENGTH** operating mode

- 1 Y-axis with automatic scaling
- 2 X-axis manually adjustable via **Time Span**
- 3 Yellow curve: Time curve of the current measured values (**ACTUAL**)
- 4 Blue curve: Time curve of the averaged measured values (**AVG**)

The display of the **AVG** curve is omitted if the peak detector was selected instead of the RMS detector for LF probes.

Using the marker

The measurement results can be evaluated via the marker.

Switch on the marker:

1. Press **SK3** to stop the display (**HOLD**).
↳ **SK1** now shows the marker symbol.
2. Press **SK1** to show the marker.
↳ A circle shows the marker position in the diagram (1), the time and measured value are indicated on the right above the diagram.



3. Use the **◀ ▶** keys to move the marker.
4. Press **SK1** to turn the marker off again.

If the display was stopped via **HOLD**, the measurement continues in the background. As soon as the display is restarted, there is therefore continuous recording and updating of the time curve display.

Using the peak marker

The peak values can be evaluated via the peak marker.

⇒ For information on the peak marker, see [10.7 Peak marker on page 106](#).

Stopping the measurement sequence automatically

If required, the measurement sequence can be stopped automatically after a run via the **Single Run** function.

Activate automatic stop:

⇒ **MEASUREMENT SETTINGS**: Activate **Single Run**.

- ↳ When activated, the results memory is deleted and a measurement sequence is performed over the set time period. After the time period is reached, the measurement is stopped completely. The measurement sequence can be restarted at any time via a reset.

8.3 SPATIAL AVERAGE

The **SPATIAL AVERAGE** operating mode enables the spatial averaging of measured field strength values over 1 to a maximum of 100 measuring positions. It can also be useful to measure at a single measuring position, in order to record the field strength in a specific spatial volume there, averaged over the desired measuring time, by continuous movement of the measuring probe.

The spatial averaging is determined by quadratic averaging over all measured positions and displayed as a horizontal line in the bar graph. The measurement per position can be stopped automatically after a preset time or manually. An adjustable delay allows the person performing the measurement to leave the measurement site before the measurement starts.

8.3.1 Measurement settings

The **MEASUREMENT SETTINGS** menu provides quick access to the most important measurement settings for the selected operating mode.

Function ¹⁾	Description
Zero	Offset correction (HP-01 probe only) ⇒ See <i>10.3 Offset correction – Zero on page 102</i> .
Frequency Span	Frequency range
Field	Electric or magnetic field
Range	Measuring range
Unit	Display unit
Low Cut Filter	Filter for suppression of low frequencies (low cut filter)
Detector	Detector type
Measurement Time	Stop measurements: <ul style="list-style-type: none"> Manual: The measurement must be ended manually. 5 s, 10 s...: The measurement stops after the preselected time.

Function ¹⁾	Description
Start Delay	Start type of measurement: <ul style="list-style-type: none">• No delay: The measurement starts immediately• 5 s, 10 s...: The measurement starts after the selected time. A countdown shows the time until the start.
Pulse Detection	Short integration time for HF measurements, e.g. for more accurate measurement of short radar pulses (only visible with suitable HF probes).

1) The available parameters depend on the operating mode and the probe type.

8.3.2 Measurement

- ✓ Automatic or manual stop was selected.
- ✓ Immediate or delayed start was selected.

1. Press **SK3**.
 - ↳ The measurement starts immediately or after the selected time.
2. Press **SK3** to stop the measurement manually or wait for the preselected time to elapse. Even with automatic stop, a measurement in progress can be stopped manually.
 - ↳ After the measurement has been completed, a selection window appears:
 - **Next Position:** Start the measurement at the next position
 - **Repeat Position:** Start a new measurement at the same position
 - **Cancel All:** Delete all measurements. The deletion must be confirmed again.
 - **SAVE AND FINISH:** Save measurements and end measurement.
3. Select an entry. **Cancel All** must be confirmed again.
 - ↳ The function is executed immediately and the selection window is closed.

Set start with or without delay:

1. **MEASUREMENT SETTINGS:** Select **Start Delay**.
2. Select the desired setting and press the **●** key:
 - **No delay:** The measurement starts immediately
 - **Time:** The measurement starts after the selected time. A countdown shows the time until the start.
3. Exit the menu with the **Back** key.

8.3.3 Numerical display

Two fields are available for numerical display:

- **Main field:** Displays the current measured values isotropically and for the three axes
- **Supplementary field:** Displays the averaged values of the last measured position as well as over all positions

Detector

In the **SPATIAL AVERAGE** operating mode, **RMS** is always used.

Result type

In the **SPATIAL AVERAGE** operating mode, **ACTUAL** is always used.

The display in detail




Fig. 6: Numerical display in the **SPATIAL AVERAGE** operating mode

- 1 Result type always **ACTUAL**, detector always **RMS**
- 2 Current isotropic measured value
- 3 Current measured values of the three axes
- 4 Number of the position and current time over which averaging is currently being performed
- 5 Evaluations:
 - **AVG:** Average value of the displayed position
 - **SPATIAL AVG:** Spatial average of all measured positions

8.3.4 Bar display

In the vertical bar graph, the successively measured values for each measuring position are displayed from left to right. The spatial average is shown as a horizontal line. To evaluate all positions, you can scroll to the left and right with the arrow keys after the measurement has been completed.

The display in detail




Fig. 7: Bar display in the **SPATIAL AVERAGE** operating mode

- 1 Average value of the respective position
- 2 Spatial average over all measured positions

Evaluating the bar display

- ✓ The measurement is completed (**SAVE AND FINISH**).
- ⇒ Select a measuring position with the **◀ ▶** keys.
 - ↳ In the bar display: The selected bar is highlighted brighter.
 - ↳ In the supplementary field: The position as well as the associated measured value (**AVG**) is displayed. Up to 13 bars can be displayed simultaneously in the graph. If there are more than 13 positions, the bar display can be scrolled using the **◀ ▶** keys.

8.4 TIMER LOGGING

The **TIMER LOGGING** operating mode enables time-controlled measurement of field strength values in a definable time period of up to 100 hours. During recording, the progress is displayed via a time bar. After the measurement has been completed, the saved result can be viewed as a time curve display in the data logger (see *9 DATA LOGGER* on page 91).

8.4.1 Measurement settings

The **MEASUREMENT SETTINGS** menu provides quick access to the most important measurement settings for the selected operating mode.

Function ¹⁾	Description
Zero	Offset correction (HP-01 probe only) ⇒ See <i>10.3 Offset correction – Zero</i> on page 102.
Start Time	Timer start time
Timer Duration	Timer runtime
Storage Interval	Storage interval
Frequency Span	Frequency range
Field	Electric or magnetic field
Range	Measuring range
Unit	Display unit
Low Cut Filter	Filter for suppression of low frequencies (low cut filter)
Detector	Detector type (only available with BFD-400-1 probe)
Pulse Detection	Short integration time for HF measurements, e.g. for more accurate measurement of short radar pulses (only visible with suitable HF probes)
Averaging Time	Averaging time

1) The available parameters depend on the operating mode and the probe type.

A maximum of 32,000 storage intervals can be recorded. If a short storage interval is set with a long runtime, one of the values is automatically corrected. Example: With a storage interval of 1 s, the maximum possible runtime is 8 h 53 min 20 s.

8.4.2 Sequence of a time-controlled measurement

1. Select timer settings

- **Start Time**
- **Timer Duration**
- **Storage Interval**

⇒ See 8.4.1 *Measurement settings* on page 71.

2. Activate comment functions (if required)

- **Add Text Comment**
- **Add Voice Comment**

⇒ See 7.3 *GENERAL SETTINGS* on page 45.

3. Activate timer

⇒ Press **SK3**.

- ↳ When the comment function is activated, the user is prompted for a voice comment and/or text input.
- ↳ The device waits until the specified start time for the measurement.
- ↳ The setting for automatic shutdown (**Automatic Shutdown**) is ignored and the device remains switched on (see 7.3.5 *DEVICE* on page 47).

The following actions are possible during this time:

Start recording immediately:

⇒ Press **SK3**.

Deactivate timer again:

⇒ Press **SK1**.

- ↳ In this case, previously recorded voice or text comments will be deleted.

Activate stand-by until recording starts:

⇒ Press **SK2**.

- ↳ The device is put into a power-saving sleep mode (stand-by), wakes up again at the specified time, and then performs the measurements. A certain lead time is required to reactivate the connected probes.
- ⇒ During standby, the device can be woken up at any time by pressing any key and will be in the same state as before standby.

This function is only available for long periods of 5 minutes or more and for probes with electrical interface.

4. Timer is started

- When recording is started, the previously recorded measurement data is reset.
- Then the measurement data are stored cyclically until the measuring duration (**Timer Duration**) is reached.

The following actions are possible during this time:

End measurement prematurely:

⇒ Press **SK3**.

- ↳ Even if the measurement is terminated prematurely, all intervals measured up to that point are saved.
- ↳ Afterwards, the timer is automatically deactivated again.

The rechargeable battery life can be extended by activating the screen saver. This makes longer measuring times possible.

⇒ See 7.3.1 *DISPLAY* on page 45.

5. After the measurement

The device switches off automatically after the set measuring time (**Timer Duration**) has elapsed (regardless of the setting for **Automatic Shutdown**).

Automatic shutdown does not take place in the following cases:

- The user has ended the measurement prematurely.
- A key was pressed directly after the measuring period (**Timer Duration**) elapsed.

8.4.3 Numerical display

Two fields are available for numerical display:

- **Main field:** Displays current or static measured values depending on the selected result type and detection type
- **Supplementary field:** Always displays static values

Detector

A selection is only available for the BFD-400-1 probe. For all other probes, **RMS** is specified.

Select a detector:

⇒ **MEASUREMENT SETTINGS:** Select a detector under **Detector**.

Detector	Description	Availability
RMS	All measured values are recorded and displayed as RMS values.	All probes
Peak	All measured values are recorded and displayed as peak values.	BFD-400-1 probe only

Result type

The result types are always displayed in the supplementary field. To display them in the main field, the result type must be selected in the selection field using the cross key.

Select a result type:

⇒ Press the **◀ ▶** keys repeatedly until the desired result type is displayed.

↳ The selection option depends on the selected detector:

Detector	Selection via cross key	Main field		Supplementary field
		Top	Bottom	
RMS (all probes)	ACTUAL	ACTUAL	X Y Z	MAX, MIN, MAXAVG, AVG
	MINIMUM	MIN	ACTUAL	
	MAXIMUM	MAX	ACTUAL	
	AVERAGE	AVG	ACTUAL	
	MAX AVERAGE	MAXAVG	ACTUAL	

Detector	Selection via cross key	Main field		Supplementary field
		Top	Bottom	
Peak (BFD-400-1 only)	ACTUAL	ACTUAL	X Y Z	MAX, MIN
	MINIMUM	MIN	ACTUAL	
	MAXIMUM	MAX	ACTUAL	

The display in detail




Fig. 8: Numerical display in the **TIMER LOGGING** operating mode

- 1 Result type selection field
- 2 Selected detector (selection in **MEASUREMENT SETTINGS**)
- 3 Main field:
 - Left: Result type **ACTUAL**.
The current isotropic value and the three axes are displayed.
 - Right: Other result type, here as an example **AVERAGE**.
The selected result type is displayed and **ACTUAL** is always displayed as well
- 4 Supplementary field

The measured values are always displayed, regardless of whether data is being recorded.

8.4.4 Bar display

The bar display graphically shows the progress of the measurement. In addition, the start time, timer duration and storage interval are specified numerically.




Fig. 9: Progress display via time bar: Activated timer (left), after start (right)

No	Activated timer	Timer started
-		
1	Animated symbol for activated timer	Animated symbol for remaining time
2	Start time of recording	Remaining time
3	Time bar of recording duration	
4	Recording duration and storage interval	
5	Softkey for cancel, stand-by and start	Softkey for stop

8.4.5 Time curve display in the DATA LOGGER

When viewing saved results via the **DATA LOGGER**, the results are displayed graphically as a progression over time. In the process, the up to 32,000 measurement intervals are condensed to a maximum of 240 measurement intervals to enable display and evaluation with the **Marker** and **Peak Marker**. In case of later data evaluation on the PC, detailed evaluation in full time resolution is possible.

The time axis displayed on the device is labeled with the total measurement duration in the format hh:mm:ss. When the marker is switched on, the maximum value that occurred in the (condensed) measurement interval is displayed as **ACT** value together with the time of the interval end.

The display in detail

⇒ To call up the time curve display in the **DATA LOGGER**, see **9 DATA LOGGER on page 91**.




Fig. 10: Graphic display in the **TIMER LOGGING** operating mode after calling it up in the **DATA LOGGER**

- 1 Unit
- 2 Time and ACT measured value with marker switched on
- 3 Graphical display of the current values
- 4 Measuring duration in the format hh:mm:ss

Using the marker

1. Press **SK1** to turn on the marker.
↳ A circle shows the marker position in the diagram, the time and measured value are indicated on the right above the diagram.
2. Use the **◀ ▶** keys to move the marker.
3. Press **SK1** to turn the marker off again.

Using the peak marker

The peak values can be evaluated via the peak marker.

⇒ For information on the peak marker, see **10.7 Peak marker on page 106**.

8.5 SPECTRUM

The **SPECTRUM** operating mode enables the FFT analysis of the measurement signal in the selected frequency range with display of the frequency spectrum, evaluation via a frequency marker and display of the broadband level. Either one of the single axes **X**, **Y** or **Z** or **Isotropic** can be selected as the measuring axis. In addition, a selectable limit value curve can be displayed in the spectrum. When the unit **%** is selected, the spectrum is normalized to the field strength limits of a personal protection standard.

8.5.1 Measurement settings

The **MEASUREMENT SETTINGS** menu provides quick access to the most important measurement settings for the selected operating mode.

Function ¹⁾	Description
Reset Results	Reset measurement results
Zero	Offset correction (HP01 probe only) ⇒ See 10.3 <i>Offset correction – Zero</i> on page 102.
Result Type	Result type (see <i>Result type</i> on page 79)
Frequency Span	Frequency range
Frequency Scale	Linear or logarithmic scaling
Field	Electric or magnetic field
FFT Points	Determines the frequency resolution of the FFT analysis (number of frequency values = FFT points / 2)
Range	Measuring range
Axis	Spatial axis of the probe shown in the graph
Unit	Display unit
Low Cut Filter	Filter for suppression of low frequencies (low cut filter)
Detector	Detector type: RMS, Peak
Standard	Displays a selection list of the standards according to whose limits normalization is performed or the limit progression is displayed in the spectrum (see 8.5 <i>SPECTRUM</i> on page 78).
Number of Averages	Number of spectra over which averaging is performed

1) The available parameters depend on the selected operating mode and the connected probe type.

8.5.2 Measuring and evaluating a spectrum

The measurement starts immediately after selecting the operating mode.

The **◀ ▶** keys can be used to move and evaluate the marker at any time during the measurement. However, to use the peak marker, the display must be stopped.

Stop and start measurement:

⇒ Press **SK3**.

In the graphical display, the measured values can be evaluated using the **Peak Marker** function (see *8.5.4 Graphic display on page 81*).

8.5.3 Numerical display

Two fields are available for numerical display:

- **Main field:** Displays current or statistical broadband values depending on the selected result type and detection type
- **Supplementary field:** Always displays statistical broadband values

Detector

A selection is only available for the BFD-400-1 probe. For all other probes, **RMS** is specified.

Select a detector:

⇒ **MEASUREMENT SETTINGS:** Select a detector under **Detector**.

Detector	Description	Availability
RMS	All measured values are recorded and displayed as RMS values.	All probes
Peak	All measured values are recorded and displayed as peak values.	BFD-400-1 probe only

Result type

In **SPECTRUM** mode, the control pad is used for the marker. The selection of the result type is therefore made in the measurement settings.

Select a result type:

⇒ **MEASUREMENT SETTINGS:** Select the desired result type under **Result Type**.

↳ The selection option depends on the detector and the probe.

When the result type is selected in the measurement settings, the result type displayed in the graphical display also switches over automatically.

Detector	Selection via measurement settings	Main field		Supplementary field
		Top	Bottom	
RMS (no HF probes)	ACTUAL	ACTUAL	X Y Z	MAX, AVG
	MAXIMUM	MAX	ACTUAL	
	AVERAGE	AVG	ACTUAL	
Peak (BFD-400-1 only)	ACTUAL	ACTUAL	X Y Z	MAX
	MAXIMUM	MAX	ACTUAL	

The display in detail




Fig. 11: **SPECTRUM** operating mode: Numerical display of the broadband values (left) and the highest spectral line in % of the selected standard (right).

- 1 Selected result type (selection in **MEASUREMENT SETTINGS**)
- 2 Selected detector (selection in **MEASUREMENT SETTINGS**)
- 3 Main field: Result type **ACTUAL**
 - **Left:** Current isotropic value and the three axes
 - **Right:** Current isotropic value and the three axes for the highest line of the normalized spectrum with frequency indicated

Reset the measured values:

⇒ **MEASUREMENT SETTINGS > Reset Results > ● key.**

- ↳ The measured values are reset and the menu is closed.

8.5.4 Graphic display

Properties of the graphical representation:

X-axis

- The entire frequency range up to the set span is always displayed (**MEASUREMENT SETTINGS > Frequency Span**).
- The frequency scaling can be set to either linear from 0 Hz or logarithmic (**MEASUREMENT SETTINGS > Frequency Scale**).

Y-axis

- The field strength is displayed on a logarithmic scale.

Measuring curve

- **Representation:** Maximum of one measuring curve (X, Y, Z axis or isotropic)
- **If standard is selected:** The associated limit value curve is additionally displayed. The field strength axis is scaled automatically. Some standards are only defined from higher frequencies and can therefore only be displayed partially or not at all.
- **% unit selected:** Spectrum is displayed normalized, related to the selected standard.
- **If no standard is selected (Standard = None):** A message prompts to select a standard.

The display in detail




Fig. 12: Graphical display of the spectrum

- 1 Type of measuring curve (X, Y, Z-axis or isotropic)
- 2 Selected standard
- 3 Marker position
- 4 Marker functions (see *Using the marker on page 82*)
- 5 Values at the marker position
- 6 Limit curve of the selected standard
- 7 Spectrum

Using the marker

⇒ Use the \blacktriangleleft \triangleright keys to move the marker to the desired position on the measuring curve.

Using the peak marker

The highest spectral lines can be evaluated via the peak marker.

- ✓ The peak marker can only be selected after the display has been stopped.
- ⇒ For information on the peak marker, see *10.7 Peak marker on page 106*.

8.6 Shaped Time Domain

In the **SHAPED TIME DOMAIN** operating mode, an evaluation method is used in the time domain, which ensures gapless recording of the weighted peak or RMS values related to a selectable personal protection standard. The result is displayed as an exposure index in %.

The applied measurement method is described in international standards and is generally referred to as **Weighted Peak Method** or **Weighted RMS Method** respectively.

In addition to the numerical result display, a logarithmically scaled bar display shows the exposure index graphically over the entire measurement range of the probe. Instead of the bar display, a time curve graph can also be displayed.

The **SHAPED TIME DOMAIN** operating mode is only available for the EHP-50F/G and BFD-400-1 probes.

8.6.1 Measurement settings

The **MEASUREMENT SETTINGS** menu provides quick access to the most important measurement settings for the selected operating mode.

Function ¹⁾	Description
Reset Results	Reset measurement results
Field	Electric or magnetic field
Range	Measuring range
Low Cut Filter (BFD-400-1 only)	Selection of the lower cutoff frequency, e.g. to reduce the influence of the earth's magnetic field
Method	Method for weighting: <ul style="list-style-type: none"> WPM-TD (IEC/EN 62311): Weighted Peak Method (fixed for the EHP-50F/G probe) WRM-TD (IEC/EN 62233): Weighted RMS Method
Weighting	Displays a selection list of standards according to whose limits the evaluation is performed.
Time Curve	Graphic display: <ul style="list-style-type: none"> Bar display: Time Curve = Off Time curve graph: Time Curve = On

Function ¹⁾	Description
Time Span	Time domain (X axis)
Single Run	Measurement ends after set Time Span

1) The available parameters depend on the selected operating mode and the connected probe type.

8.6.2 Numerical display

Two fields are available for numerical display:

- **Main field:** Displays current or static measured values, depending on the selected result type and detection type, as well as the selected evaluation standard
- **Supplementary field:** Always displays static values

Detector

The **Peak** or **RMS** detector to be used is determined by the selected measurement method (see 8.6.1 *Measurement settings on page 83*, **Method**).

Evaluation curve

The limits to be used for calculating the exposure index are determined by selecting a standard (see 8.6.1 *Measurement settings on page 83*, **Weighting**).

Result type

The result types are always displayed in the supplementary field. To display them in the main field, the result type must be selected in the selection field using the cross key.

Select a result type:

⇒ Press the **◀ ▶** keys repeatedly until the desired result type is displayed.

Detector ¹⁾	Selection via cross key	Main field		Supplementary field
		Top	Bottom	
RMS + Peak	ACTUAL	ACTUAL	X Y Z	MAX, MIN
	MINIMUM	MIN	ACTUAL	
	MAXIMUM	MAX	ACTUAL	

1) In this mode of operation, the EHP-50F/G probe has only the **Peak** detector type, on the EHP-50G the WPM option must be enabled.

The display in detail




Fig. 13: Numerical display in the **SHAPED TIME DOMAIN** operating mode

- 1 Selected result type (selection via cross key)
- 2 Selected detector (selection in **MEASUREMENT SETTINGS**)
- 3 Selected evaluation standard
- 4 Main field:
 - **Left:** Result type **ACTUAL**.
The current isotropic value and the three axes are displayed.
 - **Right:** Other result type, here as an example **MAXIMUM**.
The selected result type is displayed and **ACTUAL** is always displayed as well
- 5 Supplementary field:
 - Statistical values **MIN** and **MAX**

8.6.3 Bar display

The bar represents the **ACTUAL** values with logarithmic scaling. The left and right limits are specified by the measuring range limits of the connected probe. **MIN** and **MAX** are displayed as marker lines.

Activate the bar display:

To display the bar graph, the time curve graph must be turned off.

⇒ **MEASUREMENT SETTINGS**: Select **Time Curve = Off**.

The display in detail




Fig. 14: Bar display in the **SHAPED TIME DOMAIN** operating mode

- 1 **MIN** value numerical and graphical
- 2 **MAX** value numerical and graphical
- 3 Current measured value (**ACTUAL**)
- 4 Overall bar scaled to measuring range
- 5 Measurement method and weighting standard

8.6.4 Time curve display

The time curve graph represents the isotropic result of the exposure index running from right to left with a rolling memory.

Activate the time curve display:

⇒ **MEASUREMENT SETTINGS**: Activate **Time Curve**.

- ↳ Since the curve memory is always active in the **SHAPED TIME DOMAIN** operating mode (even with **Time Curve = Off**), the complete curve progression since the last operating mode change or reset appears immediately.




Fig. 15: Time curve display in the **SHAPED TIME DOMAIN** operating mode

- 1 Selected standard
- 2 Measured values in % of standard
- 3 Result type
- 4 Time curve of the measurement
- 5 Time axis

Using the marker

- ✓ The display is in **HOLD** mode.
- 1. Press **SK1** to turn on the marker.
- 2. Use the **◀ ▶** keys to move the marker to the desired position on the measuring curve.
- 3. Press **SK1** to turn the default marker off again.




Fig. 16: Marker in the **SHAPED TIME DOMAIN** operating mode

- 1 **SK1**: Switch marker on/off
- 2 Movement symbols for standard markers
- 3 Measured values at the marker position
- 4 Marker position
- 5 **SK4**: Switch peak marker on/off

If the display was stopped via Hold, the measurement continues in the background. As soon as the display is restarted, there is therefore continuous recording and updating of the time curve display.

Using the peak marker

The peak values can be evaluated via the peak marker.

⇒ For information on the peak marker, see *10.7 Peak marker on page 106*.

Stopping the measurement sequence automatically

If required, the measurement sequence can be stopped automatically after a run via the **Single Run** function.

Activate automatic stop:

⇒ **MEASUREMENT SETTINGS**: Activate **Single Run**.

- ↳ When activated, the results memory is deleted and a measurement sequence is performed over the set time period. After the time period is reached, the measurement is stopped completely. The measurement sequence can be restarted at any time via a reset.

9

DATA LOGGER

The data memory manages the stored measurement results, screenshots and media (photos and videos). Selected data can be displayed and evaluated with the Data Viewer. All acquired data is stored on the SD card of the device, organized by projects.

- 9.1 Structure of the DATA LOGGER (page 92)**
- 9.2 Managing projects (PROJECT) (page 93)**
- 9.3 Managing measurements (MEASUREMENTS) (page 94)**
- 9.4 Managing screenshots (SCREENSHOTS) (page 96)**
- 9.5 Managing media (MEDIA) (page 96)**

9.1 Structure of the DATA LOGGER

All content (measurements, screenshots, media) is managed in projects. Up to 99 projects can be created, edited and deleted. To call up the saved content, first select the desired project. Then the associated content can be selected.

Open the data memory:

- ✓ The device is in the measuring mode of any operating mode.
- ⇒ Open the device settings with **SK4**, then select **DATA LOGGER**.
 - ↳ The main menu opens.




Fig. 17: Main menu **DATA LOGGER**

- 1 Selected project
- 2 Number of saved measurements in the selected project
- 3 Number of saved screenshots in the selected project
- 4 Number of stored media in the selected project
- 5 Selection to display the project at startup
- 6 Free storage space

9.2 Managing projects (PROJECT)

- ⇒ Select **PROJECT** in the main menu.
 - ↳ The submenu opens.

9.2.1 Creating a new project

- ⇒ Press **SK4**.
 - ↳ The project is created and named **Project n**. **n** is incremented up continuously (to 99).

9.2.2 Renaming a project

1. Select the project and press **SK2**.
2. Change the project title in the editor.
To do this, use the **◀ ▶** and **▲ ▼** keys to select the desired characters in the character area and accept them with the **●** key.

Move the cursor in the title window:

- ◀ Move one character to the left in the title window
- ▷ Move one character to the right in the title window

Functions of the keys **SK1** to **SK4**:

- ✗ Cancel input
- ↑ Toggle upper/lower case
- ☒ Delete last character
- ✓ Save changes

9.2.3 Deleting a project

1. Select the project and press **SK1**.
2. Confirm the deletion.

9.3 Managing measurements (MEASUREMENTS)

In the **MEASUREMENTS** menu, the measurements stored in a project can be called up and evaluated, supplemented with comments or deleted.

Select a measurement:

- ✓ The desired project has been selected
(see 9.2 *Managing projects (PROJECT) on page 93*).
- 1. Mark **MEASUREMENTS** and select it with the ● or ▶ key.
↳ The submenu opens.
- 2. Mark the desired measurement.

You now have the following options:

- Open and evaluate the measurement
- Add a text comment
- Add a voice comment
- Delete the measurement

9.3.1 Open and evaluate a measurement

⇒ Open the marked measurement with the ● or ▶ key.

↳ The measurement is displayed.

Additional functions are available via the keys **SK1** to **SK4**:

- Turn on the marker
- Change measurement settings
(limited selection, e.g. change the measurement unit)
- △ Show previous measurement of the selected project
- ▽ Show next measurement of the selected project

Using the marker

1. Press **SK1** to turn on the marker.
2. Use the ▲ ▼ keys to move the marker to the desired position on the measuring curve.
3. Press **SK1** to turn the default marker off again.

⇒ For more information on the marker functions, see the descriptions in the operating modes.

Using the peak marker

The peak values can be evaluated via the peak marker.

⇒ For information on the peak marker, see *10.7 Peak marker on page 106*.

9.3.2 Adding a text comment

✓ The measurement is marked in the overview page (**MEASUREMENTS**).

1. Press **SK3**.
 - ↳ The editor for entering a comment opens.
2. Use the **◀ ▶** and **▲ ▼** keys to select the desired characters in the character area and accept them with the **●** key.
3. Press **SK4** to save the comment.

Move the cursor in the title window:

- ◀ Move one character to the left in the title window
- ▷ Move one character to the right in the title window

Functions of the keys **SK1 to **SK4**:**

- ✗ Cancel input
- ⇧ Toggle upper/lower case
- ☒ Delete last character
- ✓ Save changes

9.3.3 Adding a voice comment

✓ The measurement is marked in the overview page (**MEASUREMENTS**).

1. Press **SK4**.
 - ↳ The recording starts immediately.
2. Press **SK4** to stop the recording.
 - ↳ The recording is played back.
3. After that, the following functions of the keys **SK1** to **SK4** are available:
 -  Delete recording
 - REC Repeat recording

- ▷ Play recording
- ✓ Save recording

4. Press **SK4** to save the recording.

- ↳ In the overview page (**MEASUREMENTS**), the symbol for the voice comment appears behind the selected measurement.

9.3.4 Deleting a measurement

✓ The measurement is marked in the overview page (**MEASUREMENTS**).

⇒ Press **SK1** and confirm the deletion.

- ↳ The measurement is deleted.

9.4 Managing screenshots (SCREENSHOTS)

In the **SCREENSHOTS** menu, the screenshots stored in a project can be called up and deleted.

Select a screenshot:

✓ The desired project has been selected
(see *9.2 Managing projects (PROJECT) on page 93*).

1. Mark **SCREENSHOTS** and select it with the ● or ▶ key.

- ↳ The submenu opens.

2. Mark the desired screenshot.

Show the marked screenshot:

⇒ Press the ● or ▶ key to open the marked screenshot.

⇒ **SK3** key: Show previous screenshot

⇒ **SK4** key: Show next screenshot

⇒ Press the **Back** key to return to the menu.

Delete the marked screenshot:

1. Press **SK1**.

2. Confirm deletion with **SK4** or cancel with **SK1**.

9.5 Managing media (MEDIA)

In conjunction with a smartphone and the associated app, images and videos can be stored and accessed in the media area. This function is not available at the moment.

10

Cross-mode functions

This chapter describes functions and settings that affect several operating modes or are not mode-specific.

- 10.1 Post-Processing (page 98)**
- 10.2 Selection of a standard (page 100)**
- 10.3 Offset correction – Zero (page 102)**
- 10.4 Commenting on measurement results (page 103)**
- 10.5 Alarm function (page 104)**
- 10.6 Acoustic intensity display (HF probes only) (page 105)**
- 10.7 Peak marker (page 106)**
- 10.8 Display of overdriven measured values (page 107)**

10.1 Post-Processing

⇒ See 7.5.1 *POST-PROCESSING* on page 47.

This menu contains settings for post-processing the measurement data of broadband HF probes. These setting options are thus limited to the operating modes of **FIELD STRENGTH**, **SPECTRUM** and **TIMER LOGGING**. Two types of post-processing are available:

- The application of a correction factor
- The conversion to display in % of the standard for measured field strengths at a reference frequency

For evaluating probes, only the correction factor can be applied.

10.1.1 Applying a correction factor

⇒ See 7.5.1 *POST-PROCESSING* on page 47: **Apply Correction Factor CF**

When calibrating the HF probes, the measuring error at the defined calibration frequencies is recorded and stored in the probe. If the correction is applied (**Apply Correction Factor CF = On**), then the measuring error is taken into account in the measurement result and thus a higher measurement accuracy is achieved. However, the correction can only be applied meaningfully when measuring at a single prevailing frequency, which must also be known. If this frequency does not exactly correspond to a calibration frequency, it can still be entered as a reference frequency (**Reference Frequency**) and the corresponding correction factor is then determined by interpolation from the adjacent correction factors.

10.1.2 Setting the reference frequency

⇒ See 7.5.1 *POST-PROCESSING* on page 47: **Reference Frequency**

Reference Frequency provides a selection list of probe-specific calibration frequencies. In addition, the input of any frequency is possible with a resolution of up to 1 kHz.

The last set value in MHz is always displayed, even if the frequency no longer matches the probe after a probe change. Only when the calibration factor or the display in % of the standard are activated is the frequency list updated by reading from the probe data and set to the lowest value.

Set the reference frequency:

1. Select Reference Frequency.

- ↳ A list opens with the calibration frequencies stored in the probe. The last selected value is automatically highlighted.

2. If necessary, select another value from the list.

In addition to the values from the list, any intermediate value can be set with a resolution of 1 kHz.

Set any value:

1. After selecting **Reference Frequency**, press the **SK1** softkey.

2. Set the digit and value with the cross key.

3. Press **SK4** to transfer the new value to the selection list.

- ↳ The pen symbol indicates a frequency where calibration has not been performed and where the calibration factor is determined by interpolation. There can be only one entry with pen symbol at a time. This remains in the list until another frequency value is selected and is then deleted again.

HF probes are broadband probes and cannot measure selectively at the set frequency. In the case of incorrect frequency specification or multifrequency fields, these settings can therefore lead to incorrect results.

10.1.3 Display in % of standard

Non-evaluating probes measure the field strength. The **% of Standard** unit is only available for selection for these probes if the conversion for a specific personal protection standard has been activated in the menu. The measured value display in % is related to the power density and not to the field strength.

Activate conversion:

✓ **DEVICE SETTINGS > EXPERT SETTINGS**

1. Select **Standard**.

2. Reference frequency of the field (**Reference Frequency**) indicated.

3. Activate **% of Standard**: Select **Lowest Limit** or **Reference Frequency**.

The reference to the lowest limit value of a standard (**Lowest Limit**) is recommended when the frequency of the field source is not known.

The **Lowest Limit** setting is not available if the use of the correction factor is switched on.

Reference Frequency	Correction Factor	Lowest Limit
<p>REF: 2.45 GHz Hz E-Field</p> <p>ACTUAL RMS</p> <p>ICNIRP 2020 GP</p> <p>4.71 %</p> <p>Y 12.31 Z 1.292</p>	<p>CF: 2.45 GHz Hz E-Field</p> <p>ACTUAL RMS</p> <p>ICNIRP 2020 GP</p> <p>243 %</p> <p>Y 5.304 Z 1.871</p>	<p>REF: Lowest Limit Hz E-Field</p> <p>ACTUAL RMS</p> <p>ICNIRP 2020 GP</p> <p>379 %</p> <p>Y 6.301 Z .9926</p>

The reference frequency (**Reference Frequency**) is displayed in the probe info field, e.g. with **REF: 2.45 GHz**.

If the correction factor is applied at the same time, the entry **CF: 2.45 GHz** appears instead.

When referring to the smallest (strictest) limit value, **REF: Lowest Limit** is displayed.

The standard selected in the menu is also shown in the display (in the yellow field above the isotropic measured value).

10.2 Selection of a standard

There is a wide range of national and international standards setting exposure limits for electric and magnetic fields. They can differ in frequency range and range of effect (influence on the body).

The standards (limit value curves) to be available for selection on the FieldMan can be configured via the Narda-TSX PC software. Predefined standards are available, which can be extended by self-created standards.

User-defined standards are saved on the SD card during configuration and are marked on the device with a preceding asterisk. Predefined standards, on the other hand, are stored in the FieldMan.

The standards for evaluative measurements of the **SHAPED TIME DOMAIN** operating mode are implemented in the measuring probes and can only be changed by a firmware update of the manufacturer.

10.2.1 Standards for HF probes

The HF probes of the FieldMan measure broadband frequencies and cannot be set to a specific frequency. The measurement result can be displayed as the percentage of the limit value that has been reached if the frequency of a field source is known or in relation to the lowest limit value above the frequency of a standard. The settings are made in the menu under **EXPERT SETTINGS**.

A selection of predefined standards appears below. The selection options in the FieldMan may differ from this and depend on the device configuration.

Standard ¹⁾	Frequency range
2013/35/EU LAL	1 Hz to 10 MHz
2013/35/EU HAL	1 Hz to 10 MHz
2013/35/EU Limbs	1 Hz to 10 MHz
2013/35/EU Thermal	100 kHz to 300 GHz
26. BlmSchV 2013 (1a)	1 Hz to 10 MHz
26. BlmSchV 2013 (1b)	100 kHz to 300 GHz
EMFV 2016 LAL	1 Hz to 10 MHz
EMFV 2016 HAL	1 Hz to 10 MHz
EMFV 2016 Limbs	1 Hz to 10 MHz
EMFV 2016 Thermal	100 kHz to 300 GHz
FCC 96-326 GP	300 kHz to 100 GHz
FCC 96-326 Occ	300 kHz to 100 GHz
GB8702-2014 GP	1 Hz to 300 GHz
ICNIRP 1998 GP	1 Hz to 300 GHz
ICNIRP 1998 Occ	1 Hz to 300 GHz
ICNIRP 2010 GP	1 Hz to 10 MHz
ICNIRP 2010 Occ	1 Hz to 10 MHz
ICNIRP 2020 GP	100 kHz to 300 GHz
ICNIRP 2020 Occ	100 kHz to 300 GHz
IEEE 2019 Unrest NS	1 Hz to 5 MHz
IEEE 2019 Restrd NS	1 Hz to 5 MHz
IEEE 2019 Unrestricted	100 kHz to 300 GHz
IEEE 2019 Restricted	100 kHz to 300 GHz

Standard ¹⁾	Frequency range
SC6-2015 Uncrlid NS	3 kHz to 10 MHz
SC6-2015 Ctrlid NS	3 kHz to 10 MHz
SC6-2015 Uncontrolled	0.1(1) MHz to 300 GHz
SC6-2015 Controlled	0.1(1) MHz to 300 GHz

1) **LAL**: Low, **ALs**; **HAL**: High ALs; **Limbs**: Limbs ALs; **Thermal**: ALs Thermal; **GP**: General Public; **Occ**: Occupational; **Unrest**: Unrestricted; **Restrd**: Restricted; **Uncrlid**: Uncontrolled; **Ctrlid**: Controlled

10.2.2 Standards for LF probes

For the LF probes, the standard is used to display the limit curve graphically in the spectrum or to display the measurement result as a normalized spectrum. The selection is made under **MEASUREMENT SETTINGS** > **Standard**. The same table applies as for HF probes. The selection **None** is used to switch off the display of a limit value curve in the **SPECTRUM** operating mode.

10.3 Offset correction – Zero

⇒ See measurement settings in the operating modes.

Manual offset correction is only required for the HP-01 probe. The correction process is started by triggering **Zero** in the measurement settings and is recommended before measuring small static fields. For offset correction of the HP-01, the sensor tip must be placed in a zero field chamber before the correction process is started, in order to exclude the influence of external fields and especially that of the earth's magnetic field.

Perform the offset correction:

1. Press **SK2**, then select **Zero**.
↳ A dialog box opens.
2. Follow the instructions in the dialog box.
3. Continue with **SK4** or cancel with **SK1**.
↳ The progress and completion of the offset correction are displayed.
4. Follow the instructions in the dialog box.
5. Press the **Back** key to return to the measuring mode.

10.4 Commenting on measurement results

✓ DEVICE SETTINGS > GENERAL SETTINGS

⇒ See 7.3.2 *SAVE OPTIONS* on page 46.

In this menu you can set whether a comment is to be recorded with the saving of measurement results via **voice or text input**. Both functions can also be activated.

If the respective type of comment is activated and a measurement result (not a screenshot) was saved via the save key, the menu navigation for the voice comment opens first and then the menu navigation for the text input via the editor. In the **TIMER LOGGING** operating mode, the prompt for entering a voice or text comment already appears after pressing **Enable Timer**, i.e. before the actual start of measurement.

Text comments and voice comments can also be added or changed at any time later in **DATA LOGGER**.

10.4.1 Activating voice comments

Activate voice comments:

1. **Add Voice Comment = On**
2. Return to the measuring interface.

Enter a voice comment:

⇒ See 9.3.3 *Adding a voice comment* on page 95.

10.4.2 Activating text comments

For simplified text input, a predefined text (**Default Text**) can be used and added to during input.

Activate text comments:

1. **Add Text Comment = On**
2. Edit **Default Text** if necessary.
3. Return to the measuring interface.

Enter a text comment:

⇒ See 9.3.2 *Adding a text comment* on page 95.

10.5 Alarm function

⇒ See 7.3.4 *ALARM* on page 46: **Alarm Function**

In this menu, alarm thresholds can be set and the alarm function can be activated. After activating the alarm function, an alarm symbol appears in the status bar of the display.

When the alarm threshold is exceeded, a conspicuous acoustic signal sounds with a visual alarm message. If the mute function is activated (Mute = **On**), only the visual alarm is available.



Fig. 18: Display of alarm function

10.6 Acoustic intensity display (HF probes only)

⇒ See 7.3 *GENERAL SETTINGS* on page 45: **Audible Field Indicator**

In this menu, the acoustic display can be activated and the sensitivity can be adjusted by selecting the gain. In principle, the audio frequency increases as the field strength level increases in order to be able to detect field maxima or leaks on HF lines.

Setting	Scope of application
Off	Inoperative
High Gain	Up to 20 V/m or 20%
Normal Gain	Up to 80 V/m or 80%
Low Gain	Up to 240 V/m or 240%

If another unit of measurement is used, the specified values must be converted into V/m accordingly.

10.7 Peak marker

In addition to the marker, the peak marker is available for evaluating the peak values in the following operating modes.

- **FIELD STRENGTH**
- **SPECTRUM**
- **SHAPED TIME DOMAIN**
- **TIMER LOGGING** (after calling the measurement in the **DATA LOGGER**)

For this purpose, up to 25 peak values are recorded and sorted in descending order. Number 1 is the highest peak value. The selected peak value is displayed within the cross key symbol.

Marker type	On/Off	Symbols		Representa- tion on the display	Control via cross key
		Off	On		
Marker	SK1	-○-	---	◀ ▶	◀ ▶
Peak Marker	SK4	○ ~~~	○ ~~~	▲ ◀ 1/25 ▶ ▼	◀ ▶ ▲▼

Use the Peak Marker:

- ✓ The marker is switched on (see the descriptions in the respective operating modes).

1. Press **SK4** to switch on the peak marker.
2. Move the marker:
 - a. Use the **◀ ▶** keys to move the marker to the nearest peak on the left or right.
 - b. Use the **▲▼** keys to move the marker to the next higher or next lower peak.
 - ↳ The selected peak value is displayed within the cross key symbol.
3. Press **SK4** to turn the peak marker off again.

10.8 Display of overdriven measured values

Overdriving can lead to damage or even destruction of a measuring probe. In addition, during overdriving, the measurement results are undervalued due to the occurring compression and thus recorded as too low. Measurement data stored in data records are identified by override symbols.

A currently overdriven state is indicated by a red instead of a yellow display field in connection with an upward pointing triangle symbol



Due to previous overdriving, the statistical measured values of **MAX**, **MAXAVG** and **AVG** are also undervalued and are therefore displayed in red after overdriving has occurred. In this case, the values in the measurement settings should be reset.

11

PC software and updates

In this chapter you will find instructions for using the Narda-TSX PC software as well as for updating the firmware of the Narda FieldMan.

11.1 Narda-TSX PC software (page 110)

11.2 Firmware update (page 111)

11.1 Narda-TSX PC software

The newly developed, extremely powerful Narda-TSX PC software is available for evaluating and documenting the measurement results, media and other information. It is Narda's new software platform that will support other Narda products in the future in addition to FieldMan. The PC software is also required for firmware updating and enables remote control of the FieldMan.

For connection to a PC, the FieldMan has the following interfaces:

- Serial COM interface via the USB-C port
- Network interface via the Ethernet port
- Serial COM interface via the optical port

11.1.1 Establishing a USB connection

The device comes with a USB cable that can be used for power supply and connection to a PC.

Establish a USB connection:

1. Under **GENERAL SETTINGS > CONNECTIVITY > SERIAL INTERFACE**, activate the **USB** function.
2. Connect the device at the USB-C port (see *Fig. 2: 6*) to a USB port on the PC using the supplied USB cable.
 - ↳ The first time you connect, the FieldMan is automatically set up on the PC.
 - ↳ After setup, the FieldMan can be used.

⇒ Instructions for further use of the device can be found in the online help for the Narda-TSX PC software.

11.1.2 Establishing a network connection

An Ethernet cable with RJ45 connector is required to establish a network connection.

Establishing a network connection:

1. Under **GENERAL SETTINGS > CONNECTIVITY > ETHERNET**, activate the **Ethernet** function. Select the appropriate network settings and activate **DHCP** or enter the address settings manually.
2. Connect the device using a suitable Ethernet cable at the Ethernet port (see *Fig. 2: 9*) to a router or network hub.
3. Instructions for further use of the device can be found in the online help for the Narda-TSX PC software.

11.1.3 Establishing an optical connection

In principle, an optical connection can also be established with a PC and the PC software can be used via this connection. However, due to the higher transmission speed, a USB or Ethernet connection is much better suited for this purpose. However, for remote measurements with HF probes, the optical connection via fiber optic cable and optical-electrical converter to USB is the best solution, because in this way interference is avoided.

Establish an optical connection:

1. Under **GENERAL SETTINGS > CONNECTIVITY > OPTICAL INTERFACE**, select the **Remote** function.
2. Connect the device at the optical connector (see *Fig. 2: 7*) to a PC via the optical cable.
 - ↳ The first time the device is connected, it is automatically set up on the PC.
 - ↳ After the setup, the device can be used.
3. For information on remote control of the device, refer to the online help for the Narda-TSX PC software.

11.2 Firmware update

The firmware update of the Narda FieldMan is performed using the Narda-TSX PC software.

⇒ The description of how to perform the firmware update can be found in the online help for the Narda-TSX PC software.

12

Care, maintenance and disposal

This chapter describes how to clean the device and replace the rechargeable batteries.

- 12.1 Cleaning the device (page 114)**
- 12.2 Replacing/removing rechargeable batteries (page 115)**
- 12.3 Disposal (page 116)**

12.1 Cleaning the device

ATTENTION

Penetrating liquids

Liquids that get inside can damage or destroy the device.

⇒ Make absolutely sure that no liquids get into the interior of the device.

ATTENTION

Solvents

Solvents can attack the surfaces of the device.

⇒ Do not use solvents to clean the basic unit, probe and Netzteil/Ladegerät.

To clean the device:

1. Clean the device with a soft cloth. As cleaning agent, we recommend the use of lukewarm water to which a drop of liquid detergent has been added.
2. To avoid streaks and stains, wipe the still damp parts of the device with a dry cloth.

12.2 Replacing/removing rechargeable batteries

⚠ CAUTION

Defective rechargeable battery

A defective rechargeable battery can lead to injuries and damage to the device.

- ⇒ Do not operate the device if the rechargeable battery is damaged.
- ⇒ Replace a defective rechargeable battery immediately.

- ⇒ Replace the rechargeable battery when the capacity noticeably decreases.
You can obtain a replacement rechargeable battery as a spare part from your Narda sales partner (order number 2460/90.07).

Replace the rechargeable battery:

- ✓ The device is switched off.
- 1. Open the 3 screws on the rechargeable battery compartment with a screwdriver and remove the cover.
- 2. Unlock the connector at the top and pull it off.
- 3. Insert the new rechargeable battery and place it in the handle.
- 4. Replace the cover and screw it tight.



- ⇒ Fully charge the rechargeable battery before use.

12.3 Disposal

12.3.1 Disposal of end-of-life equipment

The crossed-out wheeled garbage can symbol indicates that this product is subject to the European WEEE Directive 2012/19/EU on the disposal of waste electrical and electronic equipment and must be disposed of separately from household waste in accordance with your national regulations.

In the European Union, all electronic measuring systems purchased from Narda after August 13, 2005 can be returned at the end of their useful life.

⇒ Further information is available from your Narda sales partner.

12.3.2 Disposal of removable batteries

Batteries must not be disposed of in household waste, but must be disposed of separately from the product in accordance with the applicable regulations. Batteries can be returned for free at the corresponding collection points, your dealer or directly via Narda.

⇒ Please discharge the batteries before disposal.

12.3.3 Deletion of private data

⇒ Remove the micro SD memory card before passing on or disposing of the device.

There is no personal data on the FieldMan itself.

13

Conformity

In this chapter you will find important information on declarations of conformity and approvals.

- 13.1 EU Declaration of Conformity (page 118)**
- 13.2 UKCA Declaration of Conformity (page 118)**
- 13.3 Regulatory Compliance Mark (RCM) (page 118)**
- 13.5 Radio approval (page 119)**

13.1 EU Declaration of Conformity

Narda STS hereby declares that this equipment is in compliance with Directives 2014/53/EU,

2014/35/EU and 2011/65/EU, as well as product standards EN 301 489-1 V2.2.3, EN 301 489-17 V3.2.4, EN 61326-1:2021, EN 61010-1:2010.

The full text of the EU declaration of conformity is available at www.narda-sts.com

13.2 UKCA Declaration of Conformity

Narda STS hereby declares that this equipment complies with the product standards EN 301 489-1 V2.2.3, EN 301 489-17 V3.2.4, EN 61326-1:2021, EN 61010-1:2010 and the following regulations:

- Radio Equipment Regulations
- Electrical Equipment (Safety) Regulations
- The Restriction of the Use of Certain Hazardous Substances in Electrical and Electronic Equipment Regulations

The full text of the UKCA declaration of conformity is available at www.narda-sts.com.

13.3 Regulatory Compliance Mark (RCM)



13.4 FCC and IC statement



This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.



Per RSS-Gen, Section 8.4 This device complies with Industry Canada license-exempt RSS standard(s). Operation is subject to the following two conditions:

- (1) this device may not cause interference, and
- (2) this device must accept any interference, including interference that may cause undesired operation of the device.

13.5 Radio approval

This device contains components for radio communication via WiFi and Bluetooth and therefore represents a radio system. To use radio communication, the device option 2460/95.12 must be purchased and enabled.

⇒ For initial setup and country configuration, see *4.6 Initial commissioning on page 27*.

Country	Approval number
China	CMIIT ID:
Japan	
USA	FCC ID: 2A77Y-246001A
Canada	IC: 28882-246001A

13.6 Technical data

Parameter	Value
Frequency range	2.4 GHz – 2.495 GHz
Bandwidth	20 MHz
Max. transmitting power	≤ 17.5 dBm (56.2 mW)

Index

A

Abbreviations 18
Acoustic intensity display 46
Add voice comment (Data Logger) 95
Alarm
 Function 104
 Settings 46
Altitude 49
Applications 9
Attaching marking rings 26
Automatic shutdown 47

B

Band filter 48
Bluetooth 50
Brightness 45

C

Center frequency 48
Charge status, rechargeable battery 25
Charging the rechargeable battery 24
Clean, device 114
Color scheme 45
Comment on measurement results 103
Comment, measurement results 103
Connection
 Ethernet 110
 Optical 111
 USB 110
Controls 30
Correction factor
 Apply 98
 Settings 47
Create, setup 55
Create/manage setups 55

D

Dangers
 Measurement error 13

Strong fields 12
Undervaluation of the field
 strength 13
Data Logger
 Add text comment 95
 Delete measurement 96
 Manage measurements 94
 Manage media 96
 Manage screenshots 96
 Projects 93
 Structure 92
 Voice comment
 Add 95

Date 49

Device
 Clean 114
 Switch on 27

Device information 51

Device overview 22

Device settings
 Change 40
 Overview 44
 Personalize 45

DHCP 51

Display
 Function key symbols 36
 In measuring mode 42
 LCD 33
 LED 32
 Probe info 34
 Status bar symbols 35

Distance measurement 49

E

Electromagnetic fields 8
Equip case 21
Ethernet 51
Exit submenu 40

F

- Factory reset 47
- Factory settings 47
- Field Strength 60
- Fields, electromagnetic 8
- Filter type 48
- Firmware update 111
- Fixed keys 38
- Format (memory card) 47
- Format memory card 47
- Function keys, symbols 36

G

- GNSS
 - Settings 49
 - Synchronization 49
- GPS
 - Accuracy 49
 - Settings 49
 - System 49

H

- Host name 50

I

- Information
 - Device 51
 - Probes 52
- Intended use 12
- Interface
 - Optical 50
 - Serial 50
 - Wireless 50
- IP address 51

K

- Keys
 - Fixed 38
 - Softkeys 38

L

- Language, user interface 16
- Latitude 49

M

- LCD display 33
- LED display 32
- Longitude 49

N

- Network 50
- Network connection 110
- Non-intended use 12

O

- Offset correction 102
- Operating concept 38
- Operating instructions, structure 16
- Operating mode
 - Field Strength 60
 - Overview 58
 - Shaped Time Domain 83
 - Spatial Average 67
 - Spectrum 78
 - Timer Logging 71
- Operating steps, basic 39
- Operation with rechargeable battery 24
- Optical connection 111
- Optical interface 50
- Overdriven measured values 107

Overview of operating modes and probe types 58

P

Package contents 20

Packaging 20

Peak marker 106

Percent of standard 47

Personalize, device settings 45

Post-process measurement data 98

Post-Processing 98

Post-processing of measurement data 98

Power supply 24

Probe

Connect 25

Test 26

Probe change during operation 54

Probe connection 25

Probe info on the display 34

Probe information 52

Probe test 26

Probe types, overview 58

R

Rechargeable battery

Charge state 25

Charging 24

Correct handling of 13

Dispose 116

Operation 24

Replace 115

Rechargeable battery/device

disposal 116

Reference frequency 47

Reset, settings 44

Resetting settings 44

S

Screen saver

Settings 45

Use 39

Screenshot

Take automatically 46

Take manually 41

SD card directory structure 53

SD card structure 53

SD card, structure 53

Select country 28

Select country of use 28

Select language 45

Select operating mode 39

Serial interface 50

Set default text 46

Set reference frequency 98

Set time 27

Set time zone 27

Shaped Time Domain 83

Shutdown (automatic) 47

Signs and symbols 17

Softkeys 38

Software update 111

Spatial Average 67

Spectrum 78

Standards 9

Device settings 47

Display in % 99

HF probes 101

LF probes 102

Select 100

Status bar, symbols 35

Strong fields 12

Subnet mask 51

Switching on, commissioning 27

Switching on/off, basic operation 39

Symbols 18

Function keys 36

Status bar 35

Symbols and signs 17

Synchronization with GNSS 49

T

TCP 50
Terms 18
Text comment
 Activate 103
 Add (Data Logger) 95
 Set 46
Text markings 18
Time 49
Timer Logging 71

U

Undervaluation of the field strength 13
Unpacking 20
Update 111
USB connection 110
USB on/off 50
Use
 Intended 12
 Unintended 12
User interface, language 16

V

Voice comment
 Activate 103
 Set 46
Volume 46

W

Warnings
 Structure 17
 Warning words 17
WiFi, wireless interface 50

Z

Zero 102

Narda Safety Test Solutions GmbH

Sandwiesenstrasse 7
72793 Pfullingen, Germany
Phone +49 7121 97 32 0
info@narda-sts.com

Narda Safety Test Solutions

North America Representative Office
435 Moreland Road
Hauppauge, NY11788, USA
Phone +1 631 231 1700
info@narda-sts.com

Narda Safety Test Solutions S.r.l.

Via Benessea 29/B
17035 Cisano sul Neva, Italy
Phone +39 0182 58641
nardait.support@narda-sts.it

Narda Safety Test Solutions GmbH

Beijing Representative Office
Xiyuan Hotel, No. 1 Sanlihe Road, Haidian
100044 Beijing, China
Phone +86 10 6830 5870
support@narda-sts.cn

www.narda-sts.com