

图纸发布类别: **正式归档图纸**

成品尺寸	80x80mm
展开图尺寸:	80x480mm
公差:	±1mm

单位:mm

**4 Charging Camera**

1. The camera is with built-in rechargeable battery  
2. When charging, please use the camera USB cable to connect camera and camera adapter, then plug the adapter into power outlet(100v-240v) for charging, the indicator light on camera will turns solid white(if the indicator light flashes when charging please contact customer service)  
3. Once full charging, the white indicator will turns off

**Installing Camera**

1. Drill or drive the mounting screws into the wall, if it's stone wall, then requires screw anchor  
2. 2.1 Turn the ON/OFF switch of the camera to the ON side, the camera enters the state of waiting to be added, the prompt tone will be played and the red light will flash red quickly  
2.2 Switch the camera to work mode connected to base station. Press and hold the sync button for 5s, the camera will play a prompt sound and the red light will flash red quickly  
Note: Mode switching is only valid when the camera is waiting to be added.  
2.3 Enter the base station interface on the app, click the “+Add Device” in bottom, or press the sync button of the base station to enter the state of adding camera, and the indicator light flashes green.  
2.4 Use a RJ45 cable to connect the base station to the LAN port of the camera.  
2.5 Power on the base station using the supplied power adapter. The red indicator light of the base station starts to flash, and it enters the state of waiting to be added.

**What's in the Box**

Dear User,  
Thanks for selecting this product. Please kindly add your camera according to the Quick Start and keep the Quick Start properly.

WiFi Security Camera x1  
Camera USB cable x1  
Screws x1  
Mounting Base x1  
Quick Start x1

**Product Overview**

Indicator Light  
Solid Red : Camera starting up  
Quick Flashing Red : Waiting for adding to a Wi-Fi network. Work with router directly.  
Slow Flashing Red : Waiting for adding to the base station. Work with the base station only.  
Quick Flashing Green : Connecting to server.  
Solid Green : Connected to server successfully.  
Slow Flashing Yellow : Camera upgrading.

**Federal Communications Commission (FCC) Declaration of Conformity**

PCC Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, including interference that may cause undesired operation.

Note: This equipment has been found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:  
—Reorient or relocate the receiving antenna.  
—Increase the separation between the equipment and receiver.  
—Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.  
—Consult the dealer or an experienced radio/TV technician for help.

**Radiation Exposure Statement**

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled/controlled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator and your body.

**Smart Camera User Manual**

**Get Ready**

1 Download the Smart Life app from App Store or Google Play.

**2 Register an account on your TuyaSmart app**

STEP 1. Enter your mobile phone number or email address.

**3 Adding Device**

1 Stand-alone mode:

Note:  
Stand-alone mode means you can connect the camera directly to your router's 2.4 G Wi-Fi network.  
When you first add the camera for the first time, the camera defaults to stand-alone mode.  
After the camera is reset, it will also return to the default stand-alone mode.

1.1 Connect the mobile phone to the 2.4 G Wi-Fi network of the router.  
Note: The camera only supports 2.4 G Wi-Fi, not 5G Wi-Fi, so make sure your phone is connected to a 2.4 G Wi-Fi network.  
1.2 Turn the ON/OFF switch of the camera to the ON side, the camera enters the state of waiting to be added, the prompt tone will be played and the indicator light will flash red quickly.  
Note:  
If the indicator light does not light up, please charge the camera before completing the setup.  
If the indicator light is not turning green after your camera is turned on, please press the sync button for 5s to reset the device.  
If the camera is not added while the device is waiting to be added or the camera fails to be added, and the indicator light is off, please quick

**System Requirements**

- Mobile device running iOS® 8 or higher or Android™ 4.1x or higher
- Existing Wi-Fi Network

**Technical Specifications**

- Operating temperature: -20 ~ 45°C, Operating humidity: 10%~95% No condensation.
- Frequency Range: 2.412~2.462GHz, RF Output Power: 17.5 dBm
- Power: General 5V Direct Current 1A, symbol  $\equiv$  means direct current

**Please read the instruction manual carefully before using the product**

## FCC-认证使用

版本	物料编号	变更者	变更时间	版本升级原因描述
1.0				原始版本

材质	105g铜版纸	客户  中性英文 认证使用	产品名称	低功耗相机	物料名称	SC053-WQ2-低功耗相机 -中性英文-说明书-FCC- 认证使用	设计	大川
印刷色	单黑		型号	SC053-WQ2	物料编号		审核	吴俊
加工工艺	风琴6折页,正反印刷						时间	20230227
接合方式	/							