

## 18 ANTENNA REQUIREMENT

Test Standard	47 CFR Part 15, Subpart C 15.247
Test Method	N/A


### 18.1 CONCLUSION

#### Standard Requirement:

An intentional radiator shall be designed to ensure that no antenna other than that furnished by the responsible party shall be used with the device. The use of a antenna that uses a unique coupling to the intentional radiator, the manufacturer may design the unit permanently attached antenna or of an so that a broken antenna can be replaced by the user, but the use of a standard antenna jack or electrical connector is prohibited.

#### EUT Antenna:

The antenna is integrated on the main PCB and no consideration of replacement. The best case gain of the antenna is 2.7dBi.




## 19 CONDUCTED SPURIOUS EMISSIONS

<b>Test Standard</b>	47 CFR Part 15, Subpart C 15.247
<b>Test Method</b>	ANSI C63.10 (2013) Section 7.8.6 & Section 11.11
<b>Test Mode (Pre-Scan)</b>	TX
<b>Test Mode (Final Test)</b>	TX
<b>Tester</b>	Charlie
<b>Temperature</b>	25 °C
<b>Humidity</b>	60%

### 19.1 LIMITS

<b>Limit:</b>	In any 100 kHz bandwidth outside the frequency band in which the spread spectrum or digitally modulated intentional radiator is operating, the radio frequency power that is produced by the intentional radiator shall be at least 20 dB below that in the 100 kHz bandwidth within the band that contains the highest level of the desired power, based on either an RF conducted or a radiated measurement, provided the transmitter demonstrates compliance with the peak conducted power limits. If the transmitter complies with the conducted power limits based on the use of RMS averaging over a time interval, as permitted under paragraph (b)(3) of this section, the attenuation required under this paragraph shall be 30 dB instead of 20 dB. Attenuation below the general limits specified in §15.209(a) is not required. In addition, radiated emissions which fall in the restricted bands, as defined in §15.205(a), must also comply with the radiated emission limits specified in §15.209(a) (see §15.205(c)).
---------------	--

### 19.2 BLOCK DIAGRAM OF TEST SETUP



### 19.3 TEST DATA

**Pass: Please Refer To Appendix: Appendix1 For Details**

BlueAsia


## 20 CONDUCTED BAND EDGES MEASUREMENT

<b>Test Standard</b>	47 CFR Part 15, Subpart C 15.247
<b>Test Method</b>	ANSI C63.10 (2013) Section 7.8.8 & Section 11.13.3.2
<b>Test Mode (Pre-Scan)</b>	TX
<b>Test Mode (Final Test)</b>	TX
<b>Tester</b>	Charlie
<b>Temperature</b>	25 °C
<b>Humidity</b>	60%

### 20.1 LIMITS

<b>Limit:</b>	In any 100 kHz bandwidth outside the frequency band in which the spread spectrum or digitally modulated intentional radiator is operating, the radio frequency power that is produced by the intentional radiator shall be at least 20 dB below that in the 100 kHz bandwidth within the band that contains the highest level of the desired power, based on either an RF conducted or a radiated measurement, provided the transmitter demonstrates compliance with the peak conducted power limits. If the transmitter complies with the conducted power limits based on the use of RMS averaging over a time interval, as permitted under paragraph (b)(3) of this section, the attenuation required under this paragraph shall be 30 dB instead of 20 dB. Attenuation below the general limits specified in §15.209(a) is not required. In addition, radiated emissions which fall in the restricted bands, as defined in §15.205(a), must also comply with the radiated emission limits specified in §15.209(a) (see §15.205(c)).
---------------	--

### 20.2 BLOCK DIAGRAM OF TEST SETUP



### 20.3 TEST DATA

**Pass: Please Refer To Appendix: Appendix1 For Details**

BlueAsia


## 21 APPENDIX

### Appendix1


#### 21.1 MAXIMUM CONDUCTED OUTPUT POWER

Condition	Mode	Frequency (MHz)	Antenna	Conducted Power (dBm)	Limit (dBm)	Verdict
NVNT	1-DH1	2402	Ant1	-1.777	21	Pass
NVNT	1-DH1	2441	Ant1	-4.776	21	Pass
NVNT	1-DH1	2480	Ant1	-7.61	21	Pass
NVNT	2-DH1	2402	Ant1	-0.886	21	Pass
NVNT	2-DH1	2441	Ant1	-3.298	21	Pass
NVNT	2-DH1	2480	Ant1	-5.313	21	Pass
NVNT	3-DH1	2402	Ant1	-0.729	21	Pass
NVNT	3-DH1	2441	Ant1	-3.134	21	Pass
NVNT	3-DH1	2480	Ant1	-4.746	21	Pass


Power NVNT 1-DH1 2402MHz Ant1




Power NVNT 1-DH1 2441MHz Ant1




Power NVNT 1-DH1 2480MHz Ant1



Power NVNT 2-DH1 2402MHz Ant1




Power NVNT 2-DH1 2441MHz Ant1




Power NVNT 2-DH1 2480MHz Ant1




Power NVNT 3-DH1 2402MHz Ant1



Power NVNT 3-DH1 2441MHz Ant1




Power NVNT 3-DH1 2480MHz Ant1




## 21.2 -20DB BANDWIDTH

Condition	Mode	Frequency (MHz)	Antenna	-20 dB Bandwidth (MHz)	Limit -20 dB Bandwidth (MHz)	Verdict
NVNT	1-DH1	2402	Ant1	0.848	0	Pass
NVNT	1-DH1	2441	Ant1	0.859	0	Pass
NVNT	1-DH1	2480	Ant1	0.846	0	Pass
NVNT	2-DH1	2402	Ant1	1.229	0	Pass
NVNT	2-DH1	2441	Ant1	1.241	0	Pass
NVNT	2-DH1	2480	Ant1	1.248	0	Pass
NVNT	3-DH1	2402	Ant1	1.221	0	Pass
NVNT	3-DH1	2441	Ant1	1.252	0	Pass
NVNT	3-DH1	2480	Ant1	1.251	0	Pass


### -20dB Bandwidth NVNT 1-DH1 2402MHz Ant1




### -20dB Bandwidth NVNT 1-DH1 2441MHz Ant1




-20dB Bandwidth NVNT 1-DH1 2480MHz Ant1




-20dB Bandwidth NVNT 2-DH1 2402MHz Ant1




-20dB Bandwidth NVNT 2-DH1 2441MHz Ant1




-20dB Bandwidth NVNT 2-DH1 2480MHz Ant1




-20dB Bandwidth NVNT 3-DH1 2402MHz Ant1



-20dB Bandwidth NVNT 3-DH1 2441MHz Ant1




-20dB Bandwidth NVNT 3-DH1 2480MHz Ant1





### 21.3 OCCUPIED CHANNEL BANDWIDTH


Condition	Mode	Frequency (MHz)	Antenna	99% OBW (MHz)
NVNT	1-DH1	2402	Ant1	0.81314
NVNT	1-DH1	2441	Ant1	0.81165
NVNT	1-DH1	2480	Ant1	0.79262
NVNT	2-DH1	2402	Ant1	1.2007
NVNT	2-DH1	2441	Ant1	1.1822
NVNT	2-DH1	2480	Ant1	1.1637
NVNT	3-DH1	2402	Ant1	1.2044
NVNT	3-DH1	2441	Ant1	1.1882
NVNT	3-DH1	2480	Ant1	1.1602

#### OBW NVNT 1-DH1 2402MHz Ant1




#### OBW NVNT 1-DH1 2441MHz Ant1



**OBW NVNT 1-DH1 2480MHz Ant1**

**OBW NVNT 2-DH1 2402MHz Ant1**




### OBW NVNT 2-DH1 2441MHz Ant1




### OBW NVNT 2-DH1 2480MHz Ant1



### OBW NVNT 3-DH1 2402MHz Ant1



### OBW NVNT 3-DH1 2441MHz Ant1



### OBW NVNT 3-DH1 2480MHz Ant1

