

Standard	IEEE802.11 an
Chipset	Atheros AR9390-AL1B
Radio stream <b>[Note1]</b>	3T3R
Antenna Type / con.	3 U.FL connectors (diversity ant)
Bus Interface	PCI Express
Form Factor	Mini PCIe
Data Rate	802.11a: 54, 48, 36, 24, 18, 12, 9, 6 Mbps 802.11n: MCS 0 to 23 for HT20MHz MCS 0 to 23 for HT40MHz
Media Access Control	CSMA/CA with ACK
Spreading /Modulation Techniques	802.11a: OFDM (BPSK, QPSK, 16-QAM, 64-QAM) 802.11n: OFDM (BPSK, QPSK, 16-QAM, 64-QAM)
Frequency Range <b>[Note2]</b>	5GHz 11a/n: 5.150GHz ~ 5.825GHz
Transmit Output Power (Tolerance: +/-2dBm)	802.11a: 11dBm ± 2dBm@54Mbps 802.11an HT20: 15dBm ± 2dBm@MCS0 802.11an HT20: 11dBm ± 2dBm@MCS7 802.11an HT40: 15dBm ± 2dBm@MCS0 802.11an HT40: 11dBm ± 2dBm@MCS7
Receiver Sensitivity (Tolerance: +/-2dBm)	802.11a: -78dBm ± 2dBm@54Mbps 802.11an HT20: -95dBm ± 2dBm@MCS0

	802.11an HT20: -75dBm ± 2dBm@MCS7 802.11an HT40: -93dBm ± 2dBm@MCS0 802.11an HT40: -72dBm ± 2dBm@MCS7
Operating Voltage	3.3V ±10% I/O supply voltage
Power Consumption	TX Mode: 970mA RX Mode: 300mA Associated Idle: 50 mA
Temperature Range	-40~+80°C (Operating) <b>[Note3]</b>
Humidity (non-condensing)	20~80%(Operating), 5~95%(Storing) <b>[Note3]</b>
Security	WEP / WPA / WPA2
OS supported	Windows XP/Vista/Win7, Linux

Antenna info.	Antenna		Peak gain ( dBi )				
	Model	Type	Connector	5150~5250MHz	5250~5350MHz	5470~5725MHz	5725~5850MHz
Brand:Perkinelmer Model:CB5A	PCB Antenna	UFL		5.6 dBi	5.6 dBi	6.1 dBi	5.9 dBi

## Federal Communication Commission Interference Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.

- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

FCC Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

**IMPORTANT NOTE:**

**Radiation Exposure Statement:**

The product comply with the US portable RF exposure limit set forth for an uncontrolled environment and are safe for intended operation as described in this manual. The further RF exposure reduction can be achieved if the product can be kept as far as possible from the user body or set the device to lower output power if such function is available.

This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

Country Code selection feature to be disabled for products marketed to the US/CANADA

**This device is intended only for OEM integrators under the following conditions:**

- 1) The transmitter module may not be co-located with any other transmitter or antenna,

As long as the condition above is met, further transmitter test will not be required.

However, the OEM integrator is still responsible for testing their end-product for any additional compliance requirements required with this module installed

#### **IMPORTANT NOTE**

In the event that these conditions can not be met (for example certain laptop configurations or co-location with another transmitter), then the FCC authorization is no longer considered valid and the FCC ID can not be used on the final product. In these circumstances, the OEM integrator will be responsible for re-evaluating the end product (including the transmitter) and obtaining a separate FCC authorization.

#### **End Product Labeling**

The final end product must be labeled in a visible area with the following: "Contains FCC ID: **2AA8Z-XRPAD2**".

#### **Manual Information to the End User**

The OEM integrator has to be aware not to provide information to the end user regarding how to install or remove this RF module in the user's manual of the end product which integrates this module.

The end user manual shall include all required regulatory information/warning as shown in this manual.