Tune up procedure

Tune up procedure shall be over the power range or at specific operating power levels.

- It must provide an operational voltage (3.4 ~ 4.2V DC) to turn on the device and on one certain channel in service mode by means of company proprietary software.
- **2.** Base station simulator (CMU 200) measures the Entertainment Tablet device specific RF characteristics.
- 3. The maximum gains of each individual device are adjusted until the target value met.

Tune-up Power		
Mode	Frequency Bands	Tune-up Power
GSM	GSM850	32.0dBm±1dBm
	GSM1900	28.5dBm±1dBm
GPRS	GPRS850(1 slots)	32.0dBm±1dBm
	GPRS850(2 slots)	30.5dBm±1dBm
	GPRS850(3 slots)	29.0dBm±1dBm
	GPRS850(4 slots)	28.0dBm±1dBm
	GPRS1900(1 slots)	28.5dBm±1dBm
	GPRS1900(2 slots)	27.5dBm±1dBm
	GPRS1900(3 slots)	26.0dBm±1dBm
	GPRS1900(4 slots)	25.0dBm±1dBm
EDGE	EDGE850(1 slots)	26.0dBm±1dBm
	EDGE850(2 slots)	24.5dBm±1dBm
	EDGE850(3 slots)	23.0dBm±1dBm
	EDGE850(4 slots)	21.5dBm±1dBm
	EDGE1900(1 slots)	25.0dBm±1dBm
	EDGE1900(2 slots)	23.5dBm±1dBm
	EDGE1900(3 slots)	21.5dBm±1dBm
	EDGE1900(4 slots)	20.0dBm±1dBm
WCDMA Band V	RMC	22.0dBm±1dBm
	HSDPA	21.5dBm±1dBm
	HSUPA	21.0dBm±1dBm

WCDMA Band II	RMC	21.0dBm±1dBm
	HSDPA	20.5dBm \pm 1dBm
	HSUPA	20.0dBm \pm 1dBm
WIFI	2.4GHz	16.0dBm \pm 1dBm
ВТ	2.4GHz	5.0dBm±1dBm

Then these appropriate gain settings are stored in each device individually.

The user has no possibility to change these settings later on, and during manufacturing each device will be individual calibrated. The measurement is done in fully calibrated setup, which is based on a CMU 200 base station simulator. Furthermore, the highest power level is verified afterwards in a call measurement on three channels (low, middle and high).