



# HEARING AID COMPATIBILITY RF EMISSIONS TEST REPORT

**FCC ID** : 2ADINS6601L  
**Equipment** : LTE Smartphone  
**Brand Name** : NUU  
**Model Name** : X7 Plus, S6601L, NUU X7 Plus  
**WD Emission Result** : PASS  
**Applicant** : Sun Cupid Technology (HK) Ltd.  
16/F,CEO Tower,77 Wing Hong Street,Cheung  
Sha Wan,Kowloon,Hong Kong.  
**Manufacturer** : Sun Cupid Technology (HK) Ltd.  
16/F,CEO Tower,77 Wing Hong Street,Cheung  
Sha Wan,Kowloon,Hong Kong.  
**Standard** : FCC 47 CFR §20.19  
ANSI C63.19-2019  
**Date Tested** : Apr. 06, 2024 ~ Apr. 06, 2024

We, Sporton International Inc. (Kunshan), would like to declare that the tested sample provided by manufacturer and the test data has been evaluated in accordance with the test procedures given in ANSI C63.19-2019 / 47 CFR Part 20.19 and has been in compliance with the applicable technical standards.

The test results in this report apply exclusively to the tested model / sample. Without written approval of Sporton International Inc. (Kunshan), the test report shall not be reproduced except in full.



Approved by: Si Zhang

**Sportun International Inc. (Kunshan)**  
No. 1098, Pengxi North Road, Kunshan Economic Development Zone Jiangsu Province 215300  
People's Republic of China



## Table of Contents

1. General Information .....	4
2. Testing Location.....	5
3. Applied Standards .....	5
4. Air Interfaces .....	6
5. WD Emission Requirements .....	7
6. System Description and Operation .....	8
7. RF Emissions Test Procedure.....	11
8. Test Equipment List .....	13
9. System Validation .....	14
10. Modulation Interference Factor.....	15
11. Evaluation of WD RF interference potential .....	16
11.1    Evaluation RF <sub>AIP</sub> .....	16
12. Conducted RF Output Power (Unit: dBm).....	18
13. RF <sub>AIL</sub> Test Results .....	18
14. Uncertainty Assessment .....	19
15. References.....	20

**Appendix A. Plots of System Performance Check**

**Appendix B. Plots of RF Emission Measurement**

**Appendix C. DASY Calibration Certificate**

**Appendix D. Test Setup Photos**

**Appendix E. UID specifications for HAC RFE**



## History of this test report

Report No.	Version	Description	Issued Date
HA420424A	Rev. 01	Initial issue of report	Jul. 01, 2024
HA420424A	Rev. 02	1. Updated the relevant data of tune up in section 11. 2. Updated the section 4/12/13.	Jul. 22, 2024



## 1. General Information

Product Feature & Specification	
Applicant Name	Sun Cupid Technology (HK) Ltd.
Equipment Name	LTE Smartphone
Brand Name	NUU
Model Name	X7 Plus, S6601L, NUU X7 Plus
IMEI Code	IMEI 1: 359712750010610 IMEI 2: 359712750010628
FCC ID	2ADINS6601L
HW	V01
SW	S6601L-VZ-U-MV03203-01.g
EUT Stage	Identical Prototype
Frequency Band	GSM850: 824 MHz ~ 849 MHz GSM1900: 1850MHz ~ 1910MHz WCDMA Band II: 1850 MHz ~ 1910 MHz WCDMA Band IV: 1710 MHz ~ 1755 MHz WCDMA Band V: 824 MHz ~ 849 MHz LTE Band 2: 1850 MHz ~ 1910 MHz LTE Band 4: 1710 MHz ~ 1755 MHz LTE Band 5: 824 MHz ~ 849 MHz LTE Band 12: 699 MHz ~ 716 MHz LTE Band 13: 777 MHz ~ 787 MHz LTE Band 25: 1850 MHz ~ 1915 MHz LTE Band 26: 814 MHz ~ 849 MHz LTE Band 41: 2496 MHz ~ 2690 MHz LTE Band 66: 1710 MHz ~ 1780 MHz LTE Band 71: 663 MHz ~ 698 MHz WLAN 2.4GHz Band: 2412 MHz ~ 2462 MHz WLAN 5.2GHz Band: 5180 MHz ~ 5240 MHz WLAN 5.3GHz Band: 5260 MHz ~ 5320 MHz WLAN 5.5GHz Band: 5500 MHz ~ 5720 MHz WLAN 5.8GHz Band: 5745 MHz ~ 5825 MHz Bluetooth: 2402 MHz ~ 2480 MHz
Mode	GSM/GPRS/EGPRS RMC/AMR 12.2Kbps HSDPA HSUPA DC-HSDPA HSPA+ (16QAM uplink is supported) LTE: QPSK, 16QAM WLAN 2.4GHz 802.11b/g/n HT20 WLAN 5GHz 802.11a/n HT20/HT40 WLAN 5GHz 802.11ac VHT20/VHT40/VHT80 Bluetooth BR/EDR/LE
Remark: The different model names are only for market segment purpose, there is no other difference.	



## **2. Testing Location**

Sportun International Inc. (Kunshan) is accredited to ISO/IEC 17025:2017 by American Association for Laboratory Accreditation with Certificate Number 5145.02.

Testing Laboratory			
Test Firm	Sportun International Inc. (Kunshan)		
Test Site Location	No. 1098, Pengxi North Road, Kunshan Economic Development Zone Jiangsu Province 215300 People's Republic of China TEL : +86-512-57900158		
Test Site No.	Sportun Site No.	FCC Designation No.	FCC Test Firm Registration No.
	SAR05-KS	CN1257	314309

## **3. Applied Standards**

- FCC CFR47 Part 20.19
- ANSI C63.19-2019
- FCC KDB 285076 D01 HAC Guidance v06r04
- FCC KDB 285076 D03 HAC FAQ v01r06



#### 4. Air Interfaces

Air Interface	Band MHz	Type	C63.19 RF <sub>AIR</sub> Tested	Simultaneous Transmitter	Name of Voice Service	Power Reduction
GSM	GSM850	VO	Yes	WLAN, BT	CMRS Voice	No
	GSM1900			WLAN, BT		No
	EDGE850	VD	Yes	WLAN, BT	Google Meet	No
	EDGE1900			WLAN, BT		
WCDMA	Band II	VO	No <sup>(1)</sup>	WLAN, BT	CMRS Voice	No
	Band IV			WLAN, BT		No
	Band V			WLAN, BT		No
	HSPA	VD	No <sup>(1)</sup>	WLAN, BT	Google Meet	No
LTE FDD	Band 2	VD	No <sup>(1)</sup>	WLAN, BT	VoLTE / Google Meet	No
	Band 4			WLAN, BT		No
	Band 5			WLAN, BT		No
	Band 12			WLAN, BT		No
	Band 13			WLAN, BT		No
	Band 25			WLAN, BT		No
	Band 26			WLAN, BT		No
	Band 66			WLAN, BT		No
	Band 71			WLAN, BT		No
LTE TDD	Band 41	VD	No <sup>(1)</sup>	WLAN, BT	VoLTE / Google Meet	No
Wi-Fi	2450	VD	No <sup>(1)</sup>	GSM, WCDMA, LTE	VoWiFi / Google Meet	No
	5200			GSM, WCDMA, LTE		No
	5300			GSM, WCDMA, LTE		No
	5500			GSM, WCDMA, LTE		No
	5800			GSM, WCDMA, LTE		No
BT	2450	DT	No	GSM, WCDMA, LTE	NA	No

**Type Transport:**

VO= Voice only

DT= Digital Transport only (no voice)

VD= CMRS and IP Voice Service over Digital Transport

**Remark:**

1. The air interface max power plus MIF is complies with ANSI C63.19-2019 Table 4.1 RF<sub>AIR</sub>
2. Because features of Google Meet allow the option of voice-only communications, Meet has been tested for HAC/T-Coil compatibility to ensure the best user experience.



## **5. WD Emission Requirements**

The WD's conducted power must be at or below either the stated RFAIPL (Table 4.1) or the stated peak power level (Table 4.2), or the average near-field emissions over the measurement area must be at or below the stated RFAIL (Table 4.3), or the stated peak field strength (Table 4.4). The WD may demonstrate compliance by meeting any of these four requirements, but it must do so in each of its operating bands at its established worst-case normal speech-mode operating condition.

**Table 4.1 - Wireless device RF audio interference power level**

Frequency range (MHz)	RF <sub>AIPL</sub> (dBm)
< 960	29
960 - 2000	26
> 2000	25

**Table 4.2 - Wireless device RF peak power level**

Frequency range (MHz)	RF <sub>Peak Power</sub> (dBm)
< 960	35
960 - 2000	32
> 2000	31

**Table 4.3 - Wireless device RF audio interference level**


Frequency range (MHz)	RF <sub>AIL</sub> [dB(V/m)]
< 960	39
960 - 2000	36
> 2000	35

**Table 4.4 - Wireless device RF peak near-field level**

Frequency range (MHz)	RF <sub>Peak</sub> [dB(V/m)]
< 960	45
960 - 2000	42
> 2000	41

## **6. System Description and Operation**

### **<System Components>**



#### **Remark:**

A typical al DASY system for HAC measurements consists of

- 6-axis robotic arm (Staubli TX2-60L/ TX2-90XL) for positioning the probe
- Mounting Platform for keeping the phantoms at a field location relative to the robot
- Measurement Server for handling all time-critical tasks, such as measurement data acquisition and supervision of safety features
- EOC (Electrical to Optical Converter) for converting the optical signal from the Data Acquisition Electronics (DAE) to electrical before being transmitted to the measurement server
- LB (Light Beam unit) for probe alignment (measurement of the exact probe length and eccentricity)
- Test Arch for Device Under Test (DUT) testing
- DAE that reads the probe voltages and transmits them to the DASY PC. It is also used to detect probe touch and collision signals
- Device Holder for positioning the DUT beneath the phantom
- ANT (wideband Antenna) for broadcasting the downlink signals emitted by base station simulators (BSS) to the WD
- Operator PC for running the DASY software to define/execute the measurements.

The following components are needed for RFail measurements only:

- Modulation Interference Factor (MIF)
- Isotropic E-field, free-space probe (e.g., EF3DVx)
- Radiofrequency (RF) emission calibration dipoles for system check / validation purposes.

**<EF3DV3 E-Field Probe Specification>**

<b>Construction</b>	One dipole parallel, two dipoles normal to probe axis Interleaved sensors Built-in shielding against static charges PEEK enclosure material
<b>Calibration</b>	In air from 30 MHz to 6.0 GHz (absolute accuracy $\pm 5.1\%$ , $k=2$ )
<b>Frequency</b>	30 MHz – 6 GHz Linearity: $\pm 0.2$ dB (100 MHz – 3 GHz)
<b>Directivity</b>	$\pm 0.2$ dB in air (rotation around probe axis) $\pm 0.4$ dB in air (rotation normal to probe axis)
<b>Dynamic Range</b>	2 – $>1000$ V/m
<b>Linearity</b>	$\pm 0.2$ dB
<b>Dimensions</b>	Overall length: 337 mm (tip: 20 mm) Tip diameter: 3.9 mm (body: 12 mm) Distance from probe tip to dipole centers: 1.5 mm Sensor displacement to probe's calibration point: $<0.7$ mm

**Voltage to E-field Conversion**

The measured voltage is first linearized to a quantity proportional to the square of the E-field using the (a, b, c, d) set of parameters specific to the communication system and sensor :

$$V_{\text{compi}} = U_i + U_i^2 \cdot \frac{10^{\frac{d}{10}}}{dcp_i}$$

where  $V_{\text{compi}}$  = compensated signal of channel i ( $\mu$ V) ( $i = x, y, z$ )

$U_i$  = input signal of channel i ( $\mu$ V) ( $i = x, y, z$ )

$d$  = PMR factor d (dB) (Probe parameter)

$dcp_i$  = diode compression point of channel i ( $\mu$ V) (Probe parameter,  $i = x, y, z$ )

$$V_{\text{compi} \text{dB}\sqrt{\mu\text{V}}} = 10 + \log_{10} (V_{\text{compi}})$$

$$\text{corr}_i = a_i \cdot e - \left( \frac{V_{\text{compi} \text{dB}\sqrt{\mu\text{V}}}^{-b_i}}{c_i} \right)^2$$

where  $coor_i$  = correction factor of channel i (dB) ( $i = x, y, z$ )

$V_{\text{compi} \text{dB}\sqrt{\mu\text{V}}}$  = compensated voltage of channel i ( $\text{dB}\sqrt{\mu\text{V}}$ ) ( $i = x, y, z$ )

$a_i$  = PMR factor a of channel i (dB) (Probe parameter,  $i = x, y, z$ )

$b_i$  = PMR factor b of channel i ( $\text{dB}\sqrt{\mu\text{V}}$ ) (Probe parameter,  $i = x, y, z$ )

$c_i$  = PMR factor c of channel i (Probe parameter,  $i = x, y, z$ )

The voltage  $V_{i \text{dB}\sqrt{\mu\text{V}}}$  is the linearized voltage in  $\text{dB}\sqrt{\mu\text{V}}$  :

$$V_{i \text{dB}\sqrt{\mu\text{V}}} = V_{\text{compi} \text{dB}\sqrt{\mu\text{V}}} - \text{corr}_i$$

where  $V_{i \text{dB}\sqrt{\mu\text{V}}}$  = linearized voltage of channel i ( $\text{dB}\sqrt{\mu\text{V}}$ ) ( $i = x, y, z$ )

$V_{\text{compi} \text{dB}\sqrt{\mu\text{V}}}$  = compensated voltage of channel i ( $\text{dB}\sqrt{\mu\text{V}}$ ) ( $i = x, y, z$ )

$\text{corr}_i$  = correction factor of channel i (dB) ( $i = x, y, z$ )



Finally, the linearized voltage is converted in  $\mu\text{V}$  :

$$V_i = 10^{\frac{V_{i \text{ dB}}}{10}}$$

where  $V_i$  = linearized voltage of channel  $i$  ( $\mu\text{V}$ ) ( $i = x, y, z$ )  
 $V_{i \text{ dB}} =$  linearized voltage of channel  $i$  ( $\text{dB}\sqrt{\mu\text{V}}$  ( $i = x, y, z$ ))

The E-field data for each channel are calculated using the linearized voltage :

$$\text{E-field Probes : } E_i = \sqrt{\frac{V_i}{\text{Norm}_i \cdot \text{ConvF}}}$$

where  $V_i$  = compensated signal of channel  $i$ , ( $i = x, y, z$ )  
 $\text{Norm}_i$  = sensor sensitivity ( $\mu\text{V}/(\text{V}/\text{m})^2$ ) of channel  $i$  ( $i = x, y, z$ )  
 $\text{ConvF}$  = sensitivity enhancement in solution  
 $E_i$  = electric field strength of channel  $i$  in  $\text{V}/\text{m}$

The RMS value of the field components gives the total field strength (Hermitian magnitude) :

$$E_{\text{tot}} = \sqrt{E_x^2 + E_y^2 + E_z^2}$$

### Averaged E-field Calculation

The averaged E-field is defined by

$$E_{\text{avg}} = \frac{1}{n} \cdot \sum_{i=1}^n E_i$$

where  $n$  = the number of measurement grid point  
 $E_i$  = the E-field measured at point  $i$

### RFail Calculation

The RFail is finally computed with

$$RFail[\text{dB}(\text{V}/\text{m})] = 20 \cdot \log_{10}(E_{\text{avg}}) + MIF$$

where  $RFail$  = the Radio Frequency Audio Interference Level in  $\text{dB}(\text{V}/\text{m})$   
 $E_{\text{avg}}$  = the averaged E-field in ( $\text{V}/\text{m}$ ) calculated  
 $MIF$  = the Modulation Interference Factor in  $\text{dB}$ .



## 7. RF Emissions Test Procedure

### Test Instructions





Figure of WD near-field emission scan flowchart according to ANSI C63.19:2019



**The references and reference plane that shall be used in the WD emissions measurement**

**Device Under Test Positioning under the Test Arch**

**Test procedure: Indirect measurement—preferred**

- a. The measurement procedure using a probe and instrumentation chain with a response of <10 kHz (see ANSI C63.19-2019 section4.5.1) is identical to the direct measurement method of ANSI C63.19-2019 section4.5.3.2.2; however, because of the bandwidth limitations, it cannot include the direct use of the spectral and temporal weighting functions. The output of such measurement systems must be readings of steady state rms field strength in dB(V/m).
- b. The RF audio interference level in dB(V/m) is obtained by adding the Modulation Interference Factor (in decibels) to the average steady state rms field strength reading over the measurement area, in dB(V/m), from Step c). Use this result to determine the WD's compliance per ANSI C63.19-2019 section4.7.
- c. Scan the entire 50 mm by 50 mm measurement area in equally spaced step sizes and record the reading at each measurement point. The step size shall meet the specification for step size in ANSI C63.19:2019 section 4.5.3.
- d. Calculate the average of the measurements taken in Step c
- e. Convert the average value found in Step d) to RF audio interference level, in volts per meter, by taking the square root of the reading and then dividing it by the measurement system transfer function, as established in ANSI C63.19:2019 section4.5.3.2.1 pre-test procedure. Convert the result to dB(V/m) by taking the base-10 logarithm and multiplying it by 20. Expressed as a formula  

$$\text{RF audio interference level in db(V/M)} = 20 * \log(R_{ave}^{1/2} / \text{TF})$$

where  
 $R_{ave}$  is the average reading
- f. Compare this RF audio interference level to the limits in ANSI C63.19:2019 section4.7 and record the result
- g. Per ANSI C63.19-2019 section4.6, WDs capable of operating multiple transmitters shall be subject to emissions requirements for all such transmitters expected to be operated when the WD is in voice mode operation positioned at a user's ear. Each qualified transmitter is tested individually using the method of Clause 4. Other WD transmitters shall be temporarily disabled or reduced in power level such that their average antenna input power is at least 6 dB lower than the average antenna input power of the transmitter under test. The transmitter under test is set to the fixed and repeatable combination of power and modulation characteristic that is representative of the worst case (highest interference potential) likely to be encountered while the WD is experiencing normal voice mode operation. The limiting measurement for device qualification is the highest RF audio interference potential measured for any of the WD transmitters. If the highest interference measurement is from a transmitter that is not required for normal voice mode operation, a secondary rating may be given that applies when that transmitter is disabled



## 8. Test Equipment List

Manufacturer	Name of Equipment	Type/Model	Serial Number	Calibration	
				Last Cal.	Due Date
SPEAG	835MHz Calibration Dipole	CD835V3	1171	2022/3/1	2025/2/27
SPEAG	1880MHz Calibration Dipole	CD1880V3	1155	2022/3/1	2025/2/27
SPEAG	Data Acquisition Electronics	DAE4	1649	2023/4/24	2024/4/23
SPEAG	Isotropic E-Field Probe	EF3DV3	4050	2024/3/6	2025/3/5
R&S	Base Station	CMW500	143030	2023/7/5	2024/7/4
Anritsu	Vector Signal Generator	MG3710A	6201682672	2024/1/2	2025/1/1
BONN	POWER AMPLIFIER	BLMA 0830-3	087193A	NCR	NCR
BONN	POWER AMPLIFIER	BLMA 2060-2	087193B	NCR	NCR
Agilent	Dual Directional Coupler	778D	20500	2023/7/5	2024/7/4
Agilent	Dual Directional Coupler	11691D	MY48151020	2023/7/5	2024/7/4
Rohde & Schwarz	Power Meter	NRVD	102081	2023/7/5	2024/7/4
Rohde & Schwarz	Power Sensor	NRV-Z5	100538	2023/7/5	2024/7/4
Rohde & Schwarz	Power Sensor	NRV-Z5	100539	2023/7/5	2024/7/4
MCL	Attenuation1	BW-S10W5+	N/A	NCR	NCR
MCL	Attenuation2	BW-S10W5+	N/A	NCR	NCR
MCL	Attenuation3	BW-S10W5+	N/A	NCR	NCR
Rohde & Schwarz	Spectrum Analyzer	FSV7	101631	2023/10/11	2024/10/10
Testo	Thermo-Hygrometer	608-H1	1241332126	2023/7/10	2024/7/9

**Note:**

1. NCR: "No-Calibration Required"
2. The dipole calibration interval can be extended to 3 years with justification. The dipoles are also not physically damaged, or repaired during the interval. The justification data in appendix C can be found which the return loss is < -20dB, within 20% of prior calibration, the impedance is within 5 ohm of prior calibration for each dipole.


## 9. System Validation

Obtaining accurate measurements and relevant quantities in Module HAC depends on the proper functioning of many components and the correct parameter settings. Faulty results due to drift, failures, or incorrect parameters might not be recognized, as the differences might not be obvious in the measurements.

SPEAG DASY incorporates a system check, also called system verification procedure, to test for the proper functioning of the system based on the tests described in ANSI C63.19-2019: the RF interference potential test setup is verified with RF Emission Calibration Dipoles.

### <Test Setup>

1. Set the RF signal generator for either CW. Set its output power so the peak power applied to the antenna is equal to that recorded for the real or emulated signal using the WD modulation format
2. Average input power  $P = 100$  mW (20 dBm) after adjustment for return loss. An input power that generates field levels similar to those from the WD or other suitable level may also be used
3. The test fixture should meet the two-wavelength separation criterion
4. The probe-to-dipole separation, which is measured from closest surface of the dipole to the center point of the probe sensor element, should be 15 mm



**Figure of Setup Diagram**

### <Validation Procedure>

Place a dipole antenna meeting the requirements given in ANSI C63.19: 2019 D.11 in the position normally occupied by the WD. The dipole antenna serves as a known source for an electrical and magnetic output. Position the E-field probe so that:

- a. The probe and its cable are parallel to the coaxial feed of the dipole antenna
- b. The probe cable and the coaxial feed of the dipole antenna approach the measurement area from opposite directions; and
- c. The center point of the probe element(s) is 15 mm from the closest surface of the dipole elements

Scan the length of the dipole with the E-field probe and record the two maximum values found near the dipole ends.

Average the two readings and compare the reading to expected value in the calibration certificate or expected value in this standard.

Frequency (MHz)	Input Power (dBm)	Target Value (V/m)	Emax (V/m)	Deviation (%)	Date
835	20	107.7	98.6	-8.45	2024/4/6
1880	20	85.1	86.5	1.65	2024/4/6



## 10. Modulation Interference Factor

For any specific fixed and repeatable modulated signal, a Modulation Interference Factor (MIF, expressed in decibels) may be developed that relates its interference potential to its steady state rms signal level or average power level. This factor is a function only of the audio frequency amplitude modulation characteristics of the signal and is the same for field strength or conducted power measurements. It is important to emphasize that the MIF is valid only for a specific repeatable audio frequency amplitude modulation characteristic. Any change in modulation characteristic requires determination and application of a new MIF.

MIF may be determined using a radiated RF field, a conducted RF signal, or, in a preliminary stage, a mathematical analysis of a modeled RF signal.

- a. Verify the slope accuracy and dynamic range capability over the desired operating frequency band of a fast probe or sensor, square-law detector, as specified in ANSI C63.19: 2019 D.3, and weighting system as specified in ANSI C63.19: 2019 D.4 and ANSI C63.19: 2019 D.5. For the probe and instrumentation included in the measurement of MIF, additional calibration and application of calibration factors are not required.
- b. Using RF illumination, or conducted coupling, apply the specific modulated signal in question to the measurement system at a level within its confirmed operating dynamic range
- c. Measure the steady-state rms level at the output of the fast probe or sensor
- d. Measure the steady-state average level at the weighting output
- e. Without changing the square-law detector or weighting system, and using RF illumination, or conducted coupling, substitute for the specific modulated signal a 1 kHz, 80% amplitude modulated carrier at the same frequency and adjust its strength until the level at the weighting output equals the Step d) measurement
- f. Without changing the carrier level from Step e), remove the 1 kHz modulation and again measure the steady-state rms level indicated at the output of the fast probe or sensor.
- g. The MIF for the specific modulation characteristic is given by the ratio of the Step f) measurement to the Step c) measurement, expressed in decibels ( $20 \log(\text{Step f}/\text{Step c})$ )

In practice, Step e) and Step f) need not be repeated for each MIF determination if the relationship between the two measurements has been pre-established for the measurement system over the operating frequency and dynamic ranges. In such cases, only the modulation characteristic being tested needs to be available during WD testing. Since indirect measurement procedure was used for RF audio interference power level evaluation, the MIF values applied in this test report were provided by the HAC equipment provider of SPEAG, and the worst values for all air interface are listed below to be determine the Wireless device RF audio interference power level. For UID 10973 is applicable only when 5GNR TDD PC2 with 50% Duty Cycle, and all other 5GNR modes are applicable with UID 10769 more conservatively.

UID	Communication System Name	MIF(dB)
10021	GSM-FDD(TDMA,GMSK)	3.63
10025	EDGE-FDD (TDMA, 8PSK, TN 0)	3.75
10460	UMTS-FDD(WCDMA, AMR)	-25.43
10225	UMTS-FDD (HSPA+)	-20.39
10170	LTE-FDD(SC-FDMA,1RB,20MHz,16-QAM)	-9.76
10173	LTE-TDD (SC-FDMA, 1 RB, 20 MHz, 16-QAM)	-1.44
10061	IEEE 802.11b WiFi 2.4 GHz (DSSS, 11 Mbps)	-2.02
10077	IEEE 802.11g WiFi 2.4 GHz (DSSS/OFDM, 54 Mbps)	0.12
10427	IEEE 802.11n (HT Greeneld, 150 Mbps, 64-QAM)	-13.44
10069	IEEE 802.11a/h WiFi 5 GHz (OFDM, 54 Mbps)	-3.15
10616	IEEE 802.11ac WiFi (40MHz, MCS0, 90pc duty cycle)	-5.57



## ***11. Evaluation of WD RF interference potential***

**General Note:**

1. In this report, max conducted power from each air interface was first used to evaluate whether it complies with ANSI C63.19-2019 Table 4.1 RF<sub>AIPL</sub>, compliance with table 4.1 means compliance with WD emission requirements. the RF<sub>AIPL</sub> evaluation refer to section 11.1 for detail.
2. If there some air interface were not meet ANSI C63.19-2019 table 4.1 requirement, these air interfaces were further evaluation ANSI C63.19-2019 Table 4.3 RF<sub>AIL</sub> requirement. And the RF<sub>AIL</sub> evaluation result refer to section 13.

### ***11.1 Evaluation RF<sub>AIPL</sub>***

**<WWAN Max Tune-up Limit>**

Frequency Band	Average Power (dBm)	
GSM	GSM850	34.10
	EDGE850	27.40
	GSM1900	29.80
	EDGE1900	25.20
WCDMA	Band II	22.00
	HSPA	20.60
	Band IV	22.00
	HSPA	21.00
	Band V	21.80
	HSPA	20.60
FDD LTE	LTE Band 2	23.60
	LTE Band 4	23.30
	LTE Band 5	24.30
	LTE Band 12	24.00
	LTE Band 13	24.00
	LTE Band 25	23.60
	LTE Band 26	24.30
	LTE Band 66	23.30
	LTE Band 71	24.50
	FDD TDD	LTE Band 41

**<WLAN Max Tune-up Limit>**

Frequency Band	Average Power (dBm)	
WLAN2.4GHz	802.11b	19.00
	802.11g	18.00
	802.11n-HT20	18.00
WLAN5GHz	802.11a	16.90
	802.11n-HT20	16.60
	802.11n-HT40	15.50
	802.11ac-VHT20	16.60
	802.11ac-VHT40	15.50
	802.11ac-VHT80	15.30



## &lt;Evaluation RF audio interference power level&gt;

**General Note:**

1. Use maximum power plus worst case MIF to determine whether it complies with RF<sub>AIPL</sub>
2. If maximum power plus worst case MIF does not complies with RF<sub>AIPL</sub>, then further evaluation RF<sub>AIL</sub> include in section 13.
3. EDGE data modes is not necessary due the GSM Voice mode is the worst case.
4. According to ANSI C63.19 2019, if maximum power plus worst case MIF is complies with RF<sub>AIPL</sub>, means compliance with WD emission requirements.

## &lt;WWAN Ant&gt;

Frequency Band		Average Power (dBm)	Worst Case MIF (dB)	Power + MIF(dB)	C63.19 Lowest RF <sub>AIPL</sub> (dBm)	C63.19 test required
GSM	GSM850	34.10	3.63	37.73	29	Yes
	EDGE850	27.40	3.75	31.15	29	NO <sup>(3)</sup>
	GSM1900	29.80	3.63	33.43	26	Yes
	EDGE1900	25.20	3.75	28.95	26	NO <sup>(3)</sup>
WCDMA	Band II	22.00	-25.43	-3.43	26	NO
	HSPA	20.60	-20.39	0.21	26	NO
	Band IV	22.00	-25.43	-3.43	26	NO
	<b>HSPA</b>	21.00	-20.39	0.61	26	NO
	Band V	21.80	-25.43	-3.63	29	NO
	<b>HSPA</b>	20.60	-20.39	0.21	29	NO
FDD LTE	LTE Band 2	23.60	-9.76	13.84	26	NO
	LTE Band 4	23.30	-9.76	13.54	26	NO
	LTE Band 5	24.30	-9.76	14.54	29	NO
	LTE Band 12	24.00	-9.76	14.24	29	NO
	LTE Band 13	24.00	-9.76	14.24	29	NO
	LTE Band 25	23.60	-9.76	13.84	26	NO
	LTE Band 26	24.30	-9.76	14.54	29	NO
	LTE Band 66	23.30	-9.76	13.54	26	NO
	LTE Band 71	24.50	-9.76	14.74	29	NO
FDD TDD	LTE Band 41	23.20	-1.44	21.76	25	NO

## &lt;WLAN Ant&gt;

Frequency Band		Average Power (dBm)	Worst Case MIF (dB)	Power + MIF(dB)	C63.19 Lowest RF <sub>AIPL</sub> (dBm)	C63.19 test required
WLAN2.4GHz	802.11b	19.00	-2.02	16.98	25	NO
	802.11g	18.00	0.12	18.12	25	NO
	802.11n-HT20	18.00	-13.44	4.56	25	NO
WLAN5GHz	802.11a	16.90	-3.15	13.75	25	NO
	802.11n-HT20	16.60	-13.44	3.16	25	NO
	802.11n-HT40	15.50	-13.44	2.06	25	NO
	802.11ac-VHT20	16.60	-5.57	11.03	25	NO
	802.11ac-VHT40	15.50	-5.57	9.93	25	NO
	802.11ac-VHT80	15.30	-5.57	9.73	25	NO



## 12. Conducted RF Output Power (Unit: dBm)

&lt;GSM&gt;

Average Antenna Input Power(dBm)						
Band	GSM850			GSM1900		
Channel	128	189	251	512	661	810
Frequency (MHz)	824.2	836.4	848.8	1850.2	1880.0	1909.8
GSM (GMSK, 1 Tx slot)	33.12	33.11	32.94	29.68	28.87	28.57

## 13. $RF_{AIL}$ Test Results

**General Note:**

1. The HAC measurement system applies MIF value onto the measured RMS E-field, which is indirect method in ANSI C63.19-2019 version, and reports the RF audio interference level.
2. Phone Condition: Mute on; Backlight off; Max Volume.

Plot No.	Air Interface	Modulation / Mode	Channel	Average Antenna Input Power (dBm)	MIF	$RF_{AIL}$ (dBV/m)
01	GSM850	Voice	128	33.12	3.63	35.41
02	GSM850	Voice	189	33.11	3.63	34.59
03	GSM850	Voice	251	32.94	3.63	33.89
04	GSM1900	Voice	512	29.68	3.63	18.08
05	GSM1900	Voice	661	28.87	3.63	19.80
06	GSM1900	Voice	810	28.57	3.63	20.20

**Test Engineer :** Martin Li, Varus Wang, Light Wang, Ricky Gu



## 14. Uncertainty Assessment

The component of uncertainty may generally be categorized according to the methods used to evaluate them. The evaluation of uncertainty by the statistical analysis of a series of observations is termed a Type A evaluation of uncertainty. The evaluation of uncertainty by means other than the statistical analysis of a series of observation is termed a Type B evaluation of uncertainty. Each component of uncertainty, however evaluated, is represented by an estimated standard deviation, termed standard uncertainty, which is determined by the positive square root of the estimated variance.

The combined standard uncertainty of the measurement result represents the estimated standard deviation of the result. It is obtained by combining the individual standard uncertainties of both Type A and Type B evaluation using the usual "root-sum-squares" (RSS) methods of combining standard deviations by taking the positive square root of the estimated variances. Expanded uncertainty is a measure of uncertainty that defines an interval about the measurement result within which the measured value is confidently believed to lie. It is obtained by multiplying the combined standard uncertainty by a coverage factor. For purpose of this document, a coverage factor two is used, which corresponds to confidence interval of about 95 %. The DASY uncertainty Budget is showed below Table.

The judgment of conformity in the report is based on the measurement results excluding the measurement uncertainty.

Error Description	Uncertainty Value ( $\pm\%$ )	Probability Distribution	Divisor	Ci (Eav)	Standard Uncertainty (E) ( $\pm\%$ )
<b>Measurement System</b>					
Probe Calibration	5.1	Normal	1	1	5.1
Axial Isotropy	4.7	Rectangular	$\sqrt{3}$	1	2.7
Sensor Displacement	7.2	Rectangular	$\sqrt{3}$	0.5	2.1
Boundary Effects	2.4	Rectangular	$\sqrt{3}$	1	1.4
Phantom Boundary Effects	7.2	Rectangular	$\sqrt{3}$	1	4.2
Linearity	4.7	Rectangular	$\sqrt{3}$	1	2.7
Scaling with PMR Calibration	10.0	Rectangular	$\sqrt{3}$	1	5.8
System Detection Limit	1.0	Rectangular	$\sqrt{3}$	1	0.6
Readout Electronics	0.3	Normal	1	1	0.3
Response Time	0.8	Rectangular	$\sqrt{3}$	0	0.0
Integration Time	2.6	Rectangular	$\sqrt{3}$	0	0.0
RF Ambient Conditions	3.0	Rectangular	$\sqrt{3}$	1	1.7
RF Reflections	12.0	Rectangular	$\sqrt{3}$	1	6.9
Probe Positioner	1.2	Rectangular	$\sqrt{3}$	1	0.7
Probe Positioning	3.0	Rectangular	$\sqrt{3}$	1	1.7
Extrap. and Interpolation	1.0	Rectangular	$\sqrt{3}$	1	0.6
<b>Test Sample Related</b>					
Device Positioning Vertical	4.7	Rectangular	$\sqrt{3}$	1	2.7
Device Positioning Lateral	1.0	Rectangular	$\sqrt{3}$	1	0.6
Device Holder and Phantom	2.4	Rectangular	$\sqrt{3}$	1	1.4
Power Drift	5.0	Rectangular	$\sqrt{3}$	1	2.9
<b>Phantom and Setup Related</b>					
Phantom Thickness	2.4	Rectangular	$\sqrt{3}$	1	1.4
<b>Combined Std. Uncertainty</b>					13.1%
<b>Coverage Factor for 95 %</b>					K=2
<b>Expanded STD Uncertainty</b>					26.3%
Declaration of Conformity: The test results with all measurement uncertainty excluded are presented in accordance with the regulation limits or requirements declared by manufacturers.					
Comments and Explanations: The declared of product specification for EUT presented in the report are provided by the manufacturer, and the manufacturer takes all the responsibilities for the accuracy of product specification.					

### Uncertainty Budget of HAC free field assessment



## **15. References**

- [1] ANSI C63.19:2019, "American National Standard for Methods of Measurement of Compatibility between Wireless Communications Devices and Hearing Aids", Aug. 2019.
- [2] FCC KDB 285076 D01v06r04, "Equipment Authorization Guidance for Hearing Aid Compatibility", Sep 2023.
- [3] FCC KDB 285076 D03v01r06, "Hearing aid compatibility frequently asked questions", Jul. 2022
- [4] SPEAG DASY System Handbook