



FCC DFS TEST REPORT

FCC ID : 2AEM4-9471214
Equipment : Wireless Router
Brand Name : eero
Model Name : PA10001
Applicant : eero LLC
660 3rd St Fl 4, San Francisco, California, 94107, United States
Manufacturer : eero LLC
660 3rd St Fl 4, San Francisco, California, 94107, United States
Standard : FCC Part 15 Subpart E

The product was received on Nov. 08, 2024 and testing was performed from Nov. 20, 2024 to Dec. 20, 2024. We, Sporton International Inc. EMC & Wireless Communications Laboratory, would like to declare that the tested sample has been evaluated in accordance with the procedures given in FCC Part 15 Subpart E and shown compliance with the applicable technical standards.

The test results in this report apply exclusively to the tested model / sample. Without written approval from Sporton International Inc. EMC & Wireless Communications Laboratory the test report shall not be reproduced except in full.

Louis Wu

Approved by: Louis Wu

Sporton International Inc. EMC & Wireless Communications Laboratory

No. 52, Huaya 1st Rd., Guishan Dist., Taoyuan City 333, Taiwan (R.O.C.)

Table of Contents

History of this test report.....	3
Summary of Test Result.....	4
1 General Description	5
1.1 Feature of Equipment Under Test	5
1.2 Modification of EUT	5
1.3 Testing Site	6
1.4 Applied Standards	6
1.5 Support Unit used in test configuration and system	6
2 Test Configuration of Equipment Under Test	7
2.1 Test Mode	7
3 Requirements and Parameters for DFS Test.....	8
3.1 Summary of Dynamic Frequency Selection Test	8
3.2 Applicability of DFS Requirements	9
3.3 DFS Detection Thresholds.....	11
3.4 DFS Response requirement values.....	12
3.5 Short Pulse Radar Test Waveforms	13
3.6 Long Pulse Radar Test Waveform	15
3.7 Frequency Hopping Radar Test Waveform	17
4 Calibration Setup and DFS Test Results	18
4.1 Calibration of Radar Waveform	18
4.2 U-NII Detection Bandwidth	37
4.3 Channel Availability Check	50
4.4 In-Service Monitoring: Channel Move Time, Channel Closing Transmission Time and Non-Occupancy Period.....	56
4.5 Statistical Performance Check	67
5 Validate the progressive DFS	85
5.1 Test Mode	85
5.2 26dB & 99% Occupied Bandwidth Measurement	100
5.3 Maximum Conducted Output Power Measurement	101
5.4 Power Spectral Density Measurement	102
6 List of Measuring Equipment.....	104
Appendix A. Radar Parameters	
Appendix B. Test Result of Conducted Test Items	



History of this test report

Report No.	Version	Description	Issue Date
FZ492020	01	Initial issue of report	Dec. 13, 2024
FZ492020	02	Revise Section 4.4.6 This report is an updated version, replacing the report issued on Dec. 13, 2024.	Dec. 18, 2024
FZ492020	03	Revise Section 4.4.6 This report is an updated version, replacing the report issued on Dec. 18, 2024.	Dec. 20, 2024

Summary of Test Result

Report Clause	Ref Std. Clause	Test Items	Result (PASS/FAIL)	Remark
4.2	7.8.1	U-NII Detection Bandwidth	Pass	-
4.3	7.8.2	Channel Availability Check Time	Pass	-
4.4	7.8.3	Channel Move Time	Pass	-
		Channel Closing Transmission Time	Pass	-
		Non-Occupancy Period Test	Pass	-
4.5	7.8.4	Statistical Performance Check	Pass	-
5.2	15.403(i)	26dB Bandwidth	Pass	-
5.2	2.1049	99% Occupied Bandwidth	Pass	-
5.3	15.407(a)	Maximum Conducted Output Power	Pass	-
5.4	15.407(a)	Power Spectral Density	Pass	-

Conformity Assessment Condition:

The test results (PASS/FAIL) with all measurement uncertainty excluded are presented against the regulation limits or in accordance with the requirements stipulated by the applicant/manufacture who shall bear all the risks of non-compliance that may potentially occur if measurement uncertainty is taken into account.

Disclaimer:

The product specifications of the EUT presented in the test report that may affect the test assessments are declared by the manufacturer who shall take full responsibility for the authenticity.

Reviewed by: Yun Huang

Report Producer: Mila Chen

1 General Description

1.1 Feature of Equipment Under Test

Product Feature		
General Specs Bluetooth-LE, IEEE 802.15.4, Wi-Fi 2.4GHz 802.11b/g/n/ax/be and Wi-Fi 5GHz 802.11a/n/ac/ax/be.		
Antenna Type WLAN: <Ant. 0> : Dipole Antenna <Ant. 1> : Dipole Antenna Bluetooth-LE: Dipole Antenna IEEE 802.15.4: Dipole Antenna		
Antenna information		
5250 MHz ~ 5350 MHz	Peak Gain (dBi)	Ant. 0: 4.52 Ant. 1: 4.56
5470 MHz ~ 5725 MHz	Peak Gain (dBi)	Ant. 0: 5.70 Ant. 1: 5.34
Antenna information for Directional Gain		
5250 MHz ~ 5350 MHz	Peak Gain (dBi)	<5G_Ant. 0 + 5G_Ant. 1> Correlated: 4.92 Uncorrelated: 2.12
5470 MHz ~ 5725 MHz	Peak Gain (dBi)	<5G_Ant. 0 + 5G_Ant. 1> Correlated: 4.88 Uncorrelated: 2.70

Remark: The EUT's information above is declared by manufacturer. Please refer to Disclaimer in report summary.

1.2 Modification of EUT

No modifications are made to the EUT during all test items.

1.3 Testing Site

Test Site	Sporton International Inc. EMC & Wireless Communications Laboratory
Test Site Location	No.52, Huaya 1st Rd., Guishan Dist., Taoyuan City 333, Taiwan (R.O.C.) TEL: +886-3-327-3456 FAX: +886-3-328-4978
Test Site No.	Sporton Site No. 03CH05-HY
Test Site	Sporton International Inc. Wensan Laboratory
Test Site Location	No.58, Aly. 75, Ln. 564, Wenhua 3rd, Rd., Guishan Dist., Taoyuan City 333010, Taiwan (R.O.C.) TEL: +886-3-327-0868 FAX: +886-3-327-0855
Test Site No.	Sporton Site No. TH05-HY (TAF Code: 3786)
Remark	The Conducted test items subcontracted to Sporton International Inc. Wensan Laboratory.

FCC designation No.: TW1190 and TW3786

1.4 Applied Standards

According to the specifications of the manufacturer, the EUT must comply with the requirements of the following standards:

- ♦ FCC Part 15 Subpart E
- ♦ FCC KDB 789033 D02 General UNII Test Procedures New Rules v02r01
- ♦ FCC KDB 662911 D01 Multiple Transmitter Output v02r01.
- ♦ ANSI C63.10-2013
- ♦ FCC KDB 905462 D02 UNII DFS Compliance Procedures New Rules v02
- ♦ FCC KDB 905462 D03 UNII Clients Without Radar Detection New Rules v01r02

Remark:

1. All test items were verified and recorded according to the standards and without any deviation during the test.
2. The TAF code is not including all the FCC KDB listed without accreditation.

1.5 Support Unit used in test configuration and system

Item	Equipment	Brand Name	Model Name	FCC ID	HW / FW Version	Power Cord
1.	Notebook	acer	N15C1	PPD-QCNFA435	N/A	AC I/P: Unshielded, 1.2 m DC O/P: Shielded, 1.8 m



2 Test Configuration of Equipment Under Test

2.1 Test Mode

Test Configuration	
Mode 1	AP Mode
Mode 2	Mesh Mode (See Note)

Note: Networks Access Points with Bridge and/or MESH modes of operation are permitted to operate in the DFS bands but must employ a DFS function. The functionality of the Bridge mode as specified in §15.403(a) must be validated in the DFS test report. Devices operating as relays where they act as master and client must also employ DFS function for the master. The method used to validate the functionality must be documented and validation data must be documented. Bridge mode can be validated by performing a test statistical performance check (Section 7.8.4) on any one of the radar types. This is an abbreviated test to verify DFS functionality. MESH mode operational methodology must be submitted in the application for certification for evaluation by the FCC.

3 Requirements and Parameters for DFS Test

3.1 Summary of Dynamic Frequency Selection Test

UNII	Description	Limit
U-NII Band 2-A 5250-5350 MHz	Channel Availability Check Time	> 60sec
	U-NII Detection Bandwidth	> 100% of the U-NII 99% transmission power bandwidth
	Statistical Performance Check	Type 1,2,3,4 >= 60% Type 1~4 and 5 >= 80% Type 6 >= 70%
	Channel Move Time	< 10 sec
	Channel Closing Transmission Time	< 200 ms + aggregate of 60 ms over remaining 10 s period
	Non-Occupancy Period Test	> 30 minutes
U-NII Band 2-C 5470-5725 MHz	Channel Availability Check Time	> 60sec
	U-NII Detection Bandwidth	> 100% of the U-NII 99% transmission power bandwidth
	Statistical Performance Check	Type 1,2,3,4 >= 60% Type 1~4 and 5 >= 80% Type 6 >= 70%
	Channel Move Time	< 10 sec
	Channel Closing Transmission Time	< 200 ms + aggregate of 60 ms over remaining 10 s period
	Non-Occupancy Period Test	> 30 minutes

3.2 Applicability of DFS Requirements

EUT is considered as a master device.

Table 1: Applicability of DFS Requirements Prior to Use of a Channel

Requirement	Operational Mode		
	Master	Client Without Radar Detection	Client With Radar Detection
Non-Occupancy Period	Yes	Not required	Yes
DFS Detection Threshold	Yes	Not required	Yes
Channel Availability Check Time	Yes	Not required	Not required
U-NII Detection Bandwidth	Yes	Not required	Yes

Table 2: Applicability of DFS requirements during normal operation

Requirement	Operational Mode		
	Master	Client Without Radar Detection	Client With Radar Detection
DFS Detection Threshold	Yes	Not required	Yes
Channel Closing Transmission Time	Yes	Yes	Yes
Channel Move Time	Yes	Yes	Yes
U-NII Detection Bandwidth	Yes	Not required	Yes
Client Beacon Test	N/A	Yes	Yes

Additional requirements for devices with multiple bandwidth modes	Operational Mode	
	Master or Client With Radar Detection	Client Without Radar Detection
U-NII Detection Bandwidth and Statistical Performance Check	All BW modes must be tested	Not required
Channel Move Time and Channel Closing Transmission Time	Test using widest BW mode available	Test using the widest BW mode available for the link
All other tests	Any single BW mode	Not required

Note

Frequencies selected for statistical performance check (Section 7.8.4) should include several frequencies within the radar detection bandwidth and frequencies near the edge of the radar detection bandwidth. For 802.11 devices it is suggested to select frequencies in each of the bonded 20 MHz channels and the channel center frequency.

3.3 DFS Detection Thresholds

Table 3 below provides the DFS Detection Thresholds for Master Devices as well as Client Devices incorporating In-Service Monitoring.

Table 3: DFS Detection Thresholds for Master Devices

Maximum Transmit Power	Value (see notes 1, 2, and 3)
EIRP $\geq$ 200 milliwatt	-64 dBm
EIRP < 200 milliwatt and power spectral density < 10 dBm/MHz	-62 dBm
EIRP < 200 milliwatt that do not meet the power spectral density requirement	-64 dBm
Note 1: This is the level at the input of the receiver assuming a 0 dBi receive antenna. Note 2: Throughout these test procedures an additional 1 dB has been added to the amplitude of the test transmission waveforms to account for variations in measurement equipment. This will ensure that the test signal is at or above the detection threshold level to trigger a DFS response. Note 3: EIRP is based on the highest antenna gain. For MIMO devices refer to KDB Publication 662911 D01.	

The radar *Detection Threshold*, lowest antenna gain is the parameter of Interference radar DFS detection threshold, The Interference Detection Threshold is the $(-64\text{dBm}) + (0.0) [\text{dBi}] + 1 \text{ dB} = -63.0 \text{ dBm}$.

3.4 DFS Response requirement values

Table 4 provides the response requirements for Master and Client Devices incorporating DFS.

Table 4: DFS Response Requirement Values

Parameter	Value
<i>Non-occupancy period</i>	Minimum 30 minutes
<i>Channel Availability Check Time</i>	60 seconds
<i>Channel Move Time</i>	10 seconds See Note 1.
<i>Channel Closing Transmission Time</i>	200 milliseconds + an aggregate of 60 milliseconds over remaining 10 second period. See Notes 1 and 2.
<i>U-NII Detection Bandwidth</i>	Minimum 100% of the 99% power bandwidth See Note 3.
Note 1: <i>Channel Move Time</i> and the <i>Channel Closing Transmission Time</i> should be performed with Radar Type 0. The measurement timing begins at the end of the Radar Type 0 burst. Note 2: The <i>Channel Closing Transmission Time</i> is comprised of 200 milliseconds starting at the beginning of the <i>Channel Move Time</i> plus any additional intermittent control signals required to facilitate <i>Channel</i> changes (an aggregate of 60 milliseconds) during the remainder of the 10 second period. The aggregate duration of control signals will not count quiet periods in between transmissions. Note 3: During the <i>U-NII Detection Bandwidth</i> detection test, radar type 0 is used and for each frequency step the minimum percentage of detection is 90%. Measurements are performed with no data traffic.	

3.5 Short Pulse Radar Test Waveforms

Radar Type 0 was used in the evaluation of the Client device for the purpose of measuring the Channel Move Time and the Channel Closing Transmission Time.

Radar Type	Pulse Width (μsec)	PRI (μsec)	Number of Pulses	Minimum Percentage of Successful Detection	Minimum Trials
0	1	1428	18	See Note 1.	See Note 1.
1	1	Test A Test B	Roundup $\left\{ \left(\frac{1}{360} \right) \cdot \left(\frac{19 \cdot 10^6}{\text{PRI}_{\mu\text{sec}}} \right) \right\}$	60%	30
2	1-5	150-230	23-29	60%	30
3	6-10	200-500	16-18	60%	30
4	11-20	200-500	12-16	60%	30
Aggregate (Radar Types 1-4)				80%	120
Note 1: Short Pulse Radar Type 0 should be used for the detection bandwidth test, channel move time, and channel closing time tests.					

Test A: 15 unique PRI values randomly selected from the list of 23 PRI values in Table 5a

Test B: 15 unique PRI values randomly selected within the range of 518-3066 μsec, with a minimum increment of 1 μsec, excluding PRI values selected in Test A

A minimum of 30 unique waveforms are required for each of the Short Pulse Radar Types 2 through 4. If more than 30 waveforms are used for Short Pulse Radar Types 2 through 4, then each additional waveform must also be unique and not repeated from the previous waveforms.

If more than 30 waveforms are used for Short Pulse Radar Type 1, then each additional waveform is generated with Test B and must also be unique and not repeated from the previous waveforms in Tests A or B.

The aggregate is the average of the percentage of successful detections of short pulse radar types 1-4.

Table 5a - Pulse Repetition Intervals Values for Test A

Pulse Repetition Frequency Number (1 to 23)	Pulse Repetition Frequency (Pulses Per Second)	Pulse Repetition Interval (Microseconds)
1	1930.5	518
2	1858.7	538
3	1792.1	558
4	1730.1	578
5	1672.2	598
6	1618.1	618
7	1567.4	638
8	1519.8	658
9	1474.9	678
10	1432.7	698
11	1392.8	718
12	1355.0	738
13	1319.3	758
14	1285.3	778
15	1253.1	798
16	1222.5	818
17	1193.3	838
18	1165.5	858
19	1139.0	878
20	1113.6	898
21	1089.3	918
22	1066.1	938
23	326.2	3066

3.6 Long Pulse Radar Test Waveform

Radar Type	Pulse Width (μsec)	Chirp Width (MHz)	PRI (μsec)	Number of Pulses per Burst	Number of Bursts	Minimum Percentage of Successful Detection	Minimum Trials
5	50-100	5-20	1000-2000	1-3	8-20	80%	30


The parameters for this waveform are randomly chosen. Thirty unique waveforms are required for the Long Pulse radar test signal. If more than 30 waveforms are used for the Long Pulse radar test signal, then each additional waveform must also be unique and not repeated from the previous waveforms. Each waveform is defined as follows:

Note: The center frequency for each of the 30 trials of the Bin 5 radar shall be randomly selected within 80% of the Occupied Bandwidth.

- (1) The transmission period for the Long Pulse Radar test signal is 12 seconds.
- (2) There are a total of 8 to 20 Bursts in the 12 second period, with the number of Bursts being randomly chosen. This number is Burst_Count.
- (3) Each Burst consists of 1 to 3 pulses, with the number of pulses being randomly chosen. Each Burst within the 12 second sequence may have a different number of pulses.
- (4) The pulse width is between 50 and 100 microseconds, with the pulse width being randomly chosen. Each pulse within a Burst will have the same pulse width. Pulses in different Bursts may have different pulse widths.
- (5) Each pulse has a linear frequency modulated chirp between 5 and 20 MHz, with the chirp width being randomly chosen. Each pulse within a **transmission period** will have the same chirp width. The chirp is centered on the pulse. For example, with a radar frequency of 5300 MHz and a 20 MHz chirped signal, the chirp starts at 5290 MHz and ends at 5310 MHz
- (6) If more than one pulse is present in a Burst, the time between the pulses will be between 1000 and 2000 microseconds, with the time being randomly chosen. If three pulses are present in a Burst, the time between the first and second pulses is chosen independently of the time between the second and third pulses.
- (7) The 12 second transmission period is divided into even intervals. The number of intervals is equal to Burst_Count. Each interval is of length $(12,000,000 / \text{Burst_Count})$ microseconds. Each interval contains one Burst. The start time for the Burst, relative to the beginning of the interval, is between 1 and $[(12,000,000 / \text{Burst_Count}) - (\text{Total Burst Length}) + (\text{One Random PRI Interval})]$ microseconds, with the start time being randomly chosen. The step interval for the start time is 1 microsecond. The start time for each Burst is chosen independently.

A representative example of a Long Pulse radar test waveform:

- (1) The total test signal length is 12 seconds.
- (2) 8 Bursts are randomly generated for the Burst_Count.
- (3) Burst 1 has 2 randomly generated pulses.
- (4) The pulse width (for both pulses) is randomly selected to be 75 microseconds.
- (5) The PRI is randomly selected to be at 1213 microseconds.
- (6) Bursts 2 through 8 are generated using steps 3 – 5.
- (7) Each Burst is contained in even intervals of 1,500,000 microseconds. The starting location for Pulse 1, Burst 1 is randomly generated (1 to 1,500,000 minus the total Burst 1 length + 1 random PRI interval) at the 325,001 microsecond step. Bursts 2 through 8 randomly fall in successive 1,500,000 microsecond intervals (i.e. Burst 2 falls in the 1,500,001 – 3,000,000 microsecond range).




3.7 Frequency Hopping Radar Test Waveform

Radar Type	Pulse Width (μsec)	PRI (μsec)	Pulses per Hop	Hopping Rate (kHz)	Hopping Sequence Length (msec)	Minimum Percentage of Successful Detection	Minimum Trials
6	1	333	9	0.333	300	70%	30

For the Frequency Hopping Radar Type, the same Burst parameters are used for each waveform. The hopping sequence is different for each waveform and a 100-length segment is selected from the hopping sequence defined by the following algorithm:

The first frequency in a hopping sequence is selected randomly from the group of 475 integer frequencies from 5250 – 5724 MHz. Next, the frequency that was just chosen is removed from the group and a frequency is randomly selected from the remaining 474 frequencies in the group. This process continues until all 475 frequencies are chosen for the set. For selection of a random frequency, the frequencies remaining within the group are always treated as equally likely.




4 Calibration Setup and DFS Test Results

4.1 Calibration of Radar Waveform

4.1.1 Radar Waveform Calibration Procedure

The Interference Radar Detection Threshold Level is $(-64) + (0.0) \text{ [dBi]} + 1\text{dB} = -63.0 \text{ dBm}$ that had been taken into account the output power range and antenna gain. The following equipment setup was used to calibrate the conducted Radar Waveform. A vector signal generator was utilized to establish the test signal level for radar type 0~6. During this process there were no transmissions by either the Master or Client Device. The spectrum analyzer was switched to the zero span (Time Domain) at the frequency of the Radar Waveform generator. Peak detection was used. The spectrum analyzer resolution bandwidth (RBW) and video bandwidth (VBW) were set to 3 MHz to measure the radar waveform. The vector signal generator amplitude was set so that the power level measured at the spectrum analyzer was $(-64) + (0.0) \text{ [dBi]} + 1\text{dB} = -63.0 \text{ dBm}$. Capture the spectrum analyzer plots on radar waveform.

4.1.2 Radiated Calibration Setup




4.1.3 Calibration Deviation

There is no deviation with the original standard.



4.1.4 Radar Waveform Calibration Result


<5300MHz / 20MHz>






Single Burst of Radar Type 5

Single Burst of Radar Type 6



04:51:28 PM 11/20/2024




04:58:23 PM 11/20/2024




<5310MHz / 40MHz>

Radar Type 0




03:59:11 PM 11/20/2024

Radar Type 1




04:20:25 PM 11/20/2024

Radar Type 2




04:26:10 PM 11/20/2024

Radar Type 3




04:36:11 PM 11/20/2024

Radar Type 4




04:37:51 PM 11/20/2024






<5290MHz / 80MHz>


Radar Type 0




Radar Type 1




Radar Type 2



Radar Type 3




Radar Type 4






Single Burst of Radar Type 5

Single Burst of Radar Type 6



04:50:09 PM 11/20/2024




04:57:12 PM 11/20/2024




<5250MHz / 160MHz>


Radar Type 0




Radar Type 1




Radar Type 2




Radar Type 3



Radar Type 4









<5500MHz / 20MHz>

Radar Type 0




04:03:36 PM 11/20/2024

Radar Type 1




04:18:22 PM 11/20/2024

Radar Type 2




04:27:36 PM 11/20/2024

Radar Type 3




04:34:24 PM 11/20/2024

Radar Type 4




04:39:20 PM 11/20/2024






<5510MHz / 40MHz>


Radar Type 0




Radar Type 1




Radar Type 2



Radar Type 3




Radar Type 4






Single Burst of Radar Type 5

Single Burst of Radar Type 6



04:47:36 PM 11/20/2024




04:49:58 PM 11/20/2024




<5530MHz / 80MHz>


Radar Type 0




Radar Type 1




Radar Type 2




Radar Type 3



Radar Type 4









<5570MHz / 160MHz>

Radar Type 0




04:06:11 PM 11/20/2024

Radar Type 1




04:16:02 PM 11/20/2024

Radar Type 2




04:28:55 PM 11/20/2024

Radar Type 3




04:32:05 PM 11/20/2024

Radar Type 4




04:40:54 PM 11/20/2024






<5610MHz / 240MHz>


Radar Type 0




Radar Type 1




Radar Type 2



Radar Type 3




Radar Type 4






Single Burst of Radar Type 5



Single Burst of Radar Type 6



4.2 U-NII Detection Bandwidth

4.2.1 Limit of U-NII Detection Bandwidth

The U-NII Detection Bandwidth shall contain minimum 100% of the 99% power bandwidth.


During the U-NII Detection Bandwidth detection test, radar type 0 is used and for each frequency step the minimum percentage of detection is 90%. Measurements are performed with no data traffic.

4.2.2 Test Procedures

- (1) Adjust the equipment to produce a single burst of the Short Pulse Radar Type 0 at the center frequency of the EUT Operating Channel at the specified DFS Detection Threshold level.
- (2) Set the EUT up as a standalone device (no associated Client or Master, as appropriate) and no traffic. Frame based systems will be set to a talk/listen ratio of 0%/100% during this test.
- (3) Generate a single radar burst, and note the response of the EUT. Repeat for a minimum of 10 trials. The EUT must detect the Radar Waveform using the specified U-NII Detection Bandwidth criterion.
- (4) Starting at the center frequency of the EUT operating Channel, increase the radar frequency in 5 MHz steps, repeating the above test sequence, until the detection rate falls below the U-NII Detection Bandwidth criterion specified in report clause 2.3. Repeat this measurement in 1MHz steps at frequencies 5 MHz below where the detection rate begins to fall. Record the highest frequency (denote as F_H) at which detection is greater than or equal to the U-NII Detection Bandwidth criterion. Recording the detection rate at frequencies above F_H is not required to demonstrate compliance.
- (5) Starting at the center frequency of the EUT operating Channel, decrease the radar frequency in 5 MHz steps, repeating the above test sequence, until the detection rate falls below the U-NII Detection Bandwidth criterion specified in report clause 2.3. Repeat this measurement in 1MHz steps at frequencies 5 MHz above where the detection rate begins to fall. Record the lowest frequency (denote as F_L) at which detection is greater than or equal to the U-NII Detection Bandwidth criterion. Recording the detection rate at frequencies below F_L is not required to demonstrate compliance.
- (6) The U-NII Detection Bandwidth is calculated as follows:
U-NII Detection Bandwidth = $F_H - F_L$

4.2.3 Test Setup

<AP Mode>



4.2.4 Test Deviation

There is no deviation with the original standard.

4.2.5 Result of U-NII Detection Bandwidth

<20MHz / 5300MHz>

Frequency (MHz)	Fc	Trial Number (Detection = Y, No Detection = N)										Rate (%)	F _H /F _L
		1	2	3	4	5	6	7	8	9	10		
5289	-11	N	N	N	N	N	N	N	N	N	N	0	
5290	-10	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	FL
5291	-9	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5292	-8	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5293	-7	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5294	-6	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5295	-5	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5300	0	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5305	5	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5306	6	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5307	7	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5308	8	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5309	9	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5310	10	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	FH
5311	11	N	N	N	N	N	N	N	N	N	N	0	
Detection Bandwidth = F _H – F _L = 5310 – 5290 = 20 MHz													
EUT 99% Bandwidth = 19.668 MHz (Refer to channel 60)													



<40MHz / 5310MHz>

Frequency (MHz)	Fc	Trial Number (Detection = Y, No Detection = N)										Rate (%)	F _H /F _L
		1	2	3	4	5	6	7	8	9	10		
5289	-21	N	N	N	N	N	N	N	N	N	N	0	
5290	-20	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	FL
5291	-19	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5292	-18	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5293	-17	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5294	-16	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5295	-15	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5300	-10	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5305	-5	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5310	0	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5315	5	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5320	10	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5325	15	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5326	16	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5327	17	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5328	18	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5329	19	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5330	20	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	FH
5331	21	N	N	N	N	N	N	N	N	N	N	0	
Detection Bandwidth = F _H – F _L = 5330 – 5290 = 40 MHz													
EUT 99% Bandwidth = 39.217 MHz (Refer to channel 60)													



<80MHz / 5290MHz>

Frequency (MHz)	Fc	Trial Number (Detection = Y, No Detection = N)										Rate (%)	F _H /F _L
		1	2	3	4	5	6	7	8	9	10		
5249	-41	N	N	N	N	N	N	N	N	N	N	0	
5250	-40	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	FL
5251	-39	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5252	-38	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5253	-37	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5254	-36	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5255	-35	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5260	-30	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5265	-25	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5270	-20	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5275	-15	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5280	-10	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5285	-5	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5290	0	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5295	5	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5300	10	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5305	15	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5310	20	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5315	25	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5320	30	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5325	35	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5326	36	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5327	37	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5328	38	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5329	39	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5330	40	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	FH
5331	41	N	N	N	N	N	N	N	N	N	N	0	
Detection Bandwidth = F _H – F _L = 5330 – 5250 = 80 MHz													
EUT 99% Bandwidth = 77.945 MHz (Refer to channel 60)													



<160MHz / 5250MHz>

Frequency (MHz)	Fc	Trial Number (Detection = Y, No Detection = N)										Rate (%)	F _H /F _L
		1	2	3	4	5	6	7	8	9	10		
5249	1	N	N	N	N	N	N	N	N	N	N	0	
5250	0	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	FL
5255	5	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5260	10	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5265	15	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5270	20	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5275	25	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5280	30	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5285	35	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5290	40	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5295	45	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5300	50	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5305	55	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5310	60	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5315	65	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5320	70	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5325	75	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5326	76	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5327	77	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5328	78	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5329	79	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5330	80	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	FH
5331	81	N	N	N	N	N	N	N	N	N	N	0	
Detection Bandwidth = F _H – F _L = 5330 – 5250 = 80 MHz													
EUT 99% Bandwidth = 79.387 MHz (Refer to channel 60)													



<20MHz / 5500MHz>

Frequency (MHz)	Fc	Trial Number (Detection = Y, No Detection = N)										Rate (%)	F _H /F _L
		1	2	3	4	5	6	7	8	9	10		
5489	-11	N	N	N	N	N	N	N	N	N	N	0	
5490	-10	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	FL
5491	-9	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5492	-8	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5493	-7	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5494	-6	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5495	-5	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5500	0	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5505	5	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5506	6	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5507	7	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5508	8	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5509	9	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5510	10	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	FH
5511	11	N	N	N	N	N	N	N	N	N	N	0	
Detection Bandwidth = F _H – F _L = 5510 – 5490 = 20 MHz													
EUT 99% Bandwidth = 19.357 MHz (Refer to channel 60)													



<40MHz / 5510MHz>

Frequency (MHz)	Fc	Trial Number (Detection = Y, No Detection = N)										Rate (%)	F _H /F _L
		1	2	3	4	5	6	7	8	9	10		
5489	-21	N	N	N	N	N	N	N	N	N	N	0	
5490	-20	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	FL
5491	-19	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5492	-18	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5493	-17	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5494	-16	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5495	-15	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5500	-10	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5505	-5	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5510	0	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5515	5	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5520	10	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5525	15	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5526	16	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5527	17	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5528	18	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5529	19	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5530	20	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	FH
5531	21	N	N	N	N	N	N	N	N	N	N	0	
Detection Bandwidth = F _H – F _L = 5530 – 5490 = 40 MHz													
EUT 99% Bandwidth = 38.372 MHz (Refer to channel 60)													



<80MHz / 5530MHz>

Frequency (MHz)	Fc	Trial Number (Detection = Y, No Detection = N)										Rate (%)	F _H /F _L
		1	2	3	4	5	6	7	8	9	10		
5489	-41	N	N	N	N	N	N	N	N	N	N	0	
5490	-40	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	FL
5491	-39	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5492	-38	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5493	-37	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5494	-36	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5495	-35	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5500	-30	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5505	-25	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5510	-20	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5515	-15	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5520	-10	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5525	-5	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5530	0	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5535	5	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5540	10	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5545	15	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5550	20	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5555	25	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5560	30	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5565	35	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5566	36	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5567	37	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5568	38	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5569	39	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5570	40	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	FH
5571	41	N	N	N	N	N	N	N	N	N	N	0	
Detection Bandwidth = F _H – F _L = 5570 – 5490 = 80 MHz													
EUT 99% Bandwidth = 77.294 MHz (Refer to channel 60)													



<160MHz / 5570MHz>

Frequency (MHz)	Fc	Trial Number (Detection = Y, No Detection = N)										Rate (%)	F _H /F _L
		1	2	3	4	5	6	7	8	9	10		
5489	-81	N	N	N	N	N	N	N	N	N	N	0	
5490	-80	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	FL
5491	-79	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5492	-78	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5493	-77	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5494	-76	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5495	-75	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5500	-70	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5505	-65	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5510	-60	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5515	-55	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5520	-50	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5525	-45	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5530	-40	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5535	-35	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5540	-30	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5545	-25	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5550	-20	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5555	-15	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5560	-10	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5565	-5	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5570	0	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5575	5	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5580	10	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5585	15	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5590	20	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5595	25	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5600	30	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5605	35	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5610	40	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5615	45	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	



Frequency (MHz)	Fc	Trial Number (Detection = Y, No Detection = N)										Rate (%)	F _H /F _L
		1	2	3	4	5	6	7	8	9	10		
5620	50	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5625	55	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5630	60	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5635	65	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5640	70	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5645	75	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5646	76	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5647	77	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5648	78	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5649	79	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5650	80	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	FH
5651	81	N	N	N	N	N	N	N	N	N	N	0	
Detection Bandwidth = F _H – F _L = 5650 – 5490 = 160 MHz													
EUT 99% Bandwidth = 157.839 MHz (Refer to channel 60)													



<240MHz / 5610MHz>

Frequency (MHz)	Fc	Trial Number (Detection = V, No Detection = N)										Rate (%)	F _H /F _L
		1	2	3	4	5	6	7	8	9	10		
5489	-121	N	N	N	N	N	N	N	N	N	N	0	
5490	-120	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	F _L
5491	-119	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5492	-118	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5493	-117	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5494	-116	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5495	-115	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5500	-110	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5505	-105	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5510	-100	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5515	-95	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5520	-90	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5525	-85	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5530	-80	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5535	-75	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5540	-70	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5545	-65	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5550	-60	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5555	-55	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5560	-50	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5565	-45	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5570	-40	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5575	-35	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5580	-30	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5585	-25	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5590	-20	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5595	-15	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5600	-10	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5605	-5	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5610	0	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5615	+5	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	



Frequency (MHz)	Fc	Trial Number (Detection = V, No Detection = N)										Rate (%)	F _H /F _L
		1	2	3	4	5	6	7	8	9	10		
5620	+10	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5625	+15	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5630	+20	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5635	+25	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5640	+30	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5645	+35	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5650	+40	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5655	+45	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5660	+50	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5665	+55	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5670	+60	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5675	+65	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5680	+70	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5685	+75	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5690	+80	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5695	+85	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5700	+90	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5705	+95	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5710	+100	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5715	+105	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5720	+110	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5721	+111	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5722	+112	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5723	+113	Y	Y	Y	Y	Y	Y	N	Y	Y	Y	90	
5724	+114	Y	Y	Y	Y	Y	Y	Y	Y	Y	Y	100	
5725	+115	Y	Y	N	Y	Y	Y	Y	Y	Y	Y	90	F _H
5726	+116	N	N	N	N	N	N	N	N	N	N	0	
Detection Bandwidth = F _H – F _L = 5725 – 5490 = 235 MHz													
EUT 99% Bandwidth = 234.502 MHz (Refer to channel 122)													



4.3 Channel Availability Check

4.3.1 Limit of Channel Availability Check

The Initial Channel Availability Check Time tests that the EUT does not emit beacon, control, or data signals on the test Channel until the power-up sequence has been completed and the U-NII device checks for radar waveforms for **one minute** on the test Channel.

4.3.2 Test Procedures of Initial Channel Availability Check Time

This test does not use any radar waveforms and only needs to be performed one time.

- (1) The U-NII devices will be powered on and be instructed to operate on the appropriate U-NII Channel that must incorporate DFS functions. At the same time the EUT is powered on, the spectrum analyzer will be set to zero span mode with a 3 MHz RBW and 3 MHz VBW on the Channel occupied by the radar (Chr) with a 2.5 minute sweep time. The spectrum analyzer's sweep will be started at the same time power is applied to the U-NII device.
- (2) The EUT should not transmit any beacon or data transmissions until at least 1 minute after the completion of the power-on cycle.

4.3.3 Radar Burst at the Beginning of the Channel Availability Check Time

The steps below define the procedure to verify successful radar detection on the test Channel during a period equal to the Channel Availability Check Time and avoidance of operation on that Channel when a radar Burst with a level equal to the DFS Detection Threshold + 1 dB occurs at the beginning of the Channel Availability Check Time. This is illustrated in Figure 15.

- (1) The Radar Waveform generator and EUT are connected using the applicable test setup and the power of the EUT is switched off.
- (2) The EUT is powered on at T_0 . T_1 denotes the instant when the EUT has completed its power-up sequence ($T_{\text{power_up}}$). The Channel Availability Check Time commences on Chr at instant T_1 and will end no sooner than $T_1 + T_{\text{ch_avail_check}}$.
- (3) A single Burst of one of the Short Pulse Radar Types 1-4 will commence within a 6 second window starting at T_1 . An additional 1 dB is added to the radar test signal to ensure it is at or above the DFS Detection Threshold, accounting for equipment variations/errors.
- (4) Visual indication or measured results on the EUT of successful detection of the radar Burst will be recorded and reported. Observation of Chr for EUT emissions will continue for 2.5 minutes after the radar Burst has been generated.
- (5) Verify that during the 2.5 minute measurement window no EUT transmissions occurred on Chr. The Channel Availability Check results will be recorded.




Figure 15: Example of timing for radar testing at the beginning of the Channel Availability Check Time

4.3.4 Radar Burst at the End of the Channel Availability Check Time

The steps below define the procedure to verify successful radar detection on the test Channel during a period equal to the Channel Availability Check Time and avoidance of operation on that Channel when a radar Burst with a level equal to the DFS Detection Threshold + 1dB occurs at the end of the Channel Availability Check Time. This is illustrated in Figure 16.

- (1) The Radar Waveform generator and EUT are connected using the applicable test setup and the power of the EUT is switched off.
- (2) The EUT is powered on at T_0 . T_1 denotes the instant when the EUT has completed its power-up sequence ($T_{\text{power_up}}$). The Channel Availability Check Time commences on Chr at instant T_1 and will end no sooner than $T_1 + T_{\text{ch_avail_check}}$.
- (3) A single Burst of one of the Short Pulse Radar Types 1-4 will commence within a 6 second window starting at $T_1 + 54$ seconds. An additional 1 dB is added to the radar test signal to ensure it is at or above the DFS Detection Threshold, accounting for equipment variations/errors.
- (4) Visual indication or measured results on the EUT of successful detection of the radar Burst will be recorded and reported. Observation of Chr for EUT emissions will continue for 2.5 minutes after the radar Burst has been generated.
- (5) Verify that during the 2.5 minute measurement window no EUT transmissions occurred on Chr. The Channel Availability Check results will be recorded.





Figure 16: Example of timing for radar testing towards the end of the Channel Availability Check Time

4.3.5 Test Setup

<AP Mode>




4.3.6 Test Deviation

There is no deviation with the original standard.

4.3.7 Result of Channel Availability Check Time

<AP Mode>

<160MHz / 5250MHz>






Marker 1 : End of Channel Availability Check

Marker 2 (Delta1): 60 seconds before End of Channel Availability Check

Marker 3 (Delta2): 54 seconds or 6 seconds before End of Channel Availability Check



<240MHz / 5610MHz>

**EUT Power up and
Initial Channel Availability Check Time****Radar Burst at the Beginning of
the Channel Availability Check Time****Radar Burst at the End of
the Channel Availability Check Time**

Marker 1 : End of Channel Availability Check

Marker 2 (Delta1): 60 seconds before End of Channel Availability Check

Marker 3 (Delta2): 54 seconds or 6 seconds before End of Channel Availability Check

4.4 In-Service Monitoring: Channel Move Time, Channel Closing Transmission Time and Non-Occupancy Period

4.4.1 Limit of In-Service Monitoring


The EUT has In-Service Monitoring function to continuously monitor the radar signals, If radar is detected, it must leave the channel (Shutdown). The Channel Move Time to cease all transmissions on the current Channel upon detection of a Radar Waveform above the DFS Detection Threshold within 10 sec. The total duration of Channel Closing Transmission Time is comprised of 200 milliseconds starting at the beginning of the Channel Move Time plus any additional intermittent control signals required to facilitate Channel changes (an aggregate of 60 milliseconds) during the remainder of the 10 second period. The aggregate duration of control signals will not count quiet periods in between transmissions.

Non-Occupancy Period time is 30 minute during which a Channel will not be utilized after a Radar Waveform is detected on that Channel.

4.4.2 Test Procedures

- (1) One frequency will be chosen from the Operating Channels of the EUT within the 5250-5350 MHz or 5470-5725 MHz bands. For 802.11 devices, the test frequency must contain control signals. This can be verified by disabling channel loading and monitoring the spectrum analyzer. If no control signals are detected, another frequency must be selected within the emission bandwidth where control signals are detected.
- (2) In case the EUT is a Master Device, a U-NII device operating as a Client Device will be used and it is assumed that the Client will associate with the EUT (Master). For radiated tests, the emissions of the Radar Waveform generator will be directed towards the Master Device. If the Master Device has antenna gain, the main beam of the antenna will be directed toward the radar emitter. Vertical polarization is used for testing.
- (3) The TCP protocol unicast data stream was generated by the iperf software command line with at least 17% activity ratio over any 100ms period.
- (4) Timing plots are reported with calculations demonstrating a minimum channel loading of approximately 17% or greater. For example, channel loading can be estimated by setting the spectrum analyzer for zero span and approximate the Time On/ (Time On + Off Time).
- (5) At time T0 the Radar Waveform generator sends a Burst of pulses for one of the Short Pulse Radar Types 1-4 at DFS Detection Threshold levels on the Operating Channel. An additional 1 dB is added to the radar test signal to ensure it is at or above the DFS Detection Threshold, accounting for equipment variations/errors.
- (6) Observe the transmissions of the EUT at the end of the radar Burst on the Operating Channel for duration greater than 10 seconds. Measure and record the transmissions from the EUT during the observation time (Channel Move Time). Measure and record the Channel Move Time and Channel Closing Transmission Time if radar detection occurs.


- (7) When operating as a Master Device, monitor the EUT for more than 30 minutes following instant T₂ to verify that the EUT does not resume any transmissions on this Channel. Perform this test once and record the measurement result.




- (8) One 12 seconds plot is reported for the Short Pulse Radar Type 0.
- (9) Measurement of the aggregate duration of the Channel Closing Transmission Time method. With the spectrum analyzer set to zero span tuned to the center frequency of the EUT operating channel at the radar simulated frequency, peak detection, and max hold, the dwell time per bin is given by: $Dwell (0.4ms) = S (12000ms) / B (30000)$; where Dwell is the dwell time per spectrum analyzer sampling bin, S is the sweep time and B is the number of spectrum analyzer sampling bins. An upper bound of the aggregate duration of the intermittent control signals of Channel Closing Transmission Time is calculated by: $C (ms) = N \times Dwell (0.4 ms)$; where C is the Closing Time, N is the number of spectrum analyzer sampling bins (intermittent control signals) showing a U-NII transmission and Dwell is the dwell time per bin.

4.4.3 Test Setup

<AP Mode>



<Mesh Mode>



4.4.4 Test Deviation

There is no deviation with the original standard.

4.4.5 Result of Channel Move Time, Channel Closing Transmission Time and Non-Occupancy Period for Client Beacon Test

Test Mode :	Master	Temperature :	21.3 ~ 24.5 °C
Test Engineer :	Rebecca Li, Ivy Yen, Kai Kiao	Relative Humidity :	45.6 ~ 55.7 %

<AP Mode>

BW / Channel	Test Item	Test Result	Limit	Pass/Fail
<160MHz / 5250MHz>	Channel Move Time	0.070802s	< 10s	Pass
	Channel Closing Transmission Time	200ms + 0ms	< 260ms	Pass
	Non-Occupancy Period	> 30 min	> 30 min	Pass
<240MHz / 5610MHz>	Channel Move Time	0.0132s	< 10s	Pass
	Channel Closing Transmission Time	200ms + 0ms	< 260ms	Pass
	Non-Occupancy Period	> 30 min	> 30 min	Pass


<Mesh Mode>

BW / Channel	Test Item	Test Result	Limit	Pass/Fail
<160MHz / 5250MHz>	Channel Move Time	0.700417 s	< 10s	Pass
	Channel Closing Transmission Time	200ms + 22 ms	< 260ms	Pass

Note: The Channel Closing Transmission Time is comprised of 200 milliseconds starting at the beginning of the Channel Move Time plus any additional intermittent control signals required to facilitate a Channel move (an aggregate of 60 milliseconds) during the remainder of the 10 seconds period. The aggregate duration of control signals will not count quiet periods in between transmissions.


4.4.6 Channel Move Time, Channel Closing Transmission Time and Non-Occupancy Period Test Plots

<AP Mode>





<240MHz / 5610MHz> In-Service Monitoring


Channel Move Time &
Channel Closing Transmission Time**Note:**

Dwell (0.4 ms)= Sweep Time (12000 ms) / Sweep Point Bins (30000)

Channel Closing Transmission Time (200 + 0 ms) = 200 + Number (0) X Dwell (0.4 ms) < 260ms

<240MHz / 5610MHz> In-Service Monitoring


Non-Occupancy Period


Note:

The 99%OBW of Remaining Active Signal does not fall within the notched band.

Remaining active signal





<Mesh Mode>
<160MHz / 5250MHz >In-Service Monitoring
**Channel Move Time &
Channel Closing Transmission Time**

Note:

Dwell (0.4 ms)= Sweep Time (12000 ms) / Sweep Point Bins (30000)

Channel Closing Transmission Time (200 + 22ms) = 200 + Number (55) X Dwell (0.4 ms) < 260ms

4.4.7 Long Pulsed Radar Type Channel Move Time Test Plots (22second)

<AP Mode>








<Mesh Mode>

<160MHz / 5250MHz >Radar Type 5

Channel Move Time



4.4.8 Data Traffic Channel Loading and Noise Floor Plots



4.5 Statistical Performance Check

4.5.1 Limit of Statistical Performance Check

Short Pulse Radar Test

Once the performance requirements check is complete, statistical data will be gathered, to determine the ability of the device to detect the radar test waveforms (Short Pulse Radar Types 1-4) found in **Table 5**. The device can utilize a test mode to demonstrate when detection occurs to prevent the need to reset the device between trials. The percentage of successful detection is calculated by:

$$\frac{\text{TotalWaveformDetections}}{\text{TotalWaveformTrials}} \times 100 = \text{Percentage of Successful Detection Radar Waveform N} = P_d N$$

In addition an aggregate minimum percentage of successful detection across all Short Pulse Radar Types 1-4 is required and is calculated as follows:

$$\frac{P_d 1 + P_d 2 + P_d 3 + P_d 4}{4}$$

The minimum number of trials, minimum percentage of successful detection and the aggregate minimum percentage of successful detection are found in **Table 5**.

Table 5 – Short Pulse Radar Test Waveforms

Radar Type	Pulse Width (μsec)	PRI (μsec)	Number of Pulses	Minimum Percentage of Successful Detection	Minimum Number of Trials
1	1	1428	18	60%	30
2	1-5	150-230	23-29	60%	30
3	6-10	200-500	16-18	60%	30
4	11-20	200-500	12-16	60%	30
Aggregate (Radar Types 1-4)				80%	120



A minimum of 30 unique waveforms are required for each of the Short Pulse Radar Types 1 through 4. For Short Pulse Radar Type 0, the same waveform is used a minimum of 30 times. If more than 30 waveforms are used for Short Pulse Radar Types 1 through 4, then each additional waveform must also be unique and not repeated from the previous waveforms.

Radar Type	Number of Trials	Number of Successful Detections	Minimum Percentage of Successful Detection
1	35	29	82.9%
2	30	18	60%
3	30	27	90%
4	50	44	88%
Aggregate $(82.9\% + 60\% + 90\% + 88\%)/4 = 80.2\%$			

Long Pulse Radar Test

Statistical data will be gathered to determine the ability of the device to detect the Long Pulse Radar Type 5 found in **Table 6**. The device can utilize a test mode to demonstrate when detection occurs to prevent the need to reset the device between trials.

Table 6 – Long Pulse Radar Test Waveform

Radar Type	Pulse Width (μsec)	Chirp Width (MHz)	PRI (μsec)	Number of Pulses per Burst	Number of Bursts	Minimum Percentage of Successful Detection	Minimum Number of Trials
5	50-100	5-20	1000-2000	1-3	8-20	80%	30

The parameters for this waveform are randomly chosen. Thirty unique waveforms are required for the Long Pulse Radar Type waveforms. If more than 30 waveforms are used for the Long Pulse Radar Type waveforms, then each additional waveform must also be unique and not repeated from the previous waveforms.

Three subsets of trials will be performed with a minimum of ten trials per subset.

The subset of trials differs in where the Long Pulse Type 5 Signal is tuned in frequency:

- The Channel center frequency (subset case 1).
- Tuned frequencies such that 90% of the Long Pulse Type 5 frequency modulation is within the low edge of the UUT Occupied Bandwidth (subset case 2).
- Tuned frequencies such that 90% of the Long Pulse Type 5 frequency modulation is within the high edge of the UUT Occupied Bandwidth (subset case 3).

For subset case 1: the center frequency of the signal generator will remain fixed at the center of the UUT Channel.

For subset case 2: to retain 90% frequency overlap between the radar signal and the UUT Occupied Bandwidth, the center frequency of the signal generator will vary for each of the ten trials in subset case 2.

The center frequency of the signal generator for each trial is calculated by: $FL + (0.4 * \text{Chirp Width [in MHz]})$

For subset case 3: to retain 90% frequency overlap between the radar signal and the UUT Occupied Bandwidth, the center frequency of the signal generator will vary for each of the ten trials in subset case 3.

The center frequency of the signal generator for each trial is calculated by: $FH - (0.4 * \text{Chirp Width [in MHz]})$