

The metal push cover remote control is widely used for electric retractable doors, remote control road gates, remote control rolling shutter doors, garage doors, sliding doors, LED remote control lights, remote control fireworks igniters, remote control passenger car doors, burglar alarms, electric doors Alarms, MP3 motorcycle anti-theft alarms, etc. If you are a factory, it is the right choice to find us to match the remote control. We can make the corresponding remote control according to your requirements.

Remote Control Technical Parameters:

Model No. : **2AKHD4B-B/R22011KA**

Operation frequency: 434MHZ

* There are two keys, four keys optional

* Available colors: black, etc.

Working voltage: DC12V (1pc 27A/12V battery)

Working current: 10mA@12V

Radiation power: 10mw@12V

Modulation method: ASK (amplitude modulation)

Transmission distance: 50M (the receiver sensitivity : -100dbm)

Encoder Type: Learning Code

Receive Technical Parameters:

1. Receiving frequency: 434MHZ
2. Working voltage: DC 5V
3. Working current: 16mA
4. Size: 38*8*4mm
4. Demodulation method: ASK
5. Local oscillator mode: sound table stabilized frequency local oscillator
6. Receiving sensitivity: -100Bm
7. Output data level: TTL level
8. Working temperature: -20°C~+60°C

Warning:

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and
(2) This device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.