

说明书折页

尺寸:80*80 mm

User Guide

Video Doorbell

**Repeater:anyfree-MLZJ01-M
Smart Doorbell:anyfree-ML01-M**

<p>O1</p> <p>Set up your Video Doorbell</p> <p>O1.1</p> <p>Download the Hello Doorbell app</p> <p>"Please make sure you have your wifi password ready for the next step."</p> <p>Search for "Hello Doorbell" in one of the app stores above, or scan the QR code on the back of the doorbell to download the app.</p>	<p>O1.2</p> <p>Charge the doorbell</p> <p>Pull down the mounting bracket of the doorbell, find the charging port.</p>	<p>O1.3</p> <p>Turn on the doorbell</p> <p>The doorbell is off by default at the factory. Please make sure to turn on the doorbell before setting up.</p>	<p>O1.4</p> <p>Plug-in your signal station</p> <p>Plug it into the power source. Once the light is solid red, it's ready to prepare your doorbell.</p>	<p>O1.5</p> <p>Set up your Video Doorbell near your signal station</p> <p>Long press the side button on the signal station. When the light starts flashing green, connecting the device via WiFi-haloo.</p>	<p>O1.6</p> <p>In-app to instructions</p> <p>Follow the In-app instructions to set up your doorbell.</p> <p>O1.7</p> <p>Select connection method</p> <p>We provide two connection methods:</p> <ul style="list-style-type: none"> Bluetooth connection Scan code connection 	<p>A</p> <p>Bluetooth connection</p> <ul style="list-style-type: none"> Turn on the Bluetooth in phone system setting. Searching for any/free signal station and connect. <p>B</p> <p>Scan code connection</p> <ul style="list-style-type: none"> Scan the QR code on the phone with your doorbell. When the prompt sounds, it means the scan is successful. 	<p>O2</p> <p>Install your Video Doorbell</p> <p>O2.1</p> <p>Set installation height</p> <p>Install your Video Doorbell approximately five feet (1.50 meters) above the ground for optimal performance. If you're connecting to existing doorbell wiring that's higher than four feet and want to angle your Video Doorbell down for a better view, you can purchase a Wedge Kit online at anyfree.com/accessories.</p> <p>*Optional: If walling in existing conduit, first drill power on the breaker. Then remove it from the wall and disconnect the wire.</p> <p>O2.2</p> <p>Mark the screw holes</p> <p>Use the bracket as a template to mark the holes. The recommended install height is 5 feet above the ground. The holes are 105.5 mm apart.</p> <p>O2.3</p> <p>Attach your Video Doorbell to the mounting bracket</p> <p>Mount the doorbell above the hanging plate by 5-10mm, align it horizontally, stick it securely, slide it downwards, and hang it tightly.</p>
---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------------------------------------------------------------------------------------------------------------------	-------------------------------------------------------------------------------------------------------------------------------------------------------------------------	----------------------------------------------------------------------------------------------------------------------------------------------------------------------	---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

O2.4

Install the anchor(Optional)

If installing on stucco, brick, or concrete, use a #6 heavy-duty drill bit to drill holes in your wall, then insert the included anchors with KA3P30 screws. The holes are 86.5 mm apart.

O2.5

Attach the anchor to the mounting bracket

Attach the mounting bracket to the anchor using KA3P30 screws, then follow the instructions from step O2.4.

O3

Feature Introduction

O3.1

No need to charge

The doorbell operates on solar energy, eliminating the need for recharging.

O3.2

Ignore distance in open areas

The doorbell can transmit signals over a distance of more than 1km with the help of WiFi-haloo technology.

Products & Accessories

O3.3

AR interaction

During a video call with visitors, you can see all effects by waving your hand and take photos to capture the moment. Keep in mind that different festivals may offer different social filters. Stay tuned for more updates!

O3.4

Motion detection

To set up the doorbell, click on the detection environment to activate the millimeter wave radar monitoring. Once the monitoring is done, you'll receive a prompt and the millimeter wave radar will monitor your doorstep in real-time.

O3.5

Customized ringtone

You can create and customize unique ringtones in the app.

O3.6

Video message

Visitors can record video messages for you in case the doorbell calls. Video Mail will start automatically with a voice prompt.

FCC WARNING: This equipment may generate or use radio frequency energy. Changes or modifications to this equipment may cause harmful interference unless the modifications are expressly approved in the instruction manual. The user could lose the authority to operate this equipment if an unauthorized change or modification is made.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio-frequency energy and it must not be used in accordance with the instructions, may cause harmful interference to radio communications; however, there is no guarantee that interference will not occur in a particular installation. If the equipment does cause harmful interference to radio or television reception which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The rating information is located at the bottom of the unit.

This equipment complies with FCC radio exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator & your body.

EUROCOM LTD
Surrey, GU24 0WU, United Kingdom

MCM SARL
Avenue des Champs-Elysées Bureau 330
91000 Evry-Courcouronnes

O4

Technical Specifications

O4.1

General Information

Model: MLZJ01-M / ML01-M
Material: ABS + PC
Color: White / Black
Power Source: Solar Panel (5V/2W)
Battery Capacity: 2000mAh
Operating Temperature: -10°C ~ 40°C
Storage Temperature: -20°C ~ 60°C
Humidity: 10% ~ 90% RH
IP Rating: IP65
Dimensions (H x W x D): 120mm x 60mm x 35mm
Weight: 150g

O4.2

Performance Parameters

Signal Range: Up to 1km (open area)
Response Time: < 1s
Audio Frequency: 1KHz ~ 4KHz
Video Resolution: 1080P
Field of View: 180°
Night Vision: IR LED (Infrared)
Motion Detection Sensitivity: Adjustable
Tamper Alarm: Yes
Low Battery Warning: Yes
Firmware Version: V1.0

O5

Safety Instructions

O5.1

Installation Safety

Read the entire manual carefully before installation.
Ensure the doorbell is installed in a dry location.
Do not touch the internal components.
Avoid contact with water during installation.
Use appropriate tools for drilling and wiring.
Disconnect power before working on the wiring.
Securely fasten all components.
Test the doorbell after installation.

O5.2

Usage Safety

Do not expose the doorbell to direct sunlight for extended periods.
Avoid placing objects directly in front of the lens.
Keep the doorbell clean and free of dust.
Do not attempt to disassemble the doorbell.
If the doorbell malfunctions, stop using it immediately and contact customer support.
Dispose of the doorbell according to local regulations.

O6

Environmental Protection

O6.1

Eco-Friendly Design

The doorbell features a solar-powered design, reducing reliance on traditional power sources and minimizing carbon footprint.
The housing is made from recyclable materials.
The product is designed for longevity and durability.
Packaging is minimal and eco-friendly.

O6.2

Energy Efficiency

The doorbell utilizes advanced motion detection algorithms to conserve energy.
It enters a low-power sleep mode when not in use.
The solar panel efficiently converts sunlight into usable energy.
The battery management system optimizes power consumption.

O7

Customer Support

O7.1

Contact Us

Email: support@anyfree.com
Phone: +1 (800) 123-4567
Website: www.anyfree.com/support

O7.2

Return Policy

Our return policy allows for a 30-day money-back guarantee on unused equipment.
To initiate a return, please contact our customer support team.
Original packaging and accessories must be included.
Restocking fees may apply for certain items.
Shipping costs for returns are the responsibility of the customer.

O8

Legal Disclaimer

O8.1

Limitation of Liability

Anyfree Company and its affiliates shall not be liable for any damages, including consequential damages, arising from the use or misuse of this equipment.
The equipment is provided "as is" without any warranties.
No third-party claims shall be covered by this disclaimer.

O8.2

Intellectual Property

All trademarks and registered service marks contained herein are the property of their respective owners.
All other trademarks are the property of their respective holders.
Copyright © 2023 Any

折叠线

序号	技术要求	数值
1	材质要求	105g双铜
2	表面处理/颜色	彩印
3	基本公差	正负0.5mm
4	变形度/平面度	
5	重点尺寸	*号标识
6	户外防止外线	
7	盐雾要求	
8	ROHS	符合
其它要求:		

图纸编号	TC-U9ML-A-说明书-001	图纸版本号	V11												
文件编号	TC-QI-YF-0005	<div> 珠海太川云社区技术股份有限公司 ZHUHAITAICHUAN CLOUD TECHNOLOGY CO.,LTD</div>						编号	更改内容/说明	标记	签名				
图 名															
U9ML-A 说明书								视 图		颜 色		数 量			
								单 位	MM	设 计		日 期			
适用机型:		材 质		审 核		日 期									
		比 例	1 : 1	批 准	肖亮亮	日 期	2024.9.24	版本号	A-04						