

	KB718+T 29	<p>2.4G Wireless keyboard and mouse combo</p> <p>Specification</p> <p>Keyboard (White color/black color)</p> <p>English layout</p> <p>1.0: General feature</p> <ul style="list-style-type: none"> --2.4GHz wireless transmission technology, stable and strong performance --Ultra thin design, chocolate keys, fashionable appearance --Ergonomic design, ultra quiet, comfortable to use, enjoy health life and work --Multimedia shortcut control --Mini USB wireless receiver --Working distance 10 meters --High quality membrane switch --Keyboard runs with one piece AA battery, mouse runs with two pieces AAA batteries --Mouse,high definition optical technology, DPI : 800-1200-1600 one key switch, precise positioning <p>Mouse (silver black color)</p> <p>2.0: Reliability</p> <ul style="list-style-type: none"> Mouse key life 5000000 times Receiver life 100000 times Working temperature: -5+40°C Working humidity: 20% -90% Keyboard key life: 5000000 times <p>3.0 Compatible systems</p> <ul style="list-style-type: none"> Windows98SE, Windows ME, Windows 2000 or Windows XP, Windows 7, Windows 8, Windows Vista Macintosh OS 8.6 or higher <p>4.0 Size</p> <ul style="list-style-type: none"> Keyboard : 360MM*117MM * 30MM Mouse : 116MM*66MM *36MM Receiver : 18.5MM*14.6MM *6MM <p>5.0 Mechanical feature :</p> <table border="1" data-bbox="350 1730 954 1865"> <tr> <td colspan="2">Mouse</td> </tr> <tr> <td>Right and left keys strength</td> <td>65±5gf</td> </tr> <tr> <td>DPI key strength</td> <td>65±5gf</td> </tr> <tr> <td>Receiver twist strength</td> <td>20±10gf</td> </tr> </table> <table border="1" data-bbox="350 1921 954 2123"> <tr> <td colspan="2">Keyboard</td> </tr> <tr> <td>Standard key strength</td> <td>55±10g</td> </tr> <tr> <td>Standard key route</td> <td>3.9±0.1</td> </tr> <tr> <td>Multimedia key route</td> <td>2.5±0.1</td> </tr> <tr> <td colspan="2">Material : Keyboard -ABS+HIPS, Mouse &</td> </tr> </table>	Mouse		Right and left keys strength	65±5gf	DPI key strength	65±5gf	Receiver twist strength	20±10gf	Keyboard		Standard key strength	55±10g	Standard key route	3.9±0.1	Multimedia key route	2.5±0.1	Material : Keyboard -ABS+HIPS, Mouse &			
Mouse																						
Right and left keys strength	65±5gf																					
DPI key strength	65±5gf																					
Receiver twist strength	20±10gf																					
Keyboard																						
Standard key strength	55±10g																					
Standard key route	3.9±0.1																					
Multimedia key route	2.5±0.1																					
Material : Keyboard -ABS+HIPS, Mouse &																						

	<p>receiver- ABS Weight: Keyboard- 300G, mouse- 39 G, receiver 1.6 G</p> <p>6.0: Electric feature</p> <p>Mouse working current: Working ≤ 8 MA @ 3V After 4 seconds enters to the first level sleeping mode First level sleeping ≤ 0.3 MA @3V After 30 seconds enters to the second level sleeping mode Second level sleeping ≤ 60UA @3V After 1 minute seconds enters to the third level sleeping mode Third level sleeping ≤ 10UA @3V</p> <p>Keyboard working current: Working ≤ 5MA @ 3.0V Sleeping ≤ 5UA @ 3.0V</p>		

Warning

changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna

Increase the separation between the equipment and receiver.

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

- Consult the dealer or an experienced radio/TV technician for help.

NOTE: This device and its antenna(s) must not be co-located or operation in conjunction with any other antenna or transmitter.