

## User Manual

### 1. Product description:

- (1) Adapter input 100V-240V 50/60Hz
- (2) User can adjust position of head part and foot part respectively
- (3) 4 preset position and 2 user setting position
- (4) User can massage head and foot respectively
- (5) 3 massage mode
- (6) 3 massage strength
- (7) 3 massage time: 10min, 20min, 30min
- (8) remote controller powered by 2 AAA batteries
- (8) torch on remote controller
- (9) charge two mobile phone at same time(1A max per USB port)
- (10) lamp at bottom of bed, controlled by remote controller or sensor

### 2. Use instruction

#### ① Control box coding with remote controller.

- (1) Press "HEAD DOWN" and "FOOT UP" on remote controller at same time. Then LEDs on remote controller start to flash, and keep pressing this two keys. According to figure 1.



figure 1

(2)Press key on the side of control box. Then control box make hint sound, and coding is successful. According to figure2.



figure2

(3)Release two keys on remote controller and key on control box. Coding finish.

②Control box

After power on, all movement of bed will be controlled by remote controller.

③Remote controller



Figure3

(1)"TV" key: If press this key, bed will move to a preset position. This position is designed for watching TV on bed.

(2)"SIDE SLEEP" key: If press this key, bed will move to a preset position. This position is designed for helping to side sleep when people is sleeping.

(3)"ZG" key: If press this key, bed will move to a preset position. People will feel very relax at this position.

(4)"M1" key: If long press this key, bed will memory the position at that time. If short press this key, bed will move to the position user set by long press this key.

(5)"FLAT" key: If press this key, bed will put down the head part and foot part until the bed is flat.

(6)"M2" key: If long press this key, bed will memory the position at that time. If short press this key, bed will move to the position user set by long press this key.

(7)"HEAD UP" key: If press this key, bed will put up the head part until user release this key.

(8) "H&F UP" key: If press this key, bed will put up the head part and foot part at same time until user release this key.

(9) "FOOT UP" key: If press this key, bed will put up the foot part until user release this key.

(10)"HEAD DOWN" key: If press this key, bed will put down the head part until user release this key.

(11) "H&F DOWN" key: If press this key, bed will put down the head part and foot part at same time until user release this key.

- (12) "FOOT DOWN" key: If press this key, bed will put down the foot part until user release this key.
- (13)"HEAD+" key: If press this key, massage strength of head part will increase.
- (14)"TIMER/ALL OFF": If press this key when massage is going, massage will stop. User can choose the massage time through press this key repeatedly.
- (15) "FOOT+" key: If press this key, massage strength of foot part will increase.
- (16) "HEAD-" key: If press this key, massage strength of head part will decrease.
- (17)"MODE" key: If press this key, massage mode will change.
- (18)"FOOT-" key: If press this key, massage strength of foot part will decrease.
- (19) "BEDLAMP" key: If press this key, the lamp at bottom of bed will be turned on/off.
- (20) "TORCH" key: If press this key, the torch in the front of remote controller will be turned on. And if release this key, the torch will be turned off.
- (21)"SENSOR" key: If press this key, the lamp at bottom of bed will be controlled by PIR sensor. When sensor detect human moving, turn on lamp, and after 30s turn off lamp. Press this key again, the lamp will be controlled by remote controller.

#### ④Charger

Connect USB port on bed and mobile phone through USB cable, mobile phone can be charged.

#### ⑤Sensor

Sensor board detect human moving, and feedback signal to control box.

#### ⑥Lamp

In manual mode, control box turn on/off lamp when receive "BEDLAMP" signal from remote controller.

In sense mode, when sensor detect human moving, turn on lamp, and after 30s turn off lamp.

**Federal Communication Commission (FCC) Radiation Exposure Statement**

The device has been evaluated to meet general RF exposure requirement, The device can be used in portable exposure condition without restriction Federal Communication Commission (FCC) Radiation Exposure Statement Power is so low that no RF exposure calculation is needed.

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE: The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications or changes to this equipment. Such modifications or changes could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.