


EasySMX					
制作日期	2024-04-25		材质	70g书写纸	
尺寸信息	单张尺寸：80mm*120mm 成品尺寸：560mm*120mm		印刷	双面单色印刷	
变更信息					
排版方式	折页	字体	MiSans	最小字号	不低于4pt
设计人员	Kirry	格式要求	Ai / PDF	版本	1.0

技术要求：


- 1.字体及内容正确，尺寸、形状和图纸要求一致
- 2.颜色和签样样板一致；
- 3.不能漏印、露底、错位、重影，不允许有异物、凹痕、划痕
- 4.不能模糊、飞边，颜色需光滑平整；
- 5.工艺尺寸公差+0.05mm:
- 6.性能满足测试规范:

EasySMX-X05说明书

正面

  Wireless Controller EasySMX X05 USER MANUAL	EN Button Layout  — 02 —	EN Product Introduction • X05 Game Controller: Supports 2.4G Wireless, Bluetooth, and Switch connection modes. • Compatible Devices: PC, Switch, Android/iOS (MFI games above version 13.0). Connection Operations Receiver Connection Plug the USB RECEIVER into a USB port, set the MODE SWITCH BUTTON to the RECEIVER position, press the HOME BUTTON to power on the controller. When the led indicator becomes solid, the controller will vibrate briefly to indicate a successful connection. [Note] If the controller fails to pair with the receiver, forced pairing is required. Forced Pairing - Plug in the USB RECEIVER. - Click the button on the receiver briefly, the receiver led indicator will flash rapidly. - Then with the controller powered off, press and hold the Home button for 5 seconds to turn on the controller. At this time, the controller indicator light will flash rapidly. When the indicator light becomes solid, the controller will vibrate briefly, indicating successful pairing. Bluetooth Connection First Connection: Set the MODE SWITCH BUTTON to	EN the RECEIVER position, press and hold the HOME BUTTON for 5 seconds to power on the controller, the controller led indicator will flash rapidly. Open the device's Bluetooth and search for "Xbox Wireless Controller". Click to pair, and when the indicator light becomes solid, the controller will vibrate briefly to indicate successful pairing. Subsequent Connections: Set the MODE SWITCH BUTTON to the RECEIVER position, press the HOME BUTTON briefly to reconnect automatically. Switch Connection First Connection: Set the MODE SWITCH BUTTON to the RECEIVER position, press and hold the HOME button for 5 seconds to turn on the controller. The controller indicator light will flash rapidly. Open the Switch, then go to "Controllers" and "Change Grip/Order" to enter pairing mode. When the led indicator becomes solid, the controller will vibrate briefly to indicate successful pairing. Subsequent Connections: Set the MODE SWITCH BUTTON to the RECEIVER position, press the HOME BUTTON briefly to reconnect the Switch console. [Note] In Switch mode, click the O BUTTON to take a screenshot.	EN Mode Switching Hold BACK + START for 3 seconds to switch between X-input (blue light) and D-input (yellow light) modes, with a brief controller vibration indicating successful setting. Turbo Setting <table><tr><td>Manual Turbo</td><td>Example: Press M & A to set</td><td>Press and hold the A button for continuous trigger</td></tr><tr><td>Cancel Turbo</td><td>Example: Press M & A again to cancel the turbo function</td><td>Note: The buttons that can be set with turbo function are: A/B/X/Y/LB/RB/LT/RT</td></tr></table> Note: M+Left joystick left decreases the turbo speed; M+Left joystick right increases the turbo speed. RGB Light Adjustment Double-click the M button, the controller will vibrate briefly, and enter the RGB adjustment mode. Change Lighting mode: Use the left joystick UP and DOWN to switch between light modes (steady-on, breathing, dazzling, gradient, off); Change the lighting color: Use the left joystick LEFT and RIGHT to switch between light colors (red, orange, yellow, green, cyan, blue, purple); Adjust the brightness: press M+L3. After setting, press M briefly to exit the light adjustment mode.	Manual Turbo	Example: Press M & A to set	Press and hold the A button for continuous trigger	Cancel Turbo	Example: Press M & A again to cancel the turbo function	Note: The buttons that can be set with turbo function are: A/B/X/Y/LB/RB/LT/RT	EN Vibration Adjustment M+Left joystick up enhances vibration; M+Left joystick down reduces vibration (0%, 25%, 50%, 75%, 100%). Joystick and Trigger Calibration With the controller power on, press and hold HOME+BACK+B for 3 seconds to enter calibration mode. Press each trigger twice, rotate each joystick twice, place the controller horizontally, and press B briefly to exit and complete the calibration. Charging and Indicators Controller Power off state: Slow flashing red light while charging, solid green light when fully charged; Wired Connection: Maintains the current mode light. Wireless Connection: The mode light flashes slowly while charging, and stays on when fully charged. Low Battery Reminder When the controller is connected, a slow flashing indicator light indicates low voltage, please charge in time. Shutdown • Manual Power Off: Press and hold the HOME button for 5 seconds. • Automatic Power Off: The controller turns off Product Specifications <table><tr><td>Model</td><td>X05</td><td>Working Current</td><td>90mA</td></tr><tr><td>Battery Specification</td><td>750mAh</td><td>Sleep Current</td><td>100uA</td></tr><tr><td>Input Voltage</td><td>5V</td><td>Charging Time</td><td>2-3H</td></tr></table> Package Contents • Wireless Controller x1 • Wireless Receiver x1 • Type-C Data Cable x1 • Product Manual x1	Model	X05	Working Current	90mA	Battery Specification	750mAh	Sleep Current	100uA	Input Voltage	5V	Charging Time	2-3H
	Manual Turbo	Example: Press M & A to set	Press and hold the A button for continuous trigger																				
Cancel Turbo	Example: Press M & A again to cancel the turbo function	Note: The buttons that can be set with turbo function are: A/B/X/Y/LB/RB/LT/RT																					
Model	X05	Working Current	90mA																				
Battery Specification	750mAh	Sleep Current	100uA																				
Input Voltage	5V	Charging Time	2-3H																				

反面

Contents English ----- 02-07 China ----- 08-12		CN 按键布局  — 08 —		CN 产品介绍 X05是一款多模游戏手柄支持2.4G、蓝牙、Switch连接模式，适用于PC、Switch、Android/iOS（13.0以上版本MFI游戏）等设备。 连接操作 1. 接收器连接 将接收器插到电脑USB口，背部拨动开关拨到 RECEIVER 档位，短按Home键开机，此时手柄指示灯慢闪，当指示灯变为长亮，手柄短振一下，表示连接成功。 【备注】 当手柄无法与接收器配对成功，此时需要强制配对。 操作方法: 接收器插到电脑USB口，短按一下接收器上面的按键，此时接收器快闪，然后手柄在关机状态下 长按Home键5秒开机，此时手柄指示灯快闪，当手柄指示灯变为长亮，手柄短振一下，表示配对成功。 2. BT 蓝牙连接 首次连接 将手柄背部拨动开关拨到 BT 档，长按手柄HOME键5秒开机，此时手柄指示灯快闪；打开设备蓝牙搜索到 Xbox Wireless Controller，点击进行配对，当指示灯变为长亮，手柄短振一下表示配对成功。 二次连接 将手柄背部拨动开关拨到 BT 档，短按Home键开机，即可回连设备。 3. NS Switch连接		CN 首次连接 将手柄背部拨动开关拨到 RECEIVER 档，长按HOME键5秒开机，此时手柄指示灯快闪；打开Switch，依次点击【手柄】、【更改握法/顺序】进入配对模式，当指示灯变为长亮，手柄短振一下表示配对成功。 二次连接 将手柄背部拨动开关拨到 RECEIVER 档，短按Home键开机，即可回连Switch主机。 【备注】Switch模式下，单击O键进行截屏。 模式切换 手柄在接收器模式和蓝牙模式下，同时长按BACK+START3秒切换X-input模式（蓝灯）和D-input模式（黄灯），切换成功手柄短振一下。 连发设置 <table><tr><td>手动连发</td><td>第一次按下M+A键</td><td>按住A键，A键连续触发</td></tr><tr><td>取消连发</td><td>第二次按下M+A键</td><td>可设置Turbo 功能的按键有: A/B/X/Y/LB/RB/LT/RT</td></tr></table> 【备注1】 M+左摇杆左推降低连发速度； M+左摇杆右推增加连发速度。 RGB灯光调节 双击M键，手柄短震一下，进入RGB调节模式，通过左摇杆上下切换灯光模式（常亮-呼吸-炫彩-渐变-关闭）；通过左摇杆左右切换灯光颜色（红-橙-黄-绿-青-蓝-紫）；按		手动连发	第一次按下M+A键	按住A键，A键连续触发	取消连发	第二次按下M+A键	可设置Turbo 功能的按键有: A/B/X/Y/LB/RB/LT/RT	CN M+L3键调节灯光亮度；设置完成短按M键退出灯光调节模式。 振动调节 M+左摇杆上推增强震动； M+左摇杆下推减弱震动（0% 25% 50% 75% 100%）。 摇杆、扳机校准 开机状态下，长按HOME+BACK+B键3秒进入校准模式，需要分别按压两次左右扳机，分别旋转左右摇杆两圈，将手柄水平放置，短按B键退出，完成校准。 充电指示 关机状态：充电时红灯慢闪，充满绿灯常亮； 有线连接：维持当前模式灯不变； 无线连接：充电时当前模式灯慢闪，充满常亮。 关机 关机： 长按HOME键5秒关机或手柄5分钟无操作自动关机。 低电提醒 手柄连接状态下指示灯慢闪表示电压低，请及时充电。		CN 产品规格 <table><tr><td>产品型号</td><td>X05</td><td>工作电流</td><td>90mA</td></tr><tr><td>电池规格</td><td>750mAh</td><td>休眠电流</td><td>100uA</td></tr><tr><td>输入电压</td><td>5V</td><td>充电时长</td><td>2-3H</td></tr></table> 包装清单 无线手柄x1 无线接收器x1 TYPE C数据线x1 产品说明书x1  Follow us for the best after-sales service and the latest news! EasySMX Co., Limited Email: support@easysmx.com Web: www.easysmx.com		产品型号	X05	工作电流	90mA	电池规格	750mAh	休眠电流	100uA	输入电压	5V	充电时长	2-3H
手动连发	第一次按下M+A键	按住A键，A键连续触发																											
取消连发	第二次按下M+A键	可设置Turbo 功能的按键有: A/B/X/Y/LB/RB/LT/RT																											
产品型号	X05	工作电流	90mA																										
电池规格	750mAh	休眠电流	100uA																										
输入电压	5V	充电时长	2-3H																										

FCC Caution.

(1) § 15.19 Labelling requirements.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

§ 15.21 Changes or modification warning

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

§ 15.105 Information to the user.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of

the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

RF warning for Portable device:

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

According to § 15.247(e)(i) and § 1.1307(b)(1), systems operating under the provisions of this section shall be operated in a manner that ensures that the public is not exposed to radio frequency energy level in excess of the Commission's guidelines.

According to KDB 447498 (2)(a)(i)