

1. Function Introduction

Indicator light: Red

Bluetooth voice remote control

Remote control appearance:



Figure A.1 Remote control appearance

2. Detailed Function Description

2.1. IR & BLE Key code

- 1) 、Send Bluetooth key code when Bluetooth is connected to the button, and the button does not send infrared key code when Bluetooth is connected (except for the power button)。
- 2) 、When Bluetooth is not connected, the remote control emits infrared light。
- 3) 、Press the infrared and Bluetooth status buttons and the LED will flash 5 times (1000ms)。

Key Definition	Usage Page	Usage ID	IR Code	Remarks
Power	0x000C	0x0030	0x18(0x76)	1. When Bluetooth is disconnected, a red external code 0x18 appears 2. When connecting via Bluetooth, send the Bluetooth code value first, and after 500ms, send the red external code 0x76
MENU	0x0007	0x0065	0x10	
MUTE	0x000C	0x00E2	0x15	
Simulate mouse			0x5F	
UP	0x0007	0x0052	0x0D	
LEFT	0x0007	0x0050	0x17	

OK	0x0007	0x0028	0x07	
RIGHT	0x0007	0x004F	0x16	
DOWN	0x0007	0x0051	0x1E	
BACK	0x000C	0x0224	0x1F	
HOME	0x000C	0x0223	0x80	
VOICES	0x000C	0x0221	/	
VOL-	0x000C	0x00EA	0x59	
VOL+	0x000C	0x00E9	0x55	

2.2. Bluetooth pairing function

Step	Operation
Paired broadcast transmission	Press the "OK" and "Return" buttons on the remote control for more than 3 seconds at the same time, and the indicator light will enter a fast flashing (100ms) state, sending pairing or clearing pairing broadcasts (20s). Broadcast name LZ MIC RC.
Pairing results	When the pairing is successful, the indicator light changes from fast flashing to slow flashing (500ms) and goes off after 2 seconds. If pairing fails, the remote control indicator light will continue to flash fast for 20 seconds until it goes off.

2.3. Remote control mouse function

Simulate a mouse, press the mouse button to activate the mouse function, press the mouse button again or do not press the directional key for 30 seconds to turn it off.

FCC Warning

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE 1: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

NOTE 2: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.