




Installation & Usage Guide


PLANNING THE INSTALLATION
Read all instructions before installation. Before starting installation of this fixture or removal of a previous fixture, disconnect the power by turning off the circuit breaker or by removing the fuse at the fuse box.

TOOLS REQUIRED




- Wire Cutters
- Electrical Tape
- Wire Strippers
- Phillips Screwdriver

HARDWARE INCLUDED



Part	Description	Quantity
AA	Mounting Bracket	1
BB	Wire Nut	3
CC	30mm Machine Screw	2
DD	25mm Machine Screw	2
EE	Ground Screw	1

PACKAGE CONTENTS




Part	Description	Quantity
A	Base board	1
B	Cover	1
C	Ring	1

Installation


1 PREPARING THE FIXTURE

WARNING: Be sure the electricity to the wires you are working on is shut off. Either remove the fuse or turn the circuit off.




2 PREPARING THE MOUNTING BRACKET

- Align two of the threaded holes on the mounting Bracket(AA) over one set of keyhole slots on the base board(A).
- From the front side of the base board(A), insert the 30mm screws(CC) and ground screw(EE) into the aligned holes, leaving approximately 1inch of space between the screw heads and mounting bracket (AA)



3 INSTALLING THE MOUNTING BRACKET

- Attach the mounting bracket (AA) to the outlet box(not included) using the 25mm screws(DD)




Installation (cont.)

4 CONNECTING THE WIRES


- Connect the copper wire on the base board(A) to the mounting bracket(AA) by securing it with the ground screw(EE). Use a wire connector(BB) to connect the ground wire from the base board(A) to the ground wire from the outlet box.
- Use a wire connector(BB) to connect the white wire from the base board(A) to the white wire (Neutral wire)from the outlet box.
- Use a wire connector(BB) to connect the black wire from the base board(A) to the black wire(Live wire) from the outlet box.
- Wrap the three wire connection with electrical tape for a more secure connection.

Position the wires inside the outlet box.




5 SECURING THE FIXTURE

- Align the channels on the fixture with the screws(CC) protruding from the mounting bracket. Slide the base board until it clicks into place over the screws(CC). Tighten the screws(CC) to secure the base board(A) in place.



6 SELECT CCT AND ATTACHING THE COVER

- Switch to your desired CCT. Attach the cover(B) and ring(C) to the base board(A), screw up.



Safety Information

WARNING: RISK OF PERSONAL INJURY - PLEASE READ THESE INSTRUCTIONS CAREFULLY. FOLLOW ALL INSTALLATION INSTRUCTIONS AND OBSERVE ALL WARNINGS.

Retain these instructions. If you are an installer, please give these instructions to the property owner for future reference.

- Make sure the "supply" voltage corresponds to the "rated" product voltage 120V 60Hz.
- The product MUST be installed by a qualified electrician in accordance with The National Electrical Code and corresponding local codes.
- If the product is damaged, DO NOT ATTEMPT INSTALLATION AND DO NOT USE.

WARNING: Risk of fire: Always consult with a qualified electrician to ensure the correct branch circuit conductor is utilized. The minimum conductor rating requirement is 90°C (194°F) in order to be code compliant.

CAUTION: Risk of injury: Always wear the necessary safety equipment to prevent injuries when opening, handling, installing and maintaining this product.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator& your body.

This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.