AJAZZ × NACODEX

黑爵AJ139 PRO 双模鼠标

AJAZZ AJ139 PRO DUAL MODE MOUSE

使用说明书
User Manual

目 录

CONTENTS

中文 ---------- 1~4
English ---------- 5~8
IndonesiaName ---------- 9~12

非常感谢您选购了我们AJAZZ黑爵AJ139 PRO双模游戏鼠标，希望它能带给您全新的操作感受，要获得更多增强的设置和功能，可以从官网下载驱动软件。

一、技术参数

产品品牌：A·····

产品型号：黑爵AJ139 PRO

传输方式：USB有线+2.4G无线

接口类型：Type-C接口

产品尺寸：125.4x63.3x38.2mm

产品重量：≈59g

外壳材质：ABS注塑

按键数量：6按键+1开关

线材长度：1.5M

DPI 调 节：400-3200（六档DPI驱动软件可调节）

（驱动软件可调最低 50 DPI，最高 26000 DPI，驱动 DPI 调节 50 DPI 为一步）

传 感 器：PAW3395

按键寿命：10000W次

电池容量：300mAh

回 报 率（默认）：有线 USB：1000Hz / 2.4G：1000Hz

驱动软件：①、可调有线回报率：125Hz/250Hz/500Hz/1000Hz

②、可调 2.4G 回报率：125Hz/250Hz/500Hz/1000Hz

支持系统：Windows Vista/XP/7/8/10/11，Mac

二、按键功能说明



①、左键

②、右键

③、中键（滚轮键）

④、前进键

⑤、后退键

⑥、DPI切换键

a.六档 DPI 键：默认 DPI为800【绿】。（可在驱动软件中自定义调节 DPI 值）

滚轮指示灯：400（红）/800（绿）/ 1200（蓝）/ 1600（青）/ 2400（黄）/ 3200（紫）

b. DPI 灯效：默认单色呼吸。（单色常亮、关闭灯光需通过驱动软件调节）

单色呼吸（颜色与 DPI 颜色相对应）、单色常亮（颜色与 DPI 颜色相对应）、关闭灯光

⑦、电源开关

a. ON 档：往上拨到 ON 档，即电源开启；

b. OFF档：往下拨到 OFF 档，即电源关闭。

（注：在任何模式下，插入 USB 数据线，即为有线模式，并为鼠标进行充电。）

三、指示灯/低电模式说明

1. 鼠标正面指示灯

①、DPI 指示灯：对应 DPI 档位颜色

②、低电指示灯：指示灯闪烁（红灯）

③、充电指示灯：指示灯常亮（红灯）

④、配对指示灯：2.4G模式配对指示灯（绿灯）

a. 配对指示灯慢闪（绿灯）：进入 2.4G 回连状态

b. 配对指示灯快闪（绿灯）：进入 2.4G 配对状态

注：回连时间 10s，配对时间 30s，超时进入深睡

2. 低电模式：

①、低电时状态：鼠标指示灯闪烁（红灯）；

②、充电时状态：鼠标指示灯常亮（红灯）；

③、满电时状态：鼠标指示灯恢复到正常灯效；

④、电池电压低于 3.4V 以下状态：鼠标指示灯按 0.5hz 频率闪烁（红灯），提示要充电；

⑤、电池电压低于 3.2V-3.0V以下状态：鼠标自动关机。

3. 休眠模式：

①、省电休眠：鼠标停止移动 10 秒后，鼠标进入省电休眠状态，移动/按键可唤醒鼠标；

②、深度休眠：鼠标停止移动 5 分钟，鼠标进入深度休眠状态，只能按键可唤醒鼠标。

（注：深度休眠时间可在驱动软件自定义调节。）

四、模式功能说明

1. 有线模式：

有线模式切换方法：无论在任何模式下，插入 TYPE-C 线后，都自动切换为有线模式，并开始为鼠标充电。

2. 2.4G无线模式：

①、2.4G 切换方法：鼠标底部电源开关往上拨，即为 2.4G 模式。

②、2.4G 配对方法：在 2.4G 模式下，同时长按（左键+滚轮中键+右键）5 秒，鼠标指示灯快闪（绿灯），则进入配对模式，再插入 2.4G 接收器，配对成功，鼠标指示灯熄灭。

（出厂已默认配对 2.4G 接收器）

Thank you very much for purchasing our AJAZZ AJ179PRO dual mode gaming mouse. We hope it will bring you a new operating experience. To get more enhanced settings and functions, you can download the driver software from the official website.

1.Product Specification

Product brand: AJAZZ

Product model: AJ139 PRO

Transmission method: USB wired + 2.4G wireless

Interface type: Type-C interface

Product size: 125.4x63.3x38.2mm

Product weight: ≈59g

Shell material: ABS injection molding

Number of buttons: 6 buttons + 1 switch

Wire length: 1.5M

DPI adjustment: 400-3200 (six-speed DPI driver adjustable)

(The driver software can adjust the minimum DPI to 50 and the maximum DPI to 26000. The driver DPI can be adjusted in steps of 50 DPI.)

Sensor: PAW3395

Button life: 10000W times

Battery capacity: 300mAh

Return rate: Wired USB: 1000Hz / 2.4G: 1000Hz

Driver software adjustable rate of return:

①.Wired rate of return: 125Hz/250Hz/500Hz/1000Hz

②.2.4G rate of return: 125Hz/250Hz/500Hz/1000Hz

Supported systems: Windows Vista/XP/7/8/10/11, Mac

2. Function description



①. **Left click**

②. **Right click**

③. **Middle button (wheel button)**

④. **Forward key**

⑤. **Back key**

⑥. **DPI/PR switch key**

1). DPI switch key

a. Six-level DPI key: Default DPI: 800 (green).. (The DPI value can be customized and adjusted in the driver software)

DPI indicator: 400 (red) / 800 (green) / 1200 (blue) / 1600 (cyan) / 2400 (yellow) / 3200 (purple)

b. DPI lighting effect: Switch DPI. The DPI indicator light flashes 3 times corresponding to the color

⑦. **Power switch**

a. ON position: turn it up to ON position, the power is turned on;

b. OFF position: turn it down to OFF position, the power is turned off.

(Note: In any mode, inserting the USB data cable is the wired mode and the mouse is charged.)

3. Indicator light/low power mode description

3.1. Mouse front indicator light

①. DPI indicator:

Corresponding to the color of the DPI gear

②. Low power indicator:

The indicator flashes (red light)

③. Charging indicator:

The indicator is always on (red light)

④. Pairing indicator: 2.4G mode pairing indicator (green light)

a. Pairing indicator flashes slowly (green light): enter 2.4G reconnection state

b. Pairing indicator flashes quickly (green light): enter 2.4G pairing state

Note: reconnection time 10s, pairing time 30s, timeout enters deep sleep

3.2. Low Power Mode

①. Low battery status: The mouse indicator light flashes (red light);

②. Charging status: The mouse indicator light is always on (red light);

③. Fully charged status: The mouse indicator light returns to normal lighting effect;

④. Battery voltage is below 3.4V: The mouse indicator light flashes at a frequency of 0.5hz (red light), prompting charging;

⑤. Battery voltage is below 3.2V-3.0V: The mouse automatically shuts down.

3.3. Sleep Mode

①. Power-saving sleep: After the mouse stops moving for 10 seconds, it enters power-saving sleep mode, and moving/pressing a button can wake up the mouse;

②. Deep sleep: After the mouse stops moving for 5 minutes, it enters deep sleep mode, and can only be woken up by pressing a button.

(Note: The deep sleep time can be customized in the driver software.)

4. Mode connection instructions

4.1. Wired mode:

Wired mode switching method: No matter in any mode, after plugging in the TYPE-C cable, it will automatically switch to wired mode and start charging the mouse.

4.2. 2.4G wireless mode:

①. 2.4G switching method: Flip the power switch at the bottom of the mouse upwards to switch to 2.4G mode.

②. 2.4G pairing method: In 2.4G mode, press and hold (left button + middle wheel button + right button) at the same time for 5 seconds. Mouse flashes quickly (green light), you will enter pairing mode, and then plug in the 2.4G receiver. If the pairing is successful, the mouse goes out.

(The 2.4G receiver is paired by default at the factory)

Terima kasih banyak telah membeli mouse gaming dual-mode AJAZZ AJ139 PRO kami. Kami berharap ini dapat memberi Anda pengalaman pengoperasian yang baru. Untuk mendapatkan pengaturan dan fungsi yang lebih ditingkatkan, Anda dapat mengunduh perangkat lunak driver dari situs resminya.

1. Parameter teknis

Merk Produk : AJAZZ

Model produk: AJ139 PRO

Metode transmisi: kabel USB + nirkabel 2.4G

Tipe antarmuka: antarmuka Tipe-C

Ukuran produk: 125.4x63.3x38.2mm

Berat produk: ≈59g

Bahan cangkang: cetakan injeksi ABS

Jumlah tombol: 6 tombol + 1 saklar

Panjang kawat: 1.5M

Penyesuaian DPI: 400-3200 (driver DPI enam kecepatan dapat disesuaikan)

(Perangkat lunak driver dapat disesuaikan hingga minimal 50 DPI dan maksimum 26000 DPI. DPI driver dapat disesuaikan secara bertahap sebesar 50 DPI)

Sensor: PAW3395

Kehidupan tombol: 10000W kali

Kapasitas baterai: 300mAh

Tingkat pengembalian (Default) : USB berkabel : 1000Hz / 2.4G: 1000Hz

Tingkat pengembalian perangkat lunak pengemudi yang dapat disesuaikan:

Tingkat pengembalian berkabel: 125Hz/250Hz/500Hz/1000Hz

Tingkat pengembalian 2.4G: 125Hz/250Hz/500Hz/1000Hz

Sistem yang didukung: Windows Vista/XP/7/8/10/11, Mac

2. Deskripsi fungsi



①. **Left Button**

②. **Right Button**

③. **Middle Button (Scroll Wheel Button)**

④. **Forward Button**

⑤. **Backward Button**

⑥. **DPI Switching Button**

a. Six-Speed DPI Button: Default DPI: 800 (Green). (Customizable DPI values in the driver software)

DPI Indicator Lights: 400 (Red) / 800 (Green) / 1200 (Blue) / 1600 (Cyan) / 2400 (Yellow) / 3200 (Purple).

b. Efek pencahayaan DPI: ganti DPI. Lampu indikator DPI berkedip 3 kali sesuai warna

⑦. **Mode Daya**

a. Posisi ON: Dorong ke atas ke posisi ON, yaitu power dihidupkan;

b. Posisi OFF: Turun ke posisi OFF, yaitu daya dimatikan.

(Catatan: Dalam mode apa pun, colokkan kabel data USB untuk masuk ke mode kabel dan isi daya mouse.)

3. Lampu indikator/deskripsi mode daya rendah

3.1. Lampu indikator depan mouse

①. Lampu indikator DPI:

sesuai dengan warna roda gigi DPI

②. Lampu indikator baterai lemah:

Lampu indikator berkedip (lampu merah)

③. Lampu indikator pengisian daya:

Lampu indikator selalu menyala (lampu merah)

④. Indikator pemasangan: indikator pemasangan mode 2.4G (lampu hijau)

a. Lampu indikator pemasangan berkedip perlahan (lampu hijau):

Memasuki status koneksi ulang 2.4G

b. Lampu indikator pemasangan berkedip cepat (lampu hijau):

Masuk ke status pemasangan 2.4G

Catatan: Waktu penyambungan kembali adalah 10 detik, waktu pemasangan adalah 30 detik, dan akan memasuki mode tidur nyenyak setelah batas waktu habis.

3.2. Mode daya rendah

①. Status baterai lemah: Lampu indikator mouse berkedip (lampu merah);

②. Status pengisian daya: Lampu indikator mouse selalu menyala (lampu merah);

③. Saat terisi penuh: lampu indikator mouse kembali ke efek cahaya normal;

④. Ketika tegangan baterai lebih rendah dari 3.4V: lampu indikator mouse berkedip pada frekuensi 0.5hz (lampu merah), meminta pengisian daya;

⑤. Ketika tegangan baterai lebih rendah dari 3.2V-3.0V: mouse mati secara otomatis.

3.3. Modus Tidur:

①. Tidur hemat daya: 10 detik setelah mouse berhenti bergerak, mouse memasuki kondisi tidur hemat daya. Memindahkan/menekan tombol dapat membangunkan mouse;

②. Tidur nyenyak: Setelah mouse berhenti bergerak selama 5 menit, mouse memasuki kondisi tidur nyenyak, dan mouse hanya dapat dibangunkan dengan menekan sebuah tombol.

(Catatan: Waktu tidur nyenyak dapat disesuaikan di perangkat lunak driver.)

4. Petunjuk koneksi mode

4.1. Mode berkabel:

Metode peralihan mode berkabel: Apa pun modenya, setelah mencolokkan kabel TYPE-C, maka secara otomatis akan beralih ke mode berkabel dan mulai mengisi daya mouse.

4.2. Mode nirkabel 2.4G:

①. Metode peralihan 2.4G: Putar sakelar daya di bagian bawah mouse ke atas untuk masuk ke mode 2.4G.

②. Metode pemasangan 2.4G: Dalam mode 2.4G, tekan dan tahan (tombol kiri + tombol roda tengah + tombol kanan) secara bersamaan selama 5 detik. Jika lampu indikator mouse berkedip cepat (lampu hijau), Anda akan masuk ke mode berpasangan, lalu menyambungkan penerima 2.4G. Jika pemasangan berhasil, lampu indikator mouse akan padam.(Penerima 2.4G dipasangkan secara default di pabrik)

合 格 证

AJAZZ · NACODEX

检验员：

2022

了解更多产品信息请关注

微信公众号请搜索：

“ AJAZZ黑爵外设 ”

抖 音号请搜索：

“ ajazzz2009 ”

产品质保 (Product Warranty)

感谢您对黑爵产品的信任与支持，为了让您放心使用本产品，更好地保障您的权益，我公司将严格遵守并执行相关规定，实行售后服务。

1. 服务有效期：自购买之日起质量保证12个月

2. 服务内容：按随型计算机商品维修更换差异性规定进行服务

3. 不属于服务范围：

a. 已经超出有效服务或免费维修期的；

b. 未按照正确使用说明使用、维护、保管导致故障或损坏的；

c. 非本司授权维修机构维修导致的故障或损坏；

d. 质保卡上无经销商资料及盖章之产品；

e. 缺自装西三包凭证内容的；

f. 由于不可抗力（如自然灾害等）原因造成产品之不良；

g. 人为因素导致产品不良（如操作失误、碰撞、输入不合适电压等）；

h. 其他非产品设计、技术、制造、质量等问题导致的故障或损坏。

质保卡 (Warranty Card)

产品型号：_____

购买日期：_____

客户姓名：_____

联系电话：_____

联系地址：_____

制造商：深圳市黑爵同创电子科技有限公司

地址：深圳市光明区凤凰街道东坑社区科能路中集智园大厦A座21楼

电话：86-0755-27407340

执行标准号：GB/T 26245-2010

★ 各凭证为黑爵产品售后服务的重要依据，请您妥善保管。

★ 任何产品问题，可扫码咨询微信公众号小编。

Warning Statement

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

-Reorient or relocate the receiving antenna.

-Increase the separation between the equipment and receiver.

-Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

-Consult the dealer or an experienced radio/TV technician for help.