

Contents



1.	Symbols	2
2.	Initial configuration	4
3.	HOME PAGE	11
4.	Automatic Feeder OVERVIEW	14
5.	Feeding Plan	16
	5.1 MANUAL Feeding	19
	5.2 SMART CONTROL	20
	5.3 Update Fill Level	24
6.	Settings Home	25
	6.1 Connect With Available Network	28
	6.2 E-Mail Adress for automatic feeder Messages	31
	6.3 Deactivating WLAN	32
	6.4 Activating WLAN	33
7.	Automatic feeder Settings	34
8.	Status LED indicator	38
9.	Reset	40
10.	Connecting with other device	41




1. Symbols


	Home page
	Settings
	Remove
	Change
	Save
	Add device
	Overview
	Feeding plan




	Smart Control
	Food quantity level
	Manual feeding
	Time
	Synchronisation food quantity
	Random
	Factory Defaults
	Attention




2. Initial Configuration




1		Select language
2		Select unit system
3		Change name of automatic feeder (optional)

4		Enter and save preferred name (optional).
5		Select next setting
6		Add a new aquarium to network


7		Change name (optional)
8		Select next setting. Continue with Step 12.
9		Connecting with an existing aquarium (optional).

10	 <p>CREATE A NEW AQUARIUM YOU HAVE NOT CREATED AN AQUARIUM YET?</p> <p>CONNECT TO AQUARIUM YOU HAVE ALREADY CREATED AN AQUARIUM?</p> <p>AVAILABLE DEVICES</p> <table border="1"> <tr> <td>Aquarium</td> <td>CC:FF:AD</td> </tr> <tr> <td>rk2</td> <td>93:05:85</td> </tr> <tr> <td>Network2</td> <td>60:AB:AB</td> </tr> </table>	Aquarium	CC:FF:AD	rk2	93:05:85	Network2	60:AB:AB	Selecting an aquarium from the list.		
Aquarium	CC:FF:AD									
rk2	93:05:85									
Network2	60:AB:AB									
11	 <p>CONNECT TO AQUARIUM YOU HAVE ALREADY CREATED AN AQUARIUM?</p> <p>AVAILABLE DEVICES</p> <table border="1"> <tr> <td>Aquarium</td> <td>CC:FF:AD</td> </tr> <tr> <td>CONNECT</td> <td></td> </tr> <tr> <td>Aquarium</td> <td>93:10:DA</td> </tr> <tr> <td>Network1</td> <td>AC:AB:9D</td> </tr> </table>	Aquarium	CC:FF:AD	CONNECT		Aquarium	93:10:DA	Network1	AC:AB:9D	Connecting the aquarium.
Aquarium	CC:FF:AD									
CONNECT										
Aquarium	93:10:DA									
Network1	AC:AB:9D									
12	 <p>Feeding plan</p> <p>Monday - Sunday</p> <p>0:00 PM 0 ROTATIONS</p> <p>- +</p> <p>Random fast day per week</p>	Feeding plan: Select first feeding point								

13		<p>Select feeding time</p>
14		<p>Select rotations per feeding time (max. 2x)</p>
15		<p>Resume the first feeding point.</p>


16	<p>Feeding plan</p>  <p>Random fast day per week</p>	<p>Select the next feeding point (max. 4 times)</p>
17	 <p>Random fast day per week</p>	<p>Switch ON/OFF the random fast day per week.</p>
18	 <p>Random fast day per week</p> <p>BACK SAVE</p>	<p>Save settings.</p>

19



Change network name and use password (optional). End initial configuration with SKIP


20



Initial configuration completed.
Overview automatic feeder.


3. Home Page

21








HOME PAGE
Overview of current settings.

22




Change name

23	 <p>Name of the aquarium My Aquarium 1</p> <p>Feeder_16662195 EHEIM autofeeder+ ></p> <p>Next feeding: Today at 0:00 pm</p>	Enter and save preferred name.
24	 <p>My Aquarium 1</p> <p>Feeder_16662195 EHEIM autofeeder+ ></p> <p>Next feeding: Today at 0:00 pm</p>	Add a new aquarium.
25	 <p>My Aquarium 1</p> <p>Feeder_16662195 EHEIM autofeeder+ ></p> <p>Next feeding: Today at 0:00 pm</p>	Remove aquarium.

26		Add device.
27		Change to view the automatic feeder overview.


4. Automatic Feeder Overview

28




Automatic feeder Overview:
Current feeding times and filling level of the feed container.

29







Change feeding plan.

30







Show the selection menu for OVERVIEW.

31		Update filling level.
32		After filling the feed container confirm with button.
33		Start manual feeding (1 turn per click)
34		Overview feeding plan.


35	 <p>Filling level</p>  <p>AUTOMATIC FEEDER FILLED</p> <p>MANUAL FEEDING</p> <p>Feeding schedule: Sunday - Feeding at 0:00 pm, Next feeding - Today at 0:00 pm, Tuesday - Feeding at 0:00 pm</p> <p>Filling level</p>  <p>AUTOMATIC FEEDER FILLED</p>	Smart synchronisation.
36	 <p>Feeder_16662195</p> <p>Monday - Feeding at 0:00 pm</p> <p>Next feeding - Today at 0:00 pm</p> <p>Tuesday - Feeding at 0:00 pm</p> <p>Filling level</p>  <p>AUTOMATIC FEEDER FILLED</p>	Go back to home page.

5. Feeding Plan

37	 <p>HOME SETTINGS</p> <p>My Aquarium 1</p> <p>Feeder_16662195 EHEIM autofeeder+</p> <p>Next feeding - Today at 0:00 pm</p> <p>+</p>	HOME PAGE Select the automatic feeder overview.
----	--	--


38		Select feeding plan.
39		Select feeding point
40		Select feeding time (max. 4 times)

41




Select rotations per feeding time (max. 2x)

42




Resume the feeding point.

43




Select the next feeding point.

44



Switch ON/OFF the random fast day per week.


45



Save settings.

5.1 MANUAL Feeding

46




HOME PAGE Select the automatic feeder overview.

47



Start manual feeding (1 turn per click)


48




Feeding container turns for one time.



5.2 Smart Synchronisation


49




HOME PAGE
Select the automatic feeder overview.

50		Select Smart synchronisation.
51		Search for other devices.
52		Select your device.

53	 <p>Pair device</p> <p>Available Networks</p> <p>EHEIM Filter_9684357 93:CS:85</p> <p>BACK</p>	Select the network.
54	 <p>Pair device</p> <p>Filter XXXXXX 83:CS:85</p> <p>IDENTIFY PAIR</p> <p>BACK</p>	Pair with device.
55	 <p>Pair device</p> <p>The device now connects to the platform. Please be patient for a moment.</p>	The device is connected.

56	<p>Control your device using another EHEIMdigital or Topfin PRO® device</p> <p>Device is paired with</p> <p> Proxima175 Filter </p> <p>Regulation of filter flow during feeding</p> <p>min  No change max</p> <p> SAVE </p>	Regulation of the filter flow during feeding.
57	<p>Device is paired with</p> <p> Proxima175 Filter </p> <p>Regulation of filter flow during feeding</p> <p>min  No change max</p> <p> SAVE </p>	Save settings.
58	 <p>Feeder_16662195</p> <p>Sunday - Feeding at 0:00 pm Next feeding - Today at 0:00 pm Tuesday - Feeding at 0:00 pm</p> <p>Filling level  AUTOMATIC FEEDER FILLED</p>	Go back to home page.


59



Devices are connected to each other.

5.3 Update Fill Level

60




HOME PAGE
Select the automatic feeder overview.

61



Start update fill level.


62






Filling level is updated.


6. Settings Home



63



Select settings.




64	 <p>Settings</p> <p>NETWORK SETTINGS</p> <ul style="list-style-type: none"> <input type="radio"/> Deutsch <input checked="" type="radio"/> English <input type="radio"/> Français <input type="radio"/> Español <input type="radio"/> Čeština <input type="radio"/> Italiano 	<p>Call up network setting. Continue with 6.1.</p>
65	 <p>Settings</p> <p>NETWORK SETTINGS</p> <ul style="list-style-type: none"> <input type="radio"/> Deutsch <input checked="" type="radio"/> English <input checked="" type="radio"/> Français <input type="radio"/> Español <input type="radio"/> Čeština <input type="radio"/> Italiano 	<p>Select/change language.</p>
66	 <p>E-mail address for notifications</p> <p><input type="text"/> your@email.de</p> <p>Metric system <input type="radio"/></p> <p>US customary system <input checked="" type="radio"/></p> <p>USE CURRENT TIME</p>	<p>Enter the e-mail address and user name to receive messages from the automatic feeder. Continue with 6.2.</p>






67		The current time is set.
68		Manual setting of date and time
69		Activate/deactivate automatic change between summer and winter time
70		Display network information and switching off the WiFi function

71		Reset to factory settings.
72		Carry out manual update.

6.1 Connect With Available Network

73		Search for available networks.
----	---	--------------------------------


74	 <p>Settings</p> <p>Network</p> <p>Available Networks</p> <p>Network Router</p>	<p>Connect available network.</p>
75	 <p>Settings</p> <p>Network</p> <p>Available Networks</p> <p>Network Router</p> <p>Password:</p> <p>CONNECT</p> <p>DHCP</p>	<p>Enter password for the selected network.</p>
76	 <p>Available Networks</p> <p>Network Router</p> <p>Password:</p> <p>CONNECT</p> <p><input checked="" type="checkbox"/> DHCP</p>	<p>Select CONNECT to connect to the network.</p>

77	 <p>SSID - Networkname* Feeder_XXXXXXX</p> <p><input checked="" type="checkbox"/> Use password</p> <p> SAVE</p>	<p>Change Feeder XXXXXXXX network name to your own name.</p>
78	 <p>SSID - Networkname* Feeder_XXXXXXX</p> <p>Password* ##1Y2z3#</p> <p><small>Password must be at least 8 characters long.</small></p> <p><input checked="" type="checkbox"/> Use password</p> <p> SAVE</p>	<p>Activate password usage and use a password with a minimum of 8 characters.</p>
79	 <p>SSID - Networkname* Feeder_XXXXXXX</p> <p>Password* ##1Y2z3#</p> <p><small>Password must be at least 8 characters long.</small></p> <p><input checked="" type="checkbox"/> Use password</p> <p> SAVE</p> <p> SET</p>	<p>Save network settings.</p>
80	 <p>SSID - Networkname* Feeder_XXXXXXX</p> <p>Password* ##1Y2z3#</p> <p><small>Password must be at least 8 characters long.</small></p> <p><input checked="" type="checkbox"/> Use password</p> <p> SAVE</p> <p> SETTINGS</p>	<p>Go back to settings.</p>

6.2 E-Mail Adress for automatic feeder Messages

81	 <p>E-mail address for notifications</p> <p>✉ your@email.de</p> <p>USE CURRENT TIME</p> <p>⌚ 17:12:51</p> <p>26.03.2020</p>	<p>Enter the e-mail address and user name to receive messages from the automatic feeder. Only possible in networks with Internet connection.</p>
82	<p>E-mail address for notifications</p> <p>Email</p> <p>✉ <input type="text" value="your@email.de"/> </p> <p>Name <input type="text"/></p> <p>The email address will only be used to send notifications to the device. Please confirm that you have read and accept our privacy policy. <input type="checkbox"/> I AGREE DSGVO</p> 	<p>Read and confirm the privacy policy.</p>
83	<p>E-mail address for notifications</p> <p>Email</p> <p>✉ <input type="text" value="your@email.de"/> </p> <p>Name <input type="text"/></p> <p>The email address will only be used to send notifications to the device. Please confirm that you have read and accept our privacy policy. <input checked="" type="checkbox"/> I AGREE DSGVO</p> 	<p>Save the data.</p>


6.3 Deactivating WLAN

84	 <p>09:37:31 27.03.2020</p> <p>Automatic Update of Summertime and Wintertime</p> <p>SHOW NETWORK INFORMATION</p> <p>RESET DEFAULTS</p>	Select “Show Network Information”.
85	<p>Network Status X</p> <p>SSID - Networkname Feeder_16662195</p> <p>IP Address: 192.168.1.1</p> <p>Subnet Mask: 255.255.255.0</p> <p>Default Gateway: 192.168.1.1</p> <p>TURN OFF WiFi FEATURE? ❯</p>	Select “Turn off WiFi Feature”.



86		<p>Select “Deactivate WiFi” to disable the WiFi function.</p>
87		<p>Select “Deactivate WiFi” to disable the WiFi function. The status LED light on the automatic feeder flashes continuously yellow after approx. 3 - 5 seconds. WiFi function deactivated. Device settings remain available.</p>




6.4 Activating WLAN




88		<p>Touch the drive unit behind the status LED</p>
89		<p>After approx. 3 – 5 seconds the status LED lights up green.</p>




90		<p>The status LED flashes white. Network is being created. This process may take a few seconds</p>
91		<p>If the status LED lights blue, a network has been created and is visible on a WLAN-enabled device (smart phone, tablet, etc.).</p>


7. Automatic Feeder Settings

92		<p>Change to the automatic feeder overview.</p>
93		<p>Show the selection menu for OVERVIEW, FEEDING PLAN, SMART SYNCHRONISATION and SETTINGS.</p>


94		Select settings
95		Enter and save preferred name (see items 3 & 4).
96		Select automatic feeder expert settings.
97		Open automatic feeder expert settings.


98	 <p>Settings</p> <p>Automatic feeder</p> <p>Feeder_16662195</p> <p>EXPERT SETTINGS</p> <p>Protection for overfeeding</p> <p>TARA - SCA</p> <p>Version Website: 049.9 Version Server: 062.6</p>	<p>Protection for overfeeding is activated. Manual feeding by touching the drive unit is limited to max. 3 turns per day.</p>
99	 <p>Settings</p> <p>Automatic feeder</p> <p>Feeder_16662195</p> <p>EXPERT SETTINGS</p> <p>Protection for overfeeding</p> <p>TARA - SCALE</p> <p>Version Website: 049.9 Version Server: 062.6</p>	
100	 <p>Settings</p> <p>Automatic feeder</p> <p>Feeder_16662195</p> <p>EXPERT SETTINGS</p> <p>Protection for overfeeding</p> <p>TARA - SCALE</p> <p>Version Website: 049.9 Version Server: 062.6</p>	<p>Taring the scale.</p>

101	 <p>To tear the scale, pull the feed drum off the appliance.</p> <p>CANCEL OKAY</p> <p>Version Website: 049.9 Version: 062.6</p>	<p>Before taring the scala, pull the feed container from the drive unit and then click OKAY.</p>
102	 <p>SHOW NETWORK INFORMATION</p> <p>My Aquarium1</p> <p>INITIAL SETUP</p> <p>FACTORY DEFAULTS</p>	<p>Change name.</p>
103	 <p>SHOW NETWORK INFORMATION</p> <p>My Aquarium1</p> <p>INITIAL SETUP</p> <p>FACTORY DEFAULTS</p>	<p>Initial configuration reset.</p>

104	 <p>SHOW NETWORK INFORMATION</p> <p>My Aquarium1</p> <p>INITIAL SETUP</p> <p>FACTORY DEFAULTS</p>	Reset to factory settings.
-----	---	----------------------------

8. Status LED indicator

105		LED flashes white: Device control unit is starting.
106		LED lights permanently blue: Device is ready for operation (MASTER) and can be connected to WLAN-capable device (smart phone, tablet, etc.).
107		LED lights permanently green: The device is ready for operation and is connected to a MASTER device.
108		LED flashes yellow: Firmware update in progress

109		LED flashes green/yellow: Control unit waits until all connected control units are updated.
110		LED lights permanently red: Website is missing and must be called up again via http://192.168.1.1/update .
111		LED flashes red/green/blue: Resetting the network settings or resetting to factory settings.
112		LED lights alternating white/red/white: Connection to home network or to MASTER network failed (network name wrong, password wrong, poor WLAN reception).
113		LED lights alternating green/red/white: Master network or home network is no longer accessible. Control unit is restarting
114		LED flashes pink: Detection mode is activated.


115		LED lights yellow: WLAN function is deactivated. Reactivation (see items 77 - 79).
-----	--	---

9. Reset

116		Touch the drive unit behind the status LED for approx. 5 – 8 seconds.
117		LED flashes red/green/blue. Device is reset.
118		LED flashes white: Device control unit restarting.
119		LED lights permanently blue: Device is ready for operation again.


10. Connecting with device

120




Add device.

121





Select your device.


122



Select the network

123	 <p>Filter XXXXXXXX</p> <p>IDENTIFY</p> <p>ADD </p> <p>BACK</p>	<p>The selected device can be identified using DETECT. LED flashes pink.</p>
124	 <p>Filter XXXXXXXX</p> <p>IDENTIFY</p> <p>ADD </p> <p>BACK</p>	<p>The device can be added to the selected network using ADD. LED flashes white.</p>
125	 <p><input checked="" type="checkbox"/> New device was added </p> <p> EHEIM Filter XXXXXXXX</p> <p>External filter</p> <p>Please select an aquarium for this device.</p> <p>My Aquarium1</p> <p>SAVE </p>	<p>If the LED lights permanently green, complete the process with SAVE.</p>

126



Devices are connected to each other.