

Two-button remote control switch operating instructions

The intelligent two-button remote control switch is a low-power remote control switch, that supports dimming and multi-scene switching functions. A single remote control switch can support the binding of 12 lights at the same time, easy to use, and easy to operate, to meet the needs of your rich personalized lighting wireless control scenes, to your smart home life to bring "wireless" enjoyment.

Technical parameters:

Power supply voltage:DC3V(2pcs #7 battery)
Wireless Zigbee output power:+12dBm
Wireless BLE output power:+6dBm
Network protocol standard: ZigBee3.0, BLE5.1
Support the number of bound lights:12
Operating temperature range:-25~+70° C
Overall Dimension:115mm*70mm*14mm

Button Description:

S1: on/off button, short press to switch function, long press is brightness+.
S2: Scene button, short press to switch the lighting scene, long press is brightness -.
SW1 button (in the battery compartment): reset button, long press 5S remote control switch can enter zigbee find network

Operating Instructions :

Match with ZigBee gateway using method

Remote switch matching gateway: while the gateway is triggered to allow access to the network, long press the SW1 button (inside the battery compartment) for 5S, and the indicator light flashes quickly to represent that the device is looking for the network, the indicator light goes out and the gateway indicator light flashes three times quickly, the device pairing is successful, and the device can be viewed in the APP device list at the same time.

Match the light device with the remote control switch: add the light device into the gateway as well, and then assign the light and the remote control switch to the same room (grouping) through APP, note that when saving the room (grouping) settings, you need to keep pressing the S2 button (dimmer button) of the remote control switch until the saving is completed and then release it, otherwise the room (grouping) settings will be invalidated, and after the grouping is completed, the remote control switch will be able to control all the lights in the room (group).

FCC Warning Statement

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and
(2) this device must accept any interference received, including interference that may cause undesired operation.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.