



SPECIFICATION

INPUT: 5V/3A 9V/3A
Wireless charging output power: 5W 7.5W 10W 15W (MAX)
Charging efficiency: 75%
Wireless charging transmission distance: ≤ 5-8mm
Power adapter: QC3.0, PD 9V/3A
Speaker power: 5W
Battery capacity: 12000mAh

1. Power supply:

- 1.1 Insert the USB end of the charging cable into the power adapter, plug the Type-C port into this product, and the red power indicator light will turn on.
- 1.2 The product enters normal working mode, and the display screen lights up completely before entering standby mode. It defaults to 06:00 and automatically synchronizes the phone time after connecting to Bluetooth.

2. Wireless charging part:

- **2.1 Output power:**
 - 5W 7.5W 10W 15W (MAX)
- **2.2 Indicator light display mode:**
 - Connect the power, enter standby mode, and turn on the red light; Charging: The blue light stays on for a long time; Full: Do not turn the light; FOD: The blue light is flashing.
- **3. Clock, year, and date settings:**
 - **3.1 Button Function:**
 - 3 buttons (in left to right order: Previous/- button, Power button, Next/+button).
 - **3.2 Clock mode on/off function:**
 - Press and hold the "+" button for more than 3 seconds to turn on the clock in shutdown state. After turning on, enter the clock mode and the display screen will light up. Turn off alarm clock: press and hold the power button for 3 seconds to turn on the Bluetooth speaker, then press and hold for another 3 seconds to turn it off.

3.3 Time setting:

- In clock mode short press the power button to enter the time/alarm/date setting, cycle, automatically exit and save if there is no operation within 10 seconds. (Time setting cannot be done when the Bluetooth speaker is turned on. After connecting the phone, the phone time and date will be automatically synchronized)

• (1) Time setting:

- **Press the power button to enter:**
 - Year (default 2021) → date (month day, default 01, 01) → select 12H/24H system → time (hour, minute) → alarm 1 (hour → minute → ON/OFF) → alarm 2 (hour → minute → ON/OFF), in a loop. Press the power button to next, and the position that can be set will flash.
 - Press the +/− keys to add or subtract the hour value. After the alarm is turned on, the alarm indicator light in the lower left corner of the display screen will light up. If there is no operation within 10 seconds, it will automatically exit and save;

• (2) Alarm clock sound:

- Sound (double "dee" sound, once per second) for 5 minutes; Automatically close after sounding;
- (3) When the alarm goes off, short press any key to pause the alarm, enter SNOOZE (pause after 10 minutes), long press the power button to turn off the alarm;
- (4) When the alarm clock rings, the alarm indicator light in the lower left corner of the display screen also flashes at the same time: it turns on and off once every second;

3.4 Display mode selection:

- Press the +key to select dp1/dp2. DP1 mode (time display for 28 seconds, year, month, and day

display for 2 seconds, DP2 mode (only displays time).

• 3.5 Power saving mode selection:

- Short press the "-" key in clock mode to turn on and off the power saving mode (SP1/SP2). After turning on the power saving mode, there will be no operation within 10 seconds before entering the power saving mode. To wake up, simply tap the machine or desktop. The power saving mode is only effective in clock mode and is turned off by default in audio mode.

• 4. Bluetooth speaker

- 4.1 Press and hold the power button to turn on and off the Bluetooth speaker function. After turning on, there will be a prompt sound. After turning on, it will enter the waiting to connect state. At this time, you can turn on Bluetooth on your phone to search and connect. The Bluetooth name is "THROWBACK". After connecting, there will be a prompt sound indicating successful connection.
- 4.2 After connecting the Bluetooth speaker, short press the power button to play/pause, short press the - button to decrease the volume, and long press the - button to previous song, short press the + button to increase the volume, and long press the + button to next song
- 4.3 Long press the power button can be used for overall shutdown, and all functions will enter the shutdown state. If the alarm is turned on, it will also sound normally after shutdown
- 4.4 Bluetooth connection is valid for 10 meters. If there is no Bluetooth connection for 10 minutes, the device will shut down and only keep the clock mode to continue working



FCC ID: 2BBPLHGTBRETS3

THROWBACK® COPYRIGHT ALL RIGHTS RESERVED. THROWBACK is an innovative brand of Truststone Group LLC. No portion of this design may be reproduced without express written permission. Other trademarks and trade names are those of their respective owners. All rights reserved. Distributed by Truststone Group LLC, New York NY 10018.

⚠ WARNING: Cancer risk from Lead Exposure - www.P65Warnings.ca.gov
MADE IN CHINA

The device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

The BLUETOOTH® trademark and logo are registered trademarks owned by the Bluetooth SIG, Inc. All product name, logos, and brands are property of their respective owners.

FCC Warning Statement

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

-- Reorient or relocate the receiving antenna.

-- Increase the separation between the equipment and receiver.

-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

-- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and

(2) this device must accept any interference received, including interference that may cause undesired operation.

RF Exposure Statement (Bluetooth)

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

RF Exposure Statement (Wireless charger)

To maintain compliance with FCC's RF Exposure guidelines, This equipment should be installed and operated with minimum distance of 20cm the radiator your body.