# KOORUI

## WIRELESS KEYBOARD

**BKM01**
**BKM01-1**

USER MANUAL

EN | DE



## PACKING LIST

EN

1. Keyboard x1
2. USB Receiver x 1 (Stored in battery compartment)
3. User Manual x1
4. Mouse x1

**1 Product Overview**

**1 Product Overview**

| | | | |
|---|---|---|---|
| 1 DPI | 5 Right Button | 8 2.4G Indicator | 11 Power Switch |
| 2 Power Indicator | 6 Forward Button | 9 BT1 | 12 2.4G Receiver |
| 3 Scroll Wheel | 7 Backward Button | 10 BT2 | |
| 4 Left Button | | 11 Mode Switch | |



## Mouse Connection Guide

### Mouse Connected with 2.4G Mode

**Step 1:**Please fully charge the mouse first.

**Step 2:**Take out the receiver from the base and insert it into the PC USB interface.

**Step 3:**Turn on the switch on the back of the mouse, located on the USB interface.12th mark in the mouse image.

**Step 4:**Switch the connection mode on the back of the mouse to 2.4G mode, and briefly press the 11th indicator switch in the mouse image to switch the indicator light to the eighth position in the diagram.






### Mouse Connected with BT(Bluetooth) Mode

**Step 1:**Please fully charge the mouse first.

**Step 2:**Turn on the switch on the back of the mouse, located on the 12th mark in the mouse image.

**Step 3:**Short press the mode button to change it to BT mode. 11th marker in mouse image.

**Step 4:**Hold and press the mode keys for 3 seconds,11th marker in mouse image.

**Step 5:**The indicator light will flash white, indicating that the device is in Bluetooth pairing mode.

**Step 6:**Open the Bluetooth mode on your computer or other device, search for the device and find a device named "**BKM01-MS**", click Connect.

**Step 7:**Connection is completed after the BT indicator is always on. When the white indicator light on the 9th or 10th position on the back of the mouse remains on, it indicates that the mouse has successfully connected to your device.

## Mouse Features

1. Multiple Modes to Switch: There are 3 modes as BT1, BT2 and 2.4G, which can separately connect to 3 devices. You can switch the mode via the bottom mode switch button.



2. The mouse is equipped with 5 DPI (800/1200/1600/2000/2400). You can switch them cyclically by pressing DPI button.
3. Power Saving Mode: The mouse will automatically enter sleep mode if it's unused for 10 min, and it can be woken up by moving.
4. Built-in 500 mA lithium battery.The service life is 2 months.
5. Rechargeable Mouse: charge with the included charging cable. The indicator light will flash quickly when in low battery, stay steady when charging and turn off when fully charged.

**Note:**
**Forward and backward buttons are not available on Mac OS devices.**



## Keyboard Connection Guide

### Keyboard Connected with 2.4G Mode

**Step 1:**Please fully charge the keyboard first.

**Step 2:**Take out the receiver from the keyboard base and insert it into the PC USB interface.

**Step 3:**Turn on the keyboard switch in the upper right corner of the keyboard.

**Step 4:**Press and hold the 2.4G button located below the on/off button for 3 seconds, and the keyboard will switch to 2.4G connection mode.






### Keyboard Connected with BT(Bluetooth) Mode

**Step 1:**Please fully charge the mouse first.

**Step 2:** Short press the "BT1" or "BT2" button to change the connection mode to Bluetooth mode, with the button l ocated in the upper right corner of the keyboard.

**Step 3:**Hold and press the "BT1" or "BT2" button for 3 seconds, The indicator light will flash white, indicating that the device is in Bluetooth pairing mode.

**Step 4:**Open the Bluetooth mode on your computer or other device, search for the device and find a device named "**BKM01-KB**", click Connect.

**Step 5:**When the indicator light remains white, it indicates that the device has successfully connected. Please rest assured to use it.






## DIAGRAM

1. **Multi-mode Switch**: The product supports 2.4G, BT1 and BT2 connection. It can be connected with and control 3 devices. User can switch modes via the corresponding mode switch button to control the corresponding device.

a. Press the 2.4G mode button [illegible], the 2.4G mode indicator light on the top right turns on, indicating that the keyboard is 2.4G control mode at this time.

b. Press the BT1 mode button [illegible], the BT1 mode indicator light on the top right turns on, indicating that the keyboard is switched to BT1 control mode.

C. Press the BT1 mode button [illegible], the BT1 mode indicator light on the top right turns on, indicating that the keyboard is switched to BT1 control mode.

2. **Key combination function:**

| | | | |
|---|---|---|---|
| FN + F1 | Mute | FN + F2 | Volume Down |
| FN + F3 | Volume Up | FN + F4 | Previous Track |
| FN + F5 | Play/Pause | FN + F6 | Next Track |
| FN + F7 | Brightness Decrease | FN + F8 | Brightness Increase |
| FN + F9 | Select All | FN + F10 | Copy |
| FN + F11 | Paste | FN + F12 | Cut |



[illegible] Search function

FN + [illegible]

Lock F1-F12 function, after locking, press F1-F12 directly for the combination key function.

Press FN + [illegible] again
Unlock F1-F12 function, restore F1-F12 to normal function.

### Solution to Keyboard's 2.4G mode connection issue

1. Turn the keyboard switch off and then turn it back on and switch the keyboard to 2.4G mode.
2. Press the " ESC" + " +" button and release until the indicator of 2.4G mode flashes.
3. Plug the receiver into the computer. It is successfully connected when the indicator of 2.4G mode stops flashing. It can work then.

### Solution to keyboard's BT1 ( Bluetooth) mode connection issue

1. Clear the Bluetooth connection list of computer.
2. Turn on the power switch and switch it to BT1 mode.
3. Long press the button of BT1 mode for over 5s and release until its indicator light flashes.
4. Turn on the Bluetooth of computer. If your computer system is Win 7 or earlier, please select to connect "BKM01-KB". If your computer system is Win 8 or later, please select to connect "BKM01-KB". The keyboard's BT1 mode can work after successful connection.

   **BT2( Bluetooth) Mode: refer to BT1 mode solutions.**

### The keyboard response is delayed and works abnormally, how to solve it?

1. May be the dry battery power is insufficient, please replace the battery for the keyboard.
2. May be caused by computer lag, please restart the computer and try it again.
3. The maximum use distance of this product is 10M, please keep it within 10M, and do not have metal obstacles between the keyboard and receiver.



## PACKLISTE

DE

1. Tastatur x1
2. USB-Empfänger x 1 (im Batteriefach)
3. Manuell x1
4. Maus x1

**1 Klappseiten**



**1 Klappseiten**



| | | | |
|---|---|---|---|
| 1 DPI | 5 Der richtige knopf | 8 Indikator 2.4-g | 11 Der kaltschalter |
| 2 Anzeige gegen strom | 6 Hopp knopf | 9 BT1 | 12 Empfänger vom 2.4-g |
| 3 Rollende räder | 7 Knopf zurück | 10 BT2 | |
| 4 (mann) linker knopf | | 11 Strukturiert Schalter | |



## Maus-Verbindungsleitfaden

### Maus mit 2.4G Modus verbinden

**Schritt 1:**Bitte laden Sie die Maus zuerst vollständig auf.

**Schritt 2:**Nehmen Sie den Empfänger aus der Basis und stecken Sie ihn in die USB-Schnittstelle des PCs ein.

**Schritt 3:**Schalten Sie den Schalter auf der . Rückseite der Maus ein, der sich auf der zwölften Markierung im Mausbild befindet.

**Schritt 4:**Schritt 4:Schalten Sie den Verbindungsmodus auf der Rückseite der Maus in der 2.4G-Modus und drücken Sie kurz den elften Anzeigeschalter im Mausbild, um die Anzeigeleuchte auf die achte Position im Diagramm zu schalten.

### Maus mit BT (Bluetooth) Modus verbunden

**Schritt 1:**Bitte laden Sie die Maus zuerst vollständig auf.

**Schritt 2:**Schalten Sie den Schalter auf der Rückseite der Maus ein, der sich auf der zwölften Markierung im Mausbild befindet.

**Schritt 3:**Drücken Sie kurz die Mode-Taste, um sie in den BT-Modus zu wechseln. elfte Markierung im Mausbild.

**Schritt 4:**Halten und drücken Sie die Modustasten für drei Sekunden, elfte Markierung im Mausbild.Schritt 5: Die Kontrollleuchte blinkt weiß und zeigt an, dass sich das Gerät im Bluetooth -Kopplungsmodus befindet.

**Schritt 5:**Die Kontrollleuchte blinkt weiß und zeigt an, dass sich das Gerät im Bluetooth-Kopplungsmodus befindet.

**Schritt 6:**Öffnen Sie den Bluetooth-Modus auf Ihrem Computer oder einem anderen Gerät, suchen Sie nach dem Gerät und finden Sie ein Gerät namens "**BKM01-MS**", klicken Sie auf Verbinden.

**Schritt 7:**Die Verbindung wird abgeschlossen, nachdem die BT-Anzeige immer eingeschaltetist.Wenn die weiße Kontrollleuchte an der neunten oder zehnten Position auf der Rückseite der Maus eingeschaltet bleibt, zeigt sie an, dass die Maus erfolgreich mit ihrem Gerät verbunden wurde.

## Die funktion der maus

1. Verschiedene formate wechseln: lesezeichen, imperative, modus 3 "Das sind 2,4 G, die alle drei geräte separat verbinden." Ihr könnt wechseln Der modus drückt auf den unteren modus.

2. Die maus ist mit 5DPI ausgestattet (800/1200/1600/ 2000/ 2400). Sie können sie durchlaufen lassen, indem sie den knopf DPI drücken.
3. Elektrische anziehung: die maus hat automatisch einen ruhezustand erreicht Das alte wohnmobil liegt seit zehn minuten da draußen Ich will fahren.
4. Es hat 500 milliliithium-batterie eingebaut. Die lebensdauer beträgt zwei monate.
5. Ladebare maus: man benutzt den begleitfaden zum aufladen. Die zündflamme flackert bei unzureichender leistung. Halten sie es an laden stabil, stromausfall ausfall.

**"Nichts für schwache nerven!"**
**Macos OS geräte unterstützen keine außen - und rückseite.**



## Verbindungsanleitung für Tastatur

### Tastatur mit 2.4G Modus verbunden

**Schritt 1:**Bitte laden Sie zuerst die Tastatur vollständig auf.

**Schritt 2:**Nehmen Sie den Empfänger aus der Mausbasis und stecken Sie ihn in die USB-Schnittstelle des PCs ein.

**Schritt 3:**Schalten Sie den Keyboard-Schalter in der oberen rechten Ecke der Tastatur ein.

**Schritt 4:**Halten Sie die 2.4G-Taste unterhalb der Ein-/Aus-Taste für drei Sekunden gedrückt, und die Tastatur wechselt in den 2.4G-Verbindungsmodus.

### Tastatur mit BT (Bluetooth) Modus verbunden

**Schritt 1:**Bitte laden Sie die Maus zuerst vollständig auf.

**Schritt 2:**Drücken Sie kurz die Taste "BT1" oder "BT2", um den Verbindungsmodus in den Bluetooth-Modus zu ändern, wobei sich die Taste in der oberen rechten Ecke der Tastatur befindet.

**Schritt 3:**Halten Sie die Taste "BT1" oder "BT2" für drei Sekunden gedrückt und drücken Sie sie. Die Kontrollleuchte blinkt weiß und zeigt an, dass sich das Gerät im Bluetooth -Kopplungsmodus befindet.

**Schritt 4:**Öffnen Sie den Bluetooth-Modus auf ihrem Computer oder einem anderen Gerät, suchen Sie nach dem Gerät und finden Sie ein Gerät namens "**BKM01-KB**",klicken Sie auf Verbinden.

**Schritt 5:**Wenn die Kontrollleuchte weiß bleibt, zeigt sie an, dass das Gerät erfolgreich angeschlossen wurde. Bitte seien Sie versichert, es zu verwenden.






## FUNKTIONSDIAGRAMM

1. **Multi-Mode-Umschaltung**: Dieses Produkt verfügt über drei Verbindungsmodi: 2.4G, BT1, BT2, die 3 Geräte verbinden und steuern können. Benutzer können den Modus über die entsprechende Modustaste umschalten, um das entsprechende Gerät zu steuern.

a. Drücken Sie die 2.4G-Modustaste [illegible], die 2.4G Modustaste oben rechts zeigt an, dass sich die Tastatur zu diesem Zeitpunkt im 2.4-G-Steuerungsmodus befindet.

b. Drücken Sie die BT1-Modustaste [illegible], der obere rechte BT1-Modustaste zeigt an, dass die Tastatur zu diesem Zeitpunkt in den BT1-Steuermodus geschaltet ist.

C. Drücken Sie die BT2-Modustaste [illegible], der obere rechte BT2-Modustaste zeigt an, dass die Tastatur zu diesem Zeitpunkt in den BT2-Steuermodus geschaltet ist.

2. **Tastenkombinationsfunktion:**

| | | | |
|---|---|---|---|
| FN + F1 | Stumm | FN + F2 | Lautstärke - |
| FN + F3 | Lautstärke + | FN + F4 | Vorheriges Lied |
| FN + F5 | Wiedergabe/ Pause | FN + F6 | Nächstes Lied |
| FN + F7 | Helligkeit ttsabnahme | FN + F8 | Helligkeit plus |
| FN + F9 | alles wählen | FN + F10 | Kopieren |
| FN + F11 | Einfügen | FN + F12 | Ausschneiden |



[illegible] Suche

FN + [illegible]

F1-F12-Funktion sperren, nach dem Sperren F1-F12 ist die Tastenkombinationsfunktion

Drücken Sie FN + [illegible] erneut
entsperren Sie die Funktion F1-F12, stellen Sie die normale Funktion von F1-F12 wieder her.



### Lösung für abnormale Verbindung im 2.4G-Modus

1. Schalten Sie den Schalter der Tastatur aus und wieder ein und wechseln Sie die Tastatur in den 2.4-G-Modus.
2. Drücken Sie gleichzeitig die Tasten "ESC" + "+" und lassen Sie sie los, nachdem die 2.4G-Modustaste blinkt.
3. Stecken Sie den Empfänger in den Computer. die 2.4G-Modus-LED hört auf zu blinken, die Kopplung ist erfolgreich und kann normal verwendet werden.

### Lösung für abnormale Verbindung im BT1 (Bluetooth)-Modus

1. Löschen Sie die Bluetooth-Verbindungsliste des Computers
2. Schalten Sie den Netzschalter ein und wechseln Sie die Tastatur in den BT1-Modus
3. Drücken Sie die BT1-Modustaste länger als 3 Sekunden und lassen Sie die BT1-Modusleuchte nach dem Blinken los
4. Schalten Sie das Bluetooth des Laptops ein. Wenn Ihr Computersystem unter win7 ist. wählen Sie bitte " BKM01-KB" zu verbinden, wenn das System über winb und iOS, MacOS-System, wählen Sie bitte "BKM01-KB" . nach erfolgreicher Verbindung ist es einsatzbereit.
   **Lösung für abnormale Verbindung im BT1 (Bluetooth)-Modus Siehe BT1-Lösung**

### Die Tastaturantwort ist verzögert und funktioniert nicht normal, wie kann man das lösen?

1. Die Trockenbatterie ist möglicherweise schwach, bitte ersetzen Sie die Batterie für die Tastatur.
2. Dies kann durch das Einfrieren des Computers verursacht werden. Bitte starten Sie den Computer neu und versuchen Sie es erneut.
3. Die maximale Nutzungsentfernung dieses Produkts beträgt 10m. Bitte verwenden Sie es innerhalb von 10m. Außerdem sollten sich zwischen Tastatur und Empfänger keine metallischen Hindernisse befinden



FCC Warning

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE 1: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
-Connect the equipment into an outlet on a circuit different from that to which t he receiver is connected.
-Consult the dealer or an experienced radio/TV technician for help.

NOTE 2: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.