



BOM list for BEB/120/232 model

No.	Code	Specific	Num.	Note
1	R1	0.5W 62K±10% P=12.5	1	
2	R2,3	0.5W 150Ω±10% P=12.5	2	
3	C1	CL21 400V 0.22uF J P=10	1	
4	C2	CT81 3KV 2200pF	1	
5	C3	CD11GH 200V47uF M 105℃	1	
6	C4	CBB81 1.6KV 3.9nF J P=15	1	
7	C5,C6	CBB81 1600V 1.5nF J P=15	2	
8	D1-4	1N4007 1000V 1A P=12.5	4	
9	D5	1N4148 75V 150mA P=10	1	
10	Q1,2	BUL741 TO-220	2	
11	L1	DT1901	1	
12	L2	DT1902	1	
13	L3	DT2501	1	
14	Fuse	3E 125V 3A 3.6×10mm	1	
15	J1	Φ0.6 P=12.5	1	
16	Lead	AWM11125 105℃600V 18AWG	/	
17	GND	AWM11125 105℃600V 22AWG	/	
18	PCB	DFD-3 140×28mm	1	
19	IP1,2	DX10 V-2 105℃ 0.21mm	1	
20	Label	ZT4 100℃	1	
21	Potting	Potting Compound HF-28P HB	/	
22	Button	PP-HVO V-0 65℃	3	
23	Case	Case10 242X32X25mm	1	
24	Rivet	1.6X2.5	5	

BOM list for BEB/120/32 model

No.	Code	Specific	Num.	Note
1	R1	0.5W 62K±10% P=12.5	1	
2	R2,3	0.5W 150Ω±10% P=12.5	2	
3	C1	CL21 400V 0.22uF J P=10	1	
4	C2	CT81 3KV 2200pF	1	
5	C3	CD11GH 200V47uF M 105℃	1	
6	C4	CBB81 1.6KV 3.9nF J P=15	1	
7	C5	CBB81 1600V 1.5nF J P=15	1	
8	D1-4	1N4007 1000V 1A P=12.5	4	
9	D5	1N4148 75V 150mA P=10	1	
10	Q1,2	BUL741 TO-220	2	
11	L1	DT1901	1	
12	L2	DT1902	1	
13	L3	DT2501	1	
14	Fuse	3E 125V 3A 3.6×10mm	1	
15	J1	Φ0.6 P=12.5	1	
16	Lead	AWM11125 105℃600V 18AWG	/	
17	GND	AWM11125 105℃600V 22AWG	/	
18	PCB	DFD-3 140×28mm	1	
19	IP1,2	DX10 V-2 105℃ 0.21mm	1	
20	Label	ZT4 100℃	1	
21	Potting	Potting Compound HF-28P HB	/	
22	Button	PP-HVO V-0 65℃	3	
23	Case	Case10 242X32X25mm	1	
24	Rivet	1.6X2.5	5	