

Bluetooth Keyboard

Packing Contents:

- 1. wireless keyboard
- 2. USB Power Charging cable

3. Charger

4. User Guide

1.0 Product Features:

- 1. Built-in wireless Bluetooth 3.0 keyboard.
- 2. Display stand for easy viewing.
- 3. Built-in Rechargeable lithium battery lasts for approximately 55 hours per charge.
- 4. Special **【home】** screen key for one touch access to variety of application.
- 5. Light weight ,quiet keystrokes,water-proof and dust-proof
- 6. Energy saving keyboard sleep mode.

2.0 Keyboard Specification:

- 1. Bluetooth 3.0 interface standard
- 2. Operating Distance to 10 meters.
- 3. Modulation System:GFSK
- 4. Operatin Voltage:3.0-5.0V
- 5. Working Current:<5.0mA
- 6. Standby Current:2.5mA
- 7. Sleeping Current: <200μA
- 8. Charging Current:≥100mA
- 9. Standby Time:160hours
- 10. Charging Time:1hours
- 11. Lithium Battery Capacity:40mAh
- 12. Uninterrupted Working Time:38hours
- 13. Lithium Battery Life:3 years
- 14. Lithium Battery Specifications: 35*16*2mm
- 15. Key Strength:200±10g
- 16. Key Life:5 million strokes
- 17. Operating Temperature:-10 -+55°C

3. 0 Bluetooth Keyboard Pairing

Step 1 :Press POWER switch for 3 seconds the Bluetooth matching function will start . The [Bluetooth] indicator light will be blinking. The keyboard is now ready to be connected



Step 2 : According to the equipment to be connected, Start to set

Step 3 : On the settings menu,select item[General] to access [Bluetooth]settings. Click on[Bluetooth] to turn on the connection.iphone will automatically search for a Bluetooth-enabled device.

Step 4 : Wireless keyboard found. Click on the device to connect.

Step 5 : Wireless keyboard connected successfully.[power]indicator light will stay on until the keyboard is swithed off.

4. At the 2nd time connection (re-connect)

step 1:Turn on: press power switch 3 sec in the switch off condition, Blue Led fresh (long),KB will reconnect , the Led; It will enter the auto fairing mode if it is fail.

step 2:Turn off: long press power key 3 sec, blue led fresh 3 sec in the power on condition , KB is disconnect.


step 3:it will switch off the power at the time out condition.

step 4: if user do not use the KB over 10 minutes, it will disconnect, and enter into the standby mode, any key press will wake up it.

5.0 Charging

When the battery power is low, the [power] indicator light will start blinking, it is time to recharge the keyboard.

step 1 : Connect the USB-B to the charging seat.




step 4 : The indicator for the charging seat will keep lighting all the time, and it's ok for one-hour charging

Note the USB port only can be used for charging

step 2 : Connect the USB-A to the power adapter or the USB interface of your PC

step 3 : Put the interface for charging on the keyboard onto the contact of the charging seat tightly



6.0 Energy Saving Sleep mode

The keyboard will kick into sleep mode when it is inactive for 15 minutes, and the keyboard [power]indicator or light will go off. To activate from sleep mode, just press any key and wait 3 seconds, the keyboard will come back on.

7.0 Safety Caution

- 1. keep the item away from sharp objects.
- 2. Do not place heavy object on top of the keyboard.
- 3. Do not Microwave the item.
- 4. Do not force or distorted the keyboard.
- 5. Keep away from oil,chemical or any other organic liquid.

8.0 Cleaning

Clean the silicone keyboard with water,alcohol or cohoh based disinfectant.

9.0 Troubleshooting

(A) Unable to connect

- 1. Make sure the power switch is on.
- 2. Make sure the keyboard is within the operating distance.
- 3. Make sure the battery is charged.
- 4. Make sure Bluetooth setting is on
- 5. Make sure wireless keyboard is connected
- 6. Make sure wireless keyboard has been paired

(B) Unable to charge keyboard

- 1. Make sure the USB power cable is connected properly to the keyboard and the power source.
- 2. Make sure the wall charger is plug into the power outlet.

FCC Warning:

The grantee is not responsible for any changes or modifications not expressly approved by the party responsible for compliance.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

--Reorient or relocate the receiving antenna.
--Increase the separation between the equipment and receiver.
--Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
--Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.