

RF Exposure / MPE Calculation

No. : 14011106H
Applicant : DENSO TEN Limited
Type of Equipment : Car Audio
Model No. : TN0023A
FCC ID : BABTN0023A

DENSO TEN Limited declares that Model: TN0023A complies with FCC radiation exposure requirement specified in the FCC Rule 2.1091 (for mobile).

RF Exposure Calculations:

The following information provides the minimum separation distance for the highest gain antenna provided with the “TN0023A“ as calculated from (B) Limits for General Population / Uncontrolled Exposure of TABLE 1- LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE) of §1.1310 Radiofrequency radiation exposure limits.

[WLAN (2.4 GHz band) part]

This calculation is based on the highest EIRP possible from the system, considering maximum power and antenna gain, and considering a 1mW/cm² uncontrolled exposure limit. The Friis formula used was:

$$S = \frac{P \times G}{4 \times \pi \times r^2}$$

Where

P = 21.58 mW (Maximum average output power)

Time average was used for the above value in consideration of 6-minutes time-ave

Burst power average was used for the above value in consideration of worst condit

G = 0.723 Numerical Antenna gain; equal to -1.41dBi

r = 20 cm (Separation distance)

Power Density Result $S = 0.00310 \text{ mW/cm}^2$

[Bluetooth (BR/EDR) part]

This calculation is based on the highest EIRP possible from the system, considering maximum power and antenna gain, and considering a 1mW/cm² uncontrolled exposure limit. The Friis formula used was:

$$S = \frac{P \times G}{4 \times \pi \times r^2}$$

Where

P = 4.38 mW (Maximum average output power)

Time average was used for the above value in consideration of 6-minutes time-averaging

Burst power average was used for the above value in consideration of worst condition.

G = 1.175 Numerical Antenna gain; equal to 0.7dBi

r = 20 cm (Separation distance)

Power Density Result $S = 0.00102 \text{ mW/cm}^2$

UL Japan, Inc.

Ise EMC Lab.

4383-326 Asama-cho, Ise-shi, Mie-ken 516-0021 JAPAN

Telephone : +81 596 24 8999

Facsimile : +81 596 24 8124

[Bluetooth Low Energy part]

This calculation is based on the highest EIRP possible from the system, considering maximum power and antenna gain, and considering a 1mW/cm² uncontrolled exposure limit. The Friis formula used was:

$$S = \frac{P \times G}{4 \times \pi \times r^2}$$

Where

P = 0.74 mW (Maximum average output power)

Time average was used for the above value in consideration of 6-minutes time-averaging

Burst power average was used for the above value in consideration of worst condition.

G = 1.175 Numerical Antenna gain; equal to 0.7dBi

r = 20 cm (Separation distance)

Power Density Result $S = 0.00017 \text{ mW/cm}^2$

[WLAN (5 GHz band) part]

This calculation is based on the highest EIRP possible from the system, considering maximum power and antenna gain, and considering a 1mW/cm² uncontrolled exposure limit. The Friis formula used was:

$$S = \frac{P \times G}{4 \times \pi \times r^2}$$

Where

P = 3.27 mW (Maximum average output power)

Time average was used for the above value in consideration of 6-minutes time-ave

Burst power average was used for the above value in consideration of worst condit

G = 2.128 Numerical Antenna gain; equal to 3.28dBi

r = 20 cm (Separation distance)

Power Density Result $S = 0.00138 \text{ mW/cm}^2$

Therefore, if WLAN 2.4 GHz and WLAN 5 GHz transmit simultaneously,

$$S = 0.00310 \text{ mW/cm}^2 + 0.00138 \text{ mW/cm}^2 = 0.00448 \text{ mW/cm}^2$$

Therefore, if WLAN 2.4 GHz and Bluetooth transmit simultaneously,

$$S = 0.00310 \text{ mW/cm}^2 + 0.00102 \text{ mW/cm}^2 = 0.00412 \text{ mW/cm}^2$$

Therefore, if WLAN 5 GHz and Bluetooth transmit simultaneously,

$$S = 0.00138 \text{ mW/cm}^2 + 0.00102 \text{ mW/cm}^2 = 0.0024 \text{ mW/cm}^2$$

Even taking into account the tolerance, this device can be satisfied with the limits.

UL Japan, Inc.

Ise EMC Lab.

4383-326 Asama-cho, Ise-shi, Mie-ken 516-0021 JAPAN

Telephone : +81 596 24 8999

Facsimile : +81 596 24 8124