

## TEST REPORT

**CONTENTS:**

Part 22 Subpart H & Part 24 Subpart E ..... Report Number 10439  
 Part 15 Subpart C (Bluetooth Transmitter) ..... Report Number 10440  
 Part 15 Subpart B ..... Report Number 10441  
 Part 15 Subpart B (Bluetooth Receiver) ..... Report Number 10442

**CONDUCTED RF POWER OUTPUT**

**Measurement Procedure**

The RF output port of the equipment under test is directly coupled to the input of a HPE4406A Vector Signal Analyzer through a 10dB passive attenuator, adaptor (if needed), and specialized RF connector. The peak power output is measured for all channels.

CFR Part 2.1046

**Measurement Results**

\* Data supplied by Motorola SAR Lab

**AMPS**

Frequency (MHz)	Power (dBm)
824.04	27.72
836.52	27.88
848.97	27.80

**CDMA 800**

Frequency (MHz)	Power (dBm)
824.70	25.05
836.52	24.98
848.31	24.95

**CDMA 1900**

Frequency (MHz)	Power (dBm)
1851.25	24.90
1880.00	24.91
1908.75	24.90