

June, 02

CUSTOMER : Hyak

POWER : 5W

FUNCTION : Marine Handheld Transceiver, JIS 7, 12V Ni-MH Batt., Desk Top
Charger

BRAND : TEKCOM

MARINE US VERSION

ITEM	PART NO	DESCRIPTION	QTY	LOCATION
TRANSISTOR				
1	01-24001A0-A00	DIODE WIN4001	2	D206,D501
2	01-3197130-A00	TRANSISTOR 2SC1971	1	Q2
3	01-320533A-A00	TRANSISTOR 2SC2053	1	Q3
4	01-3335530-A00	TRANSISTOR 2SC3355 (2SC2408)	1	Q4
5	01-6031201-A00	LED LAMP RED D3mm	1	D401
SMT TRANSISTOR				
1	02-22838D0-A00	SMT DIODE EDS2838(SDS2838&(1SS184)	2	D11,D205
2	02-27000D0-A00	SMT DIODE EDS7000(SDS7000&ISS226)	2	D4,D204
3	02-2027210-A00	SMT DIODE ISS272	1	D203
4	02-2410DN0-A00	SMT DIODE SDP410D (ISS314&ISS356)	4	D1,D2,D3,D10
5	02-2235E70-A00	SMT DIODE DAN235E	1	D9
6	02-3FMA5G0-A00	SMT TRANSISTOR FMA5A	3	Q12,Q215,Q216
7	02-3124EC0-A00	SMT TRANSISTOR DTC124EUA	5	Q9,Q10,Q13,Q209,Q210
8	02-3409730-A00	SMT TRANSISTOR 2SC4097	12	Q5,Q6,Q20,Q201,Q202 Q203,Q204,Q205,Q206,Q207 Q208,Q217
9	02-3472630-A00	SMT TRANSISTOR 2SC4726	1	Q1
10	02-3500630-A00	SMT TRANSISTOR 2SC5006 (2SC4226-R24&2SC5086)	2	Q11,Q14
11	02-3136310-A00	SMT TRANSISTOR 2SA1363	2	Q213,Q214
12	02-3197910-A00	SMT TRANSISTOR 2SA1979U "S&E" (2SA1577Q)	2	Q211,Q212
13	02-31197QY-A00	SMT TRANSISTOR SSA1197K (2SB1197K&2SA1298)	2	Q7,Q8
14	02-4021020-A00	SMT FET 2SK210Y	1	Q16
15	02-4032030-A00	SMT FET 3SK320	1	Q19
16	02-4030220-A00	SMT FET 2SK302G RF AMP	2	Q15,Q18
17	02-4049220-A00	SMT FET 2SK492-C	1	Q17
18	02-5021710-A00	SMT VARICAP ISV217	4	D5,D6,D7,D8
19	02-6301022-A00	SMT LED LAMP KPA-3010QGC GREEN	2	D201,D202
IC				
1	03-SL386D1-A00	SMT IC AF AMP SL386D	1	IC206
2	03-0293000-A00	IC NJM2930	1	IC209
3	03-0340321-A00	SMT IC NJM3403AV	1	IC205
4	03-0405101-A00	SMT IC NJU4051	1	IC208
5	03-0567001-A00	SMT IC LMC567	1	IC207
6	03-0567600-A00	SMT IC M56760FP	1	IC3
7	03-5018V01-A00	SMT IC DBL5018V	1	IC1
8	03-7531254-A00	SMT IC UPD75312GF-543-3B9	1	IC201
9	03-75S01F1-A00	SMT IC TA75S01F	1	IC2
10	03-93C46R1-A00	SMT IC AT93C46-10SI	1	IC202

11	03-XC61AC1-A00	SMT IC XC61AC4302PR	1	IC203
12	03-XC61AN1-A00	SMT IC XC61AN4302PR	1	IC204

CRYSTAL

1	04-3211218-A00	CRYSTAL 21.145MHz +/-10PPM UM-1	1	X1
2	04-341923C-A00	CRYSTAL 4.1943MHz (+/-30PMM) NC-3	1	X201
3	04-3128218-A00	CRYSTAL 12.8MHz UM-1 +/-10PPM	1	X2
4	04-2216228-Q50	CRYSTAL FILTER 21.6MHz (PAIR) UM-1	2	F1,F2
5	04-44551EH-J50	CERAMIC FILTER 455KHz (12A) QA455-FW(CF455F).	1	F3

IFT

1	05-2000121-S50	IFT A001	1	T1
2	05-2031922-S50	IFT A319	2	T2,T3
3	05-2445G27-S50	IFT A445	2	T4,T5
4	05-330203B-A00	SMT FM COIL 3.0T*D2.0*0.5mm (-) CW	3	L6,L7,L8
5	05-340203B-A00	SMT FM COIL 4.0T*D2.0*0.5mm (-) CW	2	L1,L2
6	05-350303B-A00	SMT FM COIL 5.0T*D3.0*0.5mm (-) CW	1	L22
7	05-360303B-A00	SMT FM COIL 6.0T*D3.0*0.5mm (-) CW	1	L23
8	05-4010321-A00	TOROID COIL 1UH 4T	1	L13
9	05-8104106-A00	SMT CHOKE COIL 1608 100nH	1	L21
10	05-8561014-A00	SMT CHOKE COIL 2012 56nH (C2012-56nH)	2	L3,L5
11	05-A105026-A00	CHIP FERRITE INDUCTOR 1608 1UH +/-10% (SDFL1608Q1R0)	5	L11,L16,L17,L24,L25
12	05-A225026-A00	CHIP FERRITE INDUCTOR 1608 2.2UH +/-10% (SDFL1608Q2R2)	2	L18,L19
13	05-8221014-A00	CHIP INDUCTOR 2012 22nH (C2012C-22NJ)	1	L9
14	05-8471035-A00	SMT CHOKE 2012 0.047uH (C2012C-47NK)	2	L4,L14
15	05-8105035-A00	SMT CHOKE 2520 1UH +/-10% (ELJFC1ROKF)	2	L10,L12
16	05-B821014-A00	CHIP CERAMIC INDUCTOR 2012 82nH +/-5% (SDCL2012C82NJB)	1	L20

CHIP RESISTOR PARTS

1	06-5102731-A00	CHIP RES 1608 1K OHM 1/10W +/-5%	9	R14,R15,R20,R23,R72 R254,R255,R256,R257
2	06-5152731-A00	CHIP RES 1608 1.5K OHM 1/10W +/-5%	5	R5,R6,R7,R266,R267
3	06-5222731-A00	CHIP RES 1608 2.2K OHM 1/10W +/-5%	8	R2,R71,R76,R232,R233 R234,R235,R269
4	06-5272731-A00	CHIP RES 1608 2.7K OHM 1/10W +/-5%	2	R65,R265
5	06-5332731-A00	CHIP RES 1608 3.3K OHM 1/8W +/-5%	1	R78
6	06-5392731-A00	CHIP RES 1608 3.9K OHM 1/8W +/-5%	1	R268
7	06-5472731-A00	CHIP RES 1608 4.7K OHM 1/10W +/-5%	13	R35,R36,R37,R38,R39 R40,R41,R240,R241,R242 R243,R244,R246
8	06-5103731-A00	CHIP RES 1608 10K OHM 1/10W +/-5%.	15	R10,R11,R12,R21,R73 R67,R223,R224,R225,R226 R227,R228,R229,R230,R231
9	06-5123731-A00	CHIP RES 1608 12K OHM 1/10W +/-5%.	1	R260
10	06-5153731-A00	CHIP RES 1608 15K OHM 1/10W +/-5%	3	R9,R49,R50
11	06-5183731-A00	CHIP RES 1608 18K OHM 1/10W +/-5%	2	R16,R34
12	06-5203731-A00	CHIP RES 1608 20K OHM 1/10W +/-5%	3	R215,R216,R217
13	06-5223731-A00	CHIP RES 1608 22K OHM 1/10W +/-5%	3	R1,R236,R239
14	06-5273731-A00	CHIP RES 1608 27K OHM 1/10W +/-5%	1	R63

15	06-5303731-A00	CHIP RES 1608 30K OHM 1/10W +/-5%	1	R237
16	06-5333731-A00	CHIP RES 1608 33K OHM 1/10W +/-5%	5	R218,R219,R220,R221,R222
17	06-5363731-A00	CHIP RES 1608 36K OHM 1/10W +/-5%	4	R247,R248,R249,R250
18	06-5393731-A00	CHIP RES 1608 39K OHM 1/10W +/-5%.	1	R214
19	06-5473731-A00	CHIP RES 1608 47K OHM 1/10W +/-5%.	14	R19,R22,R66,R68,R208 R209,R210,R211,R212,R238 R262,R271,R272,R273
20	06-5683731-A00	CHIP RES 1608 68K OHM 1/10W +/-5%	1	R213
21	06-5104731-A00	CHIP RES 1608 100K OHM 1/10W +/-5%	9	R57,R59,R60,R61,R62 R205,R206,R207,R245
22	06-5154731-A00	CHIP RES 1608 150K OHM 1/10W +/-5%	1	R259
23	06-5224731-A00	CHIP RES 1608 220K OHM 1/10W +/-5%	3	R51,R253,R263
24	06-5334731-A00	CHIP RES 1608 330K OHM 1/10W +/-5%	1	R13
25	06-5394731-A00	CHIP RES 1608 390K OHM 1/10W +/-5%.	3	R8,R48,R261
26	06-5106731-A00	CHIP RES 1608 10M OHM 1/10W +/-10%	1	R274
27	06-5047731-A00	CHIP RES 1608 4.7 OHM 1/10W +/-5%.	3	R28,R29,R258
28	06-5100731-A00	CHIP RES 1608 10 OHM 1/10W +/-5%.	3	R18,R25,R251
29	06-5470731-A00	CHIP RES 1608 47 OHM 1/10W +/-5%	2	R32,R252
30	06-5560731-A00	CHIP RES 1608 56 OHM 1/10W +/-5%	2	R26,R64
31	06-5101731-A00	CHIP RES 1608 100 OHM 1/10W +/-5%	9	R42,R43,R44,R45,R201, R202,R203,R204,R264
32	06-5151731-A00	CHIP RES 1608 150 OHM 1/10W +/-5%	1	R24
33	06-5221731-A00	CHIP RES 1608 220 OHM 1/10W +/-5%	8	R17,R52,R53,R54,R55 R56,R58,R252
34	06-5331731-A00	CHIP RES 1608 330 OHM 1/10W +/-5%	1	R47
35	06-5471731-A00	CHIP RES 1608 470 OHM 1/10W +/-5%	5	R27,R30,R31,R33,R77
36	06-5681731-A00	CHIP RES 1608 680 OHM 1/10W +/-5%	1	R46
37	06-1680436-A00	RESISTOR 68 OHM 1W (S.S)	1	R401
38	06-1471131-A00	RESISTOR 470 OHM 1/10W +/-5%	1	R402
39	06-7103258-A00	ROTARY POTENTIOMETER A10K RSO915N-15KQA1-A10K-A	1	VR203
40	06-A332117-A00	SMT SEMT-FIXED 3.3K EVM3YSX50B34	1	VR201
41	06-A103117-A00	SMT SEMT-FIXED 10K EVM3YSX50B14	3	VR1,VR202,VR204

CAPACITOR PARTS

1	07-5005601-A00	CHIP CAP 1608 0.5PF 50V +/-0.25PF NPO	2	C61,C62
2	07-5010601-A00	CHIP CAP 1608 1PF 50V +/-0.25PF NPO	2	C65,C66
3	07-5020601-A00	CHIP CAP 1608 2PF 50V +/-0.25PF NPO	2	C2,C55
4	07-5030601-A00	CHIP CAP 1608 3PF 50V +/-0.25PF NPO	2	C20,C64
5	07-5050601-A00	CHIP CAP 1608 5PF 50V +/-0.25PF NPO	2	C58,C59
6	07-5060601-A00	CHIP CAP 1608 6PF 50V +/-0.25PF NPO	1	C68
7	07-5070601-A00	CHIP CAP 1608 7PF 50V +/-0.25PF NPO	1	C60
8	07-5080601-A00	CHIP CAP 1608 8PF 50V +/-0.25PF NPO	6	C10,C11,C12,C13,C14 C54
9	07-5100601-A00	CHIP CAP 1608 10PF 50V +/-0.25PF NPO	6	C3,C69,C70,C71,C72,C75
10	07-5120631-A00	CHIP CAP 1608 12PF 50V +/-5% NPO	2	C8,C9
11	07-5150631-A00	CHIP CAP 1608 15PF 50V +/-5% NPO	4	C73,C98,C99,C100
12	07-5180631-A00	CHIP CAP 1608 18PF 50V +/-5% NPO	4	C1,C4,C5,C6
13	07-5220631-A00	CHIP CAP 1608 22PF 50V +/-5% NPO	2	C7,C106
14	07-5200631-A00	CHIP CPA 1608 20PF 50V +/-5% NPO	1	C124
15	07-5270631-A00	CHIP CAP 1608 27PF 50V +/-5% NPO	1	C56
16	07-5300631-A00	CHIP CAP 1608 30PF 50V +/-5% NPO	2	C202,C203
17	07-5330631-A00	CHIP CAP 1608 33PF 50V +/-5% NPO	2	C15,C78

18	07-5470631-A00	CHIP CAP 1608 47PF 50V +/-5% NPO	3	C16,C17,C18
19	07-5680631-A00	CHIP CAP 1608 68PF 50V +/-5% NPO	1	C101
20	07-5820631-A00	CHIP CAP 1608 82PF 50V +/-5% NPO	2	C112,C113
21	07-5101631-A00	CHIP CAP 1608 100PF 50V +/-5% NPO	2	C74,C229
22	07-5391661-A00	CHIP CAP 1608 390PF 50V +/-10% X7R	2	C239,C240
23	07-5471661-A00	CHIP CAP 1608 470PF 50V +/-10% X7R	3	C262,C403,C501
24	07-5102661-A00	CHIP CAP 1608 0.001UF 50V +/-10% X7R	56	C19,C21,C22,C23,C24 C25,C26,C27,C28,C29 C30,C31,C33,C34,C35 C36,C37,C38,C39,C40 C41,C42,C43,C44,C45 C46,C47,C48,C49,C50 C51,C52,C53,C57,C63 C96,C108,C109,C125,C204 C205,C206,C207,C208,C209 C210,C211,C212,C213,C214 C215,C216,C261,C263,C401 C402
25	07-5103671-A00	CHIP CAP 1608 0.01UF 50V +80-20% Y5V	29	C79,C80,C81,C82,C83 C84,C85,C87,C89,C90 C91,C92,C93,C94,C95 C97,C123,C217,C218,C219 C220,C221,C222,C223,C224 C225,C226,C227,C228
26	07-5104681-A00	CHIP CAP 1608 0.1UF 50V +80-20% Y5V	13	C86,C88,C102,C103,C104 C201,C246,C247,C248,C249 C250,C251,C258
27	07-5153461-A00	CHIP CAP 1608 0.015UF 25V +/-10% X7R	1	C126
28	07-5152651-A00	CHIP CAP 1608 0.0015UF 50V +/-10% X7R	2	C32,C238
29	07-5222651-A00	CHIP CAP 1608 0.0022UF 50V +/-10% X7R	1	C241
30	07-5223451-A00	CHIP CAP 1608 0.022UF 25V +/-10% X7R	2	C116,C117
31	07-5332651-A00	CHIP CAP 1608 0.0033UF 50V +/-10% X7R	1	C254
32	07-5472651-A00	CHIP CAP 1608 0.0047UF 50V +/-10% X7R	1	C242
33	07-5473361-A00	CHIP CAP 1608 0.047UF 16V +/-10% X7R	2	C231,C236
34	07-5473653-A00	CHIP CAP 3216 0.047UF 50V +/-10% X7R	1	C264
35	07-5683671-A00	CHIP CAP 1608 0.068UF 50V +/-10% X7R	3	C107,C119,C260
36	07-5105281-A00	CHIP CAP 1608 1UF 10V +80-20% Y5V	9	C67,C114,C115,C230,C232 C233,C235,C237,C259
37	07-2472657-A00	MYLAR CAP 0.0047UF 50V +/-10% 9*5*3mm	1	C243
38	07-433564C-A00	ELECT CAP 3.3UF 50V (D4*5mm)	1	C118
39	07-410644C-A00	ELECT CAP 10UF 25V (D4*5mm)	3	C255,C256,C257
40	07-422634C-A00	ELECT CAP 22UF 16V (D4*5mm)	2	C76,C77
41	07-4336243-A00	ELECT CAP 33UF 10V (D4*7mm)	1	C253
42	07-4476344-A00	ELECT CAP 47UF 16V (D5*8mm)	1	C110
43	07-410734E-A00	ELECT CAP 100UF 16V (D6*5mm)	1	C245
44	07-4107143-A00	ELECT CAP 100UF 6.3V +/-20% (D4*7mm)	1	C244
45	07-6105343-A00	SMT TAN CAP 3216 1UF 16V +/-20%	2	C122,C234
46	07-6106147-A00	SMT TAN CAP 2125 10UF 6.3V +/-20%	2	C120,C252
45	07-6686125-A00	SMT TAN CPA 6032 68UF 6.3V +/-20%	1	C111
46	07-1180653-A00	CERAMIC CAP 18PF 50V +/-10% (D5mm)	1	C105
47	07-9060752-A00	CHIP TRIMMER CAP 6PF (TZC03R060A110)	1	VC1

CONNECTOR PARTS

1	08-12T0132-A00	D2.5MM STEREO EARPHONE JACK (ST-013)	1	J402/MIC SP
2	08-01810A0-A00	ANTENNA CONNECTOR HEAD (TNC)	1	TNC1
3	08-3H64E66-A00	2*9PINS SMT FEMALE HEADER (H4.4mm) G/F	1	J1
4	08-2H64066-A00	2*9PINS SMT HEADER (H1.0*L13.0mm)	1	J204
5	08-3321D11-A00	HEADER 3-PINS (1.5mm)	1	J205
6	08-4324D50-A00	CONNECTOR ASSEMBLY 3PIN 50mm (1.5mm) 28#	1	J401
7	08-1160034-A00	CHARGER JACK	1	FOR CHARGER CLIP
8	08-5030323-A00	PVC WIRE 26# RED 30mm (3+3)	1	BATT +8.4V
9	08-5040304-A00	PVC WIRE 28# BLACK 40mm (3+3)	1	CHARGER CLIP
10	08-5040324-A00	PVC WIRE 28# RED 40mm (3+3)	1	CHARGER CLIP
11	08-5045322-A00	PVC WIRE 24# RED 45mm (3+3)	1	BATT OUT+
12	08-5055364-A00	PVC WIRE 28# BLUE 55mm (3+3)	1	CHARGER -
13	08-5060324-A00	PVC WIRE 28# RED 60mm (3+3)	1	CHARGER +
14	08-5068302-A00	PVC WIRE 24# BLACK 68mm (3+3)	1	BATT OUT-
15	08-5068322-A00	PVC WIRE 24# RED 68mm (3+3)	1	TX +8.4V
16	08-5080304-A00	PVC WIRE 28# BLACK 80mm (3+3)	1	MIC -
17	08-5080314-A00	PVC WIRE 28# BROWN 80mm (3+3)	1	SP+
18	08-5080324-A00	PVC WIRE 28# RED 80mm (3+3)	1	MIC +
19	08-5080364-A00	PVC WIRE 28# BLUE 80mm (3+3)	1	SP-
20	08-AB56211-A00	SILICONE INTERCONNECTOR L21.5*H6.2*W2mm 'YP' Pitch:0.18mm	1	

SWITCH

1	09-311741A-A00	TACTILE SWITCH TM17AS	2	SW1/PTT;SW2/FUNC
---	----------------	-----------------------	---	------------------

METAL PARTS

1	30-520C565-A00	SCREW M2.0*27.50mm PB S/S	2	FOR TRANSMITTER
2	30-1200635-A00	SCREW M2.0*6.0mm PM S/S	3	FOR PTT
3	30-1200415-A00	SCREW M2.0*4.0mm BM S/S	1	FOR BATT. CON PCB
4	30-1200565-A00	SCREW M2.0*5.0mm PB S/S	4	FOR TRANSMITTER
5	30-10203N5-A00	SCREW M2.0*3.0mm PWM S/S	1	FOR MIC JACK PCB
6	30-1260431-A00	SCREW M2.6*4.0mm PM NI	1	FOR 2SC1971
7	30-1300635-A00	SCREW M3.0*6.0mm PM S/S	1	FOR BELT CLIP
8	31-3200439-A00	SCREW M2.0*4.0mm PM IRON (NI)	3	FOR PCB
9	31-5041105-A00	BATTERY CASE LOCK SCREW (Cu)	1	
10	32-5091803-A00	ANTENNA NUT 1/4"*1.8mm (Cu)	1	
11	32-5700303-A00	VOL NUT M7*1.8mm (Cu)	1	
13	33-0406059-A00	FIBER WASHER OD6.0*ID4.0*H0.5(DUPLEX GUMMED TAPE)	1	FOR MIC
14	34-4258A2A-A00	ANTENNA SPRING OD5.8*L102.7*0.8mm BRONZE	1	
15	35-3181L11-A00	LCD MOUNTING PLATE (STEEL)	1	
16	35-3181013-A00	BATTERY CONTACT PLATE(PHOSPHOR COPPER)	3	
17	35-3181C11-A00	CHARGER CONTACT PLATE (STEEL)	6	
18	35-B181R17-A00	REAR CASE (OIL BLOOMING) (Grey 431U)	1	
19	35-6882S15-A00	SHIELD PLATE (STEEL)	1	

20	35-7181015-A00	VCO SHIELD CASE (STEEL)	1
21	35-0181S12-A00	SCREW HOLD (BRASS)	3
22	35-9181A12-A00	ANTENNA HEAD (BRASS)	1

PLASTIC ASSESSRIOES

1	40-018CK19-A00	KEYBOARD MOUNT PLATE (PC) (PJ-181C)	1	
2	40-0882M11-A00	PTT MOUNT PLATE(ABS)	1	
3	40-0181M12-A00	MIC/SP RUBBER CAP(SILICONE RUBBER) (Grey 432U)	1	
4	40-0181P12-A00	PTT KEY(SILICONE RUBBER) (Grey 429U)	1	
5	40-0868817-A00	SCREW SLEEVE 1.8*0.8mm (SILICONE)	6	
6	40-118CF11-A00	FRONT HOUSING (ABS) (PJ-181C) (Grey 431U)	1	
7	40-2182B11-A00	BATTERY BACK CASE(ABS) (12V) (Grey 431U)	1	
8	40-2182F11-A00	BATTERY FRONT CASE(ABS) (12V) (Grey 431U)	1	
9	40-4181V11-A00	VOL KNOB (ABS) (433U)	1	
10	40-5181B12-A00	BATT. CON. RUBBER RING(SILICONE RUBBER)	1	
11	40-5181U12-A00	RUBBER RING FOR UNITS(SILICONE RUBBER)	1	
12	40-618CL06-A00	LENS (PMMA) (PJ-181C)	1	
13	40-7181A17-A00	RUBBER DUCK ANTENNA SLEEVE (PU) (433U)	1	
14	40-8181B11-A00	BELT CLIP(PC) (Grey 431U)	1	
15	40-A18C012-A00	UP/DOWN KEY (SILICONE RUBBER) (PJ-181C)	1	
16	41-1051002-A00	OIL COTTON SLEEVE D1*1M	0.1	FOR CHARGER CLIP
17	41-2051001-A00	PVC SLEEVE D2.0*1M	0.002	
18	42-2483893-A00	LCD DUPLEX GUMMED TAPE	1	FOR LENS
19	44-4941372-A00	FIBER PLATE W/A 13.0*9.4*0.4mm (RED)	1	
20	44-6181LE5-A00	LCD BACK LIGHT PLATE(PMMA)	1	
21	44-734001E-A00	SPEAKER NET Φ34mm (NYLON BLACK)	1	
22	44-81818B2-A00	RUBBER PAD 1.8*1.8*1.5mm(±0.2mm)	2	
23	44-90506MB-A00	MIC/SP RUBBER WASHER (SILICONE RUBBER)	1	

PACKING ACCESSORIES

1	60-1882BU1-A00	CARTON (TM-882BU)	0.1	
2	60-3868011-A00	WHITE BOX	1	
3	60-5868001-A00	INNER CARD	1	
4	60-4868011-A00	INNER BOX	1	
5	62-2001122-A00	PE PVC BAG: 200*112*0.3mm	1	FOR ADAPTOR
6	62-2160321-A00	PO PVC BAG: 1-1/4"*8-1/2" (T=0.02mm)	1	FOR ANTENNA
7	62-2801001-A00	PO PVC BAG: 4"*11" (T=0.02mm)	1	FOR TRANSCEIVER
8	62-1140351-A00	PO PVC BAG: 1-3/8"*4-1/2" (T=0.02mm TYPE R)	1	FOR BELT CLIP
9	62-1200802-A00	PE PVC BAG: 80*120mm	1	FOR CHARGER CLIP
10	63-1882BU1-A00	INSTRUCTION BOOKLET (TM-882BU)	1	
11	64-6882BU1-A00	SERIAL NO. LABEL (TM-882BU)	1	

PCB BOARD

1	13-1181CB1-A00	CPU PCB (2 Layer) (PJ-181B)	1
2	13-1181R41-A00	RF PCB (4 Layer)	1
3	13-1181M21-A00	MIC/SP PCB (2 Layer)	1
4	13-1181C21-A00	CONNECTOR PCB (2 Layer)	1

5	13-1882C11-A00	CHARGER CLIP PCB	1
---	----------------	------------------	---

OTHER PARTS

1	11-361H511-H13	SPEAKER D36mm 8 OHM 0.5W	1	SP1
2	10-612041N-A00	NI-MH RECHARGEABLE BATTERY PACK 12V 700mA "AAA" G.P	1	
3	14-11810L0-A00	LCD DISPLAY T7633AKP1 (TN TYPE)	1	LCD201
4	16-605006S-A00	CONDENSER MIC KUC F6050AL-S (-66+/-2dB)	1	MIC1
5	15-4202200-A00	POLYSWITCH SRP2000	1	
6	67-5618046-A00	ADAPTOR AC:230V/50Hz DC:18V/100mA (UK 13K PLUG)	1	

DESK TOP CHARGER PART

1	01-3855090-A00	TRANSISTOR SS8550 PNP	1	Q1
2	01-6031201-A00	LED LAMP RED D3mm	1	LED
3	02-27000D0-A00	SMT DIODE SDS7000 (1SS226)	1	D2
4	06-1010234-A00	RESISTOR 1 OHM 1/4W +/-5% D2.5*7mm	1	R2
5	06-1056234-A00	RESISTOR 5.6 OHM 1/4W +/-5% D2.5*7mm	1	R1
6	06-1151234-A00	RESISTOR 150 OHM 1/4W +/-5% D2.5*7mm	1	R4
7	06-1203232-A00	RESISTOR 20K OHM 1/4W +/-5% (S.S)	1	R3
8	06-1560234-A00	RESISTOR 56 OHM 1/4W +/-5% D2.5*7mm	1	R5
9	08-1107083-A00	CHARGER JACK DJ-0708	1	
10	13-882SCHG-A00	PCB (TM-882 EUROPE DESK TOP CHARGER)	1	
11	30-1021295-A00	SCREW M2.0*12mm KA S/S	1	
12	30-405026J-A00	SCREW M2.0*5.0mm PB (BLACK)	4	
13	35-3181S18-A00	METAL CONTACT PLATE (S/S)	4	
14	40-118BS01-A00	CHARGER BACK HOUSING (ABS)	1	
15	40-118FS01-A00	CHARGER FRONT HOUSING (ABS)	1	
16	40-6181S06-A00	LENS FOR CHARGER (PMMA)	1	
17	44-81845D2-A00	RUBBER PAD D8*3mm Single Gummed Tape (Silicone Rubber)	4	
18	62-2002201-A00	PO PVC BAG: 200*220mm	1	
19	64-1882CE0-A00	RATING LABEL	1	

Prepared By:邹 萍

Confirmed By Electronics:

Confirmed By Mechanic:

Approval By: