





P/N YRD136-MNL-0008 Rev A


ASSA ABLOY















488 988 908















Congratulations, you've installed the Yale® ProSL Key Free Keypad Deadbolt with Z-Wave Plus! Turn sheet over for Programming Instructions to customize your product.

Programming Instructions





Master PIN Code must be created before any further programming.

Warning: Changes or modifications to this device, not expressly approved by ASSA ABLOY Residential Group could void the user's authority to operate the

Definitions

All Code Lockout Mode: This feature is enabled by the Master code. When enabled, it restricts all user (except Master) PIN code access. When attempting to enter a code while the unit is in Lockout, the lock rapidly beeps 5 times.

Audio Mode: Choosing Disable (3) in Audio mode shuts off the code confirmation tone play-back for use in quiet areas. Audio mode is enabled or disabled through feature programming by the Master code.

Automatic Re-lock Time: After a successful code entry or manual unlock with the key, the lock will automatically re-lock after each unlock in an effort to keep your home secure. This feature is optional, and can be turned off. In the ON mode, the lock will automatically re-lock

Low Battery: When battery power is low, the Low Battery Warning Indicator flashes RED. If battery power is completely lost, use the 9Volt battery override. To use the 9V battery override apply 9V battery, in either direction, to terminals below the keypad for backup power option. Wake up the lock and enter your pin code to unlock the door.

Master PIN Code: The Master PIN code is used for programming and for feature settings. It must be created prior to programming the lock. The Master code will also operate (unlock/lock) the lock.

Network Setting: This setting is available through the wireless button on the interior escutcheon @ and allows the lock to connect with a network controller

One Touch Locking: When the latch is retracted, activating the keypad will extend the latch (during Automatic Re-lock duration or when Automatic Re-lock is disabled).


Shutdown Time: The unit will shutdown (flashing keypad) for sixty (60) seconds and not


Tamper Alert: Audible alarm sounds if attempting to forcibly remove outside lock from door.


User PIN Code: The User code operates the lock. Maximum number of user codes is 250 in network.

Wrong Code Entry Limit: After five (5) unsuccessful attempts at entering a valid PIN code, the unit will shut down and not allow operation for sixty (60) seconds.

Changing Master PIN Code








Feature Programming Through Menu Mode Using Master PIN code*

- 1. Wake the lock by pressing the ✓ key.
- 2. Enter the 4-8 digit Master PIN code followed by the key.
- 3. Enter digit corresponding to the function to be performed followed by the key.





Factory Settings


Factory Setting
Registration <i>required*</i>
Disabled
Enabled
Enabled
30 Seconds
5 Times
60 Seconds

*The Master PIN code must be registered prior to any other programming of the lock,

Creating User PIN Codes Master PIN code must be created first,







Symptom	Troubleshooting Suggested Action
Symptom	
Lock does not respond – door is open and accessible.	 Press each keypad key for response when pressed. Check batteries are installed and oriented correctly (polarity in the battery case. Check batteries are in good condition; replace batteries* if discharged. Check to see if cable is fully connected and not pinched.
Lock does not respond – door is locked and inaccessible.	Batteries may be completely discharged. Apply 9V battery to terminals below the keypad for backup power option.
Unit chimes to indicate code acceptance, but the door will not open.	Check to see if there is another locking device on the door. Check the door gaps for any foreign objects between door and frame. Check that the cable is firmly connected to the PC board.
Unit operates to allow access, but will not automatically re-lock.	Check to see if Auto Re-lock Mode is enabled. If low battery indicator is lit (see below), change batteries*.
PIN codes will not register.	 PIN codes must consist of 4 to 8 digits to register. The same PIN code cannot be used for multiple users. Registration/management of PIN codes is set by the authority of the Master Code. Contact the Master user. User codes must be entered within 20 seconds or the process will have to be restarted. Check mark ✓ or gear o cannot be used as part of the PIN code.
Upon entering a PIN code and pressing the \checkmark key, the lock gives a series of beeps, flashes red 7 times, and does not unlock.	All Code Lockout Mode is enabled. Only the Master can enable/disable All Code Lockout Mode. Contact the Master user.
Upon entering a PIN code and pressing the ✓ key, there are different tones.	Check to see if the lock is set to All Code Lockout Mode. Setting/managing All Code Lockout Mode is done through Master Code only. Contact the Master user.
The unit operates, but it makes no sound.	• Enable Audio Mode.
The unit displays intermittent RED flashes.	This is the Low Battery indicator alerting that it is time to replace the batteries. Replace all four (4) batteries* with new AA Alkaline batteries.
Upon entering a PIN code and pressing the \checkmark key, the unit responds with a series of beeps and the keypad flashes three times.	The digits entered were incorrect or incomplete. Re-enter the correct code followed by the check mark \checkmark key.

. When batteries are replaced, Network locks have a real time clock that will be set through the User Interface (UI); it ded to verify correct date and time particularly those locks operating under Daylight Saying Time (DST

Unlocking Door with PIN Code

Enter PIN

Vario

123


4 5 6

789

AD 00

Press V

"Unlock





User Name	PIN Code

Warning: Changes or modifications to this device, not expressly approved by ASSA ABLOY Residential Group could void the user's authority to operate the equipment.

Contain FCC ID: MZR-YRIZW2USPB1 Model: YRD136-ZW-619,605,0BP,BSP This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful Interference to radio or television reception which can be determined by turning the equipment of

- and on, the user is encouraged to try to correct the interference by one or more of the following measures Reorient or relocate the receiving antenna. Increase the separation between the equipmen
- and receiver. · Connect the equipment into an outlet on a circuit different from that to which the receiver is
- Consult the dealer or an experienced radio/TV
- technician for help Distance between EUT and users is 20 cm.

cause harmful interference, and (2) this device must accept any dispositif ne peut causer des interferences, et 2) cet FCC Part 15.21

device that are not expressly approved by the manufacturer may void the user's authority to operate the equipment

Industry Canada: Contain IC ID: 2676A-YRIZW2USPB1 Model: YRD136-7W-619 605 0RPRSP

Section 7.1.2 of RSS-GEN Under Industry Canada regulations, this radio transmitter may only operate using an antenna of a type and maximum (or lesser) gain approved for the transmitter by Industry Canada o reduce potential radio interference to other users, the antenna type and its gain should be so chosen that the equivalent isotropically radiated power (e.i.r.p.) is not more than that necessary for successful

En vertu des règlements d'Industrie Canada, cet émetteur radio ne peut fonctionner avec une antenne d'un type et un maximum (ou moins) approuvés pour gagner de l'émetteur par Industrie Canada, Pour réduire le risque d'interférence aux autres utilisateurs le type d'antenne et son gain doivent être choisies de facon que la nuissance isotrone rayonnée équivalente (PIRE) ne dépasse pas ce qui est nécessaire pour une

Section 7.1.3 of RSS-GEN This Device complies with Industry Canada License-exempt RSS standard(s). Operation is subject to the following two conditions: 1) this device may not cause interference, and 2) this device must accept any interference, including interference that may cause undesired operation of the

Cet appareil est conforme avec Industrie Canada RSS This device complies with part 15 of the FCC rules Operation is subject to the following two condition: (1) This device may not subject to the following two condition: (1) This device may not subject to the following two condition: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two conditions: (1) This device may not subject to the following two condit appareil doit accepter toute interférence, y compris les interférences qui peuvent causer un mauvais Any changes or modifications (including the antennas) to this functionnement du dispositif.

> This radio transmitter 6982A-YRHCPZW0FM has been approved by Industry Canada to operate with the antenna types listed below with the maximum permissible gain indicated. Antenna types not included in this list, having a gain greater than the maximum gain indicated for that type, are strictly prohibited for use with this device.

Le présent émetteur radio 6982A-YRHCPZW0FM a été approuvé par Industrie Canada pour fonctionner avec les types d'antenne énumérés ci-dessous et avant un gain admissible maximal. Les types d'antenne non inclus dans cette liste, et dont le gain est supérieur au gain maximal indiqué, sont strictement interdits pour l'exploitation de l'émetteur


CAN ICES-3B/NMB-3B

Resetting Lock to Factory Default

When lock is reset to factory defaults all user codes (including the Master PIN code*) are deleted and all programming features are reset to original default settings (see "Factory Default Settings").

- 1. Remove the battery cover.
- 2. Remove the batteries.
- 3. While pressing the reset button (minimum of 3 seconds) reinstall batteries. Release reset button.
- 4. Replace battery cover.

Upon reset, Master Code creation is the only option available and must be performed prior to any other programming of the lock. NOTE: After setting the Master Code, press any key to complete handing of



Enrolling Lock In Z-Wave Plus Network

Your network controller first needs to be in enrollment or exclusion mode for the lock to be enrolled or removed from network.

Once you put the controller in the enrollment or exclusion mode, the lock can be enrolled or removed in the Z-Wave Plus Plus network by pressing the (button.

- To enroll lock using the @ button option:
- 1. Remove the battery cover.
- 2. Press @ button and hold until unit beeps two (2) times. 3. Release button and network joining
- automatically begins.
- 4. Replace battery cover.
- To remove lock using the @button option:
- 1. Remove the battery cover.
- 2. Press @ button and hold until unit beeps five (5) times. 3. Release button and network removal
- automatically begins. Replace battery cover.
- Use this procedure only when network primary

controller is missing or

otherwise inoperable.

NOTE TO INSTALLER AND CONSUMER

While Yale® has included several features to prevent lockout (9-Volt battery jumper, low battery warnings), it is still possible for a lockout situation to occur. Because this product does not have a mechanical override (a key), Yale® recommends to use this product in an environment where there are additional entry points into the dwelling.

RF Exposure Statement:

FCC and IC RF Radiation Exposure Statement: This equipment complies with FCC and IC RF Radiation exposure limits set forth for an uncontrolled environment. This device and its antenna must not be colocated or operating in conjunction with any other antenna or

This equipment should be installed and operated with a minimum distance of 20 cm between the radiator and your body

RF du FCC et IC d'exposition aux dariations: Cet equipment est conforme a l'exposition de FCC et IC rayonnements RF limites e-tablies pour un environment non controle. L'antenne pour ce transmetteur ne doit pas etre meme endroit avec d'autres emetteur sauf conformement a FCC et IC procedures de produits Multi-emetteur

Cet equipment doit etre installe et utilize avec une distance minimale de 20 cm entre le radiateur et votre corps

Yale Locks & Hardware

Product Support Tel 1-855-213-5841 • www.yalehome.com

Yale® and Yale Real Living® are registered trademarks of ASSA ABLOY Residential Group. Other products' brand names may be trademarks or registered trademarks of their respective owners and are mentioned for reference purposes only. © Copyright 2019. All rights reserved. Reproduction in whole or in part without the express written permission of ASSA ABLOY Residential Group is prohibited.