

◆ Test Results :								
Phantom & Hold		Band	Ch.	SAR _{1g} (mW/g)	SAR _{10g} (mW/g)	Power Drift	Power Ref.	
Position	Angle							
RC	0_90_60	GSM850 Band	128	1.15	0.841	0.04	10.8	
RT	0_105_60	GSM850 Band	128	0.499	0.376	0.017	17	
LC	0_90_60	GSM850 Band	128	0.857	0.638	0.024	13.8	
LT	0_105_60	GSM850 Band	128	0.41	0.311	0.016	17.8	
RC	0_90_60	GSM850 Band	190	1.01	0.752	0.021	11.1	
RC	0_90_60	GSM850 Band	251	0.824	0.617	-0.023	9.73	
RC	0_90_60	PCS Band	512	0.685	0.411	0.044	11.3	
RT	0_105_60	PCS Band	512	0.317	0.182	0.126	16.9	
LC	0_90_60	PCS Band	512	0.429	0.279	0.029	11.3	
LT	0_105_60	PCS Band	512	0.321	0.19	0.156	16.4	
Flat	0_90_0	GSM850 Band	128	0.43	0.304	0.037	6.63	
Flat	0_90_0	GPRS 850	128	1.3	0.904	-0.057	13.1	
Flat	0_90_0	GPRS 850	190	1.31	0.934	-0.066	13.8	
Flat	0_90_0	GPRS 850	251	1.14	0.813	-0.0045	13.3	
Flat	0_90_0	PCS Band	512	0.245	0.147	-0.053	7.47	
Flat	0_90_0	GPRS PCS	512	0.694	0.415	-0.153	12.8	

- 1 GSM850 RC SAR is greater than 0.8mW/g , therefore the middle and high channels were required.
- 2 GSM850 RT/LT SAR is smaller than 0.8mW/g, therefore the middle and high channels weren't required.
- 3 The RC value is exceed LC for SAR. Therefore we did not test middle and high channels of LC position.
- 4 PCS Head SAR is smaller than 0.8mW/g of all, therefore it is test maximum output channel only.
- 5 GSM850 Flat SAR is smaller than 0.8mW/g, therefore the middle and high channels weren't required.
- 6 GPRS 850 Flat SAR is greater than 0.8mW/g, therefore the Low /middle and High channels were required.
- 7 GSM / GPRS PCS Flat SAR are smaller than 0.8mW/g, therefore it is test maximum output channel only.

KDB 941225 D03