

**Shenzhen Baoan Hantong Electronics Factory**

Application  
For  
Certification

2.4GHz 40 Channel Analog Modulation Cordless Phone with CID

**(FCC ID: OK836267)**

WO# 0104826  
TL/Ann Choy  
July 17, 2001

- The test results reported in this report shall refer only to the sample actually tested and shall not refer or be deemed to refer to bulk from which such a sample may be said to have been obtained.
- This report shall not be reproduced except in full without prior authorization from Intertek Testing Services Limited

FCC ID: OK836267

## **LIST OF EXHIBITS**

### *INTRODUCTION*

*EXHIBIT 1:* General Description

*EXHIBIT 2:* System Test Configuration

*EXHIBIT 3:* Emission Results

*EXHIBIT 4:* Equipment Photographs

*EXHIBIT 5:* Product Labelling

*EXHIBIT 6:* Technical Specifications

*EXHIBIT 7:* Instruction Manual

*EXHIBIT 8:* Security Code Information

# INTERTEK TESTING SERVICES

---

## MEASUREMENT/TECHNICAL REPORT

**Shenzhen Baoan Hantong Electronics Factory - MODEL: 36267, ST88223-4  
FCC ID: OK836267**

This report concerns (check one):      Original Grant       Class II Change

Equipment Type : Cordless Telephone (example : computer, modem, transmitter, etc.)

---

Deferred grant requested per 47 CFR 0.457(d)(1)(ii)?      Yes       No

If yes, defer until : \_\_\_\_\_  
date

Company Name agrees to notify the Commission by: \_\_\_\_\_  
date

of the intended date of announcement of the product so that the grant can be issued on that date.

---

Transition Rules Request per 15.37 ?      Yes       No

If no, assumed Part 15, Subpart C for intentional radiator - the new 47 CFR [10-1-99 Edition] Provision.

---

Report prepared by:

Tommy Leung  
Intertek Testing Services.  
2/F., Garment Centre,  
576 Castle Peak Road,  
Kowloon, Hong Kong.  
Phone :      852-2173-8538  
Fax:          852-2741-1693

# INTERTEK TESTING SERVICES

---

## Table of Contents

1.0	<b><u>General Description</u></b>	2
1.1	Product Description	2
1.2	Related Submittal(s) Grants	3
1.3	Test Methodology	3
1.4	Test Facility	3
2.0	<b><u>System Test Configuration</u></b>	5
2.1	Justification	5
2.2	EUT Exercising Software	5
2.3	Support Equipment List and Description	6
2.4	Equipment Modification	7
3.0	<b><u>Emission Results</u></b>	9
3.1	Field Strength Calculation	10
3.2	Radiated Emission Configuration Photograph - Base Unit	11
3.3	Radiated Emission Data - Base Unit	12
3.4	Radiated Emission Configuration Photograph - Handset	15
3.5	Radiated Emission Data - Handset	16
3.6	Radiated Emission on the bandedge	19
3.7	Line Conducted Configuration Photograph - Base Unit	21
3.8	Line Conducted Emission Data	22
4.0	<b><u>Equipment Photographs</u></b>	25
5.0	<b><u>Product Labelling</u></b>	27
6.0	<b><u>Technical Specifications</u></b>	29
7.0	<b><u>Instruction Manual</u></b>	31
8.0	<b><u>Security Code Information</u></b>	33

# INTERTEK TESTING SERVICES

---

## List of attached file

Exhibit type	File Description	filename
Test Report	Test Report	report.doc
Operation Description	Technical Description	descri.pdf
Test Setup Photo	Radiated Emission for Base	config photos.doc
Test Setup Photo	Radiated Emission for Handset	config photos.doc
Test Report	Emission Plot	emission.pdf
Test Setup Photo	Conducted Emission	config photos.doc
Test Report	Conducted Emission Test Result	conduct.pdf
External Photo	External Photo	external photos.doc
Internal Photo	Internal Photo	internal photos.doc
Block Diagram	Block Diagram	block.pdf
Schematics	Circuit Diagram	circuit.pdf
ID Label/Location	Label Artwork and Location	label.pdf
User Manual	User Manual	manual.pdf
User Manual	FCC Information	fcc information.pdf

**EXHIBIT 1**  
**GENERAL DESCRIPTION**

# INTERTEK TESTING SERVICES

---

## 1.0 General Description

### 1.1 Product Description

The 36267 is 2.4GHz 40 Channel Analog Modulation Cordless Phone with CID. The unit is capable of either tone or pulse dialing. The internal power supply's isolation is accomplished through a power transformer having an adequate dielectric rating. The circuit wiring is consistent under the requirement of part 68.

The handset unit consists of a keypad with twelve standard keys (0,...9,\*,#), 8 function keys (C/B, Calls, Up, Down, Func/Scan, Dir/Save, Edit/Flash, Del/Re/Pa), and one channel switch key. A Talk key is provided to control pick/release telephone line in a toggle base.

The base unit has a page key, which is used to page the handset unit.

The antennas used in base unit and handset are intergal, and the tested sample is a prototype.

The circuit description is saved with filename: descri.pdf

Connection between the device and the telephone network is accomplished through the use of USOC RJ11C in the 2-wire loop calling central office line.

The Model ST-88223-4 is the same as the Model 36267 in hardware aspect. The difference in model number and trade name serves as marketing strategy.

# INTERTEK TESTING SERVICES

---

## 1.2 Related Submittal(s) Grants

This is an Application for Certification of a cordless telephone system. Two transmitters are included in this Application. This specific report details the emission characteristics of each transmitter. The receivers are subject to the verification authorization process, in accordance with 15.101(b). A verification report has been prepared for the receiver sections of each device. The device is also subject to Part 68 Registration.

## 1.3 Test Methodology

Both AC mains line-conducted and radiated emission measurements were performed according to the procedures in ANSI C63.4 (1992). All measurements were performed in Open Area Test Sites. Preliminary scans were performed in the Open Area Test Sites only to determine worst case modes. All Radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the **"Justification Section"** of this Application.

## 1.4 Test Facility

The open area test site and conducted measurement facility used to collect the radiated data is located at Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong. This test facility and site measurement data have been fully placed on file with the FCC.

---

**INTERTEK TESTING SERVICES**

---

**EXHIBIT 2**  
**SYSTEM TEST CONFIGURATION**

## 2.0 System Test Configuration

### 2.1 Justification

For emission testing, the equipment under test (EUT) was configured for testing in a typical fashion (as a customer would normally use it). During testing, all cables were manipulated to produce worst case emissions. The handset was powered by a fully charged battery.

For the measurements, the EUT is attached to a cardboard box if necessary and placed on the wooden turntable. If the base unit attaches to peripherals, they are connected and operational (as typical as possible). The handset is remotely located as far from the antenna and the base as possible to ensure full power transmission from the base. Else, the base is wired to transmit full power without modulation.

The signal is maximized through rotation and placement in the three orthogonal axes. The antenna height and polarization are varied during the search for maximum signal level. The antenna height is varied from 1 to 4 meters. Detector function is in peak mode. Radiated emissions are taken at three meters unless the signal level is too low for measurement at that distance. If necessary, a pre-amplifier is used and/or the test is conducted at a closer distance.

All readings are extrapolated back to the equivalent three meter reading using inverse scaling with distance. Analyzer resolution is 100 kHz or greater. All emissions greater than 20 dB $\mu$ V/m are recorded.

Radiated emission measurement were performed from 30 MHz to tenth harmonics.

### 2.2 EUT Exercising Software

The EUT exercise program used during radiated and conducted testing was designed to exercise the various system components in a manner similar to a typical use.

For emissions testing, the units were setup to transmit continuously to simplify the measurement methodology. Care was taken to ensure proper power supply voltages during testing.

---

## INTERTEK TESTING SERVICES

---

### 2.3 Support Equipment List and Description

The FCC ID's for all equipment, plus descriptions of all cables used in the tested system (included inserted cards, which have grants) are:

*HARDWARE:*

The unit was operated standalone. An AC adapter (provided with the unit) was used to power the device. Its description is listed below.

- (1) AC adapter with two meter unshielded power cord permanently affixed.

*CABLES:*

- (1) Telecommunication cable with RJ11C connectors (1m, unshielded), terminated

*OTHERS:*

There are no special accessories necessary for compliance of this product.

## INTERTEK TESTING SERVICES

---

### 2.4 Equipment Modification

Any modifications installed previous to testing by Shenzhen Baoan Hantong Electronics Factory will be incorporated in each production model sold/leased in the United States.

No modifications were installed by ETL Division, Intertek Testing Services Hong Kong Ltd.

All the items listed under section 2.0 of this report are confirmed by:

*Confirmed by:*

*Tommy Leung  
Assistant Supervisor  
Intertek Testing Services  
Agent for Shenzhen Baoan Hantong Electronics Factory*



\_\_\_\_\_  
Signature

\_\_\_\_\_  
July 26, 2001  
\_\_\_\_\_  
Date

---

**INTERTEK TESTING SERVICES**

---

**EXHIBIT 3**  
**EMISSION RESULTS**

## INTERTEK TESTING SERVICES

---

### 3.0 Emission Results

Data is included of the worst case configuration (the configuration which resulted in the highest emission levels). A sample calculation, configuration photographs and data tables of the emissions are included.

### 3.1 Field Strength Calculation

The field strength is calculated by adding the Antenna Factor and Cable Factor, and subtracting the Amplifier Gain (if any) from the measured reading. The basic equation with a sample calculation is as follows:

$$FS = RA + AF + CF - AG$$

where  $FS$  = Field Strength in  $\text{dB}\mu\text{V}/\text{m}$

$RA$  = Receiver Amplitude (including preamplifier) in  $\text{dB}\mu\text{V}$

$CF$  = Cable Attenuation Factor in dB

$AF$  = Antenna Factor in dB

$AG$  = Amplifier Gain in dB

In the following table(s), the reading shown on the data table reflects the preamplifier gain. An example for the calculations in the following table is as follows:-

$$FS = RR + LF$$

where  $FS$  = Field Strength in  $\text{dB}\mu\text{V}/\text{m}$

$RR$  =  $RA - AG$  in  $\text{dB}\mu\text{V}$

$LF$  =  $CF + AF$  in dB

Assume a receiver reading of 52.0  $\text{dB}\mu\text{V}$  is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB is added. The amplifier gain of 29 dB is subtracted, giving a field strength of 32  $\text{dB}\mu\text{V}/\text{m}$ . This value in  $\text{dB}\mu\text{V}/\text{m}$  was converted to its corresponding level in  $\mu\text{V}/\text{m}$ .

$$RA = 52.0 \text{ dB}\mu\text{V}/\text{m}$$

$$AF = 7.4 \text{ dB}$$

$$CF = 1.6 \text{ dB}$$

$$AG = 29.0 \text{ dB}$$

$$FS = RR + LF$$

$$FS = 23 + 9 = 32 \text{ dB}\mu\text{V}/\text{m}$$

$$RR = 23.0 \text{ dB}\mu\text{V}$$

$$LF = 9.0 \text{ dB}$$

$$\text{Level in } \mu\text{V}/\text{m} = \text{Common Antilogarithm } [(32 \text{ dB}\mu\text{V}/\text{m})/20] = 39.8 \mu\text{V}/\text{m}$$

## **INTERTEK TESTING SERVICES**

---

### **3.2 Radiated Emission Configuration Photograph - Base Unit**

**Worst Case Radiated Emission**

**at 801.667 MHz**

For electronic filing, the worst case radiated emission configuration photographs are saved with filename: config photos.doc

## INTERTEK TESTING SERVICES

---

### 3.3 Radiated Emission Data - Base Unit

The data on the following pages list the significant emission frequencies, the limit and the margin of compliance.

Judgement : Passed by 7.5 dB

\*\*\*\*\*

#### **TEST PERSONNEL:**



---

*Tester Signature*

Yvonne Leung, Engineer

*Typed/Printed Name*

July 26, 2001

*Date*

# INTERTEK TESTING SERVICES

---

Company: Shenzhen Baoan Hantong Electronics Factory  
Model: 36267  
Mode : TX-Channel 1

Date of Test: May 14, 2001

Table 1, Base unit

## Radiated Emissions

Polarity	Frequency (M Hz)	Reading (dB $\mu$ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB $\mu$ V/m)	Limit (dB $\mu$ V/m)	Margin (dB)
V	2403.050	82.7	29.1	34	77.8	94	-16.2
H	801.017	33.1	21.3	16	38.4	46	-7.6
H	*1602.033	44.7	26.5	34	37.2	54	-16.8
H	3204.067	39.4	31.4	34	36.8	54	-17.2
H	*4005.083	36.0	34.2	34	36.2	54	-17.8
H	*4806.100	36.1	34.0	34	36.1	54	-17.9

NOTES: 1. Peak Detector data

2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
3. Negative value in the margin column shows emission below limit.
4. Horn antenna and average detector are used for the emission over 1000MHz.

\* Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: Yvonne Leung

# INTERTEK TESTING SERVICES

---

Company: Shenzhen Baoan Hantong Electronics Factory  
Model: 36267  
Mode : TX-Channel 40

Date of Test: May 14, 2001

Table 2, Base unit

## Radiated Emissions

Polarity	Frequency (M Hz)	Reading (dB $\mu$ V )	Antenna Factor (dB )	Pre-Amp Gain (dB )	Net at 3m (dB $\mu$ V /m )	Limit (dB $\mu$ V /m )	Margin (dB )
V	2405.000	81.8	29.1	34	76.9	94	-17.1
H	801.667	33.2	21.3	16	38.5	46	-7.5
H	*1603.333	45.4	26.5	34	37.9	54	-16.1
H	3206.667	40.2	31.4	34	37.6	54	-16.4
H	*4008.333	36.9	34.2	34	37.1	54	-16.9
H	*4810.000	36.9	34.0	34	36.9	54	-17.1

NOTES: 1. Peak Detector data

2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
3. Negative value in the margin column shows emission below limit.
4. Horn antenna and average detector are used for the emission over 1000MHz.

\* Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: Yvonne Leung

## **INTERTEK TESTING SERVICES**

---

### **3.4 Radiated Emission Configuration Photograph - Handset**

**Worst Case Radiated Emission**

**at 824.667 MHz**

For electronic filing, the worst case radiated emission configuration photographs are saved with filename: cofing photos.doc

## INTERTEK TESTING SERVICES

---


### 3.5 Radiated Emission Data - Handset

The data on the following pages list the significant emission frequencies, the limit and the margin of compliance.

Judgement : Passed by 3.4 dB

\*\*\*\*\*

#### ***TEST PERSONNEL:***



---

*Tester Signature*

Yvonne Leung, Engineer

*Typed/Printed Name*

---

July 26, 2001

*Date*

# INTERTEK TESTING SERVICES

---

Company: Shenzhen Baoan Hantong Electronics Factory  
Model: 36267  
Mode : TX-Channel 1

Date of Test: May 14, 2001

Table 3, Handset

## Radiated Emissions

Polarity	Frequency (M Hz)	Reading (dB $\mu$ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB $\mu$ V/m)	Limit (dB $\mu$ V/m)	Margin (dB)
V	2474.000	85.4	29.1	34	80.5	94	-13.5
V	824.667	37.3	21.3	16	42.6	46	-3.4
V	1649.333	55.6	26.5	34	48.1	54	-5.9
V	3298.667	43.1	31.4	34	40.5	54	-13.5
V	*4123.333	38.8	34.2	34	39.0	54	-15.0
V	*4948.000	38.4	34.0	34	38.4	54	-15.6

NOTES: 1. Peak Detector data

2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
3. Negative value in the margin column shows emission below limit.
4. Horn antenna and average detector are used for the emission over 1000MHz.

\* Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: Yvonne Leung

# INTERTEK TESTING SERVICES

---

Company: Shenzhen Baoan Hantong Electronics Factory  
Model: 36267  
Mode : TX-Channel 40

Date of Test: May 14, 2001

Table 4, Handset

## Radiated Emissions

Polarity	Frequency (M Hz)	Reading (dB $\mu$ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB $\mu$ V/m)	Limit (dB $\mu$ V/m)	Margin (dB)
V	2475.950	85.5	29.1	34	80.6	94	-13.4
V	825.317	36.7	21.8	16	42.5	46	-3.5
V	1650.633	55.9	26.5	34	48.4	54	-5.6
V	3301.267	43.2	31.4	34	40.6	54	-13.4
V	*4126.583	39.0	34.2	34	39.2	54	-14.8
V	*4951.900	39.0	34.0	34	39.0	54	-15.0

NOTES: 1. Peak Detector data

2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
3. Negative value in the margin column shows emission below limit.
4. Horn antenna and average detector are used for the emission over 1000MHz.

\* Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: Yvonne Leung

**3.6 Radiated Emission on the bandedge**

From the following plots, they show that the fundamental emissions are confined in the specified band and they are at least 50 dB below the carrier level at band edge (2400.0 and 2483.5 MHz). It meets the requirement of section 15.249(c).

**Emission Plot**

For electronic filing, the emission plots are saved with filename: emission.pdf

## **INTERTEK TESTING SERVICES**

---

### **3.7 Line Conducted Configuration Photograph - Base Unit**

**Worst Case Line-Conducted Configuration**

**at 28.635MHz**

For electronic filing, the worst case line conducted configuration photographs are saved with filename: config photos.doc

## INTERTEK TESTING SERVICES


---

### 3.8 Line Conducted Emission Data

The data on the following pages list the significant emission frequencies, the limit, and the margin of compliance.

Judgement : Passed by 19.7 dB

#### ***TEST PERSONNEL:***



---

*Tester Signature*

Yvonne Leung, Engineer

*Typed/Printed Name*

July 26, 2001

*Date*

## **INTERTEK TESTING SERVICES**

---

Company: Shenzhen Baoan Hantong Electronics Factory  
Model: 36267

Date of Test: May 14, 2001

### **Conducted Emissions**

For electronic filing, the conducted emission test result is saved with filename:  
conduct.pdf

**EXHIBIT 4**  
**EQUIPMENT PHOTOGRAPHS**

## INTERTEK TESTING SERVICES

---

### 4.0 Equipment Photographs

For electronic filing, the photographs are saved with filename: external photos.doc & internal photos.doc

**EXHIBIT 5**  
**PRODUCT LABELLING**

**5.0 Product Labelling**

For electronic filing, the FCC ID label artwork and location is saved with filename:  
label.pdf

**EXHIBIT 6**  
**TECHNICAL SPECIFICATIONS**

**6.0 Technical Specifications**

For electronic filing, the block diagram and circuit diagram are saved with filename: block.pdf and circuit.pdf respectively.

**EXHIBIT 7**  
**INSTRUCTION MANUAL**

## INTERTEK TESTING SERVICES

---

### 7.0 Instruction Manual

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf

Please note that the required FCC Information to the User is saved with filename: fcc information.pdf.

This manual will be provided to the end-user with each unit sold/leased in the United States.

**EXHIBIT 8**  
**SECURITY CODE INFORMATION**

### 8.0 Security code information

The telephone has an internal security code with 65,536 possible combinations. Each time you pick up the HANDSET, the code is randomly set to a new combination.

Communication between HANDSET and BASE UNIT may not be possible in any of the following situation:

1. After a power failure.
2. After relocation the BASE UNIT by disconnecting the AC adaptor.
3. After replacing the HANDSET battery.

To reset, place the HANDSET on the BASE UNIT for 2 to 5 seconds.