

SETUP YOUR PC AND USB PHONE

1. Turn on your PC. Insert the installation disk to your computer.
2. Go to your CD-Rom directory and double click on the installation icon. An installation wizard will guide you through the installation.
3. When finished, plugged in the USB base to your computer's USB slot and login to your SKYPE account.
4. Double click on the shortcut icon the software has created on your desktop; the program will start searching for SKYPE and the base.
5. When the program has finished loading, the icon will be minimized and will be hidden on the lower right corner of your desktop.
6. Place the 2 rechargeable NiMH AAA batteries (rated 1.2 V 750 mAh), observing their polarities, into the battery compartment on the handset.
7. Plug the charger adapter to the proper mains wall outlet (check the rating label on the adapter).
8. Place the handset on the charger unit and let the batteries charge for full 14 hours before using it for the first time.

KEYPAD FUNCTIONS



Soft Keys

The functions of the soft keys are displayed right above the soft keys.



Rock Key

Use to navigate the menus.



Talk & Recall Key

Use to make, to receive calls, and to send flash signal.



End & On/Off Key

Use to end a call, to exit menus, and to switch the phone on/off.



Star & Ringer Off Key

Use to turn the ringer on/off.



Pound, Key lock & Pause Key

Use to enter a pause and to lock the keypad.



Intercom Key

Use to enter the intercom menu.



Launch Key

Use to launch the contact list.



Calls Key

Use to enter the call records menu.



Page Key

Use to page the handset and to send registration signal.

USING THE PHONE

Make a SkypeOut Call to a Fixed Line

1. Press key. Dial the number you want. When making SKYPEOUT calls, it is necessary to dial the 00 as a prefix of the phone number you are calling. For example, North America: 00-1-905-5251258 or international: 00-852-25447555
2. You can also predial the number while in standby mode and press the key to connect the call. To add a pause to the number you are predialing, press and hold # key.

Make a Call from Skype Contact List

1. Press key to launch the contact list during standby.
2. Press Up and Down to select the contact to call. Press to call the contact.

Answer / End a Call

1. Press key to answer a call when the phone is ringing and icon is flashing on the display.
2. Press key or place the phone on the charger to end a call.

Redial a Number

1. Press key to seize a line. Press REDIAL to show and dial the last dialed number; or
2. Press LEFT or RIGHT during standby. The redial list appears and presses UP/DOWN to select the number. Press key to dial the selected number.

Save a Number in the Phonebook

1. Press NAMES. Select the phonebook (private or shared) you want to save a number.
2. Select ADD ENTRY. Enter the name and the number for the record.
3. Press SAVE to save the record.

Manage Phonebook records

1. You can view, edit, copy, and assign quick dialing to each of your phonebook records.
2. Press NAMES. Select PRIVATE or SHARED phonebook.
3. Select VIEW to edit phone record or copy phone record to either private or shared phonebook.
4. You can select QUICK DIAL to assign a quick dialing number, select STATUS to check the phonebook status, and select DELETE ALL to delete all private phonebook records.
5. To make a quick dial call, you can just press and hold a digit key that you have set a quick dial number to and your call is made.

Turn off Ringer Volume

1. Press SILENT when the phone is ringing to turn off the ringer for the call; or
2. Press and hold key when the phone is in standby to turn off the ringer for all the calls.

Adjust the Volume of the Caller's Voice

1. Press UP/DOWN to adjust the volume during a call.

Change Online Status

1. Press MENU. Press UP/DOWN to select IM CONFIG.
2. Select USER STATUS to change your online status. Press OK to confirm.

Privacy of communications may not be ensured when using this telephone.

COMPLIANCE INFORMATION

This equipment has been tested and found to comply with the limits for a class B digital device, pursuant to Part 15 of the FCC Rules and Specification ICES-003 of Industry Canada. Operation is subject to the following two conditions: (1) This device may not cause interference, and (2) This device must accept any interference, including interference that may cause undesired operation of the device. This device complies also with RSS-213 of Industry Canada.

Notice: The term "IC:" before the certification number signifies that Industry Canada technical specifications were met. This certification means that the equipment meets certain radio communications and operational requirements.

Interference

This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

1. Re-orient or relocate the receiving antenna.
2. Increase the distance between the equipment and receiver.
3. Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
4. Consult the dealer or an experienced radio/TV technician for help.

Caution

Users should ensure for their own protection that the electrical ground connections of the power utility, telephone lines and internal metallic water pipe system, if present, are connected together. This precaution may be particularly important in rural areas.

Do not attempt to repair or modify this equipment.

Repairs to certified equipment should be made by an authorized maintenance facility designated by the supplier. Any repairs or alterations made by the user to the equipment may render the equipment void in product warranty and compliance. This could also void the user's authority to operate the equipment.

RF Radiation Exposure

This equipment complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with a minimum distance of 20 centimeters between the radiator and your body. For body worn operation, this phone has been tested and meets the FCC RF exposure guidelines when used with the belt clip supplied with this product. Use of other accessories may not ensure compliance with FCC RF exposure guidelines. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

Noise

Electrical pulse noise is present at one time or another. This is most intense during electrical storms. Certain kinds of electrical equipment, such as light dimmers, fluorescent bulbs, motors, fans, etc., also generate pulse noise. Because radio frequencies are susceptible to this, you may on occasion hear pulse noise through the receiver. This is usually only a minor annoyance and should not be interpreted as a defect of the unit.

This telephone is not designed for making emergency telephone calls when the power fails. Make alternative arrangements for access to emergency services.



IMPORTANT SAFETY INFORMATION

BEFORE USING YOUR TELEPHONE EQUIPMENT, BASIC SAFETY PRECAUTIONS SHOULD ALWAYS BE FOLLOWED TO REDUCE THE RISK OF FIRE, ELECTRIC SHOCK AND INJURY, INCLUDING THE FOLLOWING.

- Read and follow all warnings and instructions marked on the product.
- Do not use this product near water, laundry tub, in a wet basement, or near a swimming pool.
- Do not place this product on an unstable table. The product may fall and be damaged.
- This product should never be placed near or over a radiator or heat register.
- This product should be operated only from the type of power source indicated on the label.
- Do not allow anything to rest on the power cord. Do not locate this product where the cord will be abused by persons walking on it.
- Do not overload wall outlets and extension cords as this can result in the risk of fire or electric shock.
- Avoid using a telephone during an electrical storm. There may be a remote risk of electric shock from lightning.
- Do not use this product to report a gas leak in the vicinity of the leak.
- Do not use this product near intensive care medical equipment or by persons with pacemakers.
- Due to the radio signals between base station and handset, wearers of hearing aids may experience interference in the form of a humming noise.

BATTERIES

- Use only the battery type listed in the instruction manual. Do not use lithium batteries or non-rechargeable batteries that may damage the handset and charger.
- Do not dispose of the battery in a fire, as they can explode.
- Do not open or mutilate the battery. Released electrolyte is corrosive and can cause damage to the eyes or skin. It can be toxic if swallowed.
- Avoid contact with metal objects when handling the battery. These objects could short out the batteries or cause the conductor to overheat resulting in burns.
- Do not attempt to recharge the battery cell by heating it. Sudden release of battery electrolyte can cause burns or irritation to the eyes or skin.
- Observe the proper polarity, or direction, of any battery. Reverse insertion of the battery cell can result in leakage or explosion.
- Remove the battery cells if you do not plan to use the product for several months at a time.
- Discard any "dead" batteries because they are likely to leak into the product.
- Do not store this product or the battery in a high temperature area. Battery stored in a freezer or refrigerator should be protected from condensation during storage and defrosting. Battery should be stabilized at room temperature before using.
- Your battery is rechargeable and can be recycled once it outlives its usefulness. Depending upon your local and state law, it might be illegal to dispose of this battery into a municipal waste system. Check with your local solid waste company for more information on your recycling options for the battery cells.

SAVE THESE INSTRUCTIONS