

Qualcomm Atheros Modular Certification

**Instructions to OEM
Integrators for AR5B22 in
Acer Humming Bird
FCC ID: PPD-AR5B22**

March 2012



ATHEROS®

Page 1 of 12

© 2000–2009 by Atheros Communications, Inc. All rights reserved.

Atheros®, Atheros Driven®, Atheros XR®, Driving the Wireless Future®, ROCm®, Super AG®, Super G®, Total 802.11n®, and Wake on Wireless® are registered by Atheros Communications, Inc. Atheros SST™, Signal-Sustain Technology™, the Air is Cleaner at 5-GHz™, XSPAN™, Wireless Future. Unleashed Now.™, and 5-UP™ are trademarks of Atheros Communications, Inc. The Atheros logo is a registered trademark of Atheros Communications, Inc. All other trademarks are the property of their respective holders.

Notice

The information in this document has been carefully reviewed and is believed to be accurate. Nonetheless, this document is subject to change without notice, and Atheros Communications, Inc. (Atheros) assumes no responsibility for any inaccuracies that may be contained in this document, and makes no commitment to update or to keep current the contained information, or to notify a person or organization of any updates. Atheros reserves the right to make changes, at any time, in order to improve reliability, function or design and to attempt to supply the best product possible. Atheros does not represent that products described herein are free from patent infringement or from any other third party right.

No part of this document may be reproduced, adapted or transmitted in any form or by any means, electronic or mechanical, for any purpose, except as expressly set forth in a written agreement signed by Atheros. Atheros or its affiliates may have patents or pending patent applications, trademarks, copyrights, maskwork rights or other intellectual property rights that apply to the ideas, material and information expressed herein. No license to such rights is provided except as expressly set forth in a written agreement signed by Atheros.

ATHEROS MAKES NO WARRANTIES OF ANY KIND WITH REGARD TO THE CONTENT OF THIS DOCUMENT. IN NO EVENT SHALL ATHEROS BE LIABLE FOR DIRECT, INDIRECT, SPECIAL, INCIDENTAL SPECULATORY OR CONSEQUENTIAL DAMAGES ARISING FROM THE USE OR INABILITY TO USE THIS PRODUCT OR DOCUMENTATION, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. IN PARTICULAR, ATHEROS SHALL NOT HAVE LIABILITY FOR ANY HARDWARE, SOFTWARE, OR DATA TRANSMITTED OR OTHERWISE USED WITH THE PRODUCT, INCLUDING THE COSTS OF REPAIRING, REPLACING, INTEGRATING, INSTALLING OR RECOVERING SUCH HARDWARE, SOFTWARE OR DATA. ATHEROS SPECIFICALLY DISCLAIMS THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE AS THEY MIGHT OTHERWISE APPLY TO THIS DOCUMENT AND TO THE IDEAS, MATERIAL AND INFORMATION EXPRESSED HEREIN.

Revision History

Revision	Revision Description of Changes
March 8, 2012	Initial release
March 15, 2012	Correct Model Number

Introduction

This document describes mandatory steps required by the OEM integrator when designing and manufacturing any host PC system utilizing this Atheros radio module.

Also refer to the Atheros Regulatory Compliance Guide available on the Atheros customer support site and from the Atheros customer support contact person.

This document lists the mandatory responsibilities and actions of the OEM integrator.

Failure to comply with all requirements and conditions in this document may result in non-compliance of the host PC with FCC rules and invalidate the Atheros FCC certification for the module.

This guide applies to this Client modules that act under control of an Access Point.

Max. average total output power

Mode	Channel	Frequency	Average power (dBm)
		(MHz)	Data Rate (bps)
			1M
802.11b_Ant 1	CH 01	2412 MHz	17.59
	CH 06	2437 MHz	19.59
	CH 11	2462 MHz	18.66
Mode	Channel	Frequency	Average power (dBm)
		(MHz)	Data Rate (bps)
			6M
802.11g_Ant 1	CH 01	2412 MHz	16.09
	CH 06	2437 MHz	19.68
	CH 11	2462 MHz	15.87
Ant 0+1			
Mode	Channel	Frequency	Average power (dBm)
		(MHz)	Data Rate (bps)
			1M
802.11b_Ant 0+1	CH 01	2412 MHz	19.57
	CH 06	2437 MHz	19.59
	CH 11	2462 MHz	19.7
Mode	Channel	Frequency	Average power (dBm)
		(MHz)	Data Rate (bps)
			6M
802.11g_Ant 0+1	CH 01	2412 MHz	15.52
	CH 06	2437 MHz	19.38
	CH 11	2462 MHz	15.29
Mode	Channel	Frequency	Average power (dBm)
		(MHz)	Data Rate (bps)
			MCS0
802.11n 20M_Ant 0+1	CH 01	2412 MHz	15.49
	CH 06	2437 MHz	19.59
	CH 11	2462 MHz	14.36
Mode	Channel	Frequency	Average power (dBm)
		(MHz)	Data Rate (bps)
			MCS0
802.11n 40M_Ant 0+1	CH 03	2422 MHz	12.03
	CH 06	2437 MHz	16.72
	CH 09	2452 MHz	13.60
Ant 1			
Mode	Channel	Frequency	Average Power (dBm)
		(MHz)	Data Rate (bps)

			6M
802.11a_Ant 1	CH 036	5180 MHz	14.5
	CH 040	5200 MHz	14.09
	CH 044	5220 MHz	14.31
	CH 048	5240 MHz	14.21
	CH 052	5260 MHz	11.53
	CH 056	5280 MHz	11.61
	CH 060	5300 MHz	11.82
	CH 064	5320 MHz	11.53
	CH 100	5500 MHz	14.5
	CH 104	5520 MHz	14.62
	CH 108	5540 MHz	14.63
	CH 112	5560 MHz	16
	CH 116	5580 MHz	16.13
	CH 120	5600 MHz	15.86
	CH 124	5620 MHz	15.75
	CH 128	5640 MHz	15.9
	CH 132	5660 MHz	16.1
	CH 136	5680 MHz	15.92
	CH 140	5700 MHz	13.66
	CH 149	5745 MHz	13.86
	CH 153	5765 MHz	13.19
	CH 157	5785 MHz	14.64
	CH 161	5805 MHz	13.65
	CH 165	5825 MHz	14.82
Ant 0+1			
Mode	Channel	Frequency	Average Power (dBm)
		(MHz)	Data Rate (bps)
			6M
802.11a_Ant 0+1	CH 036	5180 MHz	14.35
	CH 040	5200 MHz	14.21
	CH 044	5220 MHz	14.31
	CH 048	5240 MHz	14.20
	CH 052	5260 MHz	16.77
	CH 056	5280 MHz	17.25
	CH 060	5300 MHz	17.33
	CH 064	5320 MHz	17.3
	CH 100	5500 MHz	14.33
	CH 104	5520 MHz	14.25
	CH 108	5540 MHz	14.32
	CH 112	5560 MHz	15
	CH 116	5580 MHz	15.37
	CH 120	5600 MHz	joyce
	CH 124	5620 MHz	15.27
	CH 128	5640 MHz	15.1
	CH 132	5660 MHz	15.16
	CH 136	5680 MHz	15.34
	CH 140	5700 MHz	13.6
	CH 149	5745 MHz	14.9

	CH 153	5765 MHz	13.21
	CH 157	5785 MHz	15.33
	CH 161	5805 MHz	13.52
	CH 165	5825 MHz	15.68
Mode	Channel	Frequency	Average Power (dBm)
		(MHz)	Data Rate (bps)
			MCS0
802.11n 20M (5G)_Ant 0+1	CH 036	5180 MHz	13.89
	CH 040	5200 MHz	14.05
	CH 044	5220 MHz	13.79
	CH 048	5240 MHz	13.84
	CH 052	5260 MHz	16.99
	CH 056	5280 MHz	16.78
	CH 060	5300 MHz	16.96
	CH 064	5320 MHz	17.12
	CH 100	5500 MHz	15.41
	CH 104	5520 MHz	15.64
	CH 108	5540 MHz	15.64
	CH 112	5560 MHz	18.35
	CH 116	5580 MHz	18.53
	CH 120	5600 MHz	18.28
	CH 124	5620 MHz	18.44
	CH 128	5640 MHz	17.68
	CH 132	5660 MHz	17.62
	CH 136	5680 MHz	17.76
	CH 140	5700 MHz	15.28
	CH 149	5745 MHz	16.21
	CH 153	5765 MHz	13.93
	CH 157	5785 MHz	16.66
	CH 161	5805 MHz	14.26
	CH 165	5825 MHz	16.69
Mode	Channel	Frequency	Average Power (dBm)
		(MHz)	Data Rate (bps)
			MCS0
802.11n 40M(5G)_Ant 0+1	CH 038	5190 MHz	12.34
	CH 046	5230 MHz	16.50
	CH 054	5270 MHz	17.28
	CH 062	5310 MHz	12.59
	CH 102	5510 MHz	11.60
	CH 118	5590 MHz	15.71
	CH 134	5670 MHz	14.91
	CH 151	5755 MHz	17.07
	CH 159	5795 MHz	16.73

Allowed Antennas to be used with the Radio Module

The Integrator must request from Atheros sales or regulatory contact person the current list of allowable antennas for use with the specific radio module. This information is not available on the public FCC database but will be provided by Atheros. Atheros will provide a table of antenna type(s) models, cable lengths, and peak gain in each band.

Generally, the list will include Omni-directional Inverted-F (PIFA) and stamped metal/film antennas for use inside laptops. In some cases, dipole antenna types may be included in the available list. Peak gain including cable losses are quoted in the table provided by Atheros.

Use of any of the antennas in the list (identical or equivalent antenna with lower gain, dimensions and cable lengths) is acceptable in the host device, without any further FCC testing or submission.

However, use of an antenna that is higher gain than those on the list or is a Different Type, requires additional testing and submission to the FCC. Therefore, antennas with higher gain or different type than specified by Atheros may not be used with the Atheros module until new testing and reporting is completed.

You must contact the Atheros Regulatory Group to report any higher gain or new antenna type to be used with the module.

Antenna Placement

This module has been certified by FCC as single module approval with the following restrictions:

- The most conservative antenna-to-user separation distance shall be greater than 4.6mm to end user or near-by person. 4.6mm physical separation distance is measured by positioning the display section of notebook/Netbook/Laptop computers perpendicular to the keyboard section. Measure the distance from the nearest point of antenna to the bottom of host.
- Consult with Atheros to determine the allowable rotational orientations for vertical and horizontal antenna installation in applicable host devices.
- When antenna is installed in the typical notebook/Netbook/laptop computer platform, the antenna cable shall be positioned away from antenna elements to conform to configuration tested for compliance.
- When the antennas are installed in the display section of notebook/Netbook/Laptop computer platform, the display section shall not have metallic components and material that can influence or change the operating and exposure characteristics of the antennas.

If any one of condition listed above can not comply, please consult with Atheros regulatory contact person to determine the applicable equipment authorization procedure before marketing the host device.

Simultaneous transmission of Radio Module with Other Integrated or Plug-In Radios

Based upon FCC Knowledge Database publication number 616217 D03 (Supplement) <https://fjallfoss.fcc.gov/kdb/GetAttachment.html?id=30257>, when there are multiple radios installed in a host device, RF exposure transmitting assessment shall be performed to determine the necessary application and test requirements. Certain criteria can be used to determine the requirement for simultaneous SAR evaluation and whether Class I or Class II permissive change may apply. A brief summary of the procedures is provided below. OEM integrators must consult the actual FCC KDB 616217 Supplement document for details:

- Identify all possible combinations of simultaneous transmission configurations for all transmitters and antennas installed in the display screen and keyboard of the intended host computer configurations and provide the following information:
 - Antenna-to-antenna separation distance
 - Antenna-to-user separation distance
- Transmitters/antennas operating from external card slots and/or connectors of the host computers must be more than 5 cm from any simultaneous transmitting antennas
- If simultaneous transmission radio/ module is installed in the host as portable device (< 20 cm to the body of user) , determine the highest 1-g SAR value of each portable radio module for applicable simultaneous transmission operating modes and configurations.
- If simultaneous radio is installed in the host as mobile device (> 20 cm to the body of user) , determine the MPE (power density) according to the highest output power, , antenna gain and antenna-to-user separation distance in each frequency band.
- Determine the antenna to antenna separation distances as required for the conditions below
 - a) When the $[(\sum \text{of the highest measured 1-g SAR for each portable transmitter/antenna included in the simultaneous transmission configuration}) / 1.6 \text{ W/kg}] + \sum \text{of} [(\text{the highest MPE for each mobile transmitter/ antenna included in the simultaneous transmission configuration}) / (\text{the corresponding MPE limit})] < 1$; (where: $\sum$ excludes antennas that do not require SAR evaluation, the corresponding MPE limits based upon frequency band can be found at table 1 of section 1.1310 of CFR 47: <http://ecfr.gpoaccess.gov/cgi/t/text/text-idx?c=ecfr&sid=788a1f4d7395e22ffa71dc3905fb2f10&rgn=div8&view=text&node=47:1.0.1.1.2.9.193.10&idno=47>)
 - or
 - b) For antennas included in the simultaneous transmission configuration that require SAR evaluation, when the separation distance between each antenna pair is
 - i) greater than $5 \cdot [(\text{SAR1} + \text{SAR2}) / 1.6]^{1.5}$ cm, rounded to the nearest cm, and
 - ii) the $\sum \text{of} [(\text{the highest MPE for each mobile transmitter/ antenna included in the simultaneous transmission configuration}) / (\text{the corresponding MPE limit})] < 1$

By satisfying condition a) or b) as listed above, simultaneous SAR evaluation is not required. Incorporation of this Atheros module in conjunction with other certified transmitters in a qualified host device can be addressed as a Class I permissive change. However, the simultaneous transmission conditions must be fully documented in Class I permissive change report as described in KDB 616217 Supplement..

For each simultaneous transmission configuration which does not meet the conditions described above, submit an inquiry to Atheros Regulatory Group or equivalent responsible party of the radio module to evaluate additional FCC evaluation or application requirements.

Required Information to be documented in the Class I permissive change report

A summary of the information to be included in the Class I permissive change report is listed below. OEM integrators must consult the FCC KDB 616217 Supplement document for details.

1. FCC ID of all transmitters, maximum average conducted output power in each transmission mode and frequency band, operating configurations and exposure conditions approved for the individual transmitters.
2. Applicable antenna locations for all host configurations identified in diagrams, drawings and/or photos, including the range of antenna-to-user and antenna-to-antenna separation distances to support the required test reduction and exclusion analysis or SAR test configurations (The closest distance between each antenna and the user and the closest distance between individual antennas should be used.)
3. The type and physical dimensions of antennas incorporated in the intended host configurations
4. Antenna gain specified by the antenna manufacturer for antennas qualified for mobile exposure conditions
5. Other relevant information and restrictions required by the equipment certifications of individual transmitters, including antenna changes
6. The range of applicable physical, mechanical and electrical variations of host computer configurations supported by the test results in all relevant equipment certification.

Required Host System Labeling

FCCID and Industry Canada ID

The Integrator must affix the Atheros module's FCCID on the module. Also, when the module is not visible when installed in the host system, an additional label must appear on the outside of the host system visible to the user. Industry Canada (IC) labeling is only required on the module.

Example FCC & Canada IDs to appear on module:

FCC ID: PPD-AR5B22

IC: 4104A- AR5B22

Example wording also to appear somewhere on the outside of the host system visible to the end user:

Contains FCC ID: PPD- AR5B22

FCC Logo

The FCC logo shown below must appear on the host system signifying declared compliance of the system with FCC digital emissions rules.



Required User Manual Wording for Host PC System

The FCC requires the following text (or equivalent) included in the user documentation provided to the end user:

Example text which can be used by the Integrator in the end user instructions are:

Compliance Information:

The OEM integrator must incorporate appropriate operating instructions for all the transmitters and antennas installed in the host device with respect to any restrictions required for the individual transmitter certified by the FCC. Additional user instructions for meeting RF exposure requirements are not necessary for this Atheros module when installed in typical laptop/notebook/netbook computers provided the requirements in this document and KDB 616217 Supplement are fully satisfied.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This product does not contain any user serviceable components. Any unauthorized product changes or modifications will invalidate warranty and all applicable regulatory certifications and approvals.

FCC Part 15 Digital Emissions Compliance

We [System Manufacturer Name, Address, Telephone], declare under our sole responsibility that the product [System Name] complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

WARNING: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from the one the receiver is connected to.
- Consult the dealer or an experienced radio/TV technician for help.

The user may find the following booklet prepared by the Federal Communications Commission helpful:

The Interference Handbook

This booklet is available from the U.S. Government Printing Office, Washington, D.C. 20402. Stock No. 004-000-00345-4.

Industry Canada requires the following wording to the end user in French and English:

Industry Canada Notice:

This device complies with Canadian RSS-210.

To prevent radio interference to the licensed service, this device is intended to be operated indoors and away from windows to provide maximum shielding. Equipment (or its transmitting antenna) that is installed outdoors is subject to licensing. The installer of this radio equipment must ensure that the antenna is located or pointed such that it does not emit RF field in excess of Health Canada limits for the general population; consult Safety Code 6, obtainable from Health Canada's web site

www.hc-sc.gc.ca/rpb.

"This Class B digital apparatus complies with Canadian ICES-003"

Cet appareil numérique de la classe B est conforme à la norme NMB-003 du Canada

Avis de Conformité à la Réglementation d'Industrie Canada:

Pour empêcher toute interférence aux services faisant l'objet d'une licence, cet appareil doit être utilisé à l'intérieur seulement et devrait être placé loin des fenêtres afin de fournir un écran de blindage maximal. L'installateur du présent matériel radio doit s'assurer que l'antenne est située ou pointée de manière à ce que cette dernière n'émette pas de champs radioélectriques supérieurs aux limites spécifiées par Santé Canada pour le grand public; consulter le Code de sécurité 6, disponible sur le site Web de Santé Canada, à l'adresse suivante: www.hc-sc.gc.ca/rpb.

End of Required User Manual Wording to end user provided by radio/system integrator