



3301 E. Deseret Drive, St. George, UT 84790  
www.wilsonelectronics.com • info@wilsonelectronics.com  
phone 1-800-204-4104 • fax 1-435-656-2432

March 8, 2017

To: Whom it May Concern

Subject: Calculated Mobile Station Coupling Losses (MSCL) For FCCID: PWO460021

The following formulas were used to calculate MSCL with a 1.5' foot path loss and a 45 degree polarity mismatch between the inside antenna and the mobile device:


Path Loss dB =  $36.6 + 20\log(F \text{ MHz}) + 20\log(D_{\text{miles}})$  dB

Polarity Loss dB =  $10\log(E_1/E_2)^2$  dB =  $P_L$  dB  
 $P_L$  dB =  $10\log(E_1^2/(E_1 \sin(45_{\text{deg}}))^2)$  dB =  $20\log(1/\sin(45_{\text{deg}}))$  dB = 3.01dB

Where:

$E_1$  = Maximum Possible Magnitude of the Electric Field from the Mobile Device

$E_2$  = Magnitude of the electric field from the Mobile device with a 45deg polarity mismatch =  $E_1 \sin(\tau)$ .



MSCL dB = Path Loss dB + Polarity Loss dB - Antenna Gain dB

The results of the calculations are shown in the following table:

Uplink Center Frequency MHz	707-710	782	836.5	1732.5	1880-1882.5
Path Loss (dB)	22.69	23.53	24.12	30.44	31.16
Polarity Loss (dB)	3	3	3	3	3
Antenna Gain with Coax Loss	-5.09	-3.55	-1.65	-1.83	-0.65
<b>MSCL (dB)</b>	<b>30.78</b>	<b>30.08</b>	<b>28.77</b>	<b>35.27</b>	<b>34.81</b>

Note: Antenna Gain with Coax Loss as measured.

Sincerely

Patrick L. Cook  
Senior Electrical Engineer