

User' s Manual

(M/N: HD 335)

NICs Intec Co., Ltd.

FCC NOTICE

THIS DEVICE COMPLIES WITH PART 15 OF THE FCC RULES.
OPERATION IS SUBJECT TO THE FOLLOWING TWO CONDITION:
(1) THIS DEVICE MAY NOT CAUSE HARMFUL INTERFERENCE, AND
(2) THIS DEVICE MUST ACCEPT ANY INTERFERENCE RECEIVED,
INCLUDING INTERFERENCE THAT MAY CAUSE UNDERSIRED
OPERATION.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communication. However, there is no guarantee that interference will not

occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures :

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

NOTE : The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications to this equipment. Such modifications could void the user's authority to operate the equipment.



CASE
NUDIAN

USB USER



USB Storage was designed for users to use and install very easy.
This manual is an ideal guide to help users install the USB storage system
rightly and easily.
The USB Storage is available in Hard Disk(3.5", 2.5"), LS-120 SUPER DISK
DRIVES and ZIP DRIVE as well as CD-ROM DRIVES, CD-RW DRIVES and
CVC-ROM DRIVES



Macintosh

Your USB Storage System is compatible with any Mac having a
USB port in Mac OS 8.6, 9.1 version or higher

How to install USB storage

1. Place the CD-ROM you received with the USB Storage System
in your Drive
There is a program on the CD named "Install ISD 200 bridge"
2. Double click on the Install USB Disk Drivers icon.
3. When the installer is finished, click 'ok' to finish the installation
4. Power up the USB Storage System and connect a USB cable
between the USB Storage System and the computer
You can either connect to the computer directly or through
USB hub.
5. If everything is installed correctly, you will see a new icon on
the desktop that corresponds to the USB Storage System
In case of HDD, use HDD after formatting under Mac OS.
6. In Mac OS X version open the practice file in the NUDIAN
Mac OS10 folder





CASE
NUDIAN



P C

Your USB Storage System is compatible with any PC that has a USB port in Windows 98, ME, 2000 and XP version.

How to install a USB Storage System by plug and play process

1. Make sure that the USB Storage System is plugged into a wall outlet and is powered up
2. Place the CD-ROM that came with USB Storage System in the CD-ROM drive.
3. Plug the USB cable into the PC.
4. Windows will find new hardware
5. If Windows ask the location of new hardware, select 'searching' and select "D:/USB1.1 or USB2.0 and then click 'next' (D:the location of CD-ROM)
6. Windows will find and load the drivers from CD-ROM, and it adds a suitable drive to the equipment.

*** The drivers are now loaded. If the Storage device in your USB Storage System is Hard Disk Driver you must now partition and format the drive. This is done through the use of the DOS utility FDISK. See your Windows documentation**
If you are unfamiliar with FDISK , note that you must run FDISK before you try to format the drive and that you must run FDISK in DOS Window while Windows is running.





CASE
NUDIAN

**★ WHEN A NUDIAN CASE DON'T
BE RECOGNIZED IN A PC ★**

1. First turn on a external case before on the Power of PC
2. Upgrade the USB drive to the latest version.(www.nudian.net)
3. Set jumpers of the CD-ROM with a master
4. Check assembling the parts into a complete unit rightly and connecting all kinds of cables correctly
5. In case although "searched for new hardware" appears on the screen but warning message emerges, don't do automatic searching, after locate the directory, and enter "searching"
6. In advance locate the directory and enter "searching"
7. Pc users install the driver after transfer to PC folder among folders in CD-ROM
8. In Window 98/ME version when you install the driver if Blue Screen appears, install and use after practice and install with the Nudian-Installer
9. In WindowsXP version when you install the driver although message about changing test appears, click "continue" to finish the installation.



CASE
NUDIAN

★ An important matter of consequence ★

When 4x or higher speed of CD-R/RW are connected with CD 503U case,

It doesn't support higher speed than 4x.

It is not because of NUDIAN Case, don't misunderstand.

It is due to USB1.1 transfer speed.

USB 2.0 and IEEE 1394(FIRE WIRE) Interfaces are compatible to 40x.

Customers, who use EASY CD-CREATOR among Recording Software, might not be compatible when they use USB interfaces.

If so, please go NUDIAN HOME PAGE(www.nudian.net) to download NERO BURNING, after you download the NERO BURNING you can record in safe and easy way without a problem.

If you have any problem, when you install Driver with HDD, you have to check whether the Hard Disk is a new product first.

If so, it will be good after you set a partition for Hard Disk.

Sometimes, HDD case of Nudian can not be specified.

Most kinds of cases will be arisen when you use both 300MB - 500MB Hard or over 80GB.

If it happens after you set a partition for 80 GB Hard, you can use it.

【 Reference 】

1. After WIN95 is upgraded with OSR2.1 version in OS, USB will be recognized.

Among DOS, LINUX, UNIX are not be supported basically.

You can use MAC OS, between 8.6 and 9.1

It can not be recognized when power supply is ON -> OFF -> ON.

You should re-start again.

2. Compatible with Mac OS X

- Nudian case doesn't be compatible with the products listed below

* CD-RW : ACER

* HDD : capacity is several products of 200 - 600MB





CASE
NUDIAN

IEEE1394 FIREWIRE USERS



Windows 98SE

1. When you connect a cable to a case, a message "please put Window 98CD in the Disk" appears on the screen.
2. Put in Win 98 CD and install. A CD-ROM will be added up in "My computer"
- The driver for IEEE 1394 type is usually included in Window

* REMOVAL

1. To remove, right-click the green arrow icon. "Unplug or eject hardware" appears.
2. Click on "unplug or eject hardware" and click on "stop" in the Window.
3. A list appears after you have clicked "stop". Select the device you want to remove and click "ok"
4. A successful removal message appears; click on "ok"



Windows ME

1. Turn on power to both the product and the computer. Connect the 1394 port on the product and the connect 1394 port on your computer with the 1394 cable provided with the product
2. Next appears a new drive in "My Computer" and "Windows Explorer"
A green arrow icon, representing an external device connection, will appear.

* REMOVAL

1. When you want to remove the product, right-click on the green arrow icon and "unplug or eject hardware" will appear
2. Click on "unplug or eject hardware", and then click on "stop" in the new Window that appears.
3. A list appears after you have clicked on "stop". Select the device you want to remove, and click "ok"
4. The successful removal message appears. Click on "ok"





CASE
NUDIAN



Windows 2000

1. Turn on power to both the product and the computer. Connect the 1394 port on the product to 1394 port on your computer with the 1394 cable provided with the product.
2. Next appears a "P" drive in "My Computer" and "Windows Explorer". Also, a green arrow icon representing an external device connection, appears

* REMOVAL

1. When you want to remove the product, right-click on the green arrow icon and "unplug or eject hardware" will appear
2. Click on "unplug or eject hardware", and then click on "stop" in the new Window.
3. A list appears after you have clicked on "stop". Select the device you want to remove and click "ok".
4. The successful removal message appears. Click on "ok"



Macintosh

* If it is a CD-Case.

1. Mac OS will automatically be recognized the CD-CASE when MAC are connected with Case.
2. Recorder model is appeared to be able to use when recording on Toast down.

★ If drive can not be recognized ★

1. Please use over Windows 98SE.
2. First put IEEE 1394 connected to the main board on the slot and check the recognition of the PC
3. If it doesn't work after you practice and you have to know what chip you use for IEEE 1394 people generally use VIA, TI chip set. If you use via chip sets they maybe not presented in CD-ROM, CD-R/W, and DVD because they are low priced goods. If you have a problem like this, please deliver it to us. We will test it immediately as soon as we get it.

* Thanks for buying Nudian products one more.

**If you have any problem, please do not hesitate to contact Division Distributor.
We are ready to support you.**

