Rhein Tech Laboratories, Inc. 360 Herndon Parkway Suite 1400 Herndon, VA 20170 http://www.rheintech.com

Model: STI-34752 Standards: FCC 15.231/IC RSS-210

ID's: TXL34752/6335A-34752 Report #: 2014089

Client: STI

Appendix J: Manual

Please refer to the following pages.



Wireless Outdoor PIR Motion Detector

Model STI-34752



Program sensor before installation

Description

STI-34752 is a high grade professional motion sensor engineered with the world's best components and materials. Special Dual-Frequency infrared (DFIR™) opto-electronics provide the highest level of false alarm immunity available in a passive infrared motion sensor. The principal of DFIR is simple. A moving object produces two signal frequencies. White light, electromagnetic interference, hot air - stationary changing-temperature objects and other typical false alarm sources produce only one signal frequency. Thus, by rejecting one-frequency signals, the STI-34752 rejects false alarms. The STI-34752 features one sixelement DFIR detection system.

Features

- · 33 ft/10M range and 90 degree field of view (45 degrees to each side).
- · Mountable on flat-wall or 45 degree corner.
- · Cover tamper.
- · Strong, reliable RF signal.
- 6-8 year battery life of CR123A battery.
- Low battery indication.

Sensor Initialization

After a 30 second warm-up, the STI-34752 sensor is fully operational. During warm-up, the LED flashes. After warm-up, the sensor starts a three minute walk test mode.

Walk Test LED

- 1. LED lights for 3 minutes when motion sensed (only during walk test).
- 2. Wireless transmissions are sent for each detection (walk test can be used for receiver test as well).
- 3. Motion stops (locks out) sensing for 20 seconds after LED flashes.
- 4. When complete, replace sensor base by snapping back onto unit.

NOTE: The STI-34752 should be walk tested once per year.

Alarm Processing


STI-34752 alarm processing is designed for extreme false alarm rejection. The processing is a quantum leap above standard PIR motion sensors that simply count signal events. The fields of view are set up so moving objects produce two detector signals of different frequencies, while non-moving false alarm sources produce two detector signals of the same frequency.

Pet Immunity

STI-34752 is designed to allow the presence of pets (100 lbs/45 kg or lighter) without signaling an alarm. It includes a special micro-element lens array that produces much stronger optical signals for humans than for pets 100 lbs/45 kg or lighter. The optical sensitivity of each STI-34752 is factory calibrated to ensure accurate discrimination between humans and pets.

NOTE: Some pets (especially larger ones with very short hair), even if lighter than 100 lbs/45 kg, may produce enough infrared radiation to cause alarms. STI-34752 users are strongly advised to test the sensor with their own pets, in order to verify that the STI-34752 will not signal an alarm when their pets are moving within its fields of view.

The diagram below shows the STI-34752 zones of greatest human/pet discrimination. The STI-34752 should be mounted so pets will occupy only the lighter-colored spaces.



Operation

- Motion stops (locks out) transmitting wireless sensor alarms for 3 minutes after sending an alarm transmission. This is to conserve battery life.
- 2. Walk Test LED does not activate in normal operating mode, only works during walk test.
- 3. Tamper: when cover is opened.
- 4. Supervisory: every hour.

Programming Instructions

- 1. Remove base by releasing the snap closure located at the bottom center.
- 2. Put receiver in program mode (refer to receiver instructions for programming).
- 3. Remove battery cover and Mylar tab. Unit should immediately program in receiver. If not, press the tamper switch. Snap battery cover back in place.

Mounting Instructions

- 1. Remove the screw knockouts on sensor base for mounting.
- 2. Mount at 7.5 ft (ideal height) with provided screws and optional anchors.
- 3. Snap unit back onto sensor base. Unit immediately goes into 3 minute walk test. To reset walk test, remove cover and reattach.

NOTES:

- · Clear line of sight from sensor to monitored area, glass will blocks sensor's view.
- · Wall temperature similar to walls/floor of monitored area
- · Sensor aimed away from windows and reflected sunlight
- · Sensor aimed away from heaters or heater/cooler outlets
- · Sensor aimed so intruder path crosses three views.

Specifications

Mounting Hardware: #6 screw

Mounting Height: 7.5 ft. (ideal height)
Replacement battery: CR123A 1500mAH

Temperature range: -40° to 131°F (-40° to 55°C)

White light immunity: 25000 lux


RF Immunity 50 V/m 10-1000 MHz; 20 V/m 1-2 GHz

Housing dimensions: 4.4 x 2.4 x 2" (H x W x D)

Tamper Switch: Form A (NC). 50 mA at 30 VDC

Range: 33 ft./10M in sensor-facing direction


Sensor Optical View Pattern (side view, in feet)



Optical Fields-of-View

Long-range Mid-range Short-range Look-down 88° 30° 18° 8°

Sensor Optical View Pattern (top view, in feet)



Warranty Information

Safety Technology International, Inc. warrants to the original consumer/purchaser what this product shall be free of defects in material and workmanship under normal use and circumstances for a period of one (1) year from the original date of purchase.

Electronic warranty form at www.sti-usa.com/wc14.

Important Notice

This device complies with Industry Canada license-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes : (1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

Model: STI-34752 FCC ID: TXL34752 IC: 6335A-34752

Changes or modifications not expressly approved by Safety Technology International, Inc. could void the user's authority to operate the equipment.

Technical Support

Contact STI at 800-888-4784 ext. 202

Additional Wireless Alert Series Products

STI-34098	Single Channel Slave Receiver	STI-34701	Indoor Wireless PIR
STI-34104	4-Channel Receiver	STI-34752	Outdoor Wireless PIR
STI-V34104	4-Channel Voice Receiver	STI-6200WIR	Wireless Fire Extinguisher Theft Stopper
STI-34108	8-Channel Receiver	STI-6200WIR4	Wireless Fire Extinguisher Theft Stopper w/Receive
STI-34188	8-Zone Relay Board	STI-6400WIR	Wireless Exit Stopper Door Alarm
STI-34101	Solar Powered Driveway Monitor Sensor	STI-6400WIR4	Wireless Exit Stopper Door Alarm with Receiver
STI-34151	Battery Powered Driveway Monitor Sensor	STI-6517A	Stopper Station Shield with Sound
STI-34201	Wireless Mailbox Alert Sensor	STI-6517B	Stopper Station Shield with Sound and Transmitter
STI-34301	Wireless Garage Sentry Sensor	STI-30104	Lamp Controller
STI-34401	Wireless Universal Alert Sensor	STI-30105	Extended Antenna
STI-34501	Wireless Entry Alert Sensor	STI-34105	Voltamax 12VDC (500mA) Power Supply
STI-34601	Wireless Doorbell Button	STI-34106	Keyfob
		STI-34109	Repeater



2306 Airport Rd • Waterford, MI 48327 Phone: 248-673-9898 • Fax: 248-673-1246 info@sti-usa.com • www.sti-usa.com

Safety Technology International (Europe) Ltd.

Unit 49G Pipers Road • Park Farm Industrial Estate • Redditch Worcestershire • B98 0HU • England • Tel: 44 (0) 1527 520 999 Fax: 44 (0) 1527 501 999 • Freephone: 0800 085 1678 (UK only) E-mail: info@sti-europe.com • Web: www.sti-europe.com

