

Theory of operation; Alereon AL5616 USB dongle.

The Alereon AL5616 is a UWB radio device with a USB interface to the host computer. This device is intended to provide a short-range wireless USB connection for computers and peripheral units equipped with a USB 2.0 interface. The AL5616 is powered entirely from the USB connector of the device to which it is attached. The AL5616 operates in the frequency band defined in the FCC rules and Regulations for UWB devices. Specifically, it operates between the frequencies of 3.168 and 8.976 GHz per the industry-defined WiMedia 1.1 specification.

The AL5616 is comprised of three integrated circuit devices and supporting circuitry for filtering, interface and power conditioning. The AL5616 has a permanently attached antenna internal to the product housing. The schematic diagram shows a connector, Hirose type U.FL, in the RF path. This connector, is not accessible from outside of the unit housing. Following the antenna connector is a Diplexer type bandpass filter having two sections; The LB section has a passband from 3.1 GHz to 4.752 GHz, the HB section has a passband from 6.336GHz to 8.976GHz. This filter provides suppression of unwanted out of band transmitter emissions and receiver interference rejection in the 2.4 GHz and 5.1 GHz bands.

The AL5100 RF Transceiver generates the system reference frequency from a 44 MHz crystal resonator. The 44 MHz reference frequency is multiplied to 16.896 GHz internally in the AL5100 by a PLL multiplier. From this frequency the local oscillator frequencies for band frequencies for both transmit and receive modes are derived internally within the AL5100 by synthesis. The local oscillator frequencies are as listed as  $F_{mid}$  per the following table.

<b>BG</b>	<b>Channel</b>	<b>Ch1</b>	<b>Ch0</b>	<b><math>F_{low}</math></b>	<b><math>F_{mid}</math></b>	<b><math>F_{high}</math></b>
N/A	N/A	0	0	-	-	-
1	1 (A)	0	1	3168 MHz	3432 MHz	3696 MHz
	2 (B)	1	0	3696 MHz	3960 MHz	4224 MHz
	3 (C)	1	1	4224 MHz	4488 MHz	4752 MHz
3	7 (A)	0	1	6336 MHz	6600 MHz	6864 MHz
	8 (B)	1	0	6864 MHz	7128 MHz	7392 MHz
	9 (C)	1	1	7392 MHz	7656 MHz	7920 MHz
6	9 (A)	0	1	7392 MHz	7656 MHz	7920 MHz
	10 (B)	1	0	7920 MHz	8184 MHz	8448 MHz
	11 (C)	1	1	8448 MHz	8712 MHz	8976 MHz

In addition to the band frequencies, a 1056 MHz clock for ADCs and DACs within the AL5301 Baseband Processor/MAC is generated.

The interface between the AL5100 RF Transceiver and the AL5301 Baseband Processor/MAC consists of the analog RX-I and -Q signals and the analog TX-I and -Q signals all of which are baseband, having 2 MHz to 264 MHz frequency band. The interface also includes a 1056 MHz clock signal and CMOS logic-level control signals which determine the band frequency and mode.

The interface between the AL5301 Baseband Processor/MAC and the USB3300 USB phy device is the industry-defined ULPI consisting of CMOS logic-level: 8 data bits, control signals and a 66 MHz clock signal. The USB3300 USB phy generates the required USB timing reference from a 24 MHz crystal resonator.

The interface between the AL5616 UUSB dongle and the host system is via the industry-defined USB 2.0.

References.

MultiBand OFDM Physical Layer Specification 1.1.

MAC-PHY Interface Specification 1.0.

Universal Serial Buss Specification 2.0.