SL-1550-T15 2.4GHz A/V Transmitter Theory of Operation

1.0 Product Description

The SL-1550-T15 is a 2.4GHz Audio / Video FM transmitter designed to transmit NTSV Video and Line Level Audio signals to a wireless receiver.

2.0 Theory of Operation

The SL-1550-T15 transmitter is based upon a highly configurable hardware platform that allows micro-controller control of frequency and power level output. In the case of the SL-1550-T15 transmitter the frequency and power level outputs are configured to comply with FCC Part15 requirements.

The SL-1550-T15 transmitter operates as follows:

- A micro-controller and user interface is provided to allow the user to select the frequency and power level of operation.
- ➤ The micro-controller sets the selected frequency on the frequency synthesizer of an audio / video transmitter module via tan I2C bus.
- ➤ The micro-controller in the SL-1550-T15 transmitter is configured to allow a user to associate a frequency between 2.410GHz and 2.472Hz (in 1MHz increments) with one of 32 channels stored in non-volatile memory.
- ➤ The micro-controller sets the power level by controlling an RF digital attenuator via a serial data bus. The RF attenuator is digitally controlled to attenuate the fixed output of the transmitter module prior to a 20dB RF amplifier provided.
- ➤ The micro-controller in the SL-1550-T15 transmitter is configured so that user cannot modify the power level setting on the SL-1550-T15 transmitter. The attenuator is set for a power level of <1mW and produces a field strength of less than 94uV/meter at 3 meters.

The following section describes the SL-1550-T15 transmitter hardware design and how the features are accomplished.

SL-1550-T15 Theory of Operation

3.0 Hardware Platform Design

The SL-1550-T15 transmitter hardware platform consists of the following hardware features:

- Fixed 2.4GHz Audio / Video transmitter module with the following features:
 - I2C frequency control based upon the use of a Zarlink SP5655 frequency synthesizer.
 - Audio / Video modulator
 - Fixed 13dBm RF amplifier
- ➤ Digital attenuator with the following features:
 - Serial digital attenuation control between –1.2dB and –33.3dB based upon the use of a Hittite HMC542 digital attenuator
- > Two-stage RF power amplifier
 - Stage 1 is based upon the RFMD RF3807
 - Stage 2 is based upon the RFMD RF3809
- ➤ Micro-controller
 - Single chip NXP P89LPC932A1FA-S micro-controller
- ➤ User Interface
 - LED display of Channel and Power Level settings
 - Dome switch overlay for user control of frequency and power level settings
- Power Supplies
 - DC/DC converter that provides regulated 8VDC power from a 10V-40V power input to the SL-1550-T15 transmitter's RF power amplifiers.
 - 5V linear regulator that provides power to the transmitter module and digital attenuator.
 - 3.3V linear regulator that provides power to the micro-controller.

A block diagram of the SL-1550-T15 transmitter hardware platform is provided as document SL1550T15BlkDia.PDF

SL-1550-T15 Theory of Operation

4.0 Transmission Characteristics

The SL-1550-T15 transmits a continuous signal modulated by audio and video signal inputs as follows:

- > The center frequency is modulated by the video signal inputs
- ➤ Sub-carriers of +/- 6.5MHz from the center frequency are modulated by the audio signal inputs.
- ➤ The total bandwidth of the transmitted signal is less than 20MHz.

5.0 Antenna Characteristics

The SL-1550-T15 transmitter use a detachable antenna with the following characteristics:

- ➤ The transmitter antenna connector on the SL-1550-T15 transmitter is a reverse polarity female SMA (RP-SMA) with a male pin.
- ➤ The antenna provided is a tilt and swivel, ¼ wave, 0db gain whip antenna with a reverse polarity male SMA (RP-SMA) with a female pin socket.