



BASIC OPERATION GUIDE

DT313Y/ DT313Q

INTRODUCTION

Thank you for acquiring the DT313Y/ DT313Q, part of DT Research's line of Rugged Tablets. Featuring a slim yet robust enclosure, the DT313Y/ DT313Q with 13.3" TFT display is powered by the Intel® Core™ i quad-core or Qualcomm octa-core processor, offering optimal combinations of performance and power savings. The DT313Y/ DT313Q is available with Microsoft® Windows® or Android operating system. The software operating system features web browser, client/ server computing software, media player, accessories, and applications support.

PACKAGE CONTENTS

- One DT313Y/ DT313Q with Battery Pack and Handstrap
- AC-DC Power Adapter with Power Cord
- Basic Operation Guide

* If your DT313Y/ DT313Q contains Barcode Scanner or Front/Back Camera modules, please refer to the Tablet Modules Basic Operation Guide for detailed operation.

DT313Y/ DT313Q:



Input/ Output Ports

- A** Smart Card Reader (DT311Y only)
- Headphone Jack

- B** Headphone Jack

- C** Ethernet Port

- D** USB 3.0 Port

- E** USB Type-C Port (power input)

Button Functions

BUTTON	ACTION
1	Brightness Control Buttons
2	programmable buttons
3	Power Button
4	Battery Latch

Power/Battery LED Status:

- Blue indicates the battery is 25% to 100% charged
- Blinking blue indicates the battery is charging
- Orange indicates that the battery is between 11% to 25%
- Blinking Orange indicates that the battery is below 10%

PRECAUTIONS

- Always exercise care when operating and handling the DT313Y/ DT313Q
- Do NOT apply excessive pressure to the display screen.
- We recommend using the Digital Pen (optional) to keep the screen clean.
- Avoid prolonged exposure of the display panel to any strong heat source. Wherever possible, the DT313Y/ DT313Q should face away from direct light to reduce glare.
- If the AC-DC power adapter is used to recharge or power the tablet, do NOT use any AC-DC adapter other than the one provided or acquired from the manufacturer or its partners.
- In the unlikely event that smoke, abnormal noise, or strange odor is present, immediately power off the DT313Y/ DT313Q and disconnect all power sources. Report the problem to your device provider immediately.
- Never attempt to disassemble the DT313Y/ DT313Q, as this will void the warranty.

BASIC FEATURES

The DT313Y/ DT313Q wireless tablet integrates a bright and multi-touch display, USB ports, and embedded networking elements such as wireless LAN and Bluetooth. The DT313Y/ DT313Q is complemented by a suite of accessories, including battery expansion, charging cradles, and battery charger kit, for a comprehensive user experience.

A DT313Y/ DT313Q typically integrates an 802.11ac wireless LAN (WLAN) adapter that may connect to other wireless devices or access points. If your DT313Y/ DT313Q does not come with such a network adapter, please consult your device provider to establish the desired network connectivity.

OPERATION

Powering ON and OFF

To activate the DT313Y/ DT313Q, push and quickly release the Power Button. The display will come on in a few seconds. To put the DT313Y/ DT313Q in Standby mode, push and quickly release the Power Button. To turn the DT313Y/ DT313Q off for extended storage, power off safely using any software function that “shuts down computer” provided in the software operating system.

NOTE:

The battery packs shipped with your tablet may be low in power—please use the AC-DC adapter with the DT313Y/ DT313Q when setting up for the first time to fully charge the internal battery pack.

NOTE:

When the batterypack(s) is (are) charging, the blue-colored Battery LED should blink slowly. If plugging in the AC-DC adapter does not trigger this blinking activity and the LED stays dark, the battery pack(s) may have been drained substantially. Try unplugging/ replugging the AC-DC adapter to the DT313Y/ DT313Q a few times to activate the charging process.

NOTE:

To conserve power, use (push and quick release) the Power Button to put the tablet in “Standby” mode while not in use. Pushing briefly on the same button will wake up the system within seconds.

NOTE:

For DT313Y, avoid using the Power Button (“hold 4+ seconds” feature) to turn off the tablet—this form of hardware shutdown is intended to be a means of recovery from lockups, and not as normal operation.

Start Up

If the power up (from Standby mode or otherwise) is successful, the appropriate interface will be displayed after a launch sequence of several seconds. The wireless LAN connection may take 10-15 seconds to be established.

Configuring the Mobile Tablet

The DT313Y/ DT313Q may be configured using the utilities and methods dictated by the software operating system. The DT313Y/ DT313Q should be configurable for various properties such as user profiles, network features, and several system elements.

Wireless Networking

Wireless LAN

The DT313Y/ DT313Q is often delivered with an embedded (user-inaccessible) 802.11ac WLAN adapter equipped with a hidden custom antenna.

- Through the support of typical WLAN adapters, the DT313Y/ DT313Q should be able to detect all 802.11 access points in the vicinity for you to select the access point of your choice for connection.
- The SSID and WEP/WPA/WPA2 (if enabled) parameters on the DT313Y/ DT313Q and the access points have to match. The SSID is case-sensitive and it is recommended that you enable WEP/WPA/WPA2 encryption (or advanced alternatives) for secure access.
- When WEP/WPA/WPA2 is enabled, you may need to consult your network administrator or your networking equipment literature to properly configure associated settings such as Authentication mode, etc.
- Refer to the access point operating manuals for setting up the 802.11 access points.

Bluetooth

The Bluetooth configuration application is enabled from the Windows System Tray or from the Android Settings APP. Follow the instructions and options provided within the application to configure and invoke Bluetooth connectivity with the corresponding peripherals.

USING THE MOBILE TABLET

Peripherals Support

Through its USB ports, the DT313Y/ DT313Q supports a wide range of USB-based peripherals. These peripherals are applicable for software installation, applications storage, data storage, and system software recovery and updates.

For More Support

Users can download the Tablet Modules Basic Operation Guides from the DT Research website.

If the DT311Y/ DT311Q comes with a Mobile broadband module, please contact your product and/or service provider for the SIM Card installation procedures.



To Hold the Tablet

Left hand: grip the left back side of the tablet with your left hand four index fingers, with thumb resting on the top of the back side of the tablet and palm securely against the back.

Right hand: grip the right back side of the tablet with your right hand four index fingers, with thumb resting on the top of the back side of the tablet and palm securely against the back.

Specifications:

Item	DT313Q	DT313Y
System		
CPU	Qualcomm Octa-Core, 2.0GHz	Intel® Core™ Comet Lake i7-10710U Processor (12M Cache , up to 4.7 GHz) Intel® Core™ Comet Lake i7-10510U Processor (8M Cache , up to 4.90 GHz) Intel® Core™ Comet Lake i5-10210U Processor (6M Cache , up to 4.10 GHz)
RAM	4GB	8GB to 32GB
Storage	64GB	256GB to 2TB flash
Operating System	Android 9.0 and 10	Microsoft® Windows® 10 IoT Enterprise
Display	13.3" LED-backlight, high-brightness (1000 nits) screen with capacitive touch, outdoor viewable	
Display Resolution	1920 x 1200	1920 x 1200
Network Interface	Wi-Fi 802.11a/b/g/n/ac/ax, 2.4GHz/ 5GHz dual band; Bluetooth 5.0	
Control Switch and Buttons	1 power button, 2 brightness control buttons, 5 programmable buttons	
Indicator	1 power/ battery status LED	1 power/ battery status LED
Speaker	Built-in speaker	Built-in speaker
I/O Ports		
USB port	USB 3.0 x 3, USB Type C x 1 (for data transmitting and charging)	
Headset Jack	1 (3.5mm)	1 (3.5mm)
Smart Card/CAC Reader	N/A	Full-slot, reads ISO 7816 T=0, T=1; 1.8/3/5V smart card
SD Slot	1 micro SD card slot	N/A
Ethernet	Ethernet 10/ 100/ 1000MB Base-T LAN	
Mechanical and Environmental		
AC/DC Adapter	Input: 100 – 240V AC; Output: 20V DC, 3.25A	
Battery Pack	Hot swappable battery, 7.6V, 6000mAh	Hot swappable battery, 11.4V, 5400mAh Hot swappable battery, 11.4V, 8000mAh (optional)
Enclosure	ABS + PC plastics and magnesium-aluminum alloy	
Dimensions (H x W x D)	10.1 x 13.2 x 0.8 in/ 256 x 335 x 21 mm	
Weight	3.97 lbs/ 1.8 kg	3.97 lbs/ 1.8 kg
Regulatory	FCC Class B, CE, RoHS compliant	
Operating Temperature	Operation: -10°C to 50°C (-14°F to 122°F) Storage: -55°C to 70°C (-67°F to 158°F)	Operation: -10°C to 60°C (-14°F to 140°F), optional -30°C to 45°C (-22°F to 113°F) Storage: -55°C to 70°C (-67°F to 158°F)
Humidity	0% – 90% non-condensing	

FCC Regulatory Compliance

Warning: changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

RF Exposure Compliance

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment.

The device has been tested for use against the body with 0mm separation in Specific Absorption Rate (SAR) testing.

User must follow the specific operating instructions for satisfying RF exposure compliance. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

Supplier's Declaration of Conformity

47 CFR § 2.1077 Compliance Information

Unique Identifier Trade Name: **DT Research**, Model No.: DT313Y

Responsible Party – U.S. Contact Information**DT Research, Inc.**

2000 Concourse Drive, San Jose, CA 95131

<http://www.dtresearch.com>

FCC Compliance Statement

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

FCC ID Label is in removable battery compartment, it could be easily found by removing the battery cover.