


The test plots as follows:



Shenzhen UnionTrust Quality and Technology Co., Ltd.

Address: 16/F, Block A, Building 6, Baoneng Science and Technology Park, Qingxiang Road No.1, Longhua New District, Shenzhen, China


Tel: +86-755-28230888


Fax: +86-755-28230886

E-mail: info@uttlab.com

<http://www.uttlab.com>

UTTR-RF-RSS247-V1.0





## Right Earbud

| Type of Modulation | Test Frequency | Packet | Pulse Width | Number of Pulses in 3.16 seconds | Dwell Time    | Limit |
|--------------------|----------------|--------|-------------|----------------------------------|---------------|-------|
|                    |                |        | ms          |                                  | ms            | ms    |
| GFSK               | 2441MHz        | 1-DH1  | 0.378       | 113.000                          | 42.71         | < 400 |
|                    |                | 1-DH3  | 1.620       | 97.000                           | 157.14        | < 400 |
|                    |                | 1-DH5  | 2.891       | 65.000                           | 187.92        | < 400 |
| $\pi/4$ DQPSK      | 2441MHz        | 2-DH1  | 0.387       | 115.000                          | 44.45         | < 400 |
|                    |                | 2-DH3  | 1.620       | 86.000                           | 139.32        | < 400 |
|                    |                | 2-DH5  | 2.891       | 67.000                           | <b>193.70</b> | < 400 |
| 8DPSK              | 2441MHz        | 3-DH1  | 0.393       | 117.000                          | 45.95         | < 400 |
|                    |                | 3-DH3  | 1.620       | 93.000                           | 150.66        | < 400 |
|                    |                | 3-DH5  | 2.891       | 66.000                           | 190.81        | < 400 |

**Shenzhen UnionTrust Quality and Technology Co., Ltd.**

Address: 16/F, Block A, Building 6, Baoneng Science and Technology Park, Qingxiang Road No.1, Longhua New District, Shenzhen, China


Tel: +86-755-28230888

Fax: +86-755-28230886

E-mail: [info@uttlab.com](mailto:info@uttlab.com)
<http://www.uttlab.com>

UTTR-RF-RSS247-V1.0

The test plots as follows:



Shenzhen UnionTrust Quality and Technology Co., Ltd.

Address: 16/F, Block A, Building 6, Baoneng Science and Technology Park, Qingxiang Road No.1, Longhua New District, Shenzhen, China


Tel: +86-755-28230888

Fax: +86-755-28230886

E-mail: info@uttlab.com

<http://www.uttlab.com>

UTTR-RF-RSS247-V1.0

**Shenzhen UnionTrust Quality and Technology Co., Ltd.**

Address: 16/F, Block A, Building 6, Baoneng Science and Technology Park, Qingxiang Road No.1, Longhua New District, Shenzhen, China


Tel: +86-755-28230888

Fax: +86-755-28230886

E-mail: info@uttlab.com

<http://www.uttlab.com>

UTTR-RF-RSS247-V1.0



## 5.8 CONDUCTED OUT OF BAND EMISSION

|                          |                                                                                                                                                                                                                                                                                                                            |
|--------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>Test Requirement:</b> | FCC 47 CFR Part 15 Subpart C Section 15.247(d)<br>RSS-247 Issue 2, Section 5.5                                                                                                                                                                                                                                             |
| <b>Test Method:</b>      | ANSI C63.10-2013 Section 6.10.4 & Section 7.8.8                                                                                                                                                                                                                                                                            |
| <b>Limit:</b>            | In any 100kHz bandwidth outside the frequency bands in which the spread spectrum intentional radiator is operating, the radio frequency power that is produced by the intentional radiator shall be at least 20dB below that in the 100kHz bandwidth within the band that contains the highest level of the desired power. |
| <b>Test Procedure:</b>   | Remove the antenna from the EUT and then connect a low loss RF cable from the antenna port to the spectrum analyzer.<br>Use the following spectrum analyzer settings:                                                                                                                                                      |

### Step 1: Measurement Procedure REF

- Set instrument center frequency to 2400 MHz or 2483.5 MHz.
- Wide enough to capture the peak level of the emission operating on the channel closest to the band edge, as well as any modulation products that fall outside of the authorized band of operation.
- Set the RBW = 100 kHz.
- Set the VBW  $\geq 3 \times$  RBW.
- Detector = peak.
- Sweep time = auto couple.
- Sweep points  $\geq 2 \times$  Span/RBW
- Trace mode = max hold.
- Allow the trace to stabilize.
- Set the marker on the emission at the band edge, or on the highest modulation product outside of the band, if this level is greater than that at the band edge. Enable the marker-delta function, and then use the marker-to-peak function to move the marker to the peak of the in-band emission.

### Step 2: Measurement Procedure OOB


- Set RBW = 100 kHz.
- Set VBW  $\geq 300$  kHz.
- Detector = peak.
- Sweep = auto couple.
- Trace Mode = max hold.
- Allow trace to fully stabilize.
- Use the peak marker function to determine the maximum amplitude level.

Note: The cable loss and attenuator loss were offset into measure device as an amplitude offset.

|                          |                                      |
|--------------------------|--------------------------------------|
| <b>Test Setup:</b>       | Refer to section 4.5.3 for details.  |
| <b>Instruments Used:</b> | Refer to section 3 for details       |
| <b>Test Mode:</b>        | Hopping Frequencies Transmitter mode |
| <b>Test Results:</b>     | Pass                                 |
| <b>Test Data:</b>        |                                      |

The test plots as follows:

Left Earbud



**Shenzhen UnionTrust Quality and Technology Co., Ltd.**

Address: 16/F, Block A, Building 6, Baoneng Science and Technology Park, Qingxiang Road No.1, Longhua New District, Shenzhen, China


Tel: +86-755-28230888


Fax: +86-755-28230886

E-mail: [info@uttlab.com](mailto:info@uttlab.com)

<http://www.uttlab.com>


UTTR-RF-RSS247-V1.0







## Right Earbud



## Shenzhen UnionTrust Quality and Technology Co., Ltd.

Address: 16/F, Block A, Building 6, Baoneng Science and Technology Park, Qingxiang Road No.1, Longhua New District, Shenzhen, China

Tel: +86-755-28230888

Fax: +86-755-28230886

E-mail: info@uttlab.com

<http://www.uttlab.com>

UTTR-RF-RSS247-V1.0