

Part 15.21 statement

" Change or Modifications that are not expressly approved by the manufacturer could void the user's authority to operate the equipment. "

Part 15.105 statement

This equipment has been tested and found to comply with the limits for a class B digital device, pursuant to Part 15 of the FCC Rules.

These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Part 15 Class B Compliance

This device and its accessories comply with part15 of FCC rules and ICES-003 Class B digital apparatus requirements for Industry Canada.

Operation is subject to the following two conditions:

- (1) This device & its accessories may not cause harmful interference.
- (2) This device & its accessories must accept any interference received, including interference that may cause undesired operation.

Body-worn Operation

This Mobile Broadband USB Modem is approved for use in normal size laptop computers only (typically with 12" or larger display screens).To comply with FCC RF exposure requirements, this modem should not be used in configurations that cannot maintain at least 5mm (approximately 0.2 inches) from your body.Also, when using the USB extension cable, place the USB modem away from your body or any other transmitter of the laptop or PC.This USB modem has been tested for compliance with FCC/IC RF exposure limits in the laptop computers configurations with horizontal and vertical USB slots and can be used in laptop computers with substantially similar physical dimensions, construction and electrical and RF characteristics.When using this USB modem in your computer, it must not be co-located or simultaneously transmit with any other radio (for example, Bluetooth or WiFi radios) in the computer.

Connecting this Terminal to a PC

When connecting this terminal with a PC for the first time, it is required to install L-03D connection software (including a driver). For installing L-03D connection software, refer to the following.

- For Windows: "Preparation for using L-03D" I
- For Macintosh: "Preparation for using L-03D"

Inserting

1 Turn on a PC

2 Connect this terminal with a PC

- When using the mounting holder (Sample) and the USB extension cable (Sample)
 - Use the mounting holder and the USB extension cable to fix the terminal on the PC

1 Lift the front part as the following

1 Hold the connector part of the USB extension cable and insert into the USB connector of this terminal in direction of arrow

- * Firmly insert into the USB connector.

2 Fix the mounting holder on the top part of PC

1 Hold the connector part of the USB cable and insert it into PC USB port in direction of arrow with inscription of the USB side up

2 Fix the mounting holder into this terminal

- 100

② Ins

* Ma

2

- 11

Note

- Ch

Re

1

If th

2

- **W**

2R

③ R

- ④Hg

- W

2 St

Caut

- If y

23

- UD

- In

The

Windows Version

Installation of L-03D connection software is only required when connect this terminal to your PC for the first time. The following procedures or screen images are all based on the example of Windows 7.

Preparation before Using L-03D

Setting Zero Installation (Auto)

1 Turn on a PC and activate OS

2 Connect this terminal with the PC

The setup screen of L-03D connection software is automatically displayed by zero installation.

"自動再生(Auto play)" screen will be displayed depending on settings. If the screen is displayed, check "ソフトウェアとゲームに対しては常に次の動作を行う(Always operates for software and game)" and select "L03DLauncher.exeの実行(Execute L03DLauncher.exe)".

- When the setup screen of L-03D connection software is not automatically displayed, install via the included CD-ROM.

3 Select "L-03D 接続ソフト、L-03D 接続先(APN) 設定ツール、通信設定ファイル(ドライバ)"をインストールする(推奨)(L-03D connection software, L-03D APN setting tool, Communication configuration file (driver)(recommended))" and click "次へ(Next)"

- Install the communication configuration file (Driver) only

- Select "通信設定ファイル(ドライバ)のみインストールする (Install communication configuration file (Driver) only)" and click "次へ(Next)"
- Click "はい(Yes)" on "ユーザー アカウント制御(User account control)" screen
 - For Windows Vista
 - Click "続行(Continue)" on "ユーザー アカウント制御 (User account control)" screen
 - For Windows XP
 - ユーザーアカウント制御 (User account control)" screen is not displayed, follow the next procedure.
- Confirm the content of "使用許諾契約(The license agreement)", check "使用許諾契約の全条項に同意します。(I have read all the stipulations of this license agreement and I agree.)" and click "次へ(Next)"
- Click "次へ(Next)"
- Click "OK"

- Confirm that this terminal is recognized by PC
- Confirm the settings of driver following "インストールしたL-03D 通信設定ファイル(ドライバ)を確認する(Confirm the installed L-03D communication configuration file (Driver))"

4 Click "はい(Yes)" on "ユーザー アカウント制御 (User account control)" screen

- For Windows Vista
 - Click "続行(Continue)" on "ユーザー アカウント制御 (User account control)" screen
- For Windows XP
 - ユーザーアカウント制御(User account control)" screen is not displayed. Follow the next step.

5 Click "次へ(Next)"

6 Confirm the contents of "使用許諾契約(The license agreement)". When agree with the contents, select "使用許諾契約の全条項に同意します(I agree with all the license agreement stipulations)" and click "次へ(Next)"

Installation starts.

7 Click "完了(Finish)"

- For Windows XP
 - if use W-TCP function (recommended), make sure that "W-TCP機能を使用する (推奨) (Use WTCP function (recommended))" has the check mark and click "完了 (Finish)".

Installation of L-03D communication configuration file (Driver) continues. It may take time to move to the next procedure depending on your PC.

8 Confirm whether this terminal is recognized by the PC

On the lower right side of task tray, "デバイスドライバソフトウェアをインストールしています(Device driver software is being installed)" appears, and this terminal is recognized automatically.

To recognize this terminal automatically, L-03Dが取り外されました(L-03D is disconnected)" may appear on L-03D connection software temporarily. After a while, this terminal will be recognized.



If this terminal is recognized properly, "デバイスを使用する準備ができました(The device is ready for use)" will appear.



- For Windows Vista
 - On the bottom right of task bar, a message of "デバイスドライバソフトウェアをインストールしています(Device driver software is being installed)" appears, this terminal will be recognized automatically.



- If this terminal is recognized normally, a message of "デバイスを使用する準備ができました(Ready to use the device)" will appear.



- For Windows XP
 - On the lower right side of task tray, "新しいハードウェアが見つかりました (A new hardware has been found)" appears, and this terminal is recognized automatically.

- If this terminal is recognized properly, "新しいハードウェアがインストールされ、使用準備ができました。 (A new hardware has been installed and ready for use.)" will appear.




9 Install Flash Player

A message appears if Flash Player is not installed in your PC. Install Flash Player by the following procedures.

- Click "OK"
- Click "はい(Yes)" on "ユーザーアカウント制御(User account control)" screen
Installation of Flash Player starts.
 - For Windows Vista
 - Click "続行(Continue)" on "ユーザーアカウント制御 (User account control)" screen.
 - For Windows XP
 - "ユーザーアカウント制御 (User account control)" screen is not displayed, move to the next procedure.

- Read the content of "使用許諾契約(License agreement)", check "使用許諾契約の条件を読み、同意しました。(I agree with the license agreement stipulations)" and click "インストール(Install)"



- Click "完了(Finish)"



Installation finishes.
If "W-TCP機能を使用する (推奨)" (Use W-TCP function (recommended)) has the check mark, restart the PC after installation.

Setting Manually (CD)

- After starting a PC ▶ Insert the included CD-ROM into the PC

"自動再生(Auto play)" screen will appear depending on setting. Select "フォルダーを開いてファイルを表示(Open a folder to display files)".



- Select "Windows" inside the CD-ROM ▶ "L-03D 接続ソフト、L-03D 接続先 APN 設定ツール (L-03D connection software, L-03D APN setting tool)"

- Install the communication configuration file (Driver) only
 - Select "Windows" inside the CD-ROM▶"Driver"▶"docomo_L03D_ModemDriver_WHQL_Ver.1.6_All.exe"
 - Click "はい(Yes)" on "ユーザー アカウント制御(User account control)" screen
 - For Windows Vista
 - Click "続行(Continue)" on "ユーザー アカウント制御 (User account control)" screen
 - For Windows XP
 - "ユーザーアカウント制御 (User account control)" screen is not displayed, follow the next procedure.
 - Confirm the content of "使用許諾契約(The license agreement)", check "使用許諾契約の全条件に同意します。(I have read all the stipulations of this license agreement and I agree.)" and click "次へ(Next)"
 - Click "次へ(Next)"
 - Click "OK"
 - Connect this terminal to the PC
 - Confirm that this terminal is recognized by PC
 - Confirm the settings of driver following "Confirm the installed L-03D communication configuration file (Driver)".

- For subsequent steps, operate the same procedures as those after procedure 4 in "Setting Zero Installation (Auto)".

Connect this terminal to the PC after clicking "完了(Finish)" in procedure 7.
"自動再生(Auto play)" screen will be displayed depending on the settings. If the screen is displayed, check "ソフトウェアとゲームに対しては常に次の動作を行う(Always operates for software and game)" and select "L03DLauncher.exeの実行(Execute L03DLauncher.exe)". This terminal will be recognized by the PC.

Confirming after Installation

Confirming L-03D Connection Software

- Double click L-03D connection software icon displayed on the desktop
When the following screen is displayed, the confirmation of installation finishes.



Confirming the Installed L-03D Communication Configuration File (Drivers)

Confirm whether L-03D Communication Configuration File (Drivers) is set in a PC.

- Click "スタート(Start)"▶"コントロールパネル(Control panel)"▶"システムとセキュリティ(System and security)"

- For Windows Vista
 - Click "スタート(Start)"▶"コントロールパネル(Control panel)"▶"システムとメンテナンス(System and maintenance)"
- For Windows XP
 - Click "スタート(Start)"▶"コントロールパネル(Control panel)"▶"パフォーマンスとメンテナンス(Performance and maintenance)"▶"システム(System)"

- Click "デバイス マネージャー(Device manager)"

- For Windows Vista
 - Click "デバイス マネージャ (Device manager)"▶"続行(Continue)"
- For Windows XP
 - Click "ハードウェア(Hardware)" tab▶"デバイス マネージャ (Device manager)"


Uninstalling L-03D Connection Software (including a driver)

- Before uninstalling, remove this terminal from the PC.
- When uninstalling, make sure to install from the account with PC supervisor privileges.

- Click "スタート(Start)"▶"すべてのプログラム(All programs)"▶"L-03D 接続ソフト(L-03D connection software)"▶"Uninstall L-03D 接続ソフト(Uninstall L-03D connection software)"

- For Windows Vista
 - Click "スタート(Start)"▶"すべてのプログラム(All programs)"▶"L-03D 接続ソフト(L-03D connection software)"▶"Uninstall L-03D 接続ソフト(Uninstall L-03D connection software)".
- For Windows XP
 - Click "スタート(Start)"▶"すべてのプログラム(All programs)"▶"L-03D 接続ソフト(L-03D connection software)"▶"Uninstall L-03D 接続ソフト(Uninstall L-03D connection software)".

- 2** Click "はい(Yes)" on "ユーザーアカウント制御 (User account control)" screen
- Click "いいえ(No)" to stop uninstalling.
- For Windows Vista
 - Click "実行(Continue)" on "ユーザー アカウント制御 (User account control)" screen
 - For Windows XP
 - "ユーザーアカウント制御 (User account control)" screen is not displayed, follow the next procedure.
- 3** Click "OK" on "ファイル削除の確認 (Confirmation of deleting files)" screen



- 4** Click "はい(Yes)" on "ユーザーデータ削除の確認" (Confirming to delete user data). If user data is no more necessary.

In case that "いいえ(No)" is clicked, user data will not be deleted.

- APN Information and connection type (IPv4, IPv4/IPv6, IPv6) will not be deleted even if "はい(Yes)" is clicked.

- 5** Click "完了 (Finish)"

- For Windows XP
 - Make sure that "W-TCP機能の最適化を解除する (推奨)" (Cancel optimization of W-TCP function (recommended)) has the check mark and click "完了 (Finish)".

Uninstallation finishes.

- Restart your PC after uninstalling.

Macintosh Version

Installation of L-03D connection software is only required to install when connect this terminal to your PC for the first time.

The following images are the examples of "Mac OS X 10.6". Images may differ for "Mac OS X 10.5".

Note

- When installing, insert this terminal into USB port after OS is activated.
- Do not insert the CD-ROM into CD drive when installation via this terminal starts.
- Do not remove this terminal while installing.
- End all the applications before installing. Also end programs on Macintosh including virus check software.
- When installing, make sure to install from the account with PC supervisor privileges.

Preparation before Using L-03D

Setting via this Terminal

- 1** Turn on the PC and activate OS
- 2** Connect this terminal with the PC
CD-ROM icon is displayed on the desktop.
- 3** Double click the CD-ROM icon
- 4** Double click "L-03D 接続ソフトウェア インストーラー.pkg (L-03D connection software installer.pkg)"

- 5** Click "続ける (Continue)"

- 6** Click "続ける (Continue)"

- 7** Confirm "使用許諾契約 (The license agreement)". If agree with the contents, click "同意する (I Agree)"

- 8** Select an installation destination, click "続ける (Continue)"

- 9** Click "インストール (Install)"

- 10** Enter administrator password▶Click "OK"



- 11** Click "インストールを続ける(Continue installing)"

- 12** Click "再起動(Restart)"

The PC restarts. Installation finishes.
Remove this terminal from the PC temporarily.

Setting via CD-ROM

- 1 Start a PC ▶ Insert the CD-ROM into the PC
CD-ROM icon on desktop appears.
- 2 Double click CD-ROM icon ▶ "Mac" ▶ "L-03D
接続ソフト(L-03D connection software)" in the
order
- 3 For subsequent steps, operate the same
procedures as those after procedure 4 in
"Setting by this terminal"
Connect this terminal to the PC after restarting the PC in
procedure 12.

Confirming after Installation

Confirming L-03D Connection Software

- 1 Connect this terminal with the PC
- 2 Drag the CD image (DOCOMO icon) displayed
on desktop into trash bin
This terminal will be recognized as a modem.
- 3 Click "ネットワーク環境設定('Network'
environment configuration)"

- 4 Select "docomo L03D" and click "適用(Apply)"

- 5 Close "ネットワーク(Network)" screen

- 6 Double click to launch "Finder" ▶ "アプリケー
ション(Application)" ▶ "L-03D 接続ソフト.app
(L-03D connection software.app)"
When the following screen is displayed, the confirmation of
installation finishes.

■ Install Flash Player

A message appears when activating the L-03D
connection software for the first time if Flash Player is not
installed in your PC. Install Flash Player following the
procedures below.

- 1 Double click to launch "Finder" ▶ "アプリケー
ション(Application)" ▶ "L-03D 接続ソフト.app (L-03D
connection software.app)"

- 2 Click "OK"

- 3 Confirm the content of "使用許諾契約(The license
agreement)"; check "使用許諾契約の条件を読み、同意しま
した。(I have read the stipulations of this license
agreement and I agreed.)" and click "インストール
(Install)"



- 4 Enter administrator password ▶ Click "OK"



- 5 Click "完了(Finish)"



Installation finishes.

Note

- When communicating data via L-03D connection software,
setting environment configuration of L-03D connection
software is required. →P56

Uninstalling L-03D Connection Software (including a driver)

- Before uninstalling, remove this terminal from the PC.
- When uninstalling, make sure to install from the account with
PC supervisor privileges.

- 1 Insert the included CD-ROM into a PC
CD-ROM icon is displayed on the desktop.
- 2 Double click the CD-ROM icon ▶ "Mac"
▶ "L-03D 接続ソフト(L-03D connection
software)"
- 3 Double click "アンインストーラ.app
(Uninstaller.app)"

- 4 Click "アンインストール(Uninstall)"

- 5 Enter administrator password ▶ Click "OK"



- 6 Make sure this terminal is not connected to the
USB port before restarting

- 7 Click "再起動(Restart)"



The PC restarts. Uninstallation finishes.