

I	2	3	4	5	6																																																																																							
A	<div style="display: flex; justify-content: space-around;"> <div style="text-align: center;"> <p>Product Feature</p> </div> <div style="text-align: center;"> </div> <div style="text-align: center;"> </div> </div>				A																																																																																							
B	<div style="display: flex; justify-content: space-between;"> <div style="width: 33%;"> <p>Feature</p> <table border="1"> <thead> <tr> <th>MovFast item</th> <th>Parameters</th> </tr> </thead> <tbody> <tr><td>Dimensions</td><td>161mm x 147 mm x 68.5 mm</td></tr> <tr><td>Weight</td><td>366g</td></tr> <tr><td>Operating Temperature</td><td>-20°C ~ +60°C</td></tr> <tr><td>Humidity</td><td>5%~95% Non-condensing</td></tr> <tr><td>Drop Resistance</td><td>6 side * 30times drops for 1.5m</td></tr> <tr><td>Ingress Protection</td><td>IP65</td></tr> <tr><td>Sensors</td><td>Acceleration sensor, light sensor, and proximity sensor, E-Compass, Gyroscope.</td></tr> <tr><td>Processor</td><td>more than 10 hours. Support continuous scanning more than 24,000 times.</td></tr> <tr><td>Processor</td><td>MTK high-performance 8 cores 4*A53@2.0GHz+4*A53@1.5GHz</td></tr> <tr><td>OS</td><td>Android 11</td></tr> <tr><td>Wi-Fi</td><td>IEEE 802.11 a/b/g/n/ac</td></tr> <tr><td>Resolution</td><td>480*800</td></tr> </tbody> </table> </div> <div style="width: 33%;"> <p>Software</p> <div style="display: flex; justify-content: space-between;"> <div style="width: 48%;"> <p> Barcode Utility</p> <p>The application of scanning and decoding. Effectively recognizing, outputting the corresponding code, verification information</p> </div> <div style="width: 48%;"> <p> MovStage</p> <p>Mobile stage, which can quickly batch configure multiple PDA devices, with installing applications, configuring setting and Kiosk application etc functions. This tool increases efficiency, reduces repetitive work and errors in manual operations.</p> </div> <div style="width: 48%;"> <p> Kiosk</p> <p>Provide the user with a dedicated, functionally limited single application mode. Limit PDA devices to work exclusively assigned to a specific application. Provide the user with a tool that provides security, privacy and ensures that the user is focused on a specific application.</p> </div> </div> </div> <div style="width: 33%;"> <p>Notice</p> <p>Safety</p> <p>*Charging Connect the device with the plug or the socket corresponding to the marked input of the power adapter; To avoid injury, unauthorized person shall not open the power adapter.</p> <p>This product may cause radio interference in living environments. In that case, the user may be required to take adequate measures against interference.</p> <p>Significant Safety Instructions</p> <ul style="list-style-type: none"> Do not install or use the device during lightning storms to avoid the potential risks of lightning shock; To avoid the damages of eyes and safety, Do not Aim the laser beam to your eyes; Please turn off the power immediately if you notice abnormal odor, heat, or smoke; Suggestions Do not use the device near water or moisture to avoid liquid damage falling into the device; Do not use the device in extreme cold or hot environments, such as near flames or lit cigarettes; Do not drop, throw or bend the device; Use the device in a clean and dust-free environment if possible to prevent small items from falling into the device; Please do not use the device near medical equipment without permission; The operating temperature should be 20°C~60°C. <p>Statements</p> <p>Movfast does not assume responsibility for the following actions:</p> <ul style="list-style-type: none"> • Damages caused by use and maintenance w/out complying with the conditions specified in this guide; • Movfast will not assume any responsibilities for the damages or problems caused by optional items or consumables (rather than the initial products or approved products of Movfast). The customer users is not entitled to change or modify the product without our consent; • The product's operating system supports official system updates from Movfast, but if you change the operating system to a third-party ROM system or alter the system files by yourself, it may cause system instability and security risks and threats. <p>Disclaimer</p> <p>As a result of product upgrading, some details in this document may not match the product, and the actual product shall prevail. Movfast reserves the right to interpretation of this document. Movfast also reserves the right to alter this document without prior notice.</p> </div> </div>				MovFast item	Parameters	Dimensions	161mm x 147 mm x 68.5 mm	Weight	366g	Operating Temperature	-20°C ~ +60°C	Humidity	5%~95% Non-condensing	Drop Resistance	6 side * 30times drops for 1.5m	Ingress Protection	IP65	Sensors	Acceleration sensor, light sensor, and proximity sensor, E-Compass, Gyroscope.	Processor	more than 10 hours. Support continuous scanning more than 24,000 times.	Processor	MTK high-performance 8 cores 4*A53@2.0GHz+4*A53@1.5GHz	OS	Android 11	Wi-Fi	IEEE 802.11 a/b/g/n/ac	Resolution	480*800	B																																																													
MovFast item	Parameters																																																																																											
Dimensions	161mm x 147 mm x 68.5 mm																																																																																											
Weight	366g																																																																																											
Operating Temperature	-20°C ~ +60°C																																																																																											
Humidity	5%~95% Non-condensing																																																																																											
Drop Resistance	6 side * 30times drops for 1.5m																																																																																											
Ingress Protection	IP65																																																																																											
Sensors	Acceleration sensor, light sensor, and proximity sensor, E-Compass, Gyroscope.																																																																																											
Processor	more than 10 hours. Support continuous scanning more than 24,000 times.																																																																																											
Processor	MTK high-performance 8 cores 4*A53@2.0GHz+4*A53@1.5GHz																																																																																											
OS	Android 11																																																																																											
Wi-Fi	IEEE 802.11 a/b/g/n/ac																																																																																											
Resolution	480*800																																																																																											
C	<div style="display: flex; justify-content: space-between;"> <div style="width: 33%;"> <p>Radio Waves specs</p> <table border="1"> <thead> <tr> <th>Radio</th> <th>Frequency</th> <th>Max Output Power (dBm)</th> </tr> </thead> <tbody> <tr><td>GSM</td><td>900MHz</td><td>32.0</td></tr> <tr><td></td><td>1800MHz</td><td>28.9</td></tr> <tr><td>WCDMA</td><td>FDD I</td><td>22.44</td></tr> <tr><td></td><td>FDD VIII</td><td>22.41</td></tr> <tr><td>E-UTRA FDD</td><td>FDD 1</td><td>22.79</td></tr> <tr><td></td><td>FDD 3</td><td>23.06</td></tr> <tr><td></td><td>FDD 7</td><td>22.77</td></tr> <tr><td></td><td>FDD 8</td><td>23.59</td></tr> <tr><td></td><td>FDD 20</td><td>23.28</td></tr> <tr><td>E-UTRA TDD</td><td>TDD 34</td><td>22.56</td></tr> <tr><td></td><td>TDD 38</td><td>23.03</td></tr> <tr><td></td><td>TDD 40</td><td>22.87</td></tr> <tr><td>BT(classic)</td><td></td><td>15.1</td></tr> <tr><td>BLE</td><td></td><td>3.7</td></tr> <tr><td>WIFI(2.4G)</td><td></td><td>17.0</td></tr> <tr><td>WIFI 5G Band 1</td><td></td><td>16.9</td></tr> <tr><td>WIFI 5G Band 2</td><td></td><td>17.1</td></tr> <tr><td>WIFI 5G Band 4</td><td></td><td>13.9</td></tr> </tbody> </table> <p><small>Hereby, [Shanghai Xiangcheng Communication Technology Co., Ltd] declares that the radio equipment type [Intelligent Mobile Data Capture Terminal] is in compliance with Directive 2014/53/EU. The full text of the EU declaration of conformity is available at the following internet address: http://www.schengtech.com/ Under the declaration, the equipment is replaced by an incorrect type. Dispose of used batteries according to the instructions. Excessive sound pressure from earphones and headphones can cause hearing loss.</small></p> </div> <div style="width: 33%;"> <p></p> <table border="1"> <thead> <tr> <th>BE</th> <th>BG</th> <th>CZ</th> <th>DK</th> <th>HU</th> <th>MT</th> </tr> <tr> <th>DE</th> <th>EE</th> <th>IE</th> <th>EL</th> <th>NL</th> <th>AT</th> </tr> <tr> <th>ES</th> <th>FR</th> <th>HR</th> <th>IT</th> <th>PL</th> <th>PT</th> </tr> <tr> <th>CY</th> <th>LV</th> <th>LT</th> <th>LU</th> <th>SK</th> <th>FI</th> </tr> <tr> <th>RO</th> <th>SI</th> <th>SE</th> <th></th> <th></th> <th></th> </tr> </thead> </table> <p><small>Note: at 80 cm distance, the emission of 5150-5250MHz is restricted to indoor use only.</small></p> </div> <div style="width: 33%;"></div> </div>				Radio	Frequency	Max Output Power (dBm)	GSM	900MHz	32.0		1800MHz	28.9	WCDMA	FDD I	22.44		FDD VIII	22.41	E-UTRA FDD	FDD 1	22.79		FDD 3	23.06		FDD 7	22.77		FDD 8	23.59		FDD 20	23.28	E-UTRA TDD	TDD 34	22.56		TDD 38	23.03		TDD 40	22.87	BT(classic)		15.1	BLE		3.7	WIFI(2.4G)		17.0	WIFI 5G Band 1		16.9	WIFI 5G Band 2		17.1	WIFI 5G Band 4		13.9	BE	BG	CZ	DK	HU	MT	DE	EE	IE	EL	NL	AT	ES	FR	HR	IT	PL	PT	CY	LV	LT	LU	SK	FI	RO	SI	SE				C
Radio	Frequency	Max Output Power (dBm)																																																																																										
GSM	900MHz	32.0																																																																																										
	1800MHz	28.9																																																																																										
WCDMA	FDD I	22.44																																																																																										
	FDD VIII	22.41																																																																																										
E-UTRA FDD	FDD 1	22.79																																																																																										
	FDD 3	23.06																																																																																										
	FDD 7	22.77																																																																																										
	FDD 8	23.59																																																																																										
	FDD 20	23.28																																																																																										
E-UTRA TDD	TDD 34	22.56																																																																																										
	TDD 38	23.03																																																																																										
	TDD 40	22.87																																																																																										
BT(classic)		15.1																																																																																										
BLE		3.7																																																																																										
WIFI(2.4G)		17.0																																																																																										
WIFI 5G Band 1		16.9																																																																																										
WIFI 5G Band 2		17.1																																																																																										
WIFI 5G Band 4		13.9																																																																																										
BE	BG	CZ	DK	HU	MT																																																																																							
DE	EE	IE	EL	NL	AT																																																																																							
ES	FR	HR	IT	PL	PT																																																																																							
CY	LV	LT	LU	SK	FI																																																																																							
RO	SI	SE																																																																																										
D	<div style="display: flex; justify-content: space-between;"> <div style="width: 33%;"> <p>Function Quick Guide</p> <ul style="list-style-type: none"> Front Camera Earpiece Function Button Setup shortcut function in [Setting]—[Key Map] Scan Button Press the button to scan the 1D/2D Barcode Caution: Bright Light, Do not Aim or Align the scanner with eyes! USB Type-C Keyboard Power Button Short Press: Wake up/Lock the device Long Press: Device is Off: Press and Hold 2-3 seconds to Turn on the device *When Device is On: Press and Hold 2-3 Seconds to open the page to select power off or reboot Forced Reboot: Press and Hold 9 seconds to Reboot the Device when system crashes Hand Strap Holder Rear Camera For photo taking and 1D/2D Barcode scanning Back Cover Lock </div> <div style="width: 33%;"> <p>Keyboard</p> <table border="1"> <thead> <tr> <th>Sections</th> <th>Icon</th> <th>Functions</th> </tr> </thead> <tbody> <tr> <td>Regular Section</td> <td></td> <td>Direction Key: Left/Right/Up/Down Numeric Key: 1/2/3/4/5/6/7/8/9/0.</td> </tr> <tr> <td>Function Section</td> <td></td> <td>Direction Key: Scanner brightness up/down Volume up/down Numeric Key: F1/F2/F3/F4/F5/F6/F7/F8/F9/#/*</td> </tr> <tr> <td>Case Switching</td> <td></td> <td>Direction Key: Left/Right/Up/Down Numeric Key: Uppercase, Punctuation (ABC) Lowercase, Punctuation (abc) Space: Punctuation: Lower Case: punctuation(@ : /) abc: def: ghi: jkl: mno: pqr: tuv: wxyz: Space: punctuation(, ; : ? + -)</td> </tr> </tbody> </table> </div> <div style="width: 33%;"></div> </div>				Sections	Icon	Functions	Regular Section		Direction Key: Left/Right/Up/Down Numeric Key: 1/2/3/4/5/6/7/8/9/0.	Function Section		Direction Key: Scanner brightness up/down Volume up/down Numeric Key: F1/F2/F3/F4/F5/F6/F7/F8/F9/#/*	Case Switching		Direction Key: Left/Right/Up/Down Numeric Key: Uppercase, Punctuation (ABC) Lowercase, Punctuation (abc) Space: Punctuation: Lower Case: punctuation(@ : /) abc: def: ghi: jkl: mno: pqr: tuv: wxyz: Space: punctuation(, ; : ? + -)	D																																																																											
Sections	Icon	Functions																																																																																										
Regular Section		Direction Key: Left/Right/Up/Down Numeric Key: 1/2/3/4/5/6/7/8/9/0.																																																																																										
Function Section		Direction Key: Scanner brightness up/down Volume up/down Numeric Key: F1/F2/F3/F4/F5/F6/F7/F8/F9/#/*																																																																																										
Case Switching		Direction Key: Left/Right/Up/Down Numeric Key: Uppercase, Punctuation (ABC) Lowercase, Punctuation (abc) Space: Punctuation: Lower Case: punctuation(@ : /) abc: def: ghi: jkl: mno: pqr: tuv: wxyz: Space: punctuation(, ; : ? + -)																																																																																										
E	<div style="display: flex; justify-content: space-between;"> <div style="width: 33%;"> <p>PRODUCT SAFETY WARNINGS</p> <p>PRODUCT SAFETY WARNINGS</p> <p>PRODUCT SAFETY WARNINGS</p> <p>CE</p> <p>FC</p> </div> <div style="width: 33%;"> <p>PRODUCT SAFETY WARNINGS</p> <p>The equipment meets the requirements of the relevant regulations and standards of the European Economic Area. CE marking is a harmonized certification system set up by the European Union in order to ensure that products meet the basic requirements for safety, health and the environment during their free circulation and sale in the European market.</p> <p>The device has been tested and evaluated by the Federal Communications Commission (FCC) and complies with the relevant radio spectrum and electromagnetic compatibility requirements in the U.S. FCC certification ensures that the device is legal for sale and use in the U.S.</p> </div> <div style="width: 33%;"> <p>Ranger1 K/G Quick Start Guide MOVFAST</p> </div> </div>				E																																																																																							
F	<div style="display: flex; justify-content: space-between;"> <div style="width: 33%;"> <p>SIZE / DRAWING 张迪 PART NO. K7612000395LA</p> <p>UNIT mm TITLE Ranger 1 K/G_movfast_快速指南</p> <p>SCALE 1:1 CHECKED 张冬梅 Vender 仁睿</p> <p>SHEET 1 of 1 APPR. DATE 2024.01.22 REV V0.2</p> </div> <div style="width: 33%;"></div> <div style="width: 33%;"> <p>3rd ANGLE PROJECTION</p> <p></p> </div> </div>				F																																																																																							
G	<p></p>				G																																																																																							