



RF TEST REPORT

Product Name: TECHMATE Multi-Function Travel Companion

Model Name: SB3590, SB3590B, SB3590RG, SB3590L and
SB3590XXXXX(Where XXXXX denote any printable characters in the ASCII
standard character Table to represent variances in cosmetics or buyers)

FCC ID: 2A38HSB3590

Issued For : Jenmart Industrial (HK) Co., Limited

Units A&B, 15/F, Neich Tower, 128 Gloucester Road, Wanchai,
Hong Kong

Issued By : Shenzhen LGT Test Service Co., Ltd.

Room 205, Building 13, Zone B, Zhenxiong Industrial Park,
No.177, Renmin West Road, Jinsha, Kengzi Street, Pingshan
District, Shenzhen, Guangdong, China

Report Number: LGT23L013HA02

Sample Received Date: Dec. 06, 2023

Date of Test: Dec. 06, 2023 – Dec. 27, 2023

Date of Issue: Dec. 27, 2023

The test report is effective only with both signature and specialized stamp. This report shall not be reproduced except in full without the written approval of the Laboratory. The results in this report only apply to the tested sample.



TEST REPORT CERTIFICATION

Applicant: Jenmart Industrial (HK) Co., Limited
Address: Units A&B, 15/F, Neich Tower, 128 Gloucester Road, Wanchai, Hong Kong
Manufacture: Rich Glory Electronics Co., Ltd.
Address: No.10 Xiling Road, Fengcheng Street, Xinfeng County, Shaoguan City, GuangDong Province, China
Product Name: TECHMATE Multi-Function Travel Companion
Trademark: Studebaker
Model Name: SB3590, SB3590B, SB3590RG, SB3590L and SB3590XXXXX(Where XXXXX denote any printable characters in the ASCII standard character Table to represent variances in cosmetics or buyers)
Sample Status: Normal

| APPLICABLE STANDARDS | |
|---|--------------|
| STANDARD | TEST RESULTS |
| FCC 47CFR §2.1093 KDB 447498 D01 General RF Exposure Guidance v06 | PASS |

Prepared by:

Zane Shan

Zane Shan
Engineer

Approved by:

Vita Li

Vita Li
Technical Director





TABLE OF CONTENTS

| | |
|--|----------|
| 1 . GENERAL INFORMATION | 5 |
| 1.1 GENERAL DESCRIPTION OF THE EUT | 5 |
| 1.2 TEST LABORATORY | 5 |
| 2 . FCC 47CFR §2.1093 REQUIREMENT | 6 |
| 2.1 TEST STANDARDS | 6 |
| 2.2 LIMIT | 6 |
| 2.3 TEST RESULT | 8 |



Revision History

| Rev. | Issue Date | Revisions |
|------|---------------|---------------|
| 00 | Dec. 27, 2023 | Initial Issue |
| | | |



1. GENERAL INFORMATION

1.1 GENERAL DESCRIPTION OF THE EUT

| | | |
|-------------------|--|--------------|
| Product Name: | TECHMATE Multi-Function Travel Companion | |
| Trademark: | Studebaker | |
| Model Name: | SB3590 | |
| Series Model: | SB3590B, SB3590RG, SB3590L and SB3590XXXXX (Where XXXXX denote any printable characters in the ASCII standard character Table to represent variances in cosmetics or buyers) | |
| Model Difference: | Only different in model name | |
| Frequency Bands: | Bluetooth | 2402-2480MHz |
| Adapter: | Input: 100-240V ~ 50/60Hz 0.8A Output: 5V3A or 9V3A or 12V2.5A or 15V2A or 20V1.5A | |
| Hardware Version: | N/A | |
| Software Version: | N/A | |

1.2 TEST LABORATORY

| | |
|---------------------------|--|
| Company Name: | Shenzhen LGT Test Service Co., Ltd. |
| Address: | Room 205, Building 13, Zone B, Zhenxiong Industrial Park, No.177, Renmin West Road, Jinsha, Kengzi Street, Pingshan District, Shenzhen, Guangdong, China |
| Accreditation Certificate | A2LA Certificate No.: 6727.01 |
| | FCC Registration No.: 746540 |
| | CAB ID: CN0136 |



2. FCC 47CFR §2.1093 REQUIREMENT

2.1 TEST STANDARDS

The limit for Maximum Permissible Exposure (MPE) specified in KDB 447498 D01 General RF Exposure Guidance v06 is followed. The gain of the antennas used in the product is extracted from the Antenna data sheets provided and also the maximum total power input to the antenna is measured. Through the Friis transmission formula and the maximum gain of the antenna, we can calculate the distance, away from the product, where the limit of MPE is reached.

Although the Friis Transmission formula is far field assumption, the calculated result of that is an over-prediction for near field power density. It is taken as worst case to specify the safety range.

2.2 LIMIT

Approximate SAR Test Exclusion Power Thresholds at Selected Frequencies and Test Separation Distances are illustrated in the following Table.

| MHz | 5 | 10 | 15 | 20 | 25 | mm |
|------|-----|-----|-----|-----|-----|--|
| 150 | 39 | 77 | 116 | 155 | 194 | <i>SAR Test Exclusion Threshold (mW)</i> |
| 300 | 27 | 55 | 82 | 110 | 137 | |
| 450 | 22 | 45 | 67 | 89 | 112 | |
| 835 | 16 | 33 | 49 | 66 | 82 | |
| 900 | 16 | 32 | 47 | 63 | 79 | |
| 1500 | 12 | 24 | 37 | 49 | 61 | |
| 1900 | 11 | 22 | 33 | 44 | 54 | |
| 2450 | 10 | 19 | 29 | 38 | 48 | |
| 3600 | 8 | 16 | 24 | 32 | 40 | |
| 5200 | 7 | 13 | 20 | 26 | 33 | |
| 5400 | 6 | 13 | 19 | 26 | 32 | |
| 5800 | 6 | 12 | 19 | 25 | 31 | |
| MHz | 30 | 35 | 40 | 45 | 50 | mm |
| 150 | 232 | 271 | 310 | 349 | 387 | <i>SAR Test Exclusion Threshold (mW)</i> |
| 300 | 164 | 192 | 219 | 246 | 274 | |
| 450 | 134 | 157 | 179 | 201 | 224 | |
| 835 | 98 | 115 | 131 | 148 | 164 | |
| 900 | 95 | 111 | 126 | 142 | 158 | |
| 1500 | 73 | 86 | 98 | 110 | 122 | |
| 1900 | 65 | 76 | 87 | 98 | 109 | |
| 2450 | 57 | 67 | 77 | 86 | 96 | |
| 3600 | 47 | 55 | 63 | 71 | 79 | |
| 5200 | 39 | 46 | 53 | 59 | 66 | |
| 5400 | 39 | 45 | 52 | 58 | 65 | |
| 5800 | 37 | 44 | 50 | 56 | 62 | |



The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances \leq 50 mm are determined by:

$[(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] \leq 3.0 \text{ for 1-g SAR and } \leq 7.5 \text{ for 10-g extremity SAR, where } f(\text{GHz}) \text{ is the RF channel transmit frequency in GHz.}$

Power and distance are rounded to the nearest mW and mm before calculation

The result is rounded to one decimal place for comparison

The test exclusions are applicable only when the minimum test separation distance is \leq 50 mm and for transmission frequencies between 100 MHz and 6 GHz. When the minimum test separation distance is < 5 mm, a distance of 5 mm is applied to determine SAR test exclusion.



2.3 TEST RESULT

Turn up Result

| Mode | Turn up Power |
|--------------|---------------|
| BT-GFSK | '-0.1±1dBm |
| BT-π/4-DQPSK | 3.1±1dBm |
| BT-8DPSK | 4±1dBm |



The MPE result of worst mode:

| RF Function | Frequency (MHz) | Max Turn up Power (dBm) | Max Turn up Power (mW) | Estimated SAR | Limit | Ratio | Result |
|-------------|-----------------|-------------------------|------------------------|---------------|-------|-------|--------|
| BT | 2441 | 5.00 | 3.16 | 0.988 | 3 | 0.329 | Pass |

Note:

1. The estimated SAR \leq 3.0 for 1-g SAR, Separation distance \leq 5mm, complies with the exemption requirements.

※※※※※END OF THE REPORT※※※※※