

SRF-M810 UHF Radio Frequency Identification (RFID) Module User's Manual

Overview :

As a long-range radio frequency identification (RFID) reader, the SRF-M810 is a 900MHz (UHF band) UHF RFID reader operable at various operating bands specified by individual countries. It also complies with all standard protocols defined in ISO18000-6C (EPC GEN2) .

Features :

- Small and powerful performance
- 30 dBm RF power output
- Including TTL232 communication interface can remote and back-end equipment to transfer code and control code.
- Read up 750 tags/second
- Avoid the interference of other radio frequencies with the look-up table frequency-hopping spread spectrum (FHSS)
- Pass FCC ,NCC certification
- Support external sensors and controllers
- API under Windows operating system for shorten application development time
- The complete TTL232 instruction format facilitates the expansion of device functional integrity

Recommended uses :

- Driveway control and management / personnel access control and management of residential buildings, buildings, and communities
- Industrial relate management and control
- Elevator control and management
- Logistics related management
- Asset management
- Security monitoring
- Handheld devices and scanners

NCC

Brand : CiaoDa

取得審驗證明之低功率射頻器材，非經核准，公司、商號或使用者均不得擅自變更頻率、加大功率或變更原設計之特性及功能。低功率射頻器材之使用不得影響飛航安全及干擾合法通信；經發現有干擾現象時，應立即停用，並改善至無干擾時方得繼續使用。前述合法通信，指依電信管理法規定作業之無線電通信。低功率射頻器材須忍受合法通信或工業、科學及醫療用電波輻射性電機設備之干擾。

平台商於最終產品內含已認證過之射頻模組(組件)，應於最終產品本體明顯處標示

「本產品內含射頻模組 CC XX xx LP yyy Z z 」

FCC

- FCC ID : 2A3LY-SRFM810

Federal Communications Commission (FCC) Statement

This device complies with Part 15 of the FCC Rules.

Operation is subject to the following two conditions:

- 1) this device may not cause harmful interference and
- 2) this device must accept any interference received, including interference that may cause undesired operation.

Federal Communications Commission (FCC) Statement

15.105(b)

This equipment has been tested and found to comply with the limits for a **Class B** digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

15.21

You are cautioned that changes or modifications not expressly approved by the part responsible for compliance could void the user's authority to operate the equipment.

FCC RF Radiation Exposure Statement:

1. This Transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.
2. This equipment complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with a minimum distance of **20** centimeters between the radiator and your body.

List of applicable FCC rules

This module has been tested and found to comply with the following requirements for Modular Approval.

- § 15.249 Operation within the bands 902.75-927.25 MHz.

RF exposure considerations

In the end product, the antenna(s) used with this transmitter must be installed to provide a separation distance of at least 20cm from all persons and must not be co-located or operation in conjunction with any other antenna or transmitter except in accordance with FCC multi-transmitter product procedures. User and installers must be provided with antenna installation instructions and transmitter operating conditions for satisfying the RF exposure compliance.

The OEM integrator has to be aware not to provide information to the end user regarding how to install or remove this RF module in the user's manual of the end product which integrates this module. The end user manual shall include all required regulatory information/warning as shown in User manual.

Antennas

The following external antenna type have been approved for use with this radio transmitter.

Antenna Type	Freq. (MHz)	Max. Peak Antenna Gain (dBi)
Patch	902~908	5.24

Label and compliance information

Any device incorporating this module must include an external, visible, permanent marking or label which states: “ **Contains FCC ID: 2A3LY-SRFM810** ”.

Information on test modes and additional testing requirements

This device uses various test mode programs for test set up which operate separate from production firmware. Host integrators should contact the grantee for assistance with test modes needed for module/host compliance test requirements.

Additional testing, Part 15 Subpart B disclaimer

The modular transmitter is only FCC authorized for the specific rule parts (i.e., FCC transmitter rules) listed on the grant, and that the host product manufacturer is responsible for compliance to any other FCC rules that apply to the host not covered by the modular transmitter grant of certification.

The final host product still requires Part 15 Subpart B compliance testing with the modular transmitter installed.


Product specifications :

DC POWER	5 V
Current Consumption	Max. 1500mA
RFID Protocol Support	EPC Global Gen2V2(ISO 18000-63) with DRM
Antenna	2 Port
Antenna Connector	Ipex 1
Antenna Setting	GPIO/Instruction
Antenna Impedance	50 ohm U.FL.
Antenna Return Loss	10dB min
Control Interface	UART
Frequency	922-928 MHz/Taiwan,902.75-927.25 MHz/FCC,865-868 MHz/CE
RF POWER	30 dBm
Max Read Rate	Over 750PCS per second with Direct Mode
Query	Static/Dynamic QUERY
Max Tag Read Distance	Over 9 meter with 5.24dBi Antenna
Receive Sentivity	-89 dBm
Operating Temp.	-20°C ~ +60°C
Storage Temp.	-20°C ~ +85°C
Humidity	5-90%
Dimension (L*W*H)	45.7mm L x 26.2mm W x 4mm H
Weight	
SDK Support	DLL with C, Demo Software & Source Code with C#

Pin Description :

A1	GND
A2	GND
A3	GND
A4	GND
A5	GND
A6	GND
A7	GND
A8	GND
A9	EXT RESET
A10	SHUT DOWN
A11	GND
A12	GND
A13	VIN
A14	VIN

C1	GND
C2	ANT1
C3	GND
C4	ANT2



B1	GND
B2	GND
B3	GND
B4	GND
B5	GND
B6	GND
B7	GND
B8	USB_DP
B9	USB_DM
B10	USB_5V
B11	GPIO1
B12	GPIO2
B13	DATA_UART0_TXD
B14	DATA_UART0_RXD


Pin	Pin Name	Description
A1	GND	Ground pin for main reference ground
A2	GND	Ground pin for main reference ground
A3	GND	Ground pin for main reference ground
A4	GND	Ground pin for main reference ground
A5	GND	Ground pin for main reference ground
A6	GND	Ground pin for main reference ground
A7	GND	Ground pin for main reference ground
A8	GND	Ground pin for main reference ground
A9	EXT RESET	Reserved
A10	SHUT DOWN	Shut down RF module
A11	GND	Ground pin for main reference ground
A12	GND	Ground pin for main reference ground
A13	VIN	Power supply input
A14	VIN	Power supply input

Pin	Pin Name	Description
B1	GND	Ground pin for main reference ground
B2	GND	Ground pin for main reference ground
B3	GND	Ground pin for main reference ground
B4	GND	Ground pin for main reference ground
B5	GND	Ground pin for main reference ground
B6	GND	Ground pin for main reference ground
B7	GND	Ground pin for main reference ground
B8	USB_DP	Reserved
B9	USB_BM	Reserved
B10	USB_5V	Reserved
B11	GPIO1	Function define. Refer to user guide
B12	GPIO2	Function define. Refer to user guide
B13	UART0_TXD	UART0 data transmitter output pin
B14	UART0_RXD	UART0 data receiver input pin


Pin	Pin Name	Description
C1	GND	Ground pin for main reference ground
C2	ANT1	Ipex 1 connector for antenna 1 port
C3	GND	Ground pin for main reference ground
C4	ANT2	Ipex 1 connector for antenna 2 port

Layout Guide


1. In the bottom of the RF module exposed copper, coated with thermal paste




2. Cooling Recommendations on layout



Landing Pattern Recommendation:



Dimension :



Warranty Coverage:

1. The product's warranty against defects in materials and workmanship under normal use for a period of ONE YEAR from the date of purchase by the original user of the Product. This warranty is non-transferable.
2. If the product prove to be defective within the warranty period, Szok will repair the product defect at no charge, using new or refurbished replacement parts to proper operating condition.

This Warranty Does Not Apply To:

1. Damage from flood, fire, earthquake, natural disaster or other external causes.
2. If the defects are due to damage caused by accident, misuse, tampering, unauthorized modification or human negligence, such as parts lost, loose or lack of care and physical abuse to the product (e.g, scratches, dents, or cracks).
3. Damage caused by operating the product outside the permitted, intended uses described by Szok, or service(including upgrades and expansions) performed by unauthorized representative.
4. If any serial number or logo affixed has been altered, removed, duplicated or defaced from Szok Product.