



## Shenzhen Huaxia Testing Technology Co., Ltd.

1F., Block A of Tongsheng Technology Building, Huahui Road, Dalang Street, Longhua District, Shenzhen, China

Telephone: +86-755-26648640  
Fax: +86-755-26648637  
Website: [www.cqa-cert.com](http://www.cqa-cert.com)

Report Template Version: V05  
Report Template Revision Date: 2021-11-03

# RF Exposure Evaluation Report

**Report No.:** CQASZ20220300312E-02  
**Applicant:** Globe (Jiangsu) Co., Ltd.  
**Address of Applicant:** No. 65 Xinggang Road, Zhonglou Zone, Changzhou, Jiangsu, China  
**Equipment Under Test (EUT):**  
**EUT Name:** Bluetooth Speaker  
**Model No.:** BTG501, BTF501, BTG901, BTF901  
**Test Model No.:** BTG901  
**Brand Name:** **greenworks**  
**FCC ID:** 2A3VG-BTF501  
**Standards:** 47 CFR Part 1.1307  
47 CFR Part 2.1093  
447498 D04 Interim General RF Exposure Guidance v01  
**Date of Receipt:** 2022-03-03  
**Date of Test:** 2022-03-03 to 2022-03-31  
**Date of Issue:** 2022-08-09  
**Test Result:** **PASS\***

\*In the configuration tested, the EUT complied with the standards specified above

**Tested By:** lewis zhou

( Lewis Zhou )

**Reviewed By:** K. Liao

( K Liao )

**Approved By:** Jack Ai

( Jack Ai )



## 1 Version

### Revision History Of Report

Report No.	Version	Description	Issue Date
CQASZ20220300312E-02	Rev.01	Initial report	2022-08-09

## 2 Contents

	Page
<b>1 VERSION</b> .....	2
<b>2 CONTENTS</b> .....	3
<b>3 GENERAL INFORMATION</b> .....	4
3.1 CLIENT INFORMATION .....	4
3.2 GENERAL DESCRIPTION OF EUT .....	4
3.3 GENERAL DESCRIPTION OF BT .....	4
<b>4 SAR EVALUATION</b> .....	5
4.1 RF EXPOSURE COMPLIANCE REQUIREMENT .....	5
4.1.1 Standard Requirement.....	5
4.1.2 Limits.....	5
4.1.3 EUT RF Exposure .....	7

### 3 General Information

#### 3.1 Client Information

Applicant:	Globe (Jiangsu) Co., Ltd.
Address of Applicant:	No. 65 Xinggang Road, Zhonglou Zone, Changzhou, Jiangsu, China
Manufacturer:	Globe (Jiangsu) Co., Ltd.
Address of Manufacturer:	No. 65 Xinggang Road, Zhonglou Zone, Changzhou, Jiangsu, China
Factory:	Asimom Technology Co., Ltd
Address of Factory:	1/F Block C, No.431 Yangxin Road, Yangyong Village, Dalang Town, Dongguan, 523770, China

#### 3.2 General Description of EUT

Product Name:	Bluetooth Speaker
Model No.:	BTG501, BTF501, BTG901, BTF901
Test Model No	BTG901
Trade Mark:	<b>greenworks</b>
EUT Supports Radios application:	Bluetooth mode 2402-2480MHz
Software Version:	DOSS_303_2835_211230_1.30_24V
Hardware Version:	1.0
Sample Type:	<input type="checkbox"/> Mobile <input checked="" type="checkbox"/> Portable <input type="checkbox"/> Fix Location
EUT Power Supply:	Detachable battery: DC 24V 2Ah, Charge by DC 20V for adapter Model No.:BL60G-200300-AdU Input: 100-240V~50/60Hz 1.5A Output: 20V 3A

#### 3.3 General Description of BT

Operation Frequency:	2402MHz~2480MHz
Bluetooth Version:	V5.1
Modulation Technique:	Frequency Hopping Spread Spectrum(FHSS)
Modulation Type:	GFSK, π/4DQPSK, 8DPSK
Number of Channel:	79
Transfer Rate:	1Mbps/2Mbps/3Mbps
Test Software of EUT:	BT FCC Tool V2.23
Antenna Type:	PCB antenna
Antenna Gain:	0dBi

Model No.:BTG501, BTF501, BTG901, BTF901

Their electrical circuit design, layout, components used, internal PCBs, and appearance are all the same, only the battery supply voltage is different.

The supply voltage is different because the voltage of the external battery is different

## 4 SAR Evaluation

### 4.1 RF Exposure Compliance Requirement

#### 4.1.1 Standard Requirement

447498 D04 Interim General RF Exposure Guidance v01

##### 3.2. SAR Test Reduction Guidance

SAR test reduction procedures [Glossary] allow using a particular set of test data as representative of other, similar, test conditions. This may be applied for data within different test positions (e.g. body, head, extremity), wireless modes (e.g. Wi-Fi, cellular), and frequency bands. This test reduction process provides for the use of test data for one specific channel, while referencing to those data for demonstrating compliance in other required channels for each test position of an exposure condition, within the operating mode of a frequency band. This is limited specifically to when the reported 1-g or 10-g SAR for the mid-band or highest output power channel meets any of the following conditions.

#### 4.1.2 Limits

SAR-based thresholds are derived based on frequency, power, and separation distance of the RF source. The formula defines the thresholds in general for either available maximum time-averaged power or maximum time-averaged ERP, whichever is greater.

If the ERP of a device is not easily determined, such as for a portable device with a small form factor, the applicant may use the available maximum time-averaged power exclusively if the device antenna or radiating structure does not exceed an electrical length of  $\lambda/4$ .

As for devices with antennas of length greater than  $\lambda/4$  where the gain is not well defined, but always less than that of a half-wave dipole (length  $\lambda/2$ ), the available maximum time-averaged power generated by the device may be used in place of the maximum time-averaged ERP, where that value is not known.

The separation distance is the smallest distance from any part of the antenna or radiating structure for all persons, during operation at the applicable ERP. In the case of mobile or portable devices, the separation distance is from the outer housing of the device where it is closest to the antenna.

The SAR-based exemption formula of § 1.1307(b)(3)(i)(B), repeated here as Formula (B.2), applies for single fixed, mobile, and portable RF sources with available maximum time-averaged power or effective radiated power (ERP), whichever is greater, of less than or equal to the threshold  $P_{th}$  (mW).

This method shall only be used at separation distances from 0.5 cm to 40 cm and at frequencies from 0.3 GHz to 6 GHz (inclusive).  $P_{th}$  is given by Formula (B.2).

$$P_{th} \text{ (mW)} = \begin{cases} ERP_{20 \text{ cm}}(d/20 \text{ cm})^x & d \leq 20 \text{ cm} \\ ERP_{20 \text{ cm}} & 20 \text{ cm} < d \leq 40 \text{ cm} \end{cases} \quad (\text{B.2})$$

where

$$x = -\log_{10} \left( \frac{60}{ERP_{20 \text{ cm}} \sqrt{f}} \right)$$

and  $f$  is in GHz,  $d$  is the separation distance (cm), and  $ERP_{20\text{cm}}$  is per Formula (B.1). The example values shown in Table B.2 are for illustration only.

Table B.2—Example Power Thresholds (mW)

Frequency (MHz)	Distance (mm)									
	5	10	15	20	25	30	35	40	45	50
300	39	65	88	110	129	148	166	184	201	217
450	22	44	67	89	112	135	158	180	203	226
835	9	25	44	66	90	116	145	175	207	240
1900	3	12	26	44	66	92	122	157	195	236
2450	3	10	22	38	59	83	111	143	179	219
3600	2	8	18	32	49	71	96	125	158	195
5800	1	6	14	25	40	58	80	106	136	169

**4.1.3 EUT RF Exposure****Measurement Data**

Channel	Maximum Peak Conducted Output Power (dBm)	Maximum tune-up Power (mW)	Exclusion threshold (mW)
Lowest (2402MHz)	1.69	1.48	3.0
Middle (2440MHz)	1.66	1.47	
Highest (2480MHz)	1.52	1.42	

Remark: The Max Conducted Peak Output Power data refer to report Report No.: CQASZ20220300312E-01.

\*\*\* END OF REPORT \*\*\*