

## RF Exposure evaluation

According to 447498 D04 Interim General RF Exposure Guidance v01

$$P_{th} \text{ (mW)} = \begin{cases} ERP_{20 \text{ cm}}(d/20 \text{ cm})^x & d \leq 20 \text{ cm} \\ ERP_{20 \text{ cm}} & 20 \text{ cm} < d \leq 40 \text{ cm} \end{cases} \quad (\text{B.2})$$

where

$$x = -\log_{10} \left( \frac{60}{ERP_{20 \text{ cm}} f} \right)$$

and  $f$  is in GHz,  $d$  is the separation distance (cm), and  $ERP_{20\text{cm}}$  is per Formula (B.1).  
The example values shown in Table B.2 are for illustration only.

$$P_{th} \text{ (mW)} = ERP_{20 \text{ cm}} \text{ (mW)} = \begin{cases} 2040f & 0.3 \text{ GHz} \leq f < 1.5 \text{ GHz} \\ 3060 & 1.5 \text{ GHz} \leq f \leq 6 \text{ GHz} \end{cases} \quad (\text{B.1})$$

Table B.2—Example Power Thresholds (mW)

Frequency (MHz)	Distance (mm)									
	5	10	15	20	25	30	35	40	45	50
300	39	65	88	110	129	148	166	184	201	217
450	22	44	67	89	112	135	158	180	203	226
835	9	25	44	66	90	116	145	175	207	240
1900	3	12	26	44	66	92	122	157	195	236
2450	3	10	22	38	59	83	111	143	179	219
3600	2	8	18	32	49	71	96	125	158	195
5800	1	6	14	25	40	58	80	106	136	169

$$eirp = pt \times gt = (Exd)^2/30$$

where:

pt = transmitter output power in watts,

gt = numeric gain of the transmitting antenna (unitless),

E = electric field strength in V/m, ---  $10^{((\text{dBuV/m})/20)/10^6}$

d = measurement distance in meters (m)---3m

$$S_{opt} = (Exd)^2/30 \times gt$$

$$\text{Ant gain} = -0.58 \text{ dBi}, \text{ so Ant numeric gain} = 0.875$$

### Left Part:

Field strength = 76.95 dB $\mu$ V/m @3m@2480MHz (Worst Case)

$$\text{So Pt} = \{[10^{(76.95/20)/10^6} \times 3]^2 / (30 \times 0.875)\} \times 1000 \text{ mW} = 0.017 \text{ mW}$$

$$< 2.79 \text{ mW}$$

$$\text{ERP} = 0.017 \times 0.533 = 0.009061 \text{ mW}$$

### Right Part:

Field strength = 77.84 dB $\mu$ V/m @3m@2480MHz (Worst Case)

$$\text{So Pt} = \{[10^{(77.84/20)/10^6} \times 3]^2 / (30 \times 0.875)\} \times 1000 \text{ mW} = 0.0209 \text{ mW}$$

$$< 2.79 \text{ mW}$$

$$\text{ERP} = 0.0209 \times 0.533 = 0.0111397 \text{ mW}$$

Then SAR evaluation is not required