



TEST REPORT

Product Name: Wireless Bluetooth headset
FCC ID: 2A5CE-OBT020
Trademark: N/A
Model Number: OBT 020, OBT-021, OBT-022, OBT-023, OBT-024, OBT-025, OBT-026, OBT-027, OBT-028, OBT-029, OBT-030, OBT-031, OBT-32, OBT-033, OBT-034, OBT-035, OBT-036, OBT-037, OBT-038, OTB-039
Prepared For: Shenzhen Kensing Electronic Co., Ltd.
Address: 3A, Building 5, Hanhaida (Tianliao) Science and Technology Park, Guangming New District, Shenzhen, 518000 China
Manufacturer: Shenzhen Kensing Electronic Co., Ltd.
Address: 3A, Building 5, Hanhaida (Tianliao) Science and Technology Park, Guangming New District, Shenzhen, 518000 China
Prepared By: Shenzhen CTB Testing Technology Co., Ltd.
Address: 1&2/F., Building A, No.26, Xinhe Road, Xinqiao, Xinqiao Street, Bao'an District, Shenzhen, Guangdong, China
Sample Received Date: Apr. 29, 2025
Sample tested Date: Apr. 29, 2025 to May. 30, 2025
Issue Date: May. 30, 2025
Report No.: CTB25042900504RF01
Test Standards: FCC CFR Title 47 Part 15 Subpart C Section 15.247
ANSI C63.10:2020
Test Results: PASS
Remark: This is Bluetooth radio test report.

Compiled by:

Reviewed by:

Approved by:

Zhou kui

Arron Liu

Bin Mei

Zhou Kui

Arron Liu

Bin Mei / Director

Note: If there is any objection to the inspection results in this report, please submit a written report to the company within 15 days from the date of receiving the report. The test report is effective only with both signature and specialized stamp. This result(s) shown in this report refer only to the sample(s) tested. Without written approval of Shenzhen CTB Testing Technology Co., Ltd. this report can't be reproduced except in full. The tested sample(s) and the sample information are provided by the client. "*" indicates the testing items were fulfilled by subcontracted lab. "#" indicates the items are not in CNAS accreditation scope.

TABLE OF CONTENT

Test Report Declaration	Page
1. VERSION	3
2. TEST SUMMARY	4
3. MEASUREMENT UNCERTAINTY	5
4. PRODUCT INFORMATION AND TEST SETUP	6
4.1 Product Information	6
4.2 Test Setup Configuration	6
4.3 Support Equipment	6
4.4 Channel List	7
4.5 Test Mode	7
4.6 Test Environment	7
5. TEST FACILITY AND TEST INSTRUMENT USED	8
5.1 Test Facility	8
5.2 Test Instrument Used	8
6. AC POWER LINE CONDUCTED EMISSION	11
6.1 Block Diagram Of Test Setup	11
6.2 Limit	11
6.3 Test procedure	11
6.4 Test Result	13
7. RADIATED SPURIOUS EMISSION	15
7.1 Block Diagram Of Test Setup	15
7.2 Limit	15
7.3 Test procedure	16
7.4 Test Result	17
8. BAND EDGE AND RF CONDUCTED SPURIOUS EMISSIONS	31
8.1 Block Diagram Of Test Setup	31
8.2 Limit	31
8.3 Test procedure	31
8.4 Test Result	32
9. CONDUCTED OUTPUT POWER	40
9.1 Block Diagram Of Test Setup	40
9.2 Limit	40
9.3 Test procedure	40
9.4 Test Result	41
10. 6DB OCCUPIED BANDWIDTH	51
10.1 Block Diagram Of Test Setup	51
10.2 Limit	51
10.3 Test procedure	51
10.4 Test Result	51
11. POWER SPECTRAL DENSITY	57
11.1 Block Diagram Of Test Setup	57
11.2 Limit	57
11.3 Test procedure	57
11.4 Test Result	57
12. ANTENNA REQUIREMENT	63
13. EUT TEST SETUP PHOTOGRAPHS	64

(Note: N/A means not applicable)



1. **VERSION**

Report No.	Issue Date	Description	Approved
CTB25042900504RF01	May. 30, 2025	Original	Valid

2. TEST SUMMARY

The Product has been tested according to the following specifications:

Test Item	Test Requirement	Test method	Result
AC Power Line Conducted Emission	47 CFR Part 15 Subpart C Section 15.207	ANSI C63.10:2020	PASS
Radiated Spurious emissions	47 CFR Part 15 Subpart C Section 15.205/15.209	ANSI C63.10:2020	PASS
Band edge and RF Conducted Spurious Emissions	47 CFR Part 15 Subpart C Section 15.247(d)/15.205(a)	ANSI C63.10:2020	PASS
Conducted Peak Output Power	47 CFR Part 15 Subpart C Section 15.247 (b)(3)	ANSI C63.10:2020	PASS
Bandwidth	47 CFR Part 15 Subpart C Section 15.247 (a)(2)	ANSI C63.10:2020	PASS
Power Spectral Density	47 CFR Part 15 Subpart C Section 15.247 (e)	ANSI C63.10:2020/ KDB 558074 D01v05r02	PASS
Antenna Requirement	47 CFR Part 15 Subpart C Section 15.203/15.247 (b)	/	PASS

Remark:

Test according to ANSI C63.10:2020

3. MEASUREMENT UNCERTAINTY

Where relevant, the following measurement uncertainty levels have been estimated for tests performed on the Product as specified in CISPR 16-4-2. This uncertainty represents an expanded uncertainty expressed at approximately the 95% confidence level using a coverage factor of k=2.

Item	Uncertainty
Occupancy bandwidth	54.3kHz
Conducted output power Above 1G	0.9dB
Conducted output power below 1G	0.9dB
Power Spectral Density , Conduction	0.9dB
Conduction spurious emissions	2.0dB
Out of band emission	2.0dB
3m chamber Radiated spurious emission(9K-30MHz)	4.8dB
3m chamber Radiated spurious emission(30MHz-1GHz)	4.6dB
3m chamber Radiated spurious emission(1GHz-18GHz)	5.1dB
3m chamber Radiated spurious emission(18GHz-40GHz)	3.4dB
humidity uncertainty	5.5%
Temperature uncertainty	0.63℃
frequency	1×10 ⁻⁷
Conducted Emission (150KHz-30MHz)	3.2 dB
Radiated Emission(30MHz ~ 1000MHz)	4.8 dB
Radiated Emission(1GHz ~6GHz)	4.9 dB

4. PRODUCT INFORMATION AND TEST SETUP

4.1 Product Information

Model(s):	OBT 020, OBT-021, OBT-022, OBT-023, OBT-024, OBT-025, OBT-026, OBT-027, OBT-028, OBT-029, OBT-030, OBT-031, OBT-32, OBT-033, OBT-034, OBT-035, OBT-036, OBT-037, OBT-038, OBT-039
Model Description:	All the model are the same circuit and RF module, only the name and appearance colors are different. Test sample model: OBT 020
Bluetooth Version:	Bluetooth 5.3
Hardware Version:	V1.0
Software Version:	V1.0
Operation Frequency:	Bluetooth: 2402-2480MHz Left ear: Bluetooth: 1M: 2.694dBm 2M: 2.501dBm
Max. RF output power:	Right ear: Bluetooth: 1M: 2.471dBm 2M: 2.606dBm
Type of Modulation:	Bluetooth: GFSK
Antenna installation:	Bluetooth: Chip antenna
Antenna Gain:	Bluetooth: 2.78dBi Input: 5V=0.5A
Ratings:	The capacity of the charging case battery: 3.7V, 500mAh, 1.85Wh Capacity of headphone battery: 3.7V, 60mAh, 0.222Wh

4.2 Test Setup Configuration

See test photographs attached in EUT TEST SETUP PHOTOGRAPHS for the actual connections between Product and support equipment.

4.3 Support Equipment

Item	Equipment	Mfr/Brand	Model/Type No.	Series No.	Note
1.	Adapter	JIYIN	JY-05100C	/	AE
2	Charging Box	/	/	/	AE

Notes:

1. All the equipment/cables were placed in the worst-case configuration to maximize the emission during the test.
2. Grounding was established in accordance with the manufacturer's requirements and conditions for the intended use.

4.4 Channel List

CH No.	Frequency (MHz)	CH No.	Frequency (MHz)	CH No.	Frequency (MHz)	CH No.	Frequency (MHz)
0	2402	1	2404	2	2406	3	2408
4	2410	5	2412	6	2414	7	2416
8	2418	9	2420	10	2422	11	2424
12	2426	13	2428	14	2430	15	2432
16	2434	17	2436	18	2438	19	2440
20	2442	21	2444	22	2446	23	2448
24	2450	25	2452	26	2454	27	2456
28	2458	29	2460	30	2462	31	2464
32	2466	33	2468	34	2470	35	2472
36	2474	37	2476	38	2478	39	2480

4.5 Test Mode

All test mode(s) and condition(s) mentioned were considered and evaluated respectively by performing full tests, the worst data were recorded and reported.

Test mode	Low channel	Middle channel	High channel
Transmitting (GFSK)	2402MHz	2440MHz	2480MHz
Charging(Conducted Emission)	/	/	/

4.6 Test Environment

Humidity(%):	54
Atmospheric Pressure(kPa):	101
Normal Voltage(DC):	3.7V
Normal Temperature(°C)	23
Low Temperature(°C)	0
High Temperature(°C)	40

5. TEST FACILITY AND TEST INSTRUMENT USED

5.1 Test Facility

All measurement facilities used to collect the measurement data are located at 1&2F., Building A, No. 26, Xinghe Road, Xinqiao, Xinqiao Street, Bao'an District, Shenzhen, Guangdong, China. The site and apparatus are constructed in conformance with the requirements of ANSI C63.4 and CISPR 16-1-1 other equivalent standards.

FCC Test Firm Registration Number: CN1276

5.2 Test Instrument Used

No.	Equipment	Manufacturer	Type No.	Serial No.	Firmware Version	Calibrated until
1	Spectrum Analyzer	Agilent	N9020A	MY52090073	A.14.16	2025/6/28
2	Power Sensor	Agilent	U2021XA	MY56120032	/	2025/6/28
3	Power Sensor	Agilent	U2021XA	MY56120034	/	2025/6/28
4	Communication test set	R&S	CMW500	108058	V3.5.80	2025/6/28
5	Spectrum Analyzer	KEYSIGHT	N9020A	MY51289897	A.14.16	2025/6/28
6	Signal Generator	Agilent	N5181A	MY50140365	A.01.60	2025/6/28
7	Vector signal generator	Agilent	N5182A	MY47420195	A.01.87	2025/6/28
8	Communication test set	Agilent	E5515C	MY50102567	B.19.07 (E1962B)	2025/6/28
9	2.4 GHz Filter	Shenxiang	MSF2400-24 83.5MS-1154	20181015001	/	2025/6/30
10	5 GHz Filter	Shenxiang	MSF5150-58 50MS-1155	20181015001	/	2025/6/30
11	Filter	Xingbo	XBLBQ-DZA 120	190821-1-1	/	2025/6/30
12	BT&WI-FI Automatic test software	Microwave	MTS8310	Ver. 2.0.0.0	/	/
13	Rohde & Schwarz SFU Broadcast Test System	R&S	SFU	101017	/	2025/6/28
14	Temperature humidity chamber	Hongjing	TH-80CH	DG-15174	/	2025/6/28
15	234G Automatic test software	Microwave	MTS8200	Ver. 2.0.0.0	/	/
16	966 chamber	C.R.T.	966	/	/	2027/6/21
17	Receiver	R&S	ESPI	100362	RF_ATTEN_7 (104489/003)	2025/6/28
18	Amplifier	HP	8447E	2945A02747	/	2025/6/28
19	Amplifier	Agilent	8449B	3008A01838	/	2025/6/28
20	TRILOG Broadband Antenna	Schwarzbeck	VULB 9168	00869	/	2025/6/28

21	Double Ridged Broadband Horn Antenna	Schwarzbeck	BBHA9120D	01911	/	2025/6/28
22	EMI test software	Fala	EZ-EMC	FA-03A2 RE	/	/
23	Loop Antenna	Schwarzbeck	FMZB 1519B	1519B-224	/	2025/6/28
24	loop antenna	ZHINAN	ZN30900A	GTS534	/	/
25	40G Horn antenna	A/H/System	SAS-574	588	/	2025/6/28
26	Amplifier	AEROFLEX	Aeroflex	097	/	2025/6/28
27	Power Metter	KEYSIGHT	N1912AP	N/A	A.05.00	2025/6/28


Continuous disturbance						
No.	Equipment	Manufacturer	Model No.	Serial No.	Firmware version	Calibrated until
1	843 Shield Room	C/ R/ T	843	/	/	2027/6/21
2	AMN	ROHDE&SCHWARZ	ESH3-Z5	831551852	/	2025/6/30
3	Pulse limiter	ROHDE&SCHWARZ	ESH3Z2	357881052	/	2025/6/28
4	EMI TEST RECEIVER	ROHDE&SCHWARZ	ESCI	100428	V4.42.SP3	2025/6/30
5	Coaxial cable	ZDECL	Z302S	18091904	/	2025/6/30
6	ISN	Schwarzbeck	NTFM8158	183	/	2025/6/30
7	Voltage sensor	Schwarzbeck	TK 9420	01189	/	2025/10/25
8	EZ-EMC	Frad	EMC-con3A1.1	/	/	/
9	Current Probe	FCC	F-52B	199453	/	2025/5/27
10	Communication test set	R&S	CMW500	108058	B.19.07 (E1962B)	2025/6/28
11	Communication test set	Agilent	E5515C	MY50102567	V3.5.80	2025/6/28

Radiated emission(No.1 Chamber)						
No.	Equipment	Manufacturer	Model No.	Serial No.	Firmware version	Calibrated until
1	966 Chamber	C/ R/ T	966	/	/	2027/6/21
2	Double Ridged Broadband Horn Antenna	Schwarzbeck	BBHA 9120 D	01911	/	2025/7/06
3	TRILOG Broadband Antenna	Schwarzbeck	VULB 9168	00869	/	2025/6/29
4	Amplifier	Agilent	8449B	3008A01838	/	2025/6/30
5	Amplifier	HP	8447E	2945A02747	/	2025/6/28
6	loop antenna	Schwarzbeck	FMZB 1519B	1519B-224	/	2025/6/29
7	EMI TEST RECEIVER	ROHDE&SCHWARZ	ESPI	100362	RF_ATTEN_7 (104489/003)	2025/6/28

8	Spectrum Analyzer	KEYSIGHT	N9020A	MY51289897	A.14.16	2025/6/28
9	Coaxial cable	ETS	RFC-SNS-100-NMS-80	/	/	2025/6/28
10	Coaxial cable	ETS	RFC-SN-100-NMS-20	/	/	2025/6/28
11	Coaxial cable	ETS	RFC-SNS-100-SMS-20	/	/	2025/6/28
12	Coaxial cable	ETS	RFC-NNS-100-NMS-300	/	/	2025/6/28
13	EMI test software	Frad	EZ-EMC	Ver/ FA-03A2 RE	/	/
14	Communication test set	R&S	CMW500	108058	B.19.07 (E1962B)	2025/6/28
15	Communication test set	Agilent	E5515C	MY50102567	V3.5.80	2025/6/28

6. AC POWER LINE CONDUCTED EMISSION

6.1 Block Diagram Of Test Setup



6.2 Limit

Table 4 – AC power-line conducted emissions limits

Frequency (MHz)	Conducted limit (dB μ V)	
	Quasi-peak	Average
0.15 - 0.5	66 to 56 ^{Note 1}	56 to 46 ^{Note 1}
0.5 - 5	56	46
5 - 30	60	50

Note 1: The level decreases linearly with the logarithm of the frequency.

* Decreasing linearly with the logarithm of the frequency

6.3 Test procedure


- 1) The mains terminal disturbance voltage test was conducted in a shielded room.
- 2) The EUT was connected to AC power source through a LISN 1 (Line Impedance Stabilization Network) which provides a 50 Ω /50 μ H + 5 Ω linear impedance. The power cables of all other units of the EUT were connected to a second LISN 2, which was bonded to the ground reference plane in the same way as the LISN 1 for the unit being measured. A multiple socket outlet strip was used to connect multiple power cables to a single LISN provided the rating of the LISN was not exceeded.
- 3) The tabletop EUT was placed upon a non-metallic table 0.8m above the ground reference plane. And for floor-standing arrangement, the EUT was placed on the horizontal ground reference plane,
- 4) The test was performed with a vertical ground reference plane. The rear of the EUT shall be 0.4 m from the vertical ground reference plane. The vertical ground reference plane was bonded to the horizontal ground reference plane. The LISN 1 was placed 0.8 m from the boundary of the unit under

test and bonded to a ground reference plane for LISNs mounted on top of the ground reference plane. This distance was between the closest points of the LISN 1 and the EUT. All other units of the EUT and associated equipment was at least 0.8 m from the LISN 2.

- 5) In order to find the maximum emission, the relative positions of equipment and all of the interface cables must be changed according to ANSI C63.10:2013 on conducted measurement.
- 6) All modes were tested at AC 120V and 240V, only the worst result of AC 120V 60Hz was reported.
- 7) If a EUT received DC power from the USB Port of Notebook PC, the PC's adapter received AC120V/60Hz power through a Line Impedance Stabilization Network (LISN) which supplied power source and was grounded to the ground plane.

6.4 Test Result

L: Charging mode




No.	Mk.	Freq. MHz	Reading Level dBuV	Correct Factor dB	Measure- ment dBuV	Limit dBuV	Over dB	Detector
1		0.1740	24.08	10.80	34.88	64.77	-29.89	QP
2		0.1740	8.56	10.80	19.36	54.77	-35.41	AVG
3		0.1980	21.05	10.72	31.77	63.69	-31.92	QP
4		0.1980	9.77	10.72	20.49	53.69	-33.20	AVG
5		0.2620	20.65	10.67	31.32	61.37	-30.05	QP
6		0.2620	9.24	10.67	19.91	51.37	-31.46	AVG
7		0.3980	22.81	10.57	33.38	57.90	-24.52	QP
8		0.3980	11.13	10.57	21.70	47.90	-26.20	AVG
9	*	0.6300	34.13	10.64	44.77	56.00	-11.23	QP
10		0.6300	19.31	10.64	29.95	46.00	-16.05	AVG
11		1.2700	22.75	11.12	33.87	56.00	-22.13	QP
12		1.2700	8.05	11.12	19.17	46.00	-26.83	AVG

Remark:

Factor = Cable loss + LISN factor, Margin = Measurement – Limit

N: Charging mode



No.	Mk.	Freq. MHz	Reading Level dBuV	Correct Factor dB	Measure- ment dBuV	Limit dBuV	Over dB	Detector
1		0.1740	24.58	10.80	35.38	64.77	-29.39	QP
2		0.1740	10.20	10.80	21.00	54.77	-33.77	AVG
3		0.4180	22.28	10.56	32.84	57.49	-24.65	QP
4		0.4180	10.05	10.56	20.61	47.49	-26.88	AVG
5 *		0.6419	32.81	10.66	43.47	56.00	-12.53	QP
6		0.6419	21.06	10.66	31.72	46.00	-14.28	AVG
7		1.2820	21.71	11.13	32.84	56.00	-23.16	QP
8		1.2820	8.28	11.13	19.41	46.00	-26.59	AVG
9		2.8699	21.70	11.77	33.47	56.00	-22.53	QP
10		2.8699	8.91	11.77	20.68	46.00	-25.32	AVG
11		15.6700	20.63	13.37	34.00	60.00	-26.00	QP
12		15.6700	1.11	13.37	14.48	50.00	-35.52	AVG

Remark:

Factor = Cable loss + LISN factor, Margin = Measurement – Limit

7. RADIATED SPURIOUS EMISSION

7.1 Block Diagram Of Test Setup




Figure 1. Below 30MHz





Figure 2. 30MHz to 1GHz



7.2 Limit

Spurious Emissions:

Frequency	Field strength (microvolt/meter)	Limit (dBμV/m)	Remark	Measurement distance (m)
0.009MHz-0.490MHz	2400/F(kHz)	-	-	300
0.490MHz-1.705MHz	24000/F(kHz)	-	-	30
1.705MHz-30MHz	30	-	-	30
30MHz-88MHz	100	40.0	Quasi-peak	3
88MHz-216MHz	150	43.5	Quasi-peak	3
216MHz-960MHz	200	46.0	Quasi-peak	3
960MHz-1GHz	500	54.0	Quasi-peak	3
Above 1GHz	500	54.0	Average	3

Note: 15.35(b), Unless otherwise specified, the limit on peak radio frequency emissions is 20dB above the maximum permitted average emission limit applicable to the equipment under test. This peak limit applies to the total peak emission level radiated by the device.

7.3 Test procedure

Below 1GHz test procedure as below:

- a. The EUT was placed on the top of a rotating table 0.8 meters above the ground at a 3 meter semi-anechoic chamber. The table was rotated 360 degrees to determine the position of the highest radiation.
- b. The EUT was set 3 meters away from the interference-receiving antenna, which was mounted on the top of a variable-height antenna tower.
- c. The antenna height is varied from one meter to four meters above the ground to determine the maximum value of the field strength. Both horizontal and vertical polarizations of the antenna are set to make the measurement.
- d. For each suspected emission, the EUT was arranged to its worst case and then the antenna was tuned to heights from 1 meter to 4 meters (for the test frequency of below 30MHz, the antenna was tuned to heights 1 meter) and the rota table table was turned from 0 degrees to 360 degrees to find the maximum reading.
- e. The test-receiver system was set to Peak Detect Function and Specified Bandwidth with Maximum Hold Mode.
- f. If the emission level of the EUT in peak mode was 10dB lower than the limit specified, then testing could be stopped and the peak values of the EUT would be reported. Otherwise the emissions that did not have 10dB margin would be re-tested one by one using peak, quasi-peak or average method as specified and then reported in a data sheet.

Above 1GHz test procedure as below:

- g. Different between above is the test site, change from Semi- Anechoic Chamber to fully Anechoic Chamber and change form table 0.8 meter to 1.5 meter(Above 18GHz the distance is 1 meter and table is 1.5 meter).
- h. Test the EUT in the lowest channel ,the middle channel ,the Highest channel
- i. Repeat above procedures until all frequencies measured was complete.
- j. Full battery is used during test.

Receiver set:

Frequency	Detector	RBW	VBW	Remark
0.009MHz-0.090MHz	Peak	10kHz	30KHz	Peak
0.009MHz-0.090MHz	Average	10kHz	30KHz	Average
0.090MHz-0.110MHz	Quasi-peak	10kHz	30KHz	Quasi-peak
0.110MHz-0.490MHz	Peak	10kHz	30KHz	Peak
0.110MHz-0.490MHz	Average	10kHz	30KHz	Average
0.490MHz -30MHz	Quasi-peak	10kHz	30kHz	Quasi-peak
30MHz-1GHz	Quasi-peak	120 kHz	300KHz	Quasi-peak
Above 1GHz	Peak	1MHz	3MHz	Peak
	Peak	1MHz	10Hz	Average

7.4 Test Result

Left ear:

Below 1GHz Test Results:

Antenna polarity: H

Worst case-GFSK-1M(low channel)



No.	Mk.	Freq. MHz	Reading Level dBuV	Correct Factor dB	Measure- ment dBuV/m	Limit dB/m	Over dB	Detector
1		49.4460	25.98	-6.64	19.34	40.00	-20.66	QP
2		85.1486	26.72	-9.46	17.26	40.00	-22.74	QP
3		160.0648	25.66	-0.84	24.82	43.50	-18.68	QP
4		394.8545	26.78	-0.83	25.95	46.00	-20.05	QP
5	*	622.8900	26.00	3.98	29.98	46.00	-16.02	QP
6		1000.000	28.05	8.96	37.01	54.00	-16.99	QP

Remark: Factor = Cable lose + Antenna factor - Pre-amplifier; Margin = Measurement – Limit

Antenna polarity: V
Worst case-GFSK-1M(low channel)



No.	Mk.	Freq. MHz	Reading Level dBuV	Correct Factor dB	Measure- ment dBuV/m	Limit dB/m	Over dB	Detector
1		46.9125	27.16	-6.71	20.45	40.00	-19.55	QP
2		160.0648	26.14	-0.84	25.30	43.50	-18.20	QP
3		259.2338	26.94	-3.64	23.30	46.00	-22.70	QP
4		431.0316	25.79	0.17	25.96	46.00	-20.04	QP
5		550.9480	26.62	2.86	29.48	46.00	-16.52	QP
6	*	775.5169	27.27	6.91	34.18	46.00	-11.82	QP

Remark: Factor = Cable lose + Antenna factor - Pre-amplifier; Margin = Measurement – Limit

Right ear:

Below 1GHz Test Results:

Antenna polarity: H

Worst case-GFSK-1M(low channel)



No.	Mk.	Freq. MHz	Reading Level dBuV	Correct Factor dB	Measure- ment dBuV/m	Limit dB/m	Over dB	Detector
1		36.3813	28.43	-6.67	21.76	40.00	-18.24	QP
2		57.8975	27.28	-7.18	20.10	40.00	-19.90	QP
3	*	162.8959	28.23	-1.19	27.04	43.50	-16.46	QP
4		328.4626	27.66	-2.28	25.38	46.00	-20.62	QP
5		541.3724	25.36	2.73	28.09	46.00	-17.91	QP
6		1000.000	26.55	8.96	35.51	54.00	-18.49	QP

Remark: Factor = Cable lose + Antenna factor - Pre-amplifier; Margin = Measurement- Limit

Antenna polarity: V
Worst case-GFSK-1M(low channel)



No.	Mk.	Freq. MHz	Reading Level dBuV	Correct Factor dB	Measure- ment dBuV/m	Limit dB/m	Over dB	Detector
1		51.2105	25.97	-6.71	19.26	40.00	-20.74	QP
2		123.0494	29.19	-5.37	23.82	43.50	-19.68	QP
3		160.0646	27.64	-0.84	26.80	43.50	-16.70	QP
4		233.3486	26.68	-4.15	22.53	46.00	-23.47	QP
5	*	596.1770	25.92	3.51	29.43	46.00	-16.57	QP
6		965.5420	27.13	8.72	35.85	54.00	-18.15	QP

Remark: Factor = Cable lose + Antenna factor - Pre-amplifier; Margin = Measurement- Limit

Left ear:

Above 1 GHz Test Results:

CH Low (2402MHz)-1M

Horizontal:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4804	58.30	-3.64	54.66	74	-19.34	peak
4804	48.16	-3.64	44.52	54	-9.48	AVG
7206	61.04	-0.95	60.09	74	-13.91	peak
7206	50.42	-0.95	49.47	54	-4.53	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4804	59.18	-3.64	55.54	74	-18.46	peak
4804	47.78	-3.64	44.14	54	-9.86	AVG
7206	60.94	-0.95	59.99	74	-14.01	peak
7206	48.03	-0.95	47.08	54	-6.92	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

CH Middle (2440MHz)-1M
Horizontal:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4880	55.39	-3.51	51.88	74	-22.12	peak
4880	46.33	-3.51	42.82	54	-11.18	AVG
7320	56.14	-0.82	55.32	74	-18.68	peak
7320	46.93	-0.82	46.11	54	-7.89	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4880	55.56	-3.51	52.05	74	-21.95	peak
4880	45.11	-3.51	41.60	54	-12.40	AVG
7320	57.74	-0.82	56.92	74	-17.08	peak
7320	46.76	-0.82	45.94	54	-8.06	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

CH High (2480MHz)-1M
Horizontal:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4960	55.33	-3.43	51.90	74	-22.10	peak
4960	45.64	-3.43	42.21	54	-11.79	AVG
7440	56.97	-0.75	56.22	74	-17.78	peak
7440	46.99	-0.75	46.24	54	-7.76	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4960	55.39	-3.43	51.96	74	-22.04	peak
4960	46.97	-3.43	43.54	54	-10.46	AVG
7440	55.44	-0.75	54.69	74	-19.31	peak
7440	46.50	-0.75	45.75	54	-8.25	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits

Remark:

- (1). Measuring frequencies from 9KHz to the 25 GHz, The test range is 9K ~10 times the main wave, and other spurious below the limit of 20dB will not be reflected in the report.
- (2). All modes of GFSK-1M and GFSK-2M were test at Low, Middle, and High channel, only the worst result of GFSK-1M Low Channel was reported for below 1GHz test.
- (3). For BT above 1GHz test all modes of GFSK-1M and GFSK-2M were test at Low, Middle, and High channel, only the worst result of GFSK-1M was reported.
- (4). By preliminary testing and verifying three axis (X, Y and Z) position of EUT transmitted status, it was found that "Z axis" position was the worst, and test data recorded in this report.
- (5). Radiated emission test from 9kHz to 10th harmonic of fundamental was verified, and no emission found except system noise floor in 9kHz to 30MHz and not recorded in this report.

Restricted bands around fundamental frequency (Radiated)

Operation Mode: TX CH Low (2402MHz)
Horizontal (Worst case)

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2310	62.03	-5.81	56.22	74	-17.78	peak
2310	/	-5.81	/	54	/	AVG
2390	61.25	-5.84	55.41	74	-18.59	peak
2390	/	-5.84	/	54	/	AVG
2400	62.33	-5.84	56.49	74	-17.51	peak
2400	/	-5.84	/	54	/	AVG

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2310	62.55	-5.81	56.74	74	-17.26	peak
2310	/	-5.81	/	54	/	AVG
2390	63.14	-5.84	57.30	74	-16.70	peak
2390	/	-5.84	/	54	/	AVG
2400	62.88	-5.84	57.04	74	-16.96	peak
2400	/	-5.84	/	54	/	AVG

When the peak value is smaller than the AVG limit, AVG is not reflected.

Operation Mode: TX CH High (2480MHz)
Horizontal (Worst case)

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2483.50	61.55	-5.65	55.90	74	-18.10	peak
2483.50	/	-5.65	/	54	/	AVG
2500.00	63.41	-5.65	57.76	74	-16.24	peak
2500.00	/	-5.65	/	54	/	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2483.50	63.14	-5.65	57.49	74	-16.51	peak
2483.50	/	-5.65	/	54	/	AVG
2500.00	62.55	-5.65	56.90	74	-17.10	peak
2500.00	/	-5.65	/	54	/	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						
Remark: All the other emissions not reported were too low to read and deemed to comply with FCC limit.						

When the peak value is smaller than the AVG limit, AVG is not reflected.

Right ear:

Above 1 GHz Test Results:

CH Low (2402MHz)

Horizontal:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4804	58.08	-3.64	54.44	74	-19.56	peak
4804	49.22	-3.64	45.58	54	-8.42	AVG
7206	59.16	-0.95	58.21	74	-15.79	peak
7206	48.84	-0.95	47.89	54	-6.11	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4804	57.32	-3.64	53.68	74	-20.32	peak
4804	49.28	-3.64	45.64	54	-8.36	AVG
7206	59.28	-0.95	58.33	74	-15.67	peak
7206	48.14	-0.95	47.19	54	-6.81	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

CH Middle (2440MHz)

Horizontal:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4880	54.77	-3.51	51.26	74	-22.74	peak
4880	46.12	-3.51	42.61	54	-11.39	AVG
7320	56.45	-0.82	55.63	74	-18.37	peak
7320	47.11	-0.82	46.29	54	-7.71	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4880	54.57	-3.51	51.06	74	-22.94	peak
4880	45.64	-3.51	42.13	54	-11.87	AVG
7320	57.25	-0.82	56.43	74	-17.57	peak
7320	47.72	-0.82	46.90	54	-7.10	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

CH High (2480MHz)
Horizontal:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4960	54.67	-3.43	51.24	74	-22.76	peak
4960	46.62	-3.43	43.19	54	-10.81	AVG
7440	55.43	-0.75	54.68	74	-19.32	peak
7440	46.74	-0.75	45.99	54	-8.01	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4960	54.81	-3.43	51.38	74	-22.62	peak
4960	47.29	-3.43	43.86	54	-10.14	AVG
7440	55.71	-0.75	54.96	74	-19.04	peak
7440	45.93	-0.75	45.18	54	-8.82	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Remark:

- (1). Measuring frequencies from 9KHz to the 25 GHz, The test range is 9K ~10 times the main wave, and other spurious below the limit of 20dB will not be reflected in the report.
- (2). All modes of GFSK-1M and GFSK-2M were test at Low, Middle, and High channel, only the worst result of GFSK-1M Low Channel was reported for below 1GHz test.
- (3). For BT above 1GHz test all modes of GFSK-1M and GFSK-2M were test at Low, Middle, and High channel, only the worst result of GFSK-1M was reported.
- (4). By preliminary testing and verifying three axis (X, Y and Z) position of EUT transmitted status, it was found that "Z axis" position was the worst, and test data recorded in this report.
- (5). Radiated emission test from 9kHz to 10th harmonic of fundamental was verified, and no emission found except system noise floor in 9kHz to 30MHz and not recorded in this report.

Restricted bands around fundamental frequency (Radiated)

Operation Mode: TX CH Low (2402MHz)
Horizontal (Worst case)

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2310	63.52	-5.81	57.71	74	-16.29	peak
2310	/	-5.81	/	54	/	AVG
2390	61.25	-5.84	55.41	74	-18.59	peak
2390	/	-5.84	/	54	/	AVG
2400	62.89	-5.84	57.05	74	-16.95	peak
2400	/	-5.84	/	54	/	AVG

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2310	63.47	-5.81	57.66	74	-16.34	peak
2310	/	-5.81	/	54	/	AVG
2390	64.25	-5.84	58.41	74	-15.59	peak
2390	/	-5.84	/	54	/	AVG
2400	62.01	-5.84	56.17	74	-17.83	peak
2400	/	-5.84	/	54	/	AVG

When the peak value is smaller than the AVG limit, AVG is not reflected.

Operation Mode: TX CH High (2480MHz)
Horizontal (Worst case)

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2483.50	62.10	-5.65	56.45	74	-17.55	peak
2483.50	/	-5.65	/	54	/	AVG
2500.00	63.02	-5.65	57.37	74	-16.63	peak
2500.00	/	-5.65	/	54	/	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						


Vertical:

Frequency	Reading Result	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2483.50	64.20	-5.65	58.55	74	-15.45	peak
2483.50	/	-5.65	/	54	/	AVG
2500.00	61.25	-5.65	55.60	74	-18.40	peak
2500.00	/	-5.65	/	54	/	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						
Remark: All the other emissions not reported were too low to read and deemed to comply with FCC limit.						

When the peak value is smaller than the AVG limit, AVG is not reflected.

8. BAND EDGE AND RF CONDUCTED SPURIOUS EMISSIONS

8.1 Block Diagram Of Test Setup



8.2 Limit

In any 100 kHz bandwidth outside the frequency band in which the spread spectrum or digitally modulated intentional radiator is operating, the radio frequency power that is produced by the intentional radiator shall be at least 20 dB below that in the 100 kHz bandwidth within the band that contains the highest level of the desired power, based on either an RF conducted or a radiated measurement, provided the transmitter demonstrates compliance with the peak conducted power limits. If the transmitter complies with the conducted power limits based on the use of RMS averaging over a time interval, as permitted under paragraph (b)(3) of this section, the attenuation required under this paragraph shall be 30 dB instead of 20 dB. Attenuation below the general limits specified in §15.209(a) is not required. In addition, radiated emissions which fall in the restricted bands, as defined in §15.205(a), must also comply with the radiated emission limits specified in §15.209(a) (see §15.205(c)).

8.3 Test procedure

1. Remove the antenna from the EUT and then connect a low RF cable from the antenna port to the spectrum;
2. Set the spectrum analyzer:

Below 30MHz:

RBW = 100kHz, VBW = 300kHz, Sweep = auto

Detector function = peak, Trace = max hold

Above 30MHz:

RBW = 100kHz, VBW = 300kHz, Sweep = auto

Detector function = peak, Trace = max hold


8.4 Test Result

Left ear:


8M:

BAND EDGE Graphs

GFSK/LCH




GFSK/HCH




RF Conducted Spurious Emissions Graphs


GFSK/LCH




GFSK/MCH



GFSK/HCH




2M:




RF Conducted Spurious Emissions Graphs


GFSK/LCH



GFSK/MCH




GFSK/HCH




Right ear:
1M:

BAND EDGE Graphs

GFSK/LCH




GFSK/HCH




RF Conducted Spurious Emissions Graphs


GFSK/LCH




GFSK/MCH



GFSK/HCH




2M:




RF Conducted Spurious Emissions Graphs


GFSK/LCH



GFSK/MCH




GFSK/HCH



9. COUDUCTED OUTPUT POWER

9.1 Block Diagram Of Test Setup



9.2 Limit

FCC Part15 (15.247) , Subpart C				
Section	Test Item	Limit	Frequency Range (MHz)	Result
15.247(b)(3)	Output Power	1 watt or 30dBm	2400-2483.5	PASS

9.3 Test procedure

1. Remove the antenna from the EUT and then connect a low RF cable from the antenna port to the spectrum.
2. Set the spectrum analyzer: RBW = 2MHz. VBW = 6MHz. Channel power measurement. Sweep = auto; Detector Function = peak.
3. Keep the EUT in transmitting at lowest, middle and highest channel individually. Record the max value.

9.4 Test Result

Left ear:

1M:

Mode	Channel.	Maximum Output Power [dBm]	Limit[dBm]	Verdict
GFSK	LCH	1.221	30	PASS
	MCH	2.694	30	PASS
	HCH	2.093	30	PASS

Duty Cycle

Mode	Channel.	Duty Cycle(%)	Correction Factor (dB)
GFSK	LCH	34.13	4.67
	MCH	35.48	4.50
	HCH	33.60	4.74

2M:

Mode	Channel.	Maximum Output Power [dBm]	Limit[dBm]	Verdict
GFSK	LCH	1.294	30	PASS
	MCH	2.501	30	PASS
	HCH	2.208	30	PASS

Duty Cycle

Mode	Channel.	Duty Cycle(%)	Correction Factor (dB)
GFSK	LCH	15.87	7.99
	MCH	20.00	6.99
	HCH	19.20	7.17

Note: Duty Cycle Factor= $10 \log (1/x)$, x is Duty Cycle.

Right ear:

1M:

Mode	Channel.	Maximum Output Power [dBm]	Limit[dBm]	Verdict
GFSK	LCH	1.385	30	PASS
	MCH	2.471	30	PASS
	HCH	2.074	30	PASS

Duty Cycle

Mode	Channel.	Duty Cycle(%)	Correction Factor (dB)
GFSK	LCH	53.33	2.73
	MCH	54.05	2.67
	HCH	55.41	2.56

2M:

Mode	Channel.	Maximum Output Power [dBm]	Limit[dBm]	Verdict
GFSK	LCH	1.44	30	PASS
	MCH	2.606	30	PASS
	HCH	2.258	30	PASS

Duty Cycle


Mode	Channel.	Duty Cycle(%)	Correction Factor (dB)
GFSK	LCH	27.27	5.64
	MCH	29.26	5.34
	HCH	28.00	5.53

Note: Duty Cycle Factor= $10 \log (1/x)$, x is Duty Cycle.

Left ear:

1M:

Test Graph:



Duty Cycle


1M:

Test Graph:



2M:

Test Graph:



Duty Cycle

2M:


Test Graph:



Right ear:

1M:


Test Graph:



Duty Cycle


1M:

Test Graph:



2M:

Test Graph:



Duty Cycle


2M:

Test Graph:



10. 6DB OCCUPIED BANDWIDTH

10.1 Block Diagram Of Test Setup



10.2 Limit

FCC Part15 (15.247) , Subpart C				
Section	Test Item	Limit	Frequency Range (MHz)	Result
15.247(a)(2)	Bandwidth	$\geq 500\text{KHz}$ (6dB bandwidth)	2400-2483.5	PASS

10.3 Test procedure

1. Rem1. Set RBW = 100 kHz.
2. Set the video bandwidth (VBW) $\geq 3 \times$ RBW.
3. Detector = Peak.
4. Trace mode = max hold.
5. Sweep = auto couple.
6. Allow the trace to stabilize.
7. Measure the maximum width of the emission that is constrained by the frequencies associated with the two outermost amplitude points (upper and lower frequencies) that are attenuated by 6 dB relative to the maximum level measured in the fundamental emission.

10.4 Test Result

Left ear:

1M:

Test Mode	Frequency	6dB Bandwidth (MHz)	Limit (KHz)	Result
GFSK	Low channel	0.642	≥ 500	PASS
	Mid channel	0.642	≥ 500	PASS
	High channel	0.642	≥ 500	PASS

2M:

Test Mode	Frequency	6dB Bandwidth (MHz)	Limit (KHz)	Result
GFSK	Low channel	1.117	≥ 500	PASS
	Mid channel	1.121	≥ 500	PASS
	High channel	1.135	≥ 500	PASS

Note: All modes of operation were Pre-scan and the worst-case emissions are reported.

Right ear:

1M:

Test Mode	Frequency	6dB Bandwidth (MHz)	Limit (KHz)	Result
GFSK	Low channel	0.643	≥ 500	PASS
	Mid channel	0.642	≥ 500	PASS
	High channel	0.631	≥ 500	PASS

2M:

Test Mode	Frequency	6dB Bandwidth (MHz)	Limit (KHz)	Result
GFSK	Low channel	1.127	≥ 500	PASS
	Mid channel	1.129	≥ 500	PASS
	High channel	1.164	≥ 500	PASS


Note: All modes of operation were Pre-scan and the worst-case emissions are reported.

Left ear:
1M:
Test Graph:

GFSK Low channel	 Agilent Spectrum Analyzer - Occupied BW Center Freq 2.402000000 GHz Ref Offset 7.03 dB Ref 27.03 dBm Mkr3 2.402333 GHz -6.0809 dBm Center 2.402 GHz #Res BW 100 kHz #VBW 300 kHz Span 3 MHz Sweep 1 ms Occupied Bandwidth 1.0290 MHz Total Power 7.24 dBm Transmit Freq Error 11.621 kHz OBW Power 99.00 % x dB Bandwidth 641.9 kHz x dB -6.00 dB
GFSK Mid channel	 Agilent Spectrum Analyzer - Occupied BW Center Freq 2.440000000 GHz Ref Offset 7.05 dB Ref 27.03 dBm Mkr3 2.440326 GHz -3.8862 dBm Center 2.44 GHz #Res BW 100 kHz #VBW 300 kHz Span 3 MHz Sweep 1 ms Occupied Bandwidth 1.0349 MHz Total Power 8.38 dBm Transmit Freq Error 5.084 kHz OBW Power 99.00 % x dB Bandwidth 641.7 kHz x dB -6.00 dB
GFSK High channel	 Agilent Spectrum Analyzer - Occupied BW Center Freq 2.480000000 GHz Ref Offset 7.1 dB Ref 27.10 dBm Mkr3 2.479863 GHz -2.6749 dBm Center 2.48 GHz #Res BW 100 kHz #VBW 300 kHz Span 3 MHz Sweep 1 ms Occupied Bandwidth 2.0118 MHz Total Power 7.21 dBm Transmit Freq Error -457.79 kHz OBW Power 99.00 % x dB Bandwidth 642.0 kHz x dB -6.00 dB

2M:

Test Graph:



Right ear:

1M:

Test Graph:

GFSK Low channel	 Agilent Spectrum Analyzer - Occupied BW Center Freq 2.40200000 GHz Ref Offset 7.03 dB Ref 27.03 dBm Center Freq: 2.402000000 GHz Trig: Free Run #Att: 30 dB Avg/Hold: 100/100 Radio Std: None Radio Device: BTS Mkr3 2.402328 GHz -4.7637 dBm Center 2.402 GHz #Res BW 100 kHz #VBW 300 kHz Span 3 MHz Sweep 1 ms Occupied Bandwidth 1.0434 MHz Total Power 7.47 dBm Transmit Freq Error 6.387 kHz OBW Power 99.00 % x dB Bandwidth 642.8 kHz x dB -6.00 dB
GFSK Mid channel	 Agilent Spectrum Analyzer - Occupied BW Center Freq 2.44000000 GHz Ref Offset 7.05 dB Ref 27.05 dBm Center Freq: 2.440000000 GHz Trig: Free Run #Att: 30 dB Avg/Hold: 100/100 Radio Std: None Radio Device: BTS Mkr3 2.440329 GHz -4.1628 dBm Center 2.44 GHz #Res BW 100 kHz #VBW 300 kHz Span 3 MHz Sweep 1 ms Occupied Bandwidth 1.0374 MHz Total Power 8.66 dBm Transmit Freq Error 7.829 kHz OBW Power 99.00 % x dB Bandwidth 641.6 kHz x dB -6.00 dB
GFSK High channel	 Agilent Spectrum Analyzer - Occupied BW Center Freq 2.48000000 GHz Ref Offset 7.1 dB Ref 27.10 dBm Center Freq: 2.480000000 GHz Trig: Free Run #Att: 30 dB Avg/Hold: 100/100 Radio Std: None Radio Device: BTS Mkr3 2.480324 GHz -4.3926 dBm Center 2.48 GHz #Res BW 100 kHz #VBW 300 kHz Span 3 MHz Sweep 1 ms Occupied Bandwidth 1.0388 MHz Total Power 8.14 dBm Transmit Freq Error 8.342 kHz OBW Power 99.00 % x dB Bandwidth 631.4 kHz x dB -6.00 dB


2M:

Test Graph:

GFSK Low channel	 Agilent Spectrum Analyzer - Occupied BW Center Freq 2.40200000 GHz Ref Offset 7.03 dB Ref 27.03 dBm Center Freq: 2.402000000 GHz Trig: Free Run #Atten: 30 dB Avg/Hold: 100/100 Radio Std: None Radio Device: BTS Mkr3 2.402579 GHz -7.0370 dBm Center 2.402 GHz #Res BW 100 kHz #VBW 300 kHz Span 5 MHz Sweep 1 ms Occupied Bandwidth 2.0530 MHz Total Power 7.94 dBm Transmit Freq Error 15.547 kHz OBW Power 99.00 % x dB Bandwidth 1.127 MHz x dB -6.00 dB
GFSK Mid channel	 Agilent Spectrum Analyzer - Occupied BW Center Freq 2.44000000 GHz Ref Offset 7.05 dB Ref 27.05 dBm Center Freq: 2.440000000 GHz Trig: Free Run #Atten: 30 dB Avg/Hold: 100/100 Radio Std: None Radio Device: BTS Mkr3 2.44058 GHz -3.9141 dBm Center 2.44 GHz #Res BW 100 kHz #VBW 300 kHz Span 5 MHz Sweep 1 ms Occupied Bandwidth 2.0447 MHz Total Power 9.10 dBm Transmit Freq Error 15.526 kHz OBW Power 99.00 % x dB Bandwidth 1.129 MHz x dB -6.00 dB
GFSK High channel	 Agilent Spectrum Analyzer - Occupied BW Center Freq 2.48000000 GHz Ref Offset 7.1 dB Ref 27.10 dBm Center Freq: 2.480000000 GHz Trig: Free Run #Atten: 30 dB Avg/Hold: 100/100 Radio Std: None Radio Device: BTS Mkr3 2.4806 GHz -5.9925 dBm Center 2.48 GHz #Res BW 100 kHz #VBW 300 kHz Span 5 MHz Sweep 1 ms Occupied Bandwidth 2.0433 MHz Total Power 8.60 dBm Transmit Freq Error 17.678 kHz OBW Power 99.00 % x dB Bandwidth 1.164 MHz x dB -6.00 dB

11. POWER SPECTRAL DENSITY

11.1 Block Diagram Of Test Setup



11.2 Limit

FCC Part15 (15.247) , Subpart C				
Section	Test Item	Limit	Frequency Range (MHz)	Result
15.247	Power Spectral Density	8 dBm (in any 3KHz)	2400-2483.5	PASS

11.3 Test procedure

1. Set analyzer center frequency to DTS channel center frequency.
2. Set the span to 1.5 times the DTS bandwidth.
3. Set the RBW to: $3 \text{ kHz} \leq \text{RBW} \leq 100 \text{ kHz}$.
4. Set the VBW $\geq 3 \times \text{RBW}$.
5. Detector = peak.
6. Sweep time = auto couple.
7. Trace mode = max hold.
8. Allow trace to fully stabilize.
9. Use the peak marker function to determine the maximum amplitude level within the RBW.
10. If measured value exceeds limit, reduce RBW (no less than 3 kHz) and repeat.

11.4 Test Result

Left ear:

1M:

Mode	Channel.	Power Spectral Density (dBm/3KHz)	Limit(dBm/3KHz)	Verdict
GFSK	LCH	-13.675	8	PASS
GFSK	MCH	-13.729	8	PASS
GFSK	HCH	-14.294	8	PASS

2M:

Mode	Channel.	Power Spectral Density (dBm/3KHz)	Limit(dBm/3KHz)	Verdict
GFSK	LCH	-18.62	8	PASS
GFSK	MCH	-17.374	8	PASS
GFSK	HCH	-17.755	8	PASS

Right ear:
1M:

Mode	Channel.	Power Spectral Density (dBm/3KHz)	Limit(dBm/3KHz)	Verdict
GFSK	LCH	-13.985	8	PASS
GFSK	MCH	-12.815	8	PASS
GFSK	HCH	-13.294	8	PASS

2M:

Mode	Channel.	Power Spectral Density (dBm/3KHz)	Limit(dBm/3KHz)	Verdict
GFSK	LCH	-16.131	8	PASS
GFSK	MCH	-14.898	8	PASS
GFSK	HCH	-15.221	8	PASS

Left ear:

1M:

Test Graph

Graphs

GFSK/LCH



GFSK/MCH



GFSK/HCH



2M: Test Graph

Graphs

GFSK/LCH



GFSK/MCH



GFSK/HCH



Right ear:
1M:
Test Graph

Graphs

GFSK/LCH




GFSK/MCH



GFSK/HCH



2M: Test Graph



12. ANTENNA REQUIREMENT

15.203 requirement:

An intentional radiator shall be designed to ensure that no antenna other than that furnished by the responsible party shall be used with the device. The use of a permanently attached antenna or of an antenna that uses a unique coupling to the intentional radiator, the manufacturer may design the unit so that a broken antenna can be replaced by the user, but the use of a standard antenna jack or electrical connector is prohibited.

15.247(b) (4) requirement:

The conducted output power limit specified in paragraph (b) of this section is based on the use of antennas with directional gains that do not exceed 6 dBi. Except as shown in paragraph (c) of this section, if transmitting antennas of directional gain greater than 6 dBi are used, the conducted output power from the intentional radiator shall be reduced below the stated values in paragraphs (b)(1), (b)(2), and (b)(3) of this section, as appropriate, by the amount in dB that the directional gain of the antenna exceeds 6 dBi.


EUT Antenna:

The EUT antenna is Chip antenna. The best case gain of the antenna is 2.78dBi.

13. EUT TEST SETUP PHOTOGRAPHS

Radiated Emissions


Below 1G



Above 1G



Conducted emission



***** END OF REPORT *****