



TEST REPORT FCC Part 27

Report Reference No.....: HK2203211047-4E

FCC ID.....: 2A6DD-WRS125

Compiled by
(position+printed name+signature)...: File administrators Gary Qian

Supervised by
(position+printed name+signature)...: Technique principal Eden Hu

Approved by
(position+printed name+signature)...: Manager Jason Zhou

Date of issue.....: Apr. 13, 2022

Testing Laboratory Name: Shenzhen HUAKE Testing Technology Co., Ltd.

Address: 1-2/F., Building B2, Junfeng Zhongcheng Zhizao Innovation Park,
Heping, Fuhai Street, Bao'an District, Shenzhen, Guangdong,
China

Applicant's name.....: Wicrypt Labs Limited

Address: Vistra Corporate Services Centre, Wickhams Cay II, Road Town,
Tortola, VG1110, British Virgin Islands, United Kingdom

Test specification

Standard: FCC CFR Title 47 Part 2, Part 27

TRF Originator.....: Shenzhen HUAKE Testing Technology Co., Ltd.

Shenzhen HUAKE Testing Technology Co., Ltd. All rights reserved.

This publication may be reproduced in whole or in part for non-commercial purposes as long as the Shenzhen HUAKE Testing Technology Co., Ltd. as copyright owner and source of the material. Shenzhen HUAKE Testing Technology Co., Ltd. takes no responsibility for and will not assume liability for damages resulting from the reader's interpretation of the reproduced material due to its placement and context.

Test item description: Wicrypt Spider

Trade Mark: N/A

Manufacturer.....: Wicrypt Tech Limited

Model/Type reference.....: WRS125

Series Models: N/A

Modulation Type: QPSK, 16QAM

Rating: DC 12V from adapter

Hardware version: V2.0

Software version: V2.0

Result.....: PASS

**TEST REPORT**

Test Report No. :	HK2203211047-4E	Apr. 13, 2022
		Date of issue

Equipment under Test : Wicrypt Spider

Model /Type : WRS125

Series Models : N/A

Applicant : **Wicrypt Labs Limited**

Address : Vistra Corporate Services Centre, Wickhams Cay II, Road
Town, Tortola, VG1110, British Virgin Islands, United
Kingdom

Manufacturer : **Wicrypt Tech Limited**

Address : No. 36 Garden Avenue, Bethel Plaza, Enugu, Nigeria

Test result	Pass
--------------------	-------------

The test report merely corresponds to the test sample.
It is not permitted to copy extracts of these test result without the written permission of the test laboratory.

**** Modified History ****

Revision	Description	Issued Data	Remark
Revision 1.0	Initial Test Report Release	Apr. 13, 2022	Jason Zhou



Contents

1	SUMMARY	5
1.1	Test Standards	5
1.2	Test Description	5
1.3	Information of The Test Laboratory	6
1.4	Statement of The Measurement Uncertainty	6
2	GENERAL INFORMATION	7
2.1	Environmental Conditions	7
2.2	Description of Test Modes	7
2.3	Test frequency list	7
2.4	Equipments Used During The Test	8
2.5	Related Submittal(s) / Grant (s)	8
2.6	Modifications	8
3	TEST CONDITIONS AND RESULTS	9
3.1	Output Power	9
3.2	Peak-to-Average Ratio (PAR)	14
3.3	Occupied Bandwidth and Emission Bandwidth	21
3.4	Band Edge Compliance	28
3.5	Spurious Emission	35
3.6	Frequency Stability Under Temperature & Voltage Variations	68
4	TEST SETUP PHOTOS OF THE EUT	70
5	PHOTOS OF THE EUT	71



1 SUMMARY

1.1 Test Standards

The tests were performed according to following standards:

[FCC Part 27](#): MISCELLANEOUS WIRELESS COMMUNICATIONS SERVICES.

[TIA/EIA 603 D June 2010](#): Land Mobile FM or PM Communications Equipment Measurement and Performance Standards 47 CFR FCC Part 15 Subpart B: - Unintentional Radiators.

[FCC Part 2](#): FREQUENCY ALLOCATIONS AND RADIO TREATY MATTERS; GENERAL RULES AND REGULATIONS.

[KDB971168 D01: v02r02](#) MEASUREMENT GUIDANCE FOR CERTIFICATION OF LICENSED DIGITAL TRANSMITTERS.

1.2 Test Description

Test Item	Section in CFR 47	Result
RF Output Power	Part 2.1046 Part 27.50(d)(4)	Pass
Peak-to-Average Ratio	Part 27.50(d)(4)	Pass
99% & -26 dB Occupied Bandwidth	Part 2.1049 Part 27.53(h)	Pass
Spurious Emissions at Antenna Terminal	Part 2.1051 Part 27.53(h)	Pass
Field Strength of Spurious Radiation	Part 2.1053 Part 27.53(h)	Pass
Out of band emission, Band Edge	Part 2.1051 Part 27.53(h)	Pass
Frequency stability	Part 2.1055 Part 27.54	Pass



1.3 Information of The Test Laboratory

Shenzhen HUAKE Testing Technology Co., Ltd.
Add.: 1-2/F., Building B2, Junfeng Zhongcheng Zhizao Innovation Park, Heping,
Fuhai Street, Bao'an District, Shenzhen, Guangdong, China

Testing Laboratory Authorization:

A2LA Accreditation Code is 4781.01.
FCC Designation Number is CN1229.
Canada IC CAB identifier is CN0045.
CNAS Registration Number is L9589.

1.4 Statement of The Measurement Uncertainty

The data and results referenced in this document are true and accurate. The reader is cautioned that there may be errors within the calibration limits of the equipment and facilities. The measurement uncertainty was calculated for all measurements listed in this test report acc. to CISPR 16 - 4 „Specification for radio disturbance and immunity measuring apparatus and methods – Part 4:Uncertainty in EMC Measurements“ and is documented in the Shenzhen HUAKE Testing Technology Co., Ltd. quality system acc. to DIN EN ISO/IEC 17025. Furthermore, component and process variability of devices similar to that tested may result in additional deviation. The manufacturer has the sole responsibility of continued compliance of the device.

Hereafter the best measurement capability for Shenzhen HUAKE Testing Technology Co., Ltd. is reported:

Test	Range	Measurement Uncertainty	Notes
Radiated Emission	30~1000MHz	4.10dB	(1)
Radiated Emission	Above 1GHz	4.32dB	(1)
Conducted Disturbance	0.15~30MHz	3.20dB	(1)

(1) This uncertainty represents an expanded uncertainty expressed at approximately the 95% confidence level using a coverage factor of k=2.



2 GENERAL INFORMATION

2.1 Environmental Conditions

During the measurement the environmental conditions were within the listed ranges:

Normal Temperature:	25°C
Relative Humidity:	55 %
Air Pressure:	101 kPa

2.2 Description of Test Modes

The EUT has been tested under typical operating condition. The CMW500 used to control the EUT staying in continuous transmitting and receiving mode for testing. Regards to the frequency band operation: the lowest, middle and highest frequency of channel were selected to perform the test, then shown on this report.

Note:

1. For the ERP/EIRP and radiated emission test, every axis (X, Y, Z) was verified, and show the worst result on this report.
2. Test method and refer to 3GPP TS136521.

2.3 Test frequency list

TX Channel Bandwidth	Frequency (MHz)	channel
1.4 MHz	1710.7	19957
	1732.5	20175
	1754.3	20393
3 MHz	1711.5	19965
	1732.5	20175
	1753.5	20385
5 MHz	1712.5	19975
	1732.5	20175
	1752.5	20375
10 MHz	1715.0	20000
	1732.5	20175
	1750.0	20350
15 MHz	1717.5	20025
	1732.5	20175
	1747.5	20325
20 MHz	1720.0	20050
	1732.5	20175
	1745.0	20300



2.4 Equipments Used During The Test

Test Equipment	Manufacturer	Model No.	Serial No.	Calibration Date	Calibration Due Date
LISN	ENV216	R&S	HKE-059	2022/02/18	2023/02/17
LISN	R&S	ENV216	HKE-002	2022/02/18	2023/02/17
Broadband antenna	Schwarzbeck	VULB 9163	HKE-012	2022/02/18	2023/02/17
Receiver	R&S	ESCI 7	HKE-010	2022/02/18	2023/02/17
Spectrum analyzer	Agilent	N9020A	HKE-048	2022/02/18	2023/02/17
RF automatic control unit	Tonscend	JS0806-2	HKE-060	2022/02/18	2023/02/17
Horn antenna	Schwarzbeck	9120D	HKE-013	2022/02/18	2023/02/17
Loop antenna	Schwarzbeck	FMZB 1519 B	HKE-014	2022/02/18	2023/02/17
Preamplifier	EMCI	EMC051845SE	HKE-015	2022/02/18	2023/02/17
Preamplifier	Agilent	83051A	HKE-016	2022/02/18	2023/02/17
Temperature and humidity meter	Boyang	HTC-1	HKE-075	2022/02/18	2023/02/17
High pass filter unit	Tonscend	JS0806-F	HKE-055	2022/02/18	2023/02/17
RF cable	Times	1-40G	HKE-034	2022/02/18	2023/02/17
Power meter	Agilent	E4419B	HKE-085	2022/02/18	2023/02/17
Power Sensor	Agilent	E9300A	HKE-086	2022/02/18	2023/02/17
Wireless Communication Test Set	R&S	CMU200	HKE-026	2022/02/18	2023/02/17
High gain antenna	Schwarzbeck	LB-180400KF	HKE-054	2022/02/18	2023/02/17
Horn antenna	Schwarzbeck	9120D	HKE-135	2022/02/18	2023/02/17
High gain antenna	Schwarzbeck	LB-180400KF	HKE-128	2022/02/18	2023/02/17
Broadband antenna	Schwarzbeck	VULB 9163	HKE-087	2022/02/18	2023/02/17
Signal generator	Agilent	E4433B	HKE-120	2022/02/18	2023/02/17
Signal generator	Agilent	E4421B	HKE-121	2022/02/18	2023/02/17

2.5 Related Submittal(s) / Grant (s)

This submittal(s) (test report) is intended for FCC ID: 2A6DD-WRS125 filing to comply with of the FCC Part 27 Rules.

2.6 Modifications

No modifications were implemented to meet testing criteria.



3 TEST CONDITIONS AND RESULTS


3.1 Output Power

LIMIT


According to §27.50 (d) (4): Fixed, mobile, and portable (hand-held) stations operating in the 1710–1755 MHz band are limited to 1 watt EIRP.

TEST CONFIGURATION

Conducted Power Measurement



Radiated Power Measurement:



TEST PROCEDURE

The EUT was setup according to EIA/TIA 603D.

Conducted Power Measurement:

- Place the EUT on a bench and set it in transmitting mode.
- Connect a low loss RF cable from the antenna port to a spectrum analyzer and CMW500 by a Directional Couple.
- EUT Communicate with CMW500, then select a channel for testing.
- Add a correction factor to the display of spectrum, and then test.

Radiated Power Measurement:

- The EUT shall be placed at the specified height on a support, and in the position closest to normal use as declared by provider.
- The test antenna shall be oriented initially for vertical polarization and shall be chosen to correspond to the frequency of the transmitter.
- The output of the test antenna shall be connected to the measuring receiver.
- The transmitter shall be switched on and the measuring receiver shall be tuned to the frequency of the transmitter under test.
- The test antenna shall be raised and lowered through the specified range of height until a maximum signal



level is detected by the measuring receiver.

- f. The transmitter shall then be rotated through 360° in the horizontal plane, until the maximum signal level is detected by the measuring receiver.
- g. The test antenna shall be raised and lowered again through the specified range of height until a maximum signal level is detected by the measuring receiver.
- h. The maximum signal level detected by the measuring receiver shall be noted.
- i. The transmitter shall be replaced by a substitution antenna.
- j. The substitution antenna shall be orientated for vertical polarization and the length of the substitution antenna shall be adjusted to correspond to the frequency of the transmitter.
- k. The substitution antenna shall be connected to a calibrated signal generator.
- l. If necessary, the input attenuator setting of the measuring receiver shall be adjusted in order to increase the sensitivity of the measuring receiver.
- m. The test antenna shall be raised and lowered through the specified range of height to ensure that the maximum signal is received.
- n. The input signal to the substitution antenna shall be adjusted to the level that produces a level detected by the measuring receiver, that is equal to the level noted while the transmitter radiated power was measured, corrected for the change of input attenuator setting of the measuring receiver.
- o. The measurement shall be repeated with the test antenna and the substitution antenna orientated for horizontal polarization.
- p. The measure of the effective radiated power is the larger of the two levels recorded at the input to the substitution antenna, corrected for gain of the substitution antenna if necessary.
- q. Test site anechoic chamber refer to ANSI C63.4.

TEST RESULTS

Conducted Measurement:

LTE FDD Band 4				
TX Channel Bandwidth	Frequency (MHz)	RB Size/Offset	Average Power [dBm]	
			QPSK	16QAM
1.4 MHz	1710.7	1 RB low	24.61	23.35
		1 RB high	24.47	23.56
		50% RB mid	24.48	23.37
		100% RB	24.43	23.13
	1732.5	1 RB low	24.42	23.13
		1 RB high	24.36	23.08
		50% RB mid	23.31	22.51
		100% RB	24.58	23.77
	1754.3	1 RB low	24.69	23.55
		1 RB high	24.63	23.46
		50% RB mid	24.62	23.32
		100% RB	24.44	23.31
3 MHz	1711.5	1 RB low	24.29	23.43
		1 RB high	24.44	23.58
		50% RB mid	24.52	23.48
		100% RB	23.61	22.65
	1732.5	1 RB low	23.44	22.62
		1 RB high	23.52	22.80
		50% RB mid	23.61	22.74
		100% RB	24.61	23.73
	1753.5	1 RB low	24.37	23.51
		1 RB high	24.59	23.61
		50% RB mid	23.71	22.76
		100% RB	23.62	22.76
5 MHz	1712.	1 RB low	24.37	23.51
		1 RB high	24.54	23.69
		50% RB mid	24.41	23.48
		100% RB	23.65	22.59
	1732.5	1 RB low	23.50	22.51
		1 RB high	23.55	22.57

The results shown in this test report refer only to the sample(s) tested unless otherwise stated and the sample(s) are retained for 30 days only. The document is issued by HUAKE, this document cannot be reproduced except in full with our prior written permission. The more details and the authenticity of the report will be confirmed at <http://www.cer-mark.com>.

TEL : +86-755 2302 9901 FAX : +86-755 2302 9901 E-mail : service@cer-mark.com

Add: 1-2F., Building B2, Junfeng Zhongcheng Zhizao Innovation Park, Heping Community, Fuhai Street, Bao'an District, Shenzhen, Guangdong, China



	1752.5	50% RB mid	23.57	22.73
		100% RB	24.63	23.68
		1 RB low	24.53	23.56
		1 RB high	24.50	23.45
		50% RB mid	23.53	22.56
		100% RB	23.53	22.65
10 MHz	1715.0	1 RB low	24.47	23.53
		1 RB high	24.75	23.76
		50% RB mid	24.50	23.55
		100% RB	23.76	22.78
	1732.5	1 RB low	23.61	22.70
		1 RB high	23.55	22.57
		50% RB mid	23.58	22.56
		100% RB	24.55	23.62
	1750.0	1 RB low	24.66	23.70
		1 RB high	24.29	23.33
		50% RB mid	23.61	22.73
		100% RB	23.60	22.52
15 MHz	1717.5	1 RB low	24.55	23.42
		1 RB high	24.35	23.37
		50% RB mid	24.29	23.43
		100% RB	23.77	23.40
	1732.5	1 RB low	23.48	23.47
		1 RB high	23.11	23.10
		50% RB mid	23.39	22.43
		100% RB	24.13	23.21
	1747.5	1 RB low	24.58	23.46
		1 RB high	24.38	23.33
		50% RB mid	23.09	23.03
		100% RB	23.42	23.48
20 MHz	1720.0	1 RB low	24.59	23.52
		1 RB high	24.60	23.62
		50% RB mid	24.25	23.26
		100% RB	23.53	22.53
	1732.5	1 RB low	24.82	22.53
		1 RB high	23.66	22.81
		50% RB mid	23.61	22.74
		100% RB	23.94	22.95
	1745.0	1 RB low	24.89	24.30
		1 RB high	24.47	23.19
		50% RB mid	23.50	22.64
		100% RB	23.49	22.64



Radiated Measurement

Remark:

1. We were tested all RB Configuration refer 3GPP TS136 521 for each Channel Bandwidth of LTE FDD Band 4; recorded worst case for each Channel Bandwidth of LTE FDD Band 4.
2. $EIRP = P_{Mea}(dBm) - P_{cl}(dB) + P_{Ag}(dB) + G_a(dBi)$

LTE FDD Band 4_Channel Bandwidth 1.4MHz_QPSK

Frequency (MHz)	P _{Mea} (dBm)	P _{cl} (dB)	G _a Antenna Gain(dB)	P _{Ag} (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)	Polarization
1710.7	-17.68	3.06	9.68	34.80	23.74	30.00	6.26	V
1732.5	-19.34	3.17	9.68	34.80	21.97	30.00	8.03	V
1754.3	-19.13	3.22	9.75	34.80	22.20	30.00	7.80	V

LTE FDD Band 4_Channel Bandwidth 3MHz_QPSK

Frequency (MHz)	P _{Mea} (dBm)	P _{cl} (dB)	G _a Antenna Gain(dB)	P _{Ag} (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)	Polarization
1711.5	-17.84	3.06	9.68	34.80	23.58	30.00	6.42	V
1732.5	-19.77	3.17	9.68	34.80	21.54	30.00	8.46	V
1753.5	-19.24	3.22	9.75	34.80	22.09	30.00	7.91	V

LTE FDD Band 4_Channel Bandwidth 5MHz_QPSK

Frequency (MHz)	P _{Mea} (dBm)	P _{cl} (dB)	G _a Antenna Gain(dB)	P _{Ag} (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)	Polarization
1712.5	-19.19	3.06	9.68	34.80	22.23	30.00	7.77	V
1732.5	-18.90	3.17	9.68	34.80	22.41	30.00	7.59	V
1752.5	-17.92	3.22	9.75	34.80	23.41	30.00	6.59	V

LTE FDD Band 4_Channel Bandwidth 10MHz_QPSK

Frequency (MHz)	P _{Mea} (dBm)	P _{cl} (dB)	G _a Antenna Gain(dB)	P _{Ag} (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)	Polarization
1715.0	-18.63	3.06	9.68	34.80	22.79	30.00	7.21	V
1732.5	-18.65	3.17	9.68	34.80	22.66	30.00	7.34	V
1750.0	-18.68	3.22	9.75	34.80	22.65	30.00	7.35	V

LTE FDD Band 4_Channel Bandwidth 15MHz_QPSK

Frequency (MHz)	P _{Mea} (dBm)	P _{cl} (dB)	G _a Antenna Gain(dB)	P _{Ag} (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)	Polarization
1717.5	-19.18	3.06	9.68	34.80	22.24	30.00	7.76	V
1732.5	-17.19	3.17	9.68	34.80	24.12	30.00	5.88	V
1747.5	-19.24	3.22	9.75	34.80	22.09	30.00	7.91	V

LTE FDD Band 4_Channel Bandwidth 20MHz_QPSK

Frequency (MHz)	P _{Mea} (dBm)	P _{cl} (dB)	G _a Antenna Gain(dB)	P _{Ag} (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)	Polarization
1720.0	-19.42	3.06	9.68	34.80	22.00	30.00	8.00	V
1732.5	-18.52	3.17	9.68	34.80	22.79	30.00	7.21	V
1745.0	-18.41	3.22	9.75	34.80	22.92	30.00	7.08	V

*LTE FDD Band 4 Channel Bandwidth 1.4MHz 16QAM*

Frequency (MHz)	P _{Mea} (dBm)	P _{cl} (dB)	G _a Antenna Gain(dB)	P _{Ag} (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)	Polarization
1710.7	-19.14	3.06	9.68	34.80	22.28	30.00	7.72	V
1732.5	-18.97	3.17	9.68	34.80	22.34	30.00	7.66	V
1754.3	-19.52	3.22	9.75	34.80	21.81	30.00	8.19	V

LTE FDD Band 4 Channel Bandwidth 3MHz 16QAM

Frequency (MHz)	P _{Mea} (dBm)	P _{cl} (dB)	G _a Antenna Gain(dB)	P _{Ag} (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)	Polarization
1711.5	-18.58	3.06	9.68	34.80	22.84	30.00	7.16	V
1732.5	-18.17	3.17	9.68	34.80	23.14	30.00	6.86	V
1753.5	-18.85	3.22	9.75	34.80	22.48	30.00	7.52	V

LTE FDD Band 4 Channel Bandwidth 5MHz 16QAM

Frequency (MHz)	P _{Mea} (dBm)	P _{cl} (dB)	G _a Antenna Gain(dB)	P _{Ag} (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)	Polarization
1712.5	-18.86	3.06	9.68	34.80	22.56	30.00	7.44	V
1732.5	-18.32	3.17	9.68	34.80	22.99	30.00	7.01	V
1752.5	-18.81	3.22	9.75	34.80	22.52	30.00	7.48	V

LTE FDD Band 4 Channel Bandwidth 10MHz 16QAM

Frequency (MHz)	P _{Mea} (dBm)	P _{cl} (dB)	G _a Antenna Gain(dB)	P _{Ag} (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)	Polarization
1715.0	-18.55	3.06	9.68	34.80	22.87	30.00	7.13	V
1732.5	-19.75	3.17	9.68	34.80	21.56	30.00	8.44	V
1750.0	-18.30	3.22	9.75	34.80	23.03	30.00	6.97	V

LTE FDD Band 4 Channel Bandwidth 15MHz 16QAM

Frequency (MHz)	P _{Mea} (dBm)	P _{cl} (dB)	G _a Antenna Gain(dB)	P _{Ag} (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)	Polarization
1717.5	-18.15	3.06	9.68	34.80	23.27	30.00	6.73	V
1732.5	-18.37	3.17	9.68	34.80	22.94	30.00	7.06	V
1747.5	-19.01	3.22	9.75	34.80	22.32	30.00	7.68	V

LTE FDD Band 4 Channel Bandwidth 20MHz 16QAM

Frequency (MHz)	P _{Mea} (dBm)	P _{cl} (dB)	G _a Antenna Gain(dB)	P _{Ag} (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)	Polarization
1720.0	-19.66	3.06	9.68	34.80	21.76	30.00	8.24	V
1732.5	-18.32	3.17	9.68	34.80	22.99	30.00	7.01	V
1745.0	-18.82	3.22	9.75	34.80	22.51	30.00	7.49	V




3.2 Peak-to-Average Ratio (PAR)

LIMIT

The Peak-to-Average Ratio (PAR) of the transmission may not exceed 13 dB.

TEST CONFIGURATION



TEST PROCEDURE

1. Refer to instrument's analyzer instruction manual for details on how to use the power statistics/CCDF function;
2. Set resolution/measurement bandwidth $\geq$ signal's occupied bandwidth;
3. Set the number of counts to a value that stabilizes the measured CCDF curve;
4. Set the measurement interval as follows:
 - 1). for continuous transmissions, set to 1 ms;
 - 2). for burst transmissions, employ an external trigger that is synchronized with the EUT burst timing sequence, or use the internal burst trigger with a trigger level that allows the burst to stabilize and set the measurement interval to a time that is less than or equal to the burst duration.
5. Record the maximum PAPR level associated with a probability of 0.1%.

TEST RESULTS

Remark:

1. We were tested all RB Configuration refer 3GPP TS136 521 for each Channel Bandwidth of LTE FDD Band 4; recorded worst case for each Channel Bandwidth of LTE FDD Band 4.

LTE FDD Band 4				
TX Channel Bandwidth	Frequency (MHz)	RB Size/Offset	PAPR (dB)	
			QPSK	16QAM
1.4 MHz	1710.7	1RB#0	4.22	5.23
	1732.5		4.83	5.89
	1754.3		4.05	5.07
3 MHz	1711.5	1RB#0	4.28	5.09
	1732.5		4.86	5.67
	1753.5		4.14	5.11
5 MHz	1712.5	1RB#0	4.29	5.11
	1732.5		4.83	5.73
	1752.5		4.23	5.03
10 MHz	1715.0	1RB#0	4.21	5.06
	1732.5		4.78	5.67
	1750.0		4.42	5.44
15 MHz	1717.5	1RB#0	4.19	5.13
	1732.5		4.74	5.59
	1747.5		4.63	5.56
20 MHz	1720.0	1RB#0	4.13	4.98
	1732.5		4.62	5.50
	1745.0		4.73	5.72

The results shown in this test report refer only to the sample(s) tested unless otherwise stated and the sample(s) are retained for 30 days only. The document is issued by HUAKE, this document cannot be reproduced except in full with our prior written permission. The more details and the authenticity of the report will be confirmed at <http://www.cer-mark.com>.

TEL : +86-755 2302 9901 FAX : +86-755 2302 9901 E-mail : service@cer-mark.com

Add: 1-2F., Building B2, Junfeng Zhongcheng Zhizao Innovation Park, Heping Community, Fuhai Street, Bao'an District, Shenzhen, Guangdong, China




LTE FDD Band 4-1.4MHz Channel Bandwidth PAPR

QPSK



1RB#0

16QAM



1RB#0

Low Channel



1RB#0



1RB#0

Middle Channel



1RB#0



1RB#0

High Channel

The results shown in this test report refer only to the sample(s) tested unless otherwise stated and the sample(s) are retained for 30 days only. The document is issued by HUAKE, this document cannot be reproduced except in full with our prior written permission. The more details and the authenticity of the report will be confirmed at <http://www.cer-mark.com>.

TEL : +86-755 2302 9901 FAX : +86-755 2302 9901 E-mail : service@cer-mark.com

Add: 1-2F., Building B2, Junfeng Zhongcheng Zhizao Innovation Park, Heping Community, Fuhai Street, Bao'an District, Shenzhen, Guangdong, China



LTE FDD Band 4-3MHz Channel Bandwidth PAPR

QPSK



1RB#0

16QAM



1RB#0

Low Channel



1RB#0



1RB#0

Middle Channel



1RB#0



1RB#0

High Channel

The results shown in this test report refer only to the sample(s) tested unless otherwise stated and the sample(s) are retained for 30 days only. The document is issued by HUAKE, this document cannot be reproduced except in full with our prior written permission. The more details and the authenticity of the report will be confirmed at <http://www.cer-mark.com>.

TEL : +86-755 2302 9901 FAX : +86-755 2302 9901 E-mail : service@cer-mark.com

Add: 1-2F., Building B2, Junfeng Zhongcheng Zhizao Innovation Park, Heping Community, Fuhai Street, Bao'an District, Shenzhen, Guangdong, China



LTE FDD Band 4-5MHz Channel Bandwidth PAPR

QPSK



1RB#0

16QAM




1RB#0

Low Channel



1RB#0



1RB#0

Middle Channel



1RB#0



1RB#0

High Channel

The results shown in this test report refer only to the sample(s) tested unless otherwise stated and the sample(s) are retained for 30 days only. The document is issued by HUAKE, this document cannot be reproduced except in full with our prior written permission. The more details and the authenticity of the report will be confirmed at <http://www.cer-mark.com>.

TEL : +86-755 2302 9901 FAX : +86-755 2302 9901 E-mail : service@cer-mark.com

Add: 1-2F., Building B2, Junfeng Zhongcheng Zhizao Innovation Park, Heping Community, Fuhai Street, Bao'an District, Shenzhen, Guangdong, China



LTE FDD Band 4-10MHz Channel Bandwidth PAPR

QPSK



1RB#0

16QAM



1RB#0

Low Channel



1RB#0



1RB#0

Middle Channel



1RB#0



1RB#0

High Channel

The results shown in this test report refer only to the sample(s) tested unless otherwise stated and the sample(s) are retained for 30 days only. The document is issued by HUAKE, this document cannot be reproduced except in full with our prior written permission. The more details and the authenticity of the report will be confirmed at <http://www.cer-mark.com>.

TEL : +86-755 2302 9901 FAX : +86-755 2302 9901 E-mail : service@cer-mark.com

Add: 1-2F., Building B2, Junfeng Zhongcheng Zhizao Innovation Park, Heping Community, Fuhai Street, Bao'an District, Shenzhen, Guangdong, China



LTE FDD Band 4-15MHz Channel Bandwidth PAPR

QPSK




1RB#0

16QAM



1RB#0

Low Channel



1RB#0



1RB#0

Middle Channel



1RB#0



1RB#0

High Channel



LTE FDD Band 4-20MHz Channel Bandwidth PAPR

QPSK

16QAM



1RB#0

1RB#0

Low Channel



1RB#0

1RB#0

Middle Channel



1RB#0

1RB#0

High Channel




3.3 Occupied Bandwidth and Emission Bandwidth

LIMIT

N/A

TEST CONFIGURATION



TEST PROCEDURE

The transmitter output was connected to a calibrated coaxial cable and coupler, the other end of which was connected to a spectrum analyzer. The occupied bandwidth was measured with the spectrum analyzer at low, middle and high channel in each band. The -26dBc Emission bandwidth was also measured and recorded. Set RBW was set to about 1% of emission BW, VBW $\geq$ 3 times RBW.

-26dBc display line was placed on the screen (or 99% bandwidth), the occupied bandwidth is the delta frequency between the two points where the display line intersects the signal trace.

TEST RESULTS

Remark:

1. We were tested all RB Configuration refer 3GPP TS136 521 for each Channel Bandwidth of LTE FDD Band 4; recorded worst case for each Channel Bandwidth of LTE FDD Band 4.

LTE FDD Band 4						
TX Channel Bandwidth	RB Size/Offset	Frequency (MHz)	-26dBc Emission bandwidth (MHz)		99% Occupied bandwidth (MHz)	
			QPSK	16QAM	QPSK	16QAM
1.4 MHz	6RB#0	1710.7	1.267	1.269	1.0902	1.0915
		1732.5	1.244	1.266	1.0896	1.0913
		1754.3	1.278	1.257	1.0938	1.0917
3 MHz	15RB#0	1711.5	2.927	2.933	2.6915	2.6882
		1732.5	2.899	2.893	2.6904	2.6950
		1753.5	2.930	2.938	2.6965	2.6934
5 MHz	25RB#0	1712.5	4.895	4.877	4.4987	4.5018
		1732.5	4.897	4.865	4.5011	4.5015
		1752.5	4.915	4.924	4.5027	4.4973
10 MHz	50RB#0	1715.0	9.584	9.575	8.9666	8.9459
		1732.5	9.559	9.517	8.9603	8.9533
		1750.0	9.536	9.540	8.9715	8.9569
15 MHz	75RB#0	1717.5	14.33	14.23	13.441	13.424
		1732.5	14.29	14.26	13.443	13.422
		1747.5	14.29	14.26	13.428	13.415
20 MHz	100RB#0	1720.0	18.98	18.94	17.915	17.905
		1732.5	18.94	18.94	17.910	17.902
		1745.0	18.95	18.96	17.871	17.884




LTE FDD Band 4-1.4MHz Channel Bandwidth

QPSK




6RB#0

16QAM




6RB#0

Low Channel



6RB#0




6RB#0

Middle Channel



6RB#0



6RB#0

High Channel



The results shown in this test report refer only to the sample(s) tested unless otherwise stated and the sample(s) are retained for 30 days only. The document is issued by HUAKE, this document cannot be reproduced except in full with our prior written permission. The more details and the authenticity of the report will be confirmed at <http://www.cer-mark.com>.

TEL : +86-755 2302 9901 FAX : +86-755 2302 9901 E-mail : service@cer-mark.com

Add: 1-2F., Building B2, Junfeng Zhongcheng Zhizao Innovation Park, Heping Community, Fuhai Street, Bao'an District, Shenzhen, Guangdong, China



QPSK



15RB#0

15RB#0

Agilent Spectrum Analyzer - Occupied BW


File: [] Settings: [] Presets: [] Measurements: [] **ALTAUTO** 08:13:24 AM Mar 22, 2022
 Center Freq 1.732500000 GHz Trig: Free Run Avg/Hold: 3000 Radio Std: None Frequency
 #F Gain: Low #Rtn: 30 dB Radio Device: BTS

10 dBmV Ref 40.00 dBm
 40.00
 30.00
 20.00
 10.00
 0.00
 -10.00
 -20.00
 -30.00
 -40.00
 -50.00

Center 1.733 GHz Span 6 MHz
 #Res BW 51 kHz #VBW 150 kHz #Sweep 100 ms
 Occupied Bandwidth Total Power 25.6 dBm
 2.6904 MHz
 Transmit Freq Error -70 Hz OBW Power 99.00 %
 x dB Bandwidth 2.899 MHz x dB -26.00 dB

Auto CF Step 600.000 kHz Man
 Freq Offset 0 Hz

MISC (STATUS)



15RB#0

15RB#0

Agilent Spectrum Analyzer - Occupied BW

ALU: MEAS: B324: PWR: AVERAGE: 1 CENTER: 17.53500000 GHz ALN: AUTO 100: 19:47 AM Mar 22, 2022

Center Freq 1.753500000 GHz Center Freq 1.753500000 GHz Trig: Free Run Avg/Hold: 3000 Radio Std: None

#F Gain: Low #F Res: 30 dB Radio Device: BTS

10 dBm/div Ref 40.00 dBm

Center 1.754 GHz Span 6 MHz

#Res BW 51 kHz #VBW 150 kHz #Sweep 100 ms

Occupied Bandwidth	Total Power
2.6965 MHz	25.3 dBm

Transmit Freq Error	OBW Power	
-880 Hz	99.00 %	

x dB Bandwidth	x dB	
2.930 MHz	-26.00 dB	

MFG (STATUS)


Frequency

Center Freq 1.753500000 GHz

CF Step 600.000 kHz

Auto Man

Freq Offset 0 Hz



15RB#0

15RB#0


High Channel

Add: 1-2F., Building B2, Junfeng Zhongcheng Zhizao Innovation Park, Heping Community, Fuhai Street, Bao'an District, Shenzhen, Guangdong, China




LTE FDD Band 4-5MHz Channel Bandwidth

QPSK




16QAM



25RB#0

25RB#0

Low Channel




25RB#0




25RB#0

Middle Channel



25RB#0



25RB#0

High Channel

The results shown in this test report refer only to the sample(s) tested unless otherwise stated and the sample(s) are retained for 30 days only. The document is issued by HUAKE, this document cannot be reproduced except in full with our prior written permission. The more details and the authenticity of the report will be confirmed at <http://www.cer-mark.com>.

TEL : +86-755 2302 9901 FAX : +86-755 2302 9901 E-mail : service@cer-mark.com

Add: 1-2F., Building B2, Junfeng Zhongcheng Zhizao Innovation Park, Heping Community, Fuhai Street, Bao'an District, Shenzhen, Guangdong, China




LTE FDD Band 4-10MHz Channel Bandwidth

QPSK



16QAM




50RB#0

50RB#0

Low Channel



50RB#0



50RB#0

Middle Channel



50RB#0



50RB#0

High Channel


The results shown in this test report refer only to the sample(s) tested unless otherwise stated and the sample(s) are retained for 30 days only. The document is issued by HUAKE, this document cannot be reproduced except in full with our prior written permission. The more details and the authenticity of the report will be confirmed at <http://www.cer-mark.com>.

TEL : +86-755 2302 9901 FAX : +86-755 2302 9901 E-mail : service@cer-mark.com

Add: 1-2F., Building B2, Junfeng Zhongcheng Zhizao Innovation Park, Heping Community, Fuhai Street, Bao'an District, Shenzhen, Guangdong, China


LTE FDD Band 4-15MHz Channel Bandwidth

QPSK




75RB#0

16QAM




75RB#0

Low Channel




75RB#0




75RB#0

Middle Channel



75RB#0



75RB#0

High Channel


The results shown in this test report refer only to the sample(s) tested unless otherwise stated and the sample(s) are retained for 30 days only. The document is issued by HUAK, this document cannot be reproduced except in full with our prior written permission. The more details and the authenticity of the report will be confirmed at <http://www.cer-mark.com>.

TEL : +86-755 2302 9901 FAX : +86-755 2302 9901 E-mail : service@cer-mark.com

Add: 1-2F., Building B2, Junfeng Zhongcheng Zhizao Innovation Park, Heping Community, Fuhai Street, Bao'an District, Shenzhen, Guangdong, China


LTE FDD Band 4-20MHz Channel Bandwidth

QPSK



100RB#0

16QAM




100RB#0

Low Channel




100RB#0




100RB#0

Middle Channel



100RB#0



100RB#0

High Channel

The results shown in this test report refer only to the sample(s) tested unless otherwise stated and the sample(s) are retained for 30 days only. The document is issued by HUAK, this document cannot be reproduced except in full with our prior written permission. The more details and the authenticity of the report will be confirmed at <http://www.cer-mark.com>.

TEL : +86-755 2302 9901 FAX : +86-755 2302 9901 E-mail : service@cer-mark.com

Add: 1-2F., Building B2, Junfeng Zhongcheng Zhizao Innovation Park, Heping Community, Fuhai Street, Bao'an District, Shenzhen, Guangdong, China




3.4 Band Edge Compliance

LIMIT

According to §27.53 (h): For operations in the 1710–1755 MHz and 2110–2155 MHz bands, the power of any emission outside a licensee's frequency block shall be attenuated below the transmitter power (P) by at least $43 + 10 \log_{10}(P)$ dB.

TEST CONFIGURATION




TEST PROCEDURE


1. The transmitter output port was connected to base station.
2. The RF output of EUT was connected to the power meter by RF cable and attenuator, the path loss was compensated to the results for each measurement.
3. Set EUT at maximum power through base station.
4. Select lowest and highest channels for each band and different modulation.
5. Measure Band edge using RMS (Average) detector by spectrum.


TEST RESULTS

Remark:

1. We were tested all RB Configuration refer 3GPP TS136 521 for each Channel Bandwidth of LTE FDD Band 4; recorded worst case for each Channel Bandwidth of LTE FDD Band 4.









LTE FDD Band 4-10MHz Channel Bandwidth Band Edge Compliance

QPSK



50RB#0

16QAM



50RB#0

Low Channel




50RB#0



50RB#0

High Channel





LTE FDD Band 4-20MHz Channel Bandwidth Band Edge Compliance

QPSK



100RB#0

16QAM



100RB#0

Low Channel



100RB#0



100RB#0

High Channel


3.5 Spurious Emission

LIMIT


According to §27.53 (h): For operations in the 1710–1755 MHz and 2110–2155 MHz bands, the power of any emission outside a licensee's frequency block shall be attenuated below the transmitter power (P) by at least $43 + 10 \log_{10}(P)$ dB.

TEST CONFIGURATION

Conducted Spurious Measurement:



Radiated Spurious Measurement:



TEST PROCEDURE

The EUT was setup according to EIA/TIA 603D.

Conducted Spurious Measurement:

- Place the EUT on a bench and set it in transmitting mode.
- Connect a low loss RF cable from the antenna port to a spectrum analyzer and CMW500 by a Directional Couple.
- EUT Communicate with CMW500, then select a channel for testing.
- Add a correction factor to the display of spectrum, and then test.
- The resolution bandwidth of the spectrum analyzer was set sufficient scans were taken to show the out of band Emission if any up to 10^{th} harmonic.
- Please refer to following tables for test antenna conducted emissions.

Working Frequency	Sub range (GHz)	RBW	VBW	Sweep time (s)
LTE FDD Band 4	0.000009~0.000015	1KHz	3KHz	Auto
	0.000015~0.03	10KHz	30KHz	Auto
	0.03~26.5	1 MHz	3 MHz	Auto

**Radiated Spurious Measurement:**

- a. The EUT shall be placed at the specified height on a support, and in the position closest to normal use as declared by provider.
- b. The test antenna shall be oriented initially for vertical polarization and shall be chosen to correspond to the frequency of the transmitter.
- c. The output of the test antenna shall be connected to the measuring receiver.
- d. The transmitter shall be switched on and the measuring receiver shall be tuned to the frequency of the transmitter under test.
- e. The test antenna shall be raised and lowered through the specified range of height until a maximum signal level is detected by the measuring receiver.
- f. The transmitter shall then be rotated through 360° in the horizontal plane, until the maximum signal level is detected by the measuring receiver.
- g. The test antenna shall be raised and lowered again through the specified range of height until a maximum signal level is detected by the measuring receiver.
- h. The maximum signal level detected by the measuring receiver shall be noted.
- i. The transmitter shall be replaced by a substitution antenna.
- j. The substitution antenna shall be orientated for vertical polarization and the length of the substitution antenna shall be adjusted to correspond to the frequency of the transmitter.
- k. The substitution antenna shall be connected to a calibrated signal generator.
- l. If necessary, the input attenuator setting of the measuring receiver shall be adjusted in order to increase the sensitivity of the measuring receiver.
- m. The test antenna shall be raised and lowered through the specified range of height to ensure that the maximum signal is received.
- n. The input signal to the substitution antenna shall be adjusted to the level that produces a level detected by the measuring receiver, that is equal to the level noted while the transmitter radiated power was measured, corrected for the change of input attenuator setting of the measuring receiver.
- o. The measurement shall be repeated with the test antenna and the substitution antenna orientated for horizontal polarization.
- p. The measure of the effective radiated power is the larger of the two levels recorded at the input to the substitution antenna, corrected for gain of the substitution antenna if necessary.
- q. The resolution bandwidth of the spectrum analyzer was set at 100 kHz for Part 22 and 1MHz for Part 24. The frequency range was checked up to 10th harmonic.
- r. Test site anechoic chamber refer to ANSI C63.


TEST RESULTS**Remark:**

1. We were tested all RB Configuration refer 3GPP TS136 521 for each Channel Bandwidth of LTE FDD Band 4; recorded worst case for each Channel Bandwidth of LTE FDD Band 4.


Conducted Measurement:

LTE FDD Band 4-1.4MHz Channel Bandwidth
Low Channel

QPSK



16QAM



30MHz~1GHz



30MHz~1GHz



1GHz~5GHz





1GHz~5GHz



5GHz~12GHz

5GHz~12GHz



The results shown in this test report refer only to the sample(s) tested unless otherwise stated and the sample(s) are retained for 30 days only. The document is issued by HUAKE, this document cannot be reproduced except in full with our prior written permission. The more details and the authenticity of the report will be confirmed at <http://www.cer-mark.com>.

TEL : +86-755 2302 9901 FAX : +86-755 2302 9901 E-mail : service@cer-mark.com

Add: 1-2F., Building B2, Junfeng Zhongcheng Zhizao Innovation Park, Heping Community, Fuhai Street, Bao'an District, Shenzhen, Guangdong, China



The results shown in this test report refer only to the sample(s) tested unless otherwise stated and the sample(s) are retained for 30 days only. The document is issued by HUAKE, this document cannot be reproduced except in full with our prior written permission. The more details and the authenticity of the report will be confirmed at <http://www.cer-mark.com>.

TEL : +86-755 2302 9901 FAX : +86-755 2302 9901 E-mail : service@cer-mark.com

Add: 1-2F., Building B2, Junfeng Zhongcheng Zhizao Innovation Park, Heping Community, Fuhai Street, Bao'an District, Shenzhen, Guangdong, China

