

TEST REPORT

Product Name: Mini pc
FCC ID: 2A6NCKBOX-101
Trademark: N/A
Model Number: Please refer to section 4.1
Prepared For: Shenzhen EvrTech Co., Ltd
Address: 211, JingKai Building, Longhua St., Longhua District, Shenzhen City, Guangdong Province China 518109
Manufacturer: Shenzhen EvrTech Co., Ltd
Address: 211, JingKai Building, Longhua St., Longhua District, Shenzhen City, Guangdong Province China 518109
Prepared By: Shenzhen CTB Testing Technology Co., Ltd.
Address: Floor 1&2, Building A, No. 26 of Xinhe Road, Xinqiao Community, Xinqiao Street, Baoan District, Shenzhen, Guangdong China
Sample Received Date: Apr. 9, 2022
Sample tested Date: Apr. 9, 2022 to Apr. 22, 2022
Issue Date: Apr. 22, 2022
Report No.: CTB220422010RFX
FCC Part15.247
Test Standards ANSI C63.10:2013
KDB 662911 V02r01
Test Results PASS
Remark: This is WIFI-2.4GHz band radio test report.

Compiled by:

Chen Zheng

Reviewed by:

Arron Liu

Approved by:

Bin Mei / Director

The test report is effective only with both signature and specialized stamp. This result(s) shown in this report refer only to the sample(s) tested. Without written approval of Shenzhen CTB Testing Technology Co., Ltd. This report can't be reproduced except in full. The tested sample(s) and the sample information are provided by the client.

TABLE OF CONTENT

Test Report Declaration	Page
1. VERSION	4
2. TEST SUMMARY.....	5
3. MEASUREMENT UNCERTAINTY	6
4. PRODUCT INFORMATION AND TEST SETUP.....	7
4.1 Product Information	7
4.2 Test Setup Configuration	8
4.3 Support Equipment.....	8
4.4 Channel List	9
4.5 Test Mode	9
4.6 Test Environment	9
5. TEST FACILITY AND TEST INSTRUMENT USED	10
5.1 Test Facility	10
5.2 Test Instrument Used	10
6. AC POWER LINE CONDUCTED EMISSION.....	13
6.1 Block Diagram Of Test Setup	13
6.2 Limit.....	13
6.3 Test procedure	13
6.4 Test Result	15
7. RADIATED SPURIOUS EMISSION.....	17
7.1 Block Diagram Of Test Setup	17
7.2 Limit.....	17
7.3 Test procedure	18
7.4 Test Result	19
8. BAND EDGE AND RF CONDUCTED SPURIOUS EMISSIONS	41
8.1 Block Diagram Of Test Setup	41
8.2 Limit.....	41
8.3 Test procedure	41
8.4 Test Result	42
9. CONDUCTED OUTPUT POWER.....	58
9.1 Block Diagram Of Test Setup	58
9.2 Limit.....	58

9.3	Test procedure	58
9.4	Test Result	59
10.	6DB OCCUPIED BANDWIDTH.....	60
10.1	Block Diagram Of Test Setup	60
10.2	Limit.....	60
10.3	Test procedure	60
10.4	Test Result	61
11.	POWER SPECTRAL DENSITY	70
11.1	Block Diagram Of Test Setup	70
11.2	Limit.....	70
11.3	Test procedure	70
11.4	Test Result	71
12.	ANTENNA REQUIREMENT	80
13.	EUT TEST SETUP PHOTOGRAPHS	81

(Note: N/A means not applicable)



1. VERSION

Report No.	Issue Date	Description	Approved
CTB220422010RFX	Apr. 22, 2022	Original	Valid

2. TEST SUMMARY

The Product has been tested according to the following specifications:

Test Item	Test Requirement	Test method	Result
AC Power Line Conducted Emission	47 CFR Part 15 Subpart C Section 15.207	ANSI C63.10-2013	PASS
Radiated Spurious emissions	47 CFR Part 15 Subpart C Section 15.205/15.209	ANSI C63.10-2013	PASS
Band edge and RF Conducted Spurious Emissions	47 CFR Part 15 Subpart C Section 15.247(d)/15.205(a)	ANSI C63.10-2013	PASS
Conducted Peak Output Power	47 CFR Part 15 Subpart C Section 15.247 (b)(3)	ANSI C63.10-2013	PASS
6dB Occupied Bandwidth	47 CFR Part 15 Subpart C Section 15.247 (a)(2)	ANSI C63.10-2013	PASS
Power Spectral Density	47 CFR Part 15 Subpart C Section 15.247 (e)	ANSI C63.10-2013/ KDB 558074 D05v02	PASS
Antenna Requirement	47 CFR Part 15 Subpart C Section 15.203/15.247 (b)	ANSI C63.10-2013	PASS
RF Exposure Evaluation	47 CFR Part 15 Subpart C Section 15.247 (i)/1.1310/2.1093	KDB447498D01v06	PASS

Remark:

Test according to ANSI C63.4-2014 & ANSI C63.10-2013.

3. MEASUREMENT UNCERTAINTY

Where relevant, the following measurement uncertainty levels have been estimated for tests performed on the Product as specified in CISPR 16-4-2. This uncertainty represents an expanded uncertainty expressed at approximately the 95% confidence level using a coverage factor of $k=2$.

Item	Uncertainty
Occupancy bandwidth	$U=\pm 54.3\text{Hz}$
Conducted output power Above 1G	$U=\pm 1.0\text{dB}$
Conducted output power below 1G	$U=\pm 0.9\text{dB}$
Power Spectral Density , Conduction	$U=\pm 1.0\text{dB}$
Conduction spurious emissions	$U=\pm 2.8\text{dB}$
Out of band emission	$U=\pm 54\text{Hz}$
3m chamber Radiated spurious emission(9KHz-30MHz)	$U=\pm 4.8\text{dB}$
3m chamber Radiated spurious emission(30MHz-1GHz)	$U=\pm 4.3\text{dB}$
3m chamber Radiated spurious emission(1GHz-18GHz)	$U=\pm 4.5\text{dB}$
3m chamber Radiated spurious emission(18GHz-40GHz)	$U=\pm 3.4\text{dB}$
humidity uncertainty	$U=\pm 5.3\%$
Temperature uncertainty	$U=\pm 0.59^{\circ}\text{C}$
Supply voltages	$U=\pm 3\%$
Time	$U=\pm 5\%$

4. PRODUCT INFORMATION AND TEST SETUP

4.1 Product Information

Model(s):	KBOX-101, KBOX-102, KBOX-103, KBOX-300, KBOX-800, KBOX-900, KBOX-1000, KBOX-5210, KBOX-3102, KBOX-5200, KBOX-2500, KBOX-2300, KBOX-2000, EP116, EP118, EP119, EP176, EP186, EP071, EP081, EP608, EP808, EP901, EP908, EP196, EP120, EP310, EP410, EP510, EP198, EP708, PBOX-B1, PBOX-B2, PBOX-N1, PBOX-N2, PBOX-N3, PBOX-N4, PBOX-T2, PBOX-E2, PBOX-E8, PBOX-S, PBOX-N6, PBOX-U, PBOX-M80, PBOX-H, PBOX-T1, PBOX-J1, PBOX-J2, PBOX-K1, PBOX-K2, PBOX-K3, PBOX-K5, P806L, P906L, P1106L, 1U194L, 1U196L, 1U525, 1U3240W, 1U3240A, 1U4160G, 1U4160B, ZBOX-770, ZBOX-780, ZBOX-990, ZBOX-680, ZBOX-850, ZBOX-860, ZBOX-590, ZBOX-H, ZBOX-M, ZBOX-I, ZBOX-980, ZBOX-1037, ZBOX-3000, ZBOX-4000, ZBOX-5000, ZBOX-6000, ZBOX-7000, PPC-1001K, PPC-1201K, PPC-1501K, PPC-1001P, PPC-1201P, PPC-1501P, AIO001, AIO002
Model Description:	All model's the function, software and electric circuit are the same, only with the product Installation Method and model named different. Test sample model: KBOX-101
Wi-Fi Specification:	IEEE 802.11b/g/n
Hardware Version:	V1.0
Software Version:	V1.0
Operation Frequency:	WiFi: IEEE 802.11b/g/n 20: 2412-2462MHz/ 11 channel IEEE 802.11n 40: 2422-2452MHz/ 7 channel
Max. RF output power:	WiFi (2.4G) : 9.79dBm
Type of Modulation:	WiFi: DSSS, OFDM, CCK
Antenna installation:	WiFi: External Antenna
Antenna Gain:	WiFi (2.4G) : 1.0dBi
Ratings:	AC 120V

4.2 Test Setup Configuration

See test photographs attached in EUT TEST SETUP PHOTOGRAPHS for the actual connections between Product and support equipment.

4.3 Support Equipment

Item	Equipment	Mfr/Brand	Model/Type No.	Series No.	Note
1	Monitor	Hpdal	S1	N/A	N/A
2	Mouse	Rapoo	M700	N/A	N/A
3	Keyboard	Rapoo	M700	N/A	N/A

Notes:

1. All the equipment/cables were placed in the worst-case configuration to maximize the emission during the test.
2. Grounding was established in accordance with the manufacturer's requirements and conditions for the intended use.

4.4 Channel List

CH	Frequency (MHz)	CH	Frequency (MHz)	CH	Frequency (MHz)	CH	Frequency (MHz)
1	2412	2	2417	3	2422	4	2427
5	2432	6	2437	7	2442	8	2447
9	2452	10	2457	11	2462		

4.5 Test Mode

All test mode(s) and condition(s) mentioned were considered and evaluated respectively by performing full tests, the worst data were recorded and reported.

Test mode	Low channel	Middle channel	High channel
Transmitting(802.11b/g/n20)	2412MHz	2437MHz	2462MHz
Transmitting(802.11n40)	2422MHz	2437MHz	2452MHz

NOTE: Dutycycle>98%.

Test mode	rate
802.11b	11M
802.11g	54M
802.11/n20	65M
802.11/n40	65M

4.6 Test Environment

Humidity(%):	55
Atmospheric Pressure(kPa):	101.1
Normal Voltage(AC):	120V
Normal Temperature(°C)	25
Low Temperature(°C)	0
High Temperature(°C)	50

5. TEST FACILITY AND TEST INSTRUMENT USED

5.1 Test Facility

All measurement facilities used to collect the measurement data are located at Floor 1&2, Building A, No. 26 of Xinhe Road, Xinqiao Street, Baoan District, Shenzhen China. The site and apparatus are constructed in conformance with the requirements of ANSI C63.4 and CISPR 16-1-1 other equivalent standards.

5.2 Test Instrument Used

No.	Equipment	Manufacturer	Model No.	Serial No.	Calibrated date	Calibrated until
1	Spectrum Analyzer	Agilent	N9020A	MY52090073	2021.09.27	2022.08.05
2	Power Sensor	Agilent	U2021XA	MY56120032	2021.09.27	2022.08.05
3	Power Sensor	Agilent	U2021XA	MY56120034	2021.09.27	2022.08.05
4	Communication test set	R&S	CMW500	108058	2021.09.27	2022.08.05
5	Spectrum Analyzer	R&S	FSP40	100550	2021.09.27	2022.08.05
6	Signal Generator	Agilent	N5181A	MY49060920	2021.09.27	2022.08.16
7	Signal Generator	Agilent	N5182A	MY47420195	2021.09.27	2022.08.05
8	Communication test set	Agilent	E5515C	MY50102567	2021.09.27	2022.08.16
9	band rejection filter	Shenxiang	MSF2400-2483.5MS-1154	20181015001	2021.09.27	2022.08.05
10	band rejection filter	Shenxiang	MSF5150-5850MS-1155	20181015001	2021.09.27	2022.08.05
11	band rejection filter	Xingbo	XBLBQ-DZA120	190821-1-1	2021.09.27	2022.08.05
12	BT&WI-FI Automatic test software	Microwave	MTS8310	Ver. 2.0.0.0	2021.09.27	2022.08.05
13	Rohde & Schwarz SFU Broadcast Test System	R&S	SFU	101017	2021.09.27	2022.08.05
14	Temperature humidity chamber	Hongjing	TH-80CH	DG-15174	2021.09.27	2022.08.05
15	234G	Microwave	MTS8200	Ver. 2.0.0.0	2021.09.27	2022.08.05


	Automatic test software					
16	966 chamber	C.R.T.	966 Room	966	2021.09.27	2024.08.11
17	Receiver	R&S	ESPI	100362	2021.09.27	2022.08.05
18	Amplifier	HP	8447E	2945A02747	2021.09.27	2022.08.05
19	Amplifier	Agilent	8449B	3008A01838	2021.09.27	2022.08.05
20	TRILOG Broadband Antenna	Schwarzbeck	VULB 9163	869	2021.09.27	2022.08.07
21	Horn Antenna	Schwarzbeck	BBHA9120D	1911	2021.09.27	2022.08.08
22	Software	Fala	EZ-EMC	FA-03A2 RE	2021.09.27	2022.08.05
23	3-Loop Antenna	Daze	ZN30401	17014	2021.09.27	2022.08.05
24	loop antenna	ZHINAN	ZN30900A	/	2021.09.27	2022.08.05
25	Horn antenna	A/H/System	SAS-574	588	2021.09.27	2022.08.05
26	Amplifier	AEROFLEX	/	S/N/ 097	2021.09.27	2022.08.05

Continuous disturbance						
No.	Equipment	Manufacturer	Model No.	Serial No.	Calibrated date	Calibrated until
1	AMN	ROHDE&SCHWARZ	ESH3-Z5	831551852	2021.09.27	2022.08.05
2	Pulse limiter	ROHDE&SCHWARZ	ESH3Z2	357881052	2021.09.27	2022.08.05
3	EMI TEST RECEIVER	ROHDE&SCHWARZ	ESCS30	834115/006	2021.09.27	2022.08.05
4	Coaxial cable	ZDECL	Z302S	18091904	2021.09.27	2022.08.05
5	AAN	Schwarzbeck	NTFM8158	183	2021.09.27	2022.08.05
6	Communication test set	Agilent	E5515C	MY50102567	2021.09.27	2022.08.05
7	Communication test set	R&S	CMW500	108058	2021.09.27	2022.08.05
8	EZ-EMC	Frad	EMC-con3A1.1	/	/	/

Radiated emission						
No.	Equipment	Manufacturer	Model No.	Serial No.	Calibrated date	Calibrated until
1	Double Ridged Broadband Horn Antenna	Schwarzbeck	BBHA 9120D	1911	2021.09.27	2022.08.05
2	TRILOG Broadband Antenna	Schwarzbeck	VULB 9168	869	2021.09.27	2022.08.05
3	Amplifier	Agilent	8449B	3008A01838	2021.09.27	2022.08.05
4	Amplifier	HP	8447E	2945A02747	2021.09.27	2022.08.05
5	EMI TEST RECEIVER	ROHDE&SCHWARZ	ESPI7	100362	2021.09.27	2022.08.05
6	Coaxial cable	ETS	RFC-SNS-100-NMS-80 NI	/	2021.09.27	2022.08.05
7	Coaxial cable	ETS	RFC-SNS-100-NMS-20 NI	/	2021.09.27	2022.08.05
8	Coaxial cable	ETS	RFC-SNS-100-SMS-20 NI	/	2021.09.27	2022.08.05
9	Coaxial cable	ETS	RFC-NNS-100-NMS-30 0 NI	/	2021.09.27	2022.08.05
10	Communication test set	Agilent	E5515C	MY50102567	2021.09.27	2022.08.05
11	Communication test set	R&S	CMW500	108058	2021.09.27	2022.08.05
12	EZ-EMC	Frad	EMC-con3A1.1	/	/	/

6. AC POWER LINE CONDUCTED EMISSION

6.1 Block Diagram Of Test Setup



6.2 Limit

Table 4 - AC power-line conducted emissions limits

Frequency (MHz)	Conducted limit (dBμV)	
	Quasi-peak	Average
0.15 - 0.5	66 to 56 ^{Note 1}	56 to 46 ^{Note 1}
0.5 - 5	56	46
5 - 30	60	50

Note 1: The level decreases linearly with the logarithm of the frequency.

* Decreasing linearly with the logarithm of the frequency

6.3 Test procedure

- 1) The mains terminal disturbance voltage test was conducted in a shielded room.
- 2) The EUT was connected to AC power source through a LISN 1 (Line Impedance Stabilization Network) which provides a 50Ω/50μH + 5Ω linear impedance. The power cables of all other units of the EUT were connected to a second LISN 2, which was bonded to the ground reference plane in the same way as the LISN 1 for the unit being measured. A multiple socket outlet strip was used to connect multiple power cables to a single LISN provided the rating of the LISN was not exceeded.
- 3) The tabletop EUT was placed upon a non-metallic table 0.8m above the ground reference plane. And for floor-standing arrangement, the EUT was placed on the horizontal ground reference plane,
- 4) The test was performed with a vertical ground reference plane. The rear of the EUT shall be 0.4 m from the vertical ground reference plane. The vertical ground reference


plane was bonded to the horizontal ground reference plane. The LISN 1 was placed 0,8 m from the boundary of the unit under test and bonded to a ground reference plane for LISNs mounted on top of the ground reference plane. This distance was between the closest points of the LISN 1 and the EUT. All other units of the EUT and associated equipment was at least 0,8 m from the LISN 2.

- 5) In order to find the maximum emission, the relative positions of equipment and all of the interface cables must be changed according to ANSI C63.10 on conducted measurement.

6.4 Test Result

Test Specification: Line
AC 120V 60Hz

80.0 dBuV




No.	Mk.	Freq.	Reading	Correct	Measure-	Limit	Margin	
		MHz	Level	Factor	ment			Detector
			dBuV	dB	dBuV	dBuV	dB	
1		0.2100	33.11	10.69	43.80	63.21	-19.41	QP
2		0.2100	17.98	10.69	28.67	53.21	-24.54	AVG
3		0.3790	25.23	10.59	35.82	58.30	-22.48	QP
4		0.3790	21.67	10.59	32.26	48.30	-16.04	AVG
5	*	0.8215	29.61	10.58	40.19	56.00	-15.81	QP
6		0.8215	16.90	10.58	27.48	46.00	-18.52	AVG
7		2.9340	25.81	10.63	36.44	56.00	-19.56	QP
8		2.9340	14.95	10.63	25.58	46.00	-20.42	AVG
9		7.3578	25.56	10.73	36.29	60.00	-23.71	QP
10		7.3578	13.56	10.73	24.29	50.00	-25.71	AVG
11		21.1417	24.48	10.99	35.47	60.00	-24.53	QP
12		21.1417	17.93	10.99	28.92	50.00	-21.08	AVG

Remark:

Factor = Cable loss + LISN factor, Margin = Measurement – Limit

Test Specification: Neutral
AC 120V 60Hz



No.	Mk.	Freq.	Reading	Correct	Measure-	Limit	Margin	
		MHz	Level	Factor	ment			Detector
			dBuV	dB	dBuV	dBuV	dB	
1		0.2100	35.31	10.69	46.00	63.21	-17.21	QP
2		0.2100	21.21	10.69	31.90	53.21	-21.31	AVG
3		0.4339	27.82	10.56	38.38	57.18	-18.80	QP
4		0.4339	15.91	10.56	26.47	47.18	-20.71	AVG
5		0.8256	29.64	10.58	40.22	56.00	-15.78	QP
6		0.8256	17.56	10.58	28.14	46.00	-17.86	AVG
7	*	1.9334	30.31	10.63	40.94	56.00	-15.06	QP
8		1.9334	14.43	10.63	25.06	46.00	-20.94	AVG
9		5.9739	21.76	10.68	32.44	60.00	-27.56	QP
10		5.9739	10.59	10.68	21.27	50.00	-28.73	AVG
11		11.4618	26.35	10.84	37.19	60.00	-22.81	QP
12		11.4618	15.23	10.84	26.07	50.00	-23.93	AVG

Remark:

Factor = Cable loss + LISN factor, Margin = Measurement – Limit

7. RADIATED SPURIOUS EMISSION

7.1 Block Diagram Of Test Setup




Figure 1. Below 30MHz




Figure 2. 30MHz to 1GHz




Figure 3. Above 1GHz

7.2 Limit

Spurious Emissions:

Frequency	Field strength (microvolt/meter)	Limit (dB μ V/m)	Remark	Measurement distance (m)
0.009MHz-0.490MHz	2400/F (kHz)	-	-	300
0.490MHz-1.705MHz	24000/F (kHz)	-	-	30
1.705MHz-30MHz	30	-	-	30
30MHz-88MHz	100	40.0	Quasi-peak	3
88MHz-216MHz	150	43.5	Quasi-peak	3
216MHz-960MHz	200	46.0	Quasi-peak	3
960MHz-1GHz	500	54.0	Quasi-peak	3
Above 1GHz	500	54.0	Average	3

Note: 15.35(b), Unless otherwise specified, the limit on peak radio frequency emissions is 20dB above the maximum permitted average emission limit applicable to the equipment under test. This peak limit applies to the total peak emission level radiated by the device.

7.3 Test procedure

Below 1GHz test procedure as below:

- a. The EUT was placed on the top of a rotating table 0.8 meters above the ground at a 3 meter semi-anechoic chamber. The table was rotated 360 degrees to determine the position of the highest radiation.
- b. The EUT was set 3 meters away from the interference-receiving antenna, which was mounted on the top of a variable-height antenna tower.
- c. The antenna height is varied from one meter to four meters above the ground to determine the maximum value of the field strength. Both horizontal and vertical polarizations of the antenna are set to make the measurement.
- d. For each suspected emission, the EUT was arranged to its worst case and then the antenna was tuned to heights from 1 meter to 4 meters (for the test frequency of below 30MHz, the antenna was tuned to heights 1 meter) and the rota table table was turned from 0 degrees to 360 degrees to find the maximum reading.
- e. The test-receiver system was set to Peak Detect Function and Specified Bandwidth with Maximum Hold Mode.
- f. If the emission level of the EUT in peak mode was 10dB lower than the limit specified, then testing could be stopped and the peak values of the EUT would be reported. Otherwise the emissions that did not have 10dB margin would be re-tested one by one using peak, quasi-peak or average method as specified and then reported in a data sheet.

Above 1GHz test procedure as below:

- g. Different between above is the test site, change from Semi- Anechoic Chamber to fully Anechoic Chamber and change form table 0.8 meter to 1.5 meter(Above 18GHz the distance is 1 meter and table is 1.5 meter).
- h. Test the EUT in the lowest channel ,the middle channel ,the Highest channel
- j. Repeat above procedures until all frequencies measured was complete.

Receiver set:

Frequency	Detector	RBW	VBW	Remark
0.009MHz-0.090MHz	Peak	10kHz	30KHz	Peak
0.009MHz-0.090MHz	Average	10kHz	30KHz	Average
0.090MHz-0.110MHz	Quasi-peak	10kHz	30KHz	Quasi-peak
0.110MHz-0.490MHz	Peak	10kHz	30KHz	Peak
0.110MHz-0.490MHz	Average	10kHz	30KHz	Average
0.490MHz -30MHz	Quasi-peak	10kHz	30kHz	Quasi-peak
30MHz-1GHz	Quasi-peak	120 kHz	300KHz	Quasi-peak
Above 1GHz	Peak	1MHz	3MHz	Peak
	Peak	1MHz	10Hz	Average

7.4 Test Result

Below 1GHz Test Results:
Antenna polarity: H



No.	Mk.	Freq. MHz	Reading Level dBuV	Correct Factor dB	Measure- ment dBuV/m	Limit dB/m	Over dB	Detector
1		37.3509	35.67	-5.91	29.76	40.00	-10.24	QP
2		112.7218	35.61	-7.69	27.92	43.50	-15.58	QP
3	!	206.3975	46.00	-7.77	38.23	43.50	-5.27	QP
4		250.3009	43.97	-5.70	38.27	46.00	-7.73	QP
5	*	500.3009	42.15	0.72	42.87	46.00	-3.13	QP
6	!	876.7826	35.85	6.17	42.02	46.00	-3.98	QP

Remark: Factor = Cable lose + Antenna factor - Pre-amplifier; Margin = Limit – Level

Antenna polarity: V



No.	Mk.	Freq. MHz	Reading Level dBuV	Correct Factor dB	Measure- ment dBuV/m	Limit dB/m	Over dB	Detector
1	!	58.9217	41.73	-6.11	35.62	40.00	-4.38	QP
2		111.7377	44.13	-7.80	36.33	43.50	-7.17	QP
3		250.3009	43.16	-5.70	37.46	46.00	-8.54	QP
4		374.6225	40.04	-2.58	37.46	46.00	-8.54	QP
5	*	500.3009	42.55	0.72	43.27	46.00	-2.73	QP
6		810.2653	33.70	6.05	39.75	46.00	-6.25	QP

Remark: Factor = Cable lose + Antenna factor - Pre-amplifier; Margin = Limit – Level

1. The margin of 9K-30MH measurement exceeds 20dB, so the test chart is not included. Test Mode: TM1 (the worst)
2. All modes have been tested, and the test results show that b-mode data is the worst, only b-mode test chart is put. Test Mode: TM1 (the worst)
3. After pre-scanning three directions, the report recorded the worst case Test Mode: TM1 (the worst)

Above 1 GHz Test Results:

LOW CH1 (802.11b Mode)/2412

Horizontal:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4824	66.15	-3.64	62.51	74	-11.49	peak
4824	49.52	-3.64	45.88	54	-8.12	AVG
7236	57.41	-0.95	56.46	74	-17.54	peak
7236	44.39	-0.95	43.44	54	-10.56	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4824	64.82	-3.64	61.18	74	-12.82	peak
4824	47.81	-3.64	44.17	54	-9.83	AVG
7236	58.38	-0.95	57.43	74	-16.57	peak
7236	43.19	-0.95	42.24	54	-11.76	AVG

Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits

MID CH6 (802.11b Mode)/2437

Horizontal:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4874	64.24	-3.51	60.73	74	-13.27	peak
4874	47.93	-3.51	44.42	54	-9.58	AVG
7311	57.71	-0.82	56.89	74	-17.11	peak
7311	45.31	-0.82	44.49	54	-9.51	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4874	65.77	-3.51	62.26	74	-11.74	peak
4874	47.46	-3.51	43.95	54	-10.05	AVG
7311	59.29	-0.82	58.47	74	-15.53	peak
7311	42.87	-0.82	42.05	54	-11.95	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

HIGH CH11 (802.11b Mode)/2462

Horizontal:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4924	62.18	-3.43	58.75	74	-15.25	peak
4924	48.74	-3.43	45.31	54	-8.69	AVG
7386	58.52	-0.75	57.77	74	-16.23	peak
7386	43.33	-0.75	42.58	54	-11.42	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4924	63.90	-3.43	60.47	74	-13.53	peak
4924	47.38	-3.43	43.95	54	-10.05	AVG
7386	58.95	-0.75	58.20	74	-15.80	peak
7386	43.66	-0.75	42.91	54	-11.09	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Remark:

- (1) Measuring frequencies from 1 GHz to the 25 GHz.
- (2) * denotes emission frequency which appearing within the Restricted Bands specified in provision of 15.205, then the general radiated emission limits in 15.209 apply.
- (3) Data of measurement within this frequency range shown "----" in the table above means the reading of emissions are attenuated more than 20dB below the permissible limits or the field strength is too small to be measured.
- (4) When the test results of Peak Detected below the limits of Average Detected, the Average Detected is not need completed. For example: Top Channel at Fundamental 73.16dBuV/m(PK Value) <93.98(AV Limit), at harmonic 53.20 dBuV/m(PK Value) <54 dBuV/m(AV Limit), the Average Detected not need to completed.

LOW CH1 (802.11g Mode)/2412

Horizontal:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4824	63.41	-3.64	59.77	74	-14.23	peak
4824	49.30	-3.64	45.66	54	-8.34	AVG
7236	57.44	-0.95	56.49	74	-17.51	peak
7236	44.10	-0.95	43.15	54	-10.85	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4824	62.60	-3.64	58.96	74	-15.04	peak
4824	48.26	-3.64	44.62	54	-9.38	AVG
7236	58.97	-0.95	58.02	74	-15.98	peak
7236	44.26	-0.95	43.31	54	-10.69	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

MID CH6 (802.11g Mode)/2437

Horizontal:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4874	64.85	-3.51	61.34	74	-12.66	peak
4874	48.85	-3.51	45.34	54	-8.66	AVG
7311	58.37	-0.82	57.55	74	-16.45	peak
7311	44.50	-0.82	43.68	54	-10.32	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4874	63.99	-3.51	60.48	74	-13.52	peak
4874	48.12	-3.51	44.61	54	-9.39	AVG
7311	56.12	-0.82	55.30	74	-18.70	peak
7311	42.93	-0.82	42.11	54	-11.89	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

HIGH CH11 (802.11g Mode)/2462

Horizontal:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4924	63.33	-3.43	59.90	74	-14.10	peak
4924	48.35	-3.43	44.92	54	-9.08	AVG
7386	57.29	-0.75	56.54	74	-17.46	peak
7386	43.81	-0.75	43.06	54	-10.94	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4924	62.22	-3.43	58.79	74	-15.21	peak
4924	47.26	-3.43	43.83	54	-10.17	AVG
7386	56.15	-0.75	55.40	74	-18.60	peak
7386	42.54	-0.75	41.79	54	-12.21	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Remark:

(1) Measuring frequencies from 1 GHz to the 25 GHz.

(2) * denotes emission frequency which appearing within the Restricted Bands specified in provision of 15.205, then the general radiated emission limits in 15.209 apply.

(3) Data of measurement within this frequency range shown “---” in the table above means the reading of emissions are attenuated more than 20dB below the permissible limits or the field strength is too small to be measured.

(4) When the test results of Peak Detected below the limits of Average Detected, the Average Detected is not need completed. For example: Top Channel at Fundamental 73.16dBuV/m(PK Value) <93.98(AV Limit), at harmonic 53.20 dBuV/m(PK Value) <54 dBuV/m(AV Limit), the Average Detected not need to completed.

LOW CH1 (802.11n/H20 Mode)/2412

Horizontal:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4824	64.36	-3.64	60.72	74	-13.28	peak
4824	48.69	-3.64	45.05	54	-8.95	AVG
7236	58.47	-0.95	57.52	74	-16.48	peak
7236	43.32	-0.95	42.37	54	-11.63	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4824	62.41	-3.64	58.77	74	-15.23	peak
4824	51.63	-3.64	47.99	54	-6.01	AVG
7236	57.77	-0.95	56.82	74	-17.18	peak
7236	44.47	-0.95	43.52	54	-10.48	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

MID CH6 (802.11n/H20 Mode)/2437

Horizontal:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4874.00	62.13	-3.51	58.62	74.00	-15.38	peak
4874.00	48.93	-3.51	45.42	54.00	-8.58	AVG
7311.00	59.70	-0.82	58.88	74.00	-15.12	peak
7311.00	44.97	-0.82	44.15	54.00	-9.85	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4874.00	63.20	-3.51	59.69	74.00	-14.31	peak
4874.00	48.28	-3.51	44.77	54.00	-9.23	AVG
7311.00	59.23	-0.82	58.41	74.00	-15.59	peak
7311.00	41.49	-0.82	40.67	54.00	-13.33	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

HIGH CH11 (802.11n/H20 Mode)/2462

Horizontal:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4924	61.80	-3.43	58.37	74	-15.63	peak
4924	48.19	-3.43	44.76	54	-9.24	AVG
7386	58.72	-0.75	57.97	74	-16.03	peak
7386	41.97	-0.75	41.22	54	-12.78	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4924	64.13	-3.43	60.70	74	-13.30	peak
4924	46.79	-3.43	43.36	54	-10.64	AVG
7386	56.51	-0.75	55.76	74	-18.24	peak
7386	41.35	-0.75	40.60	54	-13.40	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

LOW CH3 (802.11n/H40 Mode)/2422

Horizontal:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4844	65.83	-3.63	62.20	74	-11.80	peak
4844	47.56	-3.63	43.93	54	-10.07	AVG
7266	59.83	-0.94	58.89	74	-15.11	peak
7266	44.05	-0.94	43.11	54	-10.89	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4844	64.61	-3.63	60.98	74	-13.02	peak
4844	48.03	-3.63	44.40	54	-9.60	AVG
7266	59.67	-0.94	58.73	74	-15.27	peak
7266	44.49	-0.94	43.55	54	-10.45	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

MID CH6 (802.11n/H40 Mode)/2437

Horizontal:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4874	65.13	-3.51	61.62	74	-12.38	peak
4874	47.55	-3.51	44.04	54	-9.96	AVG
7311	58.71	-0.82	57.89	74	-16.11	peak
7311	45.07	-0.82	44.25	54	-9.75	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
4874	62.24	-3.51	58.73	74	-15.27	peak
4874	46.44	-3.51	42.93	54	-11.07	AVG
7311	56.67	-0.82	55.85	74	-18.15	peak
7311	43.31	-0.82	42.49	54	-11.51	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

HIGH CH9 (802.11n/H40 Mode)/2452

Horizontal:

Frequency (MHz)	Meter Reading (dBμV)	Factor (dB)	Emission Level (dBμV/m)	Limits (dBμV/m)	Margin (dB)	Detector Type
4904	64.33	-3.43	60.90	74	-13.10	peak
4904	49.41	-3.43	45.98	54	-8.02	AVG
7356	56.55	-0.75	55.80	74	-18.20	peak
7356	42.26	-0.75	41.51	54	-12.49	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency (MHz)	Meter Reading (dBμV)	Factor (dB)	Emission Level (dBμV/m)	Limits (dBμV/m)	Margin (dB)	Detector Type
4904	64.40	-3.43	60.97	74	-13.03	peak
4904	46.39	-3.43	42.96	54	-11.04	AVG
7356	59.15	-0.75	58.40	74	-15.60	peak
7356	42.36	-0.75	41.61	54	-12.39	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Remark:

- (1) Measuring frequencies from 1 GHz to the 25 GHz.
- (2) * denotes emission frequency which appearing within the Restricted Bands specified in provision of 15.205, then the general radiated emission limits in 15.209 apply.
- (3) Data of measurement within this frequency range shown “---” in the table above means the reading of emissions are attenuated more than 20dB below the permissible limits or the field strength is too small to be measured.
- (4) When the test results of Peak Detected below the limits of Average Detected, the Average Detected is not need completed. For example: Top Channel at Fundamental 73.16dBuV/m(PK Value) <93.98(AV Limit), at harmonic 53.20 dBuV/m(PK Value) <54 dBuV/m(AV Limit), the Average Detected not need to completed
- (5)Have tested in three orientations for radiated emissions, Only The worst record is in this report

Restricted bands around fundamental frequency (Radiated)

Operation Mode:
802.11b Mode TX CH Low (2412MHz)

Horizontal

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2390	57.07	-5.81	51.26	74	-22.74	peak
2390	/	-5.81	/	54	/	AVG
2399	64.64	-5.84	58.80	74	-15.20	peak
2399	49.48	-5.84	43.64	54	-10.36	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2390	56.97	-5.81	51.16	74	-22.84	peak
2390	/	-5.81	/	54	/	AVG
2399	63.21	-5.84	57.37	74	-16.63	peak
2399	46.95	-5.84	41.11	54	-12.89	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Operation Mode: TX CH High (2462MHz)

Horizontal

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2483.5	55.83	-5.65	50.18	74	-23.82	peak
2483.5	/	-5.65	/	54	/	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2483.5	55.89	-5.65	50.24	74	-23.76	peak
2483.5	/	-5.65	/	54	/	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						
Remark: All the other emissions not reported were too low to read and deemed to comply with FCC limit.						

Operation Mode: 802.11g Mode TX CH Low (2412MHz)

Horizontal

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2390	57.68	-5.81	51.87	74	-22.13	peak
2390	/	-5.81	/	54	/	AVG
2399	62.66	-5.84	56.82	74	-17.18	peak
2399	46.81	-5.84	40.97	54	-13.03	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2390	56.27	-5.81	50.46	74	-23.54	peak
2390	/	-5.81	/	54	/	AVG
2399	62.64	-5.84	56.80	74	-17.20	peak
2399	45.97	-5.84	40.13	54	-13.87	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Operation Mode: TX CH High (2462MHz)

Horizontal

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2483.5	55.98	-5.65	50.33	74	-23.67	peak
2483.5	/	-5.65	/	54	/	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2483.5	56.92	-5.65	51.27	74	-22.73	peak
2483.5	/	-5.65	/	54	/	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						
Remark: All the other emissions not reported were too low to read and deemed to comply with FCC limit.						

Operation Mode: 802.11n/H20 Mode TX CH Low (2412MHz)

Horizontal

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2390	57.34	-5.81	51.53	74	-22.47	peak
2390	/	-5.81	/	54	/	AVG
2399	63.69	-5.84	57.85	74	-16.15	peak
2399	48.20	-5.84	42.36	54	-11.64	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2390	55.82	-5.81	50.01	74	-23.99	peak
2390	/	-5.81	/	54	/	AVG
2399	59.95	-5.84	54.11	74	-19.89	peak
2399	47.81	-5.84	41.97	54	-12.03	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Operation Mode: TX CH High (2462MHz)

Horizontal

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2483.5	55.83	-5.65	50.18	74	-23.82	peak
2483.5	/	-5.65	/	54	/	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2483.5	56.94	-5.65	51.29	74	-22.71	peak
2483.5	/	-5.65	/	54	/	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						
Remark: All the other emissions not reported were too low to read and deemed to comply with FCC limit.						

Operation Mode: 802.11n/H40 Mode TX CH Low (2422MHz)

Horizontal

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2390	57.88	-5.81	52.07	74	-21.93	peak
2390	/	-5.81	/	54	/	AVG
2399	63.93	-5.84	58.09	74	-15.91	peak
2399	45.93	-5.84	40.09	54	-13.91	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2390	57.12	-5.81	51.31	74	-22.69	peak
2390	/	-5.81	/	54	/	AVG
2399	62.03	-5.84	56.19	74	-17.81	peak
2399	45.60	-5.84	39.76	54	-14.24	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Operation Mode: TX CH High (2452MHz)

Horizontal


Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2483.5	58.15	-5.65	52.50	74	-21.50	peak
2483.5	/	-5.65	/	54	/	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						

Vertical:

Frequency	Meter Reading	Factor	Emission Level	Limits	Margin	Detector Type
(MHz)	(dBμV)	(dB)	(dBμV/m)	(dBμV/m)	(dB)	
2483.5	57.13	-5.65	51.48	74	-22.52	peak
2483.5	/	-5.65	/	54	/	AVG
Remark: Factor = Antenna Factor + Cable Loss – Pre-amplifier. Emission level = Reading Result + Factor, Margin = Emission level - Limits						
Remark: All the other emissions not reported were too low to read and deemed to comply with FCC limit.						

8. BAND EDGE AND RF CONDUCTED SPURIOUS EMISSIONS

8.1 Block Diagram Of Test Setup



8.2 Limit


In any 100 kHz bandwidth outside the frequency band in which the spread spectrum or digitally modulated intentional radiator is operating, the radio frequency power that is produced by the intentional radiator shall be at least 20 dB below that in the 100 kHz bandwidth within the band that contains the highest level of the desired power, based on either an RF conducted or a radiated measurement, provided the transmitter demonstrates compliance with the peak conducted power limits. If the transmitter complies with the conducted power limits based on the use of RMS averaging over a time interval, as permitted under paragraph (b)(3) of this section, the attenuation required under this paragraph shall be 30 dB instead of 20 dB. Attenuation below the general limits specified in §15.209(a) is not required. In addition, radiated emissions which fall in the restricted bands, as defined in §15.205(a), must also comply with the radiated emission limits specified in §15.209(a) (see §15.205(c)).

8.3 Test procedure

1. Remove the antenna from the EUT and then connect a low RF cable from the antenna port to the spectrum;
2. Set the spectrum analyzer:
Blow 30MHz:
RBW = 100kHz, VBW = 300kHz, Sweep = auto
Detector function = peak, Trace = max hold
Above 30MHz:
RBW = 100KHz, VBW = 300KHz, Sweep = auto
Detector function = peak, Trace = max hold


8.4 Test Result

ANT 1:



BAND EDGE Graphs

802.11g/LCH



802.11g/HCH



BAND EDGE Graphs


802.11n(HT20)/L
CH



802.11n(HT20)/H
CH






802.11n(HT40)/L
CH






802.11n(HT40)/H
CH




RF Conducted Spurious Emissions Graphs




802.11b
/LCH

802.11b
/MCH

802.11b
/HCH


RF Conducted Spurious Emissions Graphs

802.11g
/LCH

802.11g
/MCH

802.11g
/HCH


RF Conducted Spurious Emissions Graphs




802.11n (HT40)/ LCH	 <table><tr><th>MARK</th><th>MODE</th><th>TIC</th><th>SQL</th><th>F</th><th>F</th><th>F</th><th>F</th><th>F</th><th>F</th></tr><tr><td>1</td><td>N</td><td>1</td><td>f</td><td>2.415 8 GHz</td><td>-16.554 dBm</td><td></td><td></td><td></td><td></td></tr><tr><td>2</td><td>N</td><td>1</td><td>f</td><td>24.623 3 GHz</td><td>-41.412 dBm</td><td></td><td></td><td></td><td></td></tr><tr><td>3</td><td>N</td><td>1</td><td>f</td><td>4.774 3 GHz</td><td>-54.779 dBm</td><td></td><td></td><td></td><td></td></tr><tr><td>4</td><td>N</td><td>1</td><td>f</td><td>7.362 5 GHz</td><td>-53.812 dBm</td><td></td><td></td><td></td><td></td></tr><tr><td>5</td><td>N</td><td>1</td><td>f</td><td>9.552 1 GHz</td><td>-55.194 dBm</td><td></td><td></td><td></td><td></td></tr></table>	MARK	MODE	TIC	SQL	F	F	F	F	F	F	1	N	1	f	2.415 8 GHz	-16.554 dBm					2	N	1	f	24.623 3 GHz	-41.412 dBm					3	N	1	f	4.774 3 GHz	-54.779 dBm					4	N	1	f	7.362 5 GHz	-53.812 dBm					5	N	1	f	9.552 1 GHz	-55.194 dBm				
MARK	MODE	TIC	SQL	F	F	F	F	F	F																																																				
1	N	1	f	2.415 8 GHz	-16.554 dBm																																																								
2	N	1	f	24.623 3 GHz	-41.412 dBm																																																								
3	N	1	f	4.774 3 GHz	-54.779 dBm																																																								
4	N	1	f	7.362 5 GHz	-53.812 dBm																																																								
5	N	1	f	9.552 1 GHz	-55.194 dBm																																																								
802.11 n(HT40) /MCH	 <table><tr><th>MARK</th><th>MODE</th><th>TIC</th><th>SQL</th><th>F</th><th>F</th><th>F</th><th>F</th><th>F</th><th>F</th></tr><tr><td>1</td><td>N</td><td>1</td><td>f</td><td>2.428 2 GHz</td><td>-17.175 dBm</td><td></td><td></td><td></td><td></td></tr><tr><td>2</td><td>N</td><td>1</td><td>f</td><td>24.609 5 GHz</td><td>-41.669 dBm</td><td></td><td></td><td></td><td></td></tr><tr><td>3</td><td>N</td><td>1</td><td>f</td><td>4.751 1 GHz</td><td>-54.880 dBm</td><td></td><td></td><td></td><td></td></tr><tr><td>4</td><td>N</td><td>1</td><td>f</td><td>7.471 6 GHz</td><td>-54.693 dBm</td><td></td><td></td><td></td><td></td></tr><tr><td>5</td><td>N</td><td>1</td><td>f</td><td>9.559 2 GHz</td><td>-55.753 dBm</td><td></td><td></td><td></td><td></td></tr></table>	MARK	MODE	TIC	SQL	F	F	F	F	F	F	1	N	1	f	2.428 2 GHz	-17.175 dBm					2	N	1	f	24.609 5 GHz	-41.669 dBm					3	N	1	f	4.751 1 GHz	-54.880 dBm					4	N	1	f	7.471 6 GHz	-54.693 dBm					5	N	1	f	9.559 2 GHz	-55.753 dBm				
MARK	MODE	TIC	SQL	F	F	F	F	F	F																																																				
1	N	1	f	2.428 2 GHz	-17.175 dBm																																																								
2	N	1	f	24.609 5 GHz	-41.669 dBm																																																								
3	N	1	f	4.751 1 GHz	-54.880 dBm																																																								
4	N	1	f	7.471 6 GHz	-54.693 dBm																																																								
5	N	1	f	9.559 2 GHz	-55.753 dBm																																																								
802.11 n(HT40) /HCH	 <table><tr><th>MARK</th><th>MODE</th><th>TIC</th><th>SQL</th><th>F</th><th>F</th><th>F</th><th>F</th><th>F</th><th>F</th></tr><tr><td>1</td><td>N</td><td>1</td><td>f</td><td>2.445 8 GHz</td><td>-16.963 dBm</td><td></td><td></td><td></td><td></td></tr><tr><td>2</td><td>N</td><td>1</td><td>f</td><td>24.610 9 GHz</td><td>-40.890 dBm</td><td></td><td></td><td></td><td></td></tr><tr><td>3</td><td>N</td><td>1</td><td>f</td><td>4.755 8 GHz</td><td>-54.881 dBm</td><td></td><td></td><td></td><td></td></tr><tr><td>4</td><td>N</td><td>1</td><td>f</td><td>7.506 1 GHz</td><td>-52.514 dBm</td><td></td><td></td><td></td><td></td></tr><tr><td>5</td><td>N</td><td>1</td><td>f</td><td>9.894 5 GHz</td><td>-56.145 dBm</td><td></td><td></td><td></td><td></td></tr></table>	MARK	MODE	TIC	SQL	F	F	F	F	F	F	1	N	1	f	2.445 8 GHz	-16.963 dBm					2	N	1	f	24.610 9 GHz	-40.890 dBm					3	N	1	f	4.755 8 GHz	-54.881 dBm					4	N	1	f	7.506 1 GHz	-52.514 dBm					5	N	1	f	9.894 5 GHz	-56.145 dBm				
MARK	MODE	TIC	SQL	F	F	F	F	F	F																																																				
1	N	1	f	2.445 8 GHz	-16.963 dBm																																																								
2	N	1	f	24.610 9 GHz	-40.890 dBm																																																								
3	N	1	f	4.755 8 GHz	-54.881 dBm																																																								
4	N	1	f	7.506 1 GHz	-52.514 dBm																																																								
5	N	1	f	9.894 5 GHz	-56.145 dBm																																																								


ANT 2:

BAND EDGE Graphs

802.11b/LCH




802.11b/HCH



BAND EDGE Graphs

802.11g/LCH



802.11g/HCH




BAND EDGE Graphs


802.11n(HT20)/L
CH




802.11n(HT20)/H
CH






802.11n(HT40)/L
CH






802.11n(HT40)/H
CH






RF Conducted Spurious Emissions Graphs




802.11b /LCH	 <table><tr><th>MARK</th><th>MODE</th><th>FREQ</th><th>POWER</th></tr><tr><td>1</td><td>N</td><td>2.4114 GHz</td><td>-7.683 dBm</td></tr><tr><td>2</td><td>N</td><td>25.0883 GHz</td><td>-41.286 dBm</td></tr><tr><td>3</td><td>N</td><td>4.8193 GHz</td><td>-55.317 dBm</td></tr><tr><td>4</td><td>N</td><td>7.3445 GHz</td><td>-54.747 dBm</td></tr><tr><td>5</td><td>N</td><td>9.5889 GHz</td><td>-55.355 dBm</td></tr></table>	MARK	MODE	FREQ	POWER	1	N	2.4114 GHz	-7.683 dBm	2	N	25.0883 GHz	-41.286 dBm	3	N	4.8193 GHz	-55.317 dBm	4	N	7.3445 GHz	-54.747 dBm	5	N	9.5889 GHz	-55.355 dBm
MARK	MODE	FREQ	POWER																						
1	N	2.4114 GHz	-7.683 dBm																						
2	N	25.0883 GHz	-41.286 dBm																						
3	N	4.8193 GHz	-55.317 dBm																						
4	N	7.3445 GHz	-54.747 dBm																						
5	N	9.5889 GHz	-55.355 dBm																						
802.11b /MCH	 <table><tr><th>MARK</th><th>MODE</th><th>FREQ</th><th>POWER</th></tr><tr><td>1</td><td>N</td><td>2.4370 GHz</td><td>-7.464 dBm</td></tr><tr><td>2</td><td>N</td><td>24.6480 GHz</td><td>-41.229 dBm</td></tr><tr><td>3</td><td>N</td><td>4.8698 GHz</td><td>-55.183 dBm</td></tr><tr><td>4</td><td>N</td><td>7.4116 GHz</td><td>-54.159 dBm</td></tr><tr><td>5</td><td>N</td><td>9.8177 GHz</td><td>-55.261 dBm</td></tr></table>	MARK	MODE	FREQ	POWER	1	N	2.4370 GHz	-7.464 dBm	2	N	24.6480 GHz	-41.229 dBm	3	N	4.8698 GHz	-55.183 dBm	4	N	7.4116 GHz	-54.159 dBm	5	N	9.8177 GHz	-55.261 dBm
MARK	MODE	FREQ	POWER																						
1	N	2.4370 GHz	-7.464 dBm																						
2	N	24.6480 GHz	-41.229 dBm																						
3	N	4.8698 GHz	-55.183 dBm																						
4	N	7.4116 GHz	-54.159 dBm																						
5	N	9.8177 GHz	-55.261 dBm																						
802.11b /HCH	 <table><tr><th>MARK</th><th>MODE</th><th>FREQ</th><th>POWER</th></tr><tr><td>1</td><td>N</td><td>2.4599 GHz</td><td>-8.324 dBm</td></tr><tr><td>2</td><td>N</td><td>24.6965 GHz</td><td>-41.043 dBm</td></tr><tr><td>3</td><td>N</td><td>4.8949 GHz</td><td>-54.690 dBm</td></tr><tr><td>4</td><td>N</td><td>7.3975 GHz</td><td>-54.667 dBm</td></tr><tr><td>5</td><td>N</td><td>9.8439 GHz</td><td>-54.861 dBm</td></tr></table>	MARK	MODE	FREQ	POWER	1	N	2.4599 GHz	-8.324 dBm	2	N	24.6965 GHz	-41.043 dBm	3	N	4.8949 GHz	-54.690 dBm	4	N	7.3975 GHz	-54.667 dBm	5	N	9.8439 GHz	-54.861 dBm
MARK	MODE	FREQ	POWER																						
1	N	2.4599 GHz	-8.324 dBm																						
2	N	24.6965 GHz	-41.043 dBm																						
3	N	4.8949 GHz	-54.690 dBm																						
4	N	7.3975 GHz	-54.667 dBm																						
5	N	9.8439 GHz	-54.861 dBm																						

RF Conducted Spurious Emissions Graphs

802.11g
/LCH

802.11g
/MCH

802.11g
/HCH



RF Conducted Spurious Emissions Graphs

802.11n
(HT20)/
LCH

802.11
n(HT20)
/MCH

802.11
n(HT20)
/HCH


802.11n (HT40)/ LCH	 <table><tr><th>MkR</th><th>MODE</th><th>TIC</th><th>SLI</th><th>F</th><th>Y</th><th>FUNCTION</th><th>FUNCTION WIDTH</th><th>FUNCTION VALUE</th></tr><tr><td>1</td><td>N</td><td>1</td><td>f</td><td>2.4273 GHz</td><td>-16.658 dBm</td><td></td><td></td><td></td></tr><tr><td>2</td><td>N</td><td>1</td><td>f</td><td>24.6339 GHz</td><td>-41.332 dBm</td><td></td><td></td><td></td></tr><tr><td>3</td><td>N</td><td>1</td><td>f</td><td>4.7331 GHz</td><td>-56.009 dBm</td><td></td><td></td><td></td></tr><tr><td>4</td><td>N</td><td>1</td><td>f</td><td>7.3745 GHz</td><td>-54.636 dBm</td><td></td><td></td><td></td></tr><tr><td>5</td><td>N</td><td>1</td><td>f</td><td>9.5680 GHz</td><td>-56.278 dBm</td><td></td><td></td><td></td></tr></table>	MkR	MODE	TIC	SLI	F	Y	FUNCTION	FUNCTION WIDTH	FUNCTION VALUE	1	N	1	f	2.4273 GHz	-16.658 dBm				2	N	1	f	24.6339 GHz	-41.332 dBm				3	N	1	f	4.7331 GHz	-56.009 dBm				4	N	1	f	7.3745 GHz	-54.636 dBm				5	N	1	f	9.5680 GHz	-56.278 dBm			
MkR	MODE	TIC	SLI	F	Y	FUNCTION	FUNCTION WIDTH	FUNCTION VALUE																																															
1	N	1	f	2.4273 GHz	-16.658 dBm																																																		
2	N	1	f	24.6339 GHz	-41.332 dBm																																																		
3	N	1	f	4.7331 GHz	-56.009 dBm																																																		
4	N	1	f	7.3745 GHz	-54.636 dBm																																																		
5	N	1	f	9.5680 GHz	-56.278 dBm																																																		
802.11 n(HT40) /MCH	 <table><tr><th>MkR</th><th>MODE</th><th>TIC</th><th>SLI</th><th>F</th><th>Y</th><th>FUNCTION</th><th>FUNCTION WIDTH</th><th>FUNCTION VALUE</th></tr><tr><td>1</td><td>N</td><td>1</td><td>f</td><td>2.4405 GHz</td><td>-15.849 dBm</td><td></td><td></td><td></td></tr><tr><td>2</td><td>N</td><td>1</td><td>f</td><td>24.6109 GHz</td><td>-42.009 dBm</td><td></td><td></td><td></td></tr><tr><td>3</td><td>N</td><td>1</td><td>f</td><td>4.7346 GHz</td><td>-54.666 dBm</td><td></td><td></td><td></td></tr><tr><td>4</td><td>N</td><td>1</td><td>f</td><td>7.4094 GHz</td><td>-53.386 dBm</td><td></td><td></td><td></td></tr><tr><td>5</td><td>N</td><td>1</td><td>f</td><td>9.5495 GHz</td><td>-54.456 dBm</td><td></td><td></td><td></td></tr></table>	MkR	MODE	TIC	SLI	F	Y	FUNCTION	FUNCTION WIDTH	FUNCTION VALUE	1	N	1	f	2.4405 GHz	-15.849 dBm				2	N	1	f	24.6109 GHz	-42.009 dBm				3	N	1	f	4.7346 GHz	-54.666 dBm				4	N	1	f	7.4094 GHz	-53.386 dBm				5	N	1	f	9.5495 GHz	-54.456 dBm			
MkR	MODE	TIC	SLI	F	Y	FUNCTION	FUNCTION WIDTH	FUNCTION VALUE																																															
1	N	1	f	2.4405 GHz	-15.849 dBm																																																		
2	N	1	f	24.6109 GHz	-42.009 dBm																																																		
3	N	1	f	4.7346 GHz	-54.666 dBm																																																		
4	N	1	f	7.4094 GHz	-53.386 dBm																																																		
5	N	1	f	9.5495 GHz	-54.456 dBm																																																		
802.11 n(HT40) /HCH	 <table><tr><th>MkR</th><th>MODE</th><th>TIC</th><th>SLI</th><th>F</th><th>Y</th><th>FUNCTION</th><th>FUNCTION WIDTH</th><th>FUNCTION VALUE</th></tr><tr><td>1</td><td>N</td><td>1</td><td>f</td><td>2.4458 GHz</td><td>-15.990 dBm</td><td></td><td></td><td></td></tr><tr><td>2</td><td>N</td><td>1</td><td>f</td><td>24.6312 GHz</td><td>-41.738 dBm</td><td></td><td></td><td></td></tr><tr><td>3</td><td>N</td><td>1</td><td>f</td><td>4.7395 GHz</td><td>-54.612 dBm</td><td></td><td></td><td></td></tr><tr><td>4</td><td>N</td><td>1</td><td>f</td><td>7.4119 GHz</td><td>-53.914 dBm</td><td></td><td></td><td></td></tr><tr><td>5</td><td>N</td><td>1</td><td>f</td><td>9.3033 GHz</td><td>-55.681 dBm</td><td></td><td></td><td></td></tr></table>	MkR	MODE	TIC	SLI	F	Y	FUNCTION	FUNCTION WIDTH	FUNCTION VALUE	1	N	1	f	2.4458 GHz	-15.990 dBm				2	N	1	f	24.6312 GHz	-41.738 dBm				3	N	1	f	4.7395 GHz	-54.612 dBm				4	N	1	f	7.4119 GHz	-53.914 dBm				5	N	1	f	9.3033 GHz	-55.681 dBm			
MkR	MODE	TIC	SLI	F	Y	FUNCTION	FUNCTION WIDTH	FUNCTION VALUE																																															
1	N	1	f	2.4458 GHz	-15.990 dBm																																																		
2	N	1	f	24.6312 GHz	-41.738 dBm																																																		
3	N	1	f	4.7395 GHz	-54.612 dBm																																																		
4	N	1	f	7.4119 GHz	-53.914 dBm																																																		
5	N	1	f	9.3033 GHz	-55.681 dBm																																																		

9. COUDUCTED OUTPUT POWER

9.1 Block Diagram Of Test Setup



9.2 Limit

FCC Part15 (15.247) , Subpart C				
Section	Test Item	Limit	Frequency Range (MHz)	Result
15.247(b)(3)	Peak Output Power	1 watt or 30dBm	2400-2483.5	PASS

9.3 Test procedure


1. Remove the antenna from the EUT and then connect a low RF cable from the antenna port to the spectrum.
2. Set the spectrum analyzer: RBW = 1MHz. VBW = 3MHz. Sweep = auto; Detector Function = Peak. Channel power function is used
3. Keep the EUT in transmitting at lowest, middle and highest channel individually. Record the max value.

9.4 Test Result

Mode	Channel.	Maximum Output Power [dBm] ant 1	Maximum Output Power [dBm] ant 2	Total Power Conducted Output Power(PK)	Limit[dBm]
802.11b	LCH	7.627	7.81	/	30
	MCH	7.771	7.471	/	30
	HCH	7.672	7.703	/	30
802.11g	LCH	6.544	6.698	/	30
	MCH	6.528	6.987	/	30
	HCH	6.607	6.954	/	30
802.11n(HT20)	LCH	5.804	6.123	9.79	30
	MCH	5.291	6.184	8.77	30
	HCH	5.189	5.828	8.53	30
802.11n(HT40)	LCH	4.745	5.282	8.03	30
	MCH	4.879	5.631	8.28	30
	HCH	4.614	5.257	7.96	30

10. 6DB OCCUPIED BANDWIDTH

10.1 Block Diagram Of Test Setup



10.2 Limit

FCC Part15 (15.247) , Subpart C				
Section	Test Item	Limit	Frequency Range (MHz)	Result
15.247(a)(2)	Bandwidth	$\geq 500\text{KHz}$ (6dB bandwidth)	2400-2483.5	PASS

10.3 Test procedure

1. Rem1. Set RBW = 100 kHz.
2. Set the video bandwidth (VBW) $\geq 3 \times \text{RBW}$.
3. Detector = Peak.
4. Trace mode = max hold.
5. Sweep = auto couple.
6. Allow the trace to stabilize.
7. Measure the maximum width of the emission that is constrained by the frequencies associated with the two outermost amplitude points (upper and lower frequencies) that are attenuated by 6 dB relative to the maximum level measured in the fundamental emission.

10.4 Test Result

ANT1:

Test Mode	Frequency	6dB Bandwidth (MHz)	Limit(kHz)	Result
802.11b	LCH	9.123	500	PASS
	MCH	9.183	500	PASS
	HCH	8.73	500	PASS
802.11g	LCH	16.397	500	PASS
	MCH	16.452	500	PASS
	HCH	16.47	500	PASS
802.11n(HT20)	LCH	17.657	500	PASS
	MCH	17.661	500	PASS
	HCH	17.666	500	PASS
802.11n(HT40)	LCH	32.672	500	PASS
	MCH	32.664	500	PASS
	HCH	32.691	500	PASS


ANT2:

Test Mode	Frequency	6dB Bandwidth (MHz)	Limit(kHz)	Result
802.11b	LCH	9.214	500	PASS
	MCH	9.348	500	PASS
	HCH	9.646	500	PASS
802.11g	LCH	16.5	500	PASS
	MCH	16.439	500	PASS
	HCH	16.47	500	PASS
802.11n(HT20)	LCH	17.687	500	PASS
	MCH	17.668	500	PASS
	HCH	17.681	500	PASS
802.11n(HT40)	LCH	32.635	500	PASS
	MCH	32.672	500	PASS
	HCH	32.696	500	PASS

Test Graph: ANT 1:

Graphs


802.11b /LCH




802.11b /MCH




802.11b/HCH




802.11g/LCH








802.11g/MCH



802.11g/HCH




802.11n(HT20)/LC H	 Agilent Spectrum Analyzer - D:\agilent\RAW Center Freq: 2.41200000 GHz Ref Offset: 6.91 dB Ref: 26.91 dBm Mkr3: 2.420829 GHz -19.132 dBm Center: 2.412 GHz #Res BW: 100 kHz #VBW: 300 kHz Span: 30 MHz Sweep: 2.933 ms <table><tr><td>Occupied Bandwidth</td><td>17.627 MHz</td><td>Total Power</td><td>5.35 dBm</td></tr><tr><td>Transmit Freq Error</td><td>200 Hz</td><td>OBW Power</td><td>99.00 %</td></tr><tr><td>x dB Bandwidth</td><td>17.66 MHz</td><td>x dB</td><td>-6.00 dB</td></tr></table>	Occupied Bandwidth	17.627 MHz	Total Power	5.35 dBm	Transmit Freq Error	200 Hz	OBW Power	99.00 %	x dB Bandwidth	17.66 MHz	x dB	-6.00 dB
Occupied Bandwidth	17.627 MHz	Total Power	5.35 dBm										
Transmit Freq Error	200 Hz	OBW Power	99.00 %										
x dB Bandwidth	17.66 MHz	x dB	-6.00 dB										
802.11n(HT20)/MC H	 Agilent Spectrum Analyzer - D:\agilent\RAW Center Freq: 2.43700000 GHz Ref Offset: 6.96 dB Ref: 26.96 dBm Mkr3: 2.445822 GHz -19.399 dBm Center: 2.437 GHz #Res BW: 100 kHz #VBW: 300 kHz Span: 30 MHz Sweep: 2.933 ms <table><tr><td>Occupied Bandwidth</td><td>17.628 MHz</td><td>Total Power</td><td>5.00 dBm</td></tr><tr><td>Transmit Freq Error</td><td>-8.361 kHz</td><td>OBW Power</td><td>99.00 %</td></tr><tr><td>x dB Bandwidth</td><td>17.66 MHz</td><td>x dB</td><td>-6.00 dB</td></tr></table>	Occupied Bandwidth	17.628 MHz	Total Power	5.00 dBm	Transmit Freq Error	-8.361 kHz	OBW Power	99.00 %	x dB Bandwidth	17.66 MHz	x dB	-6.00 dB
Occupied Bandwidth	17.628 MHz	Total Power	5.00 dBm										
Transmit Freq Error	-8.361 kHz	OBW Power	99.00 %										
x dB Bandwidth	17.66 MHz	x dB	-6.00 dB										
802.11n(HT20)/HC H	 Agilent Spectrum Analyzer - D:\agilent\RAW Center Freq: 2.46200000 GHz Ref Offset: 6.96 dB Ref: 26.96 dBm Mkr3: 2.470835 GHz -19.399 dBm Center: 2.462 GHz #Res BW: 100 kHz #VBW: 300 kHz Span: 30 MHz Sweep: 2.933 ms <table><tr><td>Occupied Bandwidth</td><td>17.634 MHz</td><td>Total Power</td><td>4.81 dBm</td></tr><tr><td>Transmit Freq Error</td><td>1.948 kHz</td><td>OBW Power</td><td>99.00 %</td></tr><tr><td>x dB Bandwidth</td><td>17.67 MHz</td><td>x dB</td><td>-6.00 dB</td></tr></table>	Occupied Bandwidth	17.634 MHz	Total Power	4.81 dBm	Transmit Freq Error	1.948 kHz	OBW Power	99.00 %	x dB Bandwidth	17.67 MHz	x dB	-6.00 dB
Occupied Bandwidth	17.634 MHz	Total Power	4.81 dBm										
Transmit Freq Error	1.948 kHz	OBW Power	99.00 %										
x dB Bandwidth	17.67 MHz	x dB	-6.00 dB										

802.11n(HT40)/LC H	 Agilent Spectrum Analyzer - D:\agilent\RAW Center Freq 2.42200000 GHz Ref Offset: 6.91 dB Ref: 26.91 dBm Mkr3 2.438252 GHz -21.126 dBm Center 2.422 GHz #Res BW 100 kHz #VBW 300 kHz Span 60 MHz Sweep 5.8 ms Occupied Bandwidth 34.592 MHz Total Power 4.49 dBm Transmit Freq Error -83.572 kHz OBW Power 99.00 % x dB Bandwidth 32.67 MHz x dB -6.00 dB
802.11n(HT40)/MC H	 Agilent Spectrum Analyzer - D:\agilent\RAW Center Freq 2.43700000 GHz Ref Offset: 6.96 dB Ref: 26.96 dBm Mkr3 2.453182 GHz -22.827 dBm Center 2.437 GHz #Res BW 100 kHz #VBW 300 kHz Span 60 MHz Sweep 5.8 ms Occupied Bandwidth 34.547 MHz Total Power 4.58 dBm Transmit Freq Error -149.89 kHz OBW Power 99.00 % x dB Bandwidth 32.66 MHz x dB -6.00 dB
802.11n(HT40)/HC H	 Agilent Spectrum Analyzer - D:\agilent\RAW Center Freq 2.45200000 GHz Ref Offset: 6.95 dB Ref: 26.95 dBm Mkr3 2.468278 GHz -21.105 dBm Center 2.452 GHz #Res BW 100 kHz #VBW 300 kHz Span 60 MHz Sweep 5.8 ms Occupied Bandwidth 34.702 MHz Total Power 4.34 dBm Transmit Freq Error -67.050 kHz OBW Power 99.00 % x dB Bandwidth 32.69 MHz x dB -6.00 dB


ANT 2:

Graphs

802.11b /LCH




802.11b /MCH




802.11b/HCH




802.11g/LCH








802.11g/MCH



802.11g/HCH




802.11n(HT20)/LC H	 Agilent Spectrum Analyzer - D:\agilent\RAW Center Freq: 2.41200000 GHz Ref Offset: 6.91 dB Ref: 26.91 dBm Mkr3: 2.42085 GHz -19.343 dBm Center: 2.412 GHz #Res BW: 100 kHz #VBW: 300 kHz Span: 30 MHz Sweep: 2.933 ms Occupied Bandwidth: 17.633 MHz Total Power: 5.68 dBm Transmit Freq Error: 6.531 kHz OBW Power: 99.00 % x dB Bandwidth: 17.69 MHz x dB: -6.00 dB
802.11n(HT20)/MC H	 Agilent Spectrum Analyzer - D:\agilent\RAW Center Freq: 2.43700000 GHz Ref Offset: 6.96 dB Ref: 26.96 dBm Mkr3: 2.445831 GHz -18.240 dBm Center: 2.437 GHz #Res BW: 100 kHz #VBW: 300 kHz Span: 30 MHz Sweep: 2.933 ms Occupied Bandwidth: 17.634 MHz Total Power: 5.61 dBm Transmit Freq Error: -2.902 kHz OBW Power: 99.00 % x dB Bandwidth: 17.67 MHz x dB: -6.00 dB
802.11n(HT20)/HC H	 Agilent Spectrum Analyzer - D:\agilent\RAW Center Freq: 2.46200000 GHz Ref Offset: 6.96 dB Ref: 26.96 dBm Mkr1: 2.462 GHz -21.252 dBm Center: 2.462 GHz #Res BW: 100 kHz #VBW: 300 kHz Span: 30 MHz Sweep: 2.933 ms Occupied Bandwidth: 17.625 MHz Total Power: 5.78 dBm Transmit Freq Error: -853 Hz OBW Power: 99.00 % x dB Bandwidth: 17.68 MHz x dB: -6.00 dB

802.11n(HT40)/LC H	 Agilent Spectrum Analyzer - D:\agilent\RAW Center Freq 2.42200000 GHz Ref Offset: 6.91 dB Ref: 26.91 dBm Mkr3 2.438226 GHz -22.188 dBm Center 2.422 GHz #Res BW 100 kHz #VBW 300 kHz Span 60 MHz Sweep 5.8 ms Occupied Bandwidth 34.555 MHz Total Power 4.96 dBm Transmit Freq Error -91.881 kHz OBW Power 99.00 % x dB Bandwidth 32.64 MHz x dB -6.00 dB
802.11n(HT40)/MC H	 Agilent Spectrum Analyzer - D:\agilent\RAW Center Freq 2.43700000 GHz Ref Offset: 6.96 dB Ref: 26.96 dBm Center 2.437 GHz #Res BW 100 kHz #VBW 300 kHz Span 60 MHz Sweep 5.8 ms Occupied Bandwidth 34.642 MHz Total Power 5.38 dBm Transmit Freq Error -83.882 kHz OBW Power 99.00 % x dB Bandwidth 32.67 MHz x dB -6.00 dB
802.11n(HT40)/HC H	 Agilent Spectrum Analyzer - D:\agilent\RAW Center Freq 2.45200000 GHz Ref Offset: 6.95 dB Ref: 26.95 dBm Mkr3 2.468262 GHz -20.288 dBm Center 2.452 GHz #Res BW 100 kHz #VBW 300 kHz Span 60 MHz Sweep 5.8 ms Occupied Bandwidth 34.642 MHz Total Power 5.06 dBm Transmit Freq Error -86.024 kHz OBW Power 99.00 % x dB Bandwidth 32.70 MHz x dB -6.00 dB

11. POWER SPECTRAL DENSITY

11.1 Block Diagram Of Test Setup



11.2 Limit

FCC Part15 (15.247) , Subpart C				
Section	Test Item	Limit	Frequency Range (MHz)	Result
15.247	Power Spectral Density	8 dBm (in any 3KHz)	2400-2483.5	PASS

11.3 Test procedure

1. Set analyzer center frequency to DTS channel center frequency.
2. Set the span to 1.5 times the DTS bandwidth.
3. Set the RBW to: $3\text{ kHz} \leq \text{RBW} \leq 100\text{ kHz}$.
4. Set the VBW $\geq 3 \times \text{RBW}$.
5. Detector = PEAK.
6. Sweep time = auto couple.
7. Trace mode = max hold.
8. Allow trace to fully stabilize.
9. Use the peak marker function to determine the maximum amplitude level within the RBW.
10. If measured value exceeds limit, reduce RBW (no less than 3 kHz) and repeat.

11.4 Test Result


Mode	Channel.	Power Spectral Density [dBm /3KHz] ANT 1	Power Spectral Density [dBm /3KHz] ANT 2	Power Spectral Density [dBm /3KHz] Total	Limit(dBm)
802.11b	LCH	-20.733	-20.77	/	8
	MCH	-20.613	-21.46	/	8
	HCH	-21.022	-20.796	/	8
802.11g	LCH	-26.769	-26.442	/	8
	MCH	-26.566	-26.376	/	8
	HCH	-26.537	-26.458	/	8
802.11n(H T20)	LCH	-26.848	-26.644	-23.73	8
	MCH	-27.182	-26.267	-23.69	8
	HCH	-27.458	-26.532	-23.69	8
802.11n(H T40)	LCH	-30.641	-30.17	-27.39	8
	MCH	-30.495	-29.789	-27.12	8
	HCH	-30.891	-29.939	-27.38	8

Test Graph


ANT 1:

Graphs


802.11b /LCH




802.11b /MCH




802.11b/HCH




802.11g/LCH







802.11g/MCH



802.11g/HCH



802.11n(HT20)/LC H	
802.11n(HT20)/MC H	
802.11n(HT20)/HC H	

802.11n(HT40)/LC H	 Agilent Spectrum Analyzer - Sweep 5A Center Freq 2.42200000 GHz Ref Offset 6.91 dB Ref 20.00 dBm Mkr1 2.418 28 GHz -30.641 dBm Center 2.42200 GHz #Res BW 3.0 kHz #VBW 10 kHz Span 60.00 MHz Sweep 6.326 s (1001 pts)
802.11n(HT40)/MC H	 Agilent Spectrum Analyzer - Sweep 5A Center Freq 2.437000000 GHz Ref Offset 6.96 dB Ref 20.00 dBm Mkr1 2.433 28 GHz -30.495 dBm Center 2.43700 GHz #Res BW 3.0 kHz #VBW 10 kHz Span 60.00 MHz Sweep 6.326 s (1001 pts)
802.11n(HT40)/HC H	 Agilent Spectrum Analyzer - Sweep 5A Center Freq 2.452000000 GHz Ref Offset 6.96 dB Ref 20.00 dBm Mkr1 2.448 28 GHz -30.891 dBm Center 2.45200 GHz #Res BW 3.0 kHz #VBW 10 kHz Span 60.00 MHz Sweep 6.326 s (1001 pts)

ANT 2:

Graphs

802.11b /LCH




802.11b /MCH




802.11b/HCH




802.11g/LCH





802.11g/MCH



802.11g/HCH



802.11n(HT20)/LC H	
802.11n(HT20)/MC H	
802.11n(HT20)/HC H	

802.11n(HT40)/LC H	
802.11n(HT40)/MC H	
802.11n(HT40)/HC H	

12. ANTENNA REQUIREMENT

15.203 requirement:

An intentional radiator shall be designed to ensure that no antenna other than that furnished by the responsible party shall be used with the device. The use of a permanently attached antenna or of an antenna that uses a unique coupling to the intentional radiator, the manufacturer may design the unit so that a broken antenna can be replaced by the user, but the use of a standard antenna jack or electrical connector is prohibited.

15.247(b) (4) requirement:

The conducted output power limit specified in paragraph (b) of this section is based on the use of antennas with directional gains that do not exceed 6 dBi. Except as shown in paragraph (c) of this section, if transmitting antennas of directional gain greater than 6 dBi are used, the conducted output power from the intentional radiator shall be reduced below the stated values in paragraphs (b)(1), (b)(2), and (b)(3) of this section, as appropriate, by the amount in dB that the directional gain of the antenna exceeds 6 dBi.

EUT Antenna:

The antenna is external Antenna and no consideration of replacement. The best case gain of the antenna is 1.0dBi.

13. EUT TEST SETUP PHOTOGRAPHS

Radiated Emission


Below 1G



Above 1G



Conducted Emission



***** END OF REPORT *****