



## User Manual

### 2.4GHz Wireless Guitar System



Thank you for purchasing our product. This product is a carefully designed mini portable wireless audio transmission system, using 2.4GHz transmission frequency, high-definition audio quality, low power consumption, long battery life, and no pairing requirement, suitable for 3.5mm audio jacks, supporting most electronic musical instruments; We hope this product brings more convenience and joy to your performance!

#### Precautions

1. Do not use the device in humid, high-temperature, strong radiation or strong magnetic environments.

2. Do not disassemble, modify, repair, or drop this device without authorization.

3. Other wireless devices and large obstacles may affect signal transmission.

4. Please turn off the device when not in use; otherwise the battery will continue to discharge.

5. If the device is not used for a long time, please charge within two months to prevent the battery from entering low-power protection mode. As the number of charges and discharges increases, the battery capacity will gradually decrease, and the maximum usage time of the product will decrease accordingly.

6. Please turn off the device while charging to speed up the charging process.

7. Please turn off the power before connecting or disconnecting from other audio devices to avoid device malfunction or damage to other audio equipment.

EN 1

Parameter	Description
Audio Quality	48K/16bit High-definition digital audio
Frequency Band	2.4GHz ISM band
Transmission Range	Outdoor 40 meters; Indoor 20 meters through walls
Latency	12ms
Signal-to-Noise Ratio	>8dB
Distortion	<0.02%
Dynamic Range	20-20KHz±1dB/-3dB
Frequency Response	20-20KHz±1dB/-3dB
Multi-device Use	Unlimited (Do not turn on simultaneously)
Battery	3.7V 1000mAh rechargeable lithium battery, compatible with charging case and USB charging

#### Product Introduction

① Audio Jack: Supports 3.5mm and 6.35mm audio jacks for wider use. Connect the transmitter to a guitar or other audio equipment.

② Charging Port: Supports Type-C charging.

③ Long Press: Turn the device on or off.

④ Double Click: Cycle through transmission channels. If you encounter transmission interference or connection issues, try adjusting the channel. Both transmitter and receiver need to be set to the same channel.

⑤ Charging Indicator: Red light on when charging; light off when charging is complete; red light flashes when battery is low.

⑥ Magnetic Charging Port: Supports simultaneous charging of wireless transmitter and receiver in the charging case, easy to place and remove with automatic magnetic alignment for charging.

⑦ Battery Level Display: When the product is placed in the charging case, the battery level indicator lights up to show the current battery level of the charging case, and auto-matically turns off after a moment. When the charging case is charging, it displays the charging progress.

⑧ Charging Case Port: Use a Type-C USB cable for charging, compatible with phone Type-C cables.

EN 2



#### FCC Statement

##### Part 15

##### Statement