



ES2 Quick Start Guide

- 1)** Charge your speaker for 2 hours if necessary. Use any 5V/1A or PD supply. The ES2 can't play max volume while charging.
- 2)** Press the 'Power On' button for two seconds to turn it on.
- 3)** BT device pairing: Double click on the 'Power On' button to set the ES2 in BT pairing mode. All the 9 LEDs will be glowing when in pairing mode. Find the ES2 on your BT device and pair.
- 4)** Adjust volume on the + / - buttons.
- 5)** To configure your ES2 for Stereo Mode, you will require two ES2 units. On both ES2s, double-click 'Power On' once more to activate TWS mode (LEDs 1 and 9 will flash alternately). The two ES2's will sync automatically. Find the ES2 on your BT device and pair.



SOUND

Maximum Loudness (SPL) 103dB @ 1 m
Drive Units: Bass 60 Watts*1, Mid-Treble 20 Watts*1
Rated Impedance: Bass 4 Ohm \pm 15%; Treble 8 Ohm \pm 15%
Cabinet Principle: Bass-Reflex
THD < 0.1% @1W, SNR > 98dB



BATTERY

Built-in, rechargeable Li-ion 13.7 Wh
Charging with USB-C, 5V or PD:
Fast charging with 2 hours full recharge.
Full recharge equals 20 hours playback



UNIT

Dimensions (HWD)
277x238x134 mm / 23 x 20 x 12 in
Weight: 2.9 kg / 6.4 lb
Control panel: Volume control, Battery indicator and Soft On/off control, Pairing and TWS.



INTERFACE

Audio Input:
3.5mm Line In and BT vers. 5.3. (up to 25m operating range).
Supported Protocols: A2DP, AVRCP, AVDTP, HFP, HSP
Supported Audio Decoding Format: SBC, AAC



FAQ

[Visit our FAQ section for further support](#)

COMPLIANCE

FCC

Warning:

To assure continued compliance, any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

COMPLIANCE

FCC

Warning:

To assure continued compliance, any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

FCC Statement:

This equipment complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference, and
2. This device must accept any interference received, including interference that may cause undesired operation.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

FCC Radiation Exposure Statement:

The device has been evaluated to meet general RF exposure requirement.

The device can be used in the portable exposure condition without restriction.