


X2-pro Quick Start Manual

Product Overview



Important Reminder:
Before installing the headset, please connect your mobile phone according to the quick manual guide to test the sound effect and volume.
If there is a big difference in sound effect and volume after installing into the helmet, please adjust the position of the speaker inside the helmet.

6 people connect and 2 people intercom mode



Introduction to wireless intercom connection operation
(Intercom and music sharing are turned off by default every time you turn on)

1. 6 devices intercom (use of ABC/CD/E buttons)
The following is an example of the connection process with device 1 as the host (The following instructions refer to device 1,2,3,4,5,6 as No.1,2,3,4,5,6 for short):

First, turn on device No.1, press the intercom button to make the device No.1 enter the intercom mode, the green light of the intercom key (A) blinks slowly, enter the intercom receiving status, press and hold the intercom key (A) for 3s to enter the intercom pairing status, device No.2 remains stationary, the green indicator light keeps on, after successful connection, at this time, press and hold the button to turn off the device No.2, the device will be off.

The host device No.1 does not shut down, keeps in the intercom mode, turn on No.3, press the intercom button and enter to the intercom receiving mode, then press and hold the Key B of No.1, enter to the intercom pairing status, the green light will be bright, after successful connection, shut down No.3, and No.3 will be stored under the key C of No.1.

The host device No.1 does not shut down, keeps in the intercom mode, turn on No.4, press the intercom button and enter to the intercom receiving mode, then press and hold the Key C of No.1, enter to the intercom pairing status, the green light will be bright, after successful connection, shut down No.4, and No.4 will be stored under the key D of No.1.

The host device No.1 does not shut down, keeps in the intercom mode, turn on No.5, press the intercom button and enter to the intercom receiving mode, then press and hold the Key E of No.1, enter to the intercom pairing status, the green light will be bright, after successful connection, shut down No.5, and No.5 will be stored under the key E of No.1.

After the operations are completed, all the devices are turned on, enter to the intercom mode, and switch the intercom with the device No.1 as the host (only two people can talk to each other at the same time).

When No.1 wants to talk to No.2, press the Key A of the No.1 to connect No.2.

When No.1 wants to talk to No.3, press the Key B of the No.1 to connect No.3.

When No.1 wants to talk to No.4, press the Key C of the No.1 to connect No.4.

When No.1 wants to talk to No.5, press the Key D of the No.1 to connect No.5.

When No.1 wants to talk to No.6, press the Key E of the No.1 to connect No.6.

Power on/off

Double click to switch language prompt tone (without blue tooth connection)



power on/off tone

Press and hold for 3 seconds to power on/off



Blue tooth connection

blue tooth Tone

In intercom mode, if the intercom is not connected successfully, the mobile phone cannot search the blue tooth device. It must be connected successfully or exit intercom mode to search the blue tooth device.

blue tooth not connected:
LED light blinks quickly

blue tooth connection successful:
LED light blinks slowly

When music is paused

When playing music

LED light steady on

Telephone function

Double click to switch manual/automatic answer (without blue tooth connection)



(Incoming call)




(Incoming call)

Answer the call automatically (after 10 seconds)



(Incoming call)



Manual answer "short press"



(On the phone)



Cancel a call



Long press 2 seconds



Short press "short press" during a call



Hang up the phone



Double click



Redial the last number



Short press



Cancel a call

Mic button function

blue tooth Mode



Full-Duplex Intercom Mode



Half-Duplex Intercom Mode



Half-Duplex intercom function

Microphone button



In speech mode



Connection conditions: Requires the same model to be paired, unlimited number of people within the effective distance.

Half-duplex intercom connection operation: all devices short press the microphone button to enter the half-duplex intercom receiving mode, at this time one of them press and hold the microphone button does not release the button to speak (release to enter the half-duplex intercom call receiving mode), and the other several units to keep in the half-duplex intercom receiving mode, so that the half-duplex intercom call receiving mode can pick up the voice. Other devices can make half-duplex intercom calls according to this operation.

Half-duplex speech: only one device can be allowed to enter the speech state, and all other device cannot be in the speech state.

Half-Duplex intercom connection

Intercom indicator (white)



Intercom talk mode tone



Product List

X2-Pro Device*1



Speakers & Microphone*1



Clip on Base*1



Caveat

1. To avoid explosion, please do not put the product into the flame;
2. Please do not disassemble the product to avoid damage to the electronic components of the product;
3. Please keep away from sharp objects to avoid damage to the product;

4. Please keep it in a dry place if not used for long time;

5. Before using the wireless device, please fully charge it;

6. If the red light does not come on while charging, it may be the voltage is too low;

7. To extend the life of the button lithium polymer battery, please charge the device at least once a month.

Instruction warning

NOTE: This product has been tested, meet the restriction of Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates and can radiate radio frequency energy and, if not installed and used in accordance with the instructions may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to correct the interference by one or more of the following measures:

•Reorient or relocate the receiving antenna.

•Increase the separation between the device and receiver.

•Connect the device into an outlet on a circuit different from that to which the receiver is connected.

•Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the device.

This device complies with part 15 of the FCC Rules. The operation needs to fulfill the following two conditions:

(1) This device may not cause harmful interference;

(2) This device must accept any interference received, including interference that may cause undesired operation.

Charging function

(When the device is switched on and the charger is plugged in, the device will automatically switch off)



Red light steady on When charging



Lights off when fully charged

Sound mixing function

Intercom pairing successful



Blue tooth Pairing Successful



Navigation Intercom Music



When both the intercom and wireless are successfully paired, the operation of volume buttons is as follows:

① short press volume up and down buttons to adjust the volume size of the wireless mode ② long press volume up and down buttons to adjust the volume size of the intercom ③ double click the volume up and down buttons to switch the wireless music of the next song and the previous song

④ When all six devices are connected successfully, such as the No.1 is talking to the No.2, If No.5 wants to talk to No.2 at this time, it will find that the indicator blinks three times, indicating that No.2 is on the call.

Mixing function: intercom and wireless can work independently, do not affect each other. When the intercom and blue tooth are connected successfully, you can listen to music and intercom at the same time.

FCC ID:2A9MI-X2-pro

FCC Statement:

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.