

RF Exposure Evaluation

Limits

The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency (RF) radiation as specified in 1.1307(b)

Limits for Maximum Permissible Exposure (MPE)

Frequency range (MHz)	Electric field strength (V/m)	Magnetic field strength (A/m)	Power density (mW/cm ²)	Averaging time (minutes)
(A) Limits for Occupational/Controlled Exposures				
0.3–3.0	614	1.63	*(100)	6
3.0–30	1842/f	4.89/f	*(900/f ²)	6
30–300	61.4	0.163	1.0	6
300–1500			f/300	6
1500–100,000			5	6
(B) Limits for General Population/Uncontrolled Exposure				
0.3–1.34	614	1.63	*(100)	30
1.34–30	824/f	2.19/f	*(180/f ²)	30
30–300	27.5	0.073	0.2	30
300–1500			f/1500	30
1500–100,000			1.0	30

f = frequency in MHz

Friis transmission formula: $Pd = (Pout \cdot G) / (4 \cdot \pi \cdot r^2)$

Where

Pd = power density in mW/cm², **Pout** = output power to antenna in mW;

G = gain of antenna in linear scale, **Pi** = 3.1416;

R = distance between observation point and center of the radiator in cm

Pd is the limit of MPE, 1 mW/cm². If we know the maximum gain of the antenna and the total power input to the antenna, through the calculation, we will know the distance r where the MPE limit is reached.

Test Procedure

Software provided by client enabled the EUT to transmit and receive data at lowest, middle and highest channel individually.

Test Result of RF Exposure Evaluation

WiFi2.4G

Channel	Frequency (MHz)	Output power to antenna (dBm)	Output power to antenna (mW)	Power Density at R=20cm (mW/cm ²)	Limit (mW/cm ²)	Result
802.11b	2412	15.35	34.28	0.0068	1.0	PASS
	2437	15.61	36.39	0.0072	1.0	PASS
	2462	15.01	31.70	0.0063	1.0	PASS
802.11g	2412	16.06	40.36	0.0080	1.0	PASS
	2437	14.02	25.23	0.0050	1.0	PASS
	2462	13.08	20.32	0.0040	1.0	PASS
802.11n(HT20)	2412	12.84	19.23	0.0038	1.0	PASS
	2437	11.76	15.00	0.0030	1.0	PASS
	2462	10.84	12.13	0.0024	1.0	PASS
802.11n(HT40)	2422	10.62	11.53	0.0023	1.0	PASS
	2437	9.87	9.71	0.0019	1.0	PASS
	2452	9.34	8.59	0.0017	1.0	PASS

Remark: antenna gain=0dBi