

Door & Window Sensor (Long Range) (VS-ZWDW01-001)


Quick Reference



3401 N Ashton Blvd. Lehi, UT 84043 USA

The Vivint Door and Window Sensor (Long Range) is a security device that is installed on doors, windows, and other objects in order to monitor and report open and closed states. The sensor transmits a signal to the control panel/hub when the magnet is moved away from, or close to, the sensor.

The door and window sensor is also equipped with a cover tamper switch for additional security.



Installation Instructions


For internal switch usage (magnet):

1. Secure the sensor to the door frame using the adhesive.
NOTE: It is recommended to install the sensor on the side that will be moving less (e.g., the frame instead of the door or window).
2. Secure the magnet adjacent to the sensor on the door or window using the adhesive. **IMPORTANT:** The maximum allowable distance between the magnet and the sensor is 0.7 in (17 mm).
NOTE: If necessary, use the provided spacer to raise the magnet so that it aligns better with the sensor. Remove the magnet's back using a small flathead screwdriver and replace it with the spacer.

Sensor (inside view) —



Back Plate (inside view) —



Installer / User Test

Open and/or close the door or window where the sensor is installed to ensure the sensor is transmitting correctly to the control panel/hub. The state change (open/closed) of the door or window should be recognized.

Technical / Hardware Specifications

Vivint Part Number (P/N)	VS-ZWDW01-001
Model Number (M/N)	DW03
Wireless Signal Range	350 ft. (106.7 m), open air
Battery (3V)	Panasonic CR2032 (or equivalent lithium batt.)
Battery Life	3-5 years (normal usage)
Transmitter	Z-Wave Long Range (LR); Z-Wave Classic
Code Outputs	Open, Close, Tamper, Low Batt., Loss of Supervision
Supervisory Interval	70 minutes per signal (12 hours for panel/hub to report supervision failure)
Operating Temp. Limits	32° to 120°F (0° to 49°C)
Relative Humidity	5-95% Non-Condensing

Standards Certifications & Listings

Conforms to UL 634	Standard for Connectors and Switches for Use with Burglar-Alarm Systems
FCC ID	2AAAS-DW03

*For complete regulatory compliance information, go to: vivint.com/fcc.



Battery Installation and Safety Instructions

To replace the battery, insert a coin (or CR2032 battery) into the slot in the enclosure and gently twist until the cover releases. Use only the recommended replacement batteries (see Specifications).

⚠️ WARNING

- **INGESTION HAZARD:** This product contains a button cell or coin battery.
- **DEATH or serious injury can occur if ingested.**
- A swallowed button cell or coin battery can cause **Internal Chemical Burns** in as little as **2 hours**.
- **KEEP** new and used batteries **OUT OF REACH** of CHILDREN
- **Seek immediate medical attention** if a battery is suspected to be swallowed or inserted inside any part of the body.



- Remove and immediately recycle or dispose of used batteries according to local regulations and keep away from children. Do NOT dispose of batteries in household trash or incinerate.
- Even used batteries may cause severe injury or death.
- Call a local poison control center for treatment information. • Non-rechargeable batteries are not to be recharged.
- Do NOT force discharge, recharge, disassemble, heat above 100°C or incinerate. Doing so may result in injury due to venting, leakage or explosion resulting in chemical burns.
- Ensure the batteries are installed according to polarity (+ and -).
- Remove and immediately recycle or dispose of batteries from equipment not used for an extended period of time according to local regulations. • Always completely secure the battery compartment. If the battery compartment does not close securely, stop using the product, remove the batteries, and keep them away from children.

California Only: Perchlorate material special handling may apply. For details, visit:

www.dtsc.ca.gov/hazardouswaste/perchlorate

Wireless Product Notice

Wireless communications hardware provides reliable communication; however, there are limitations which must be observed.

- The transmitters are required to comply with all applicable wireless rules and regulations. As such, they have limited transmitter power and limited range.
- Wireless signals may be blocked by radio signals that occur on or near their operating frequencies.

FCC and ISED Canada Regulatory Compliance Declarations*

CAUTION: Unauthorized changes or modifications could void the user's authority to operate the equipment.

This device has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of FCC Rules and Industry Canada license-exempt RSS standard(s). Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation of the device.

These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and the receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/television technician for help.

FCC (U.S.) Radiation Exposure Statement: This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20 cm (7.9 in) between the radiator and your body.